

PRIME H310M-C R2.0

DDR4 2133 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Timing	Vol tage (V)	MM socket 1 DIMM
SAMSUNG	M378A5143DB0--CPB	4GB	SS	Samsung	15-15-15-36	1.2	•
SAMSUNG	M378A1G43DB0--CPB	8GB	DS	SEC 428 BCPB	15-15-15-36	1.2	•
GLOWAY	PC4-17000	4GB	SS	N/A	15-15-15-35	1.2	•
KINGSTON	HX421C13PBK4/16	4*4GB	SS	Hynix	15-15-15-36	1.2	•
PANRAM	PUD42133C138G4NJW	4*8GB	DS	N/A	13-13-13-35	1.2	•
PANRAM	PUD42133C134G4NJW	4*4GB	SS	N/A	13-13-13-35	1.2	•
CORSAIR	CMK16GX4M4A2133C15(Ver4.23)	4*4GB	SS	N/A	15-15-15-36	1.2	•
CRUCIAL	MTA8ATF51264AZ-2G1A1	4GB	SS	Micron	15-15-15-36	1.2	•
CORSAIR	CMV4GX4M1A2133C15	4GB	SS	N/A	15-15-15-36	1.2	•
KINGSTON	HX421C14FB/8	8GB	DS	Hynix	14-14-14-35	1.2	•
APACER	78.C1GM3.AF10B	8GB	DS	Hynix	16-16-16-36	1.2	•
KINGSTON	HX421C13SBK4/16	4*4GB	SS	Hynix	15-15-15-36	1.2	•
KINGSTON	KVR21N15D8/8	8GB	DS	Hynix	15-15-15-36	1.2	•
GALAXY	GAM4DBLBM213315IE081C	8GB	DS	N/A	15-15-15-35	1.2	•
AVEXIR	AVD4U21331508G-1C0B	8GB	DS	N/A	15-15-15-35	1.2	•
CORSAIR	CMK16GX4M4A2133C13 (Ver5.29)	4*4GB	SS	N/A	13-15-15-28	1.2	•
GEIL	GPR48GB2133C15DC	2*4GB	SS	Micron	15-15-15-36	1.2	•
KINGSTON	HX421C14FBK4/32	4*8GB	DS	Hynix	14-14-14-35	1.2	•
TEKISM	T4U2133B8G15-SAD	8GB	DS	SEC 446 BCPB	15-15-15-36	1.2	•
G.SKILL	F4-2133C15Q-16GRB	4*4GB	SS	Samsung	15-15-15-35	1.2	•
CENTURY	PC4-17000	8GB	DS	Hynix	15-15-15-36	1.2	•
ADATA	AX4U2133W4G15-QRZ	4*4GB	SS	N/A	15-15-15-36	1.2	•
TEAM	TED48GM2133C15BK	8GB	DS	Hynix	15-15-15-36	1.2	•
ADATA	AD4U2133W8G15-B	16*8GB	DS	Hynix	15-15-15-36	1.2	•
CRUCIAL	CT8G4DFD8213.16FA11	4*8GB	DS	Micron	15-15-15-36	1.2	•
KINGSTON	KVR21E15S8/4	4GB	SS	Hynix	15-15-15-36	1.2	•
G.SKILL	F4-2133C15S-4GNT	4GB	SS	Hynix	15-15-15-35	1.2	•
G.SKILL	F4-2133C15S-8GNT	8GB	DS	Hynix	15-15-15-35	1.2	•
TEAM	TPAD44G2133HC15BK	4GB	SS	Samsung	15-15-15-36	1.2	•
APACER	AHU08GGB13CGT7G	8GB	DS	Hynix	16-16-16-36	1.2	•
ASINT	SLB404G08-CCN2B 1615	8GB	DS	Hynix	15-15-15-36	1.2	•
PATRIOT	PSD48G21332	8GB	DS	PAIROT	15-15-15-36	1.2	•
SAMSUNG	M378A1K43BB1-CPB	8GB	SS	Samsung	15-15-15-36	1.2	•
KINGSTON	HX421C14FB2/8	8GB	SS	Micron	14-14-14-35	1.2	•
KINGSTON	HX421C14FBK2/8	2*4GB	SS	Micron	14-14-14-35	1.2	•
KINGSTON	HX421C14FB/4	4GB	SS	Hynix	14-14-14-35	1.2	•
V-COLOR	TC48G21S818-IMS	4*8GB	SS	Micron	15-15-15-36	1.2	•
TEAM	TED416G2133C15BK	16GB	DS	Micron	15-15-15-36	1.2	•
SAMSUNG	M378A5143EB1-CPB	4GB	SS	Samsung	15-15-15-36	1.2	•
SAMSUNG	M378A5143EB1-CPB	4GB	SS	Samsung	15-15-15-36	1.2	•
TEAM	TED48G2133C15BK	8GB	SS	SpecTek	15-15-15-36	1.2	•
ANUCCELL	GRPIF1621033818594	8GB	DS	ANUCCELL	16-16-16-35	1.2	•
TIGO	TMKU8G868-2133P	8GB	SS	Micron	15-15-15-36	1.2	•
Xiede	1.2V-PC4-17000-1620	4GB	SS	Micron	15-15-15-36	1.2	•
Xiede	1.2V-PC4-17000-1620	8GB	DS	Hynix	15-15-15-36	1.2	•
V-COLOR	TC48G21S815	8GB	SS	Hynix	15-15-15-36	1.2	•
V-COLOR	TC48G21S815-ims	8GB	SS	Micron	15-15-15-36	1.2	•
SAMSUNG	M378A2K43BB1CPB	16GB	DS	SEC510	15-15-15-36	1.2	•
G.SKILL	F4-2133C15Q-32GRR	4*8GB	SS	N/A	15-15-15-35	1.2	•
G.SKILL	F4-2133C15Q2-64GRR	8*8GB	SS	Hynix	15-15-15-35	1.2	•
CRUCIAL	CT16G4DFD8213.C16FAD1	16GB	DS	Micron	15-15-15-36	1.2	•
CRUCIAL	CT8G4DFD8213.C16FDR2	8GB	DS	Micron	15-15-15-36	1.2	•
CRUCIAL	CT4G4DFS8213.C8FBD2	4GB	SS	Micron	15-15-15-36	1.2	•
GEIL	GFY48GB2133C15DC	4GB	SS	N/A	15-15-15-36	1.2	•
Klevv	IM48GU88N21-FFFHMB	8GB	SS	Hynix	15-15-15-35	1.2	•
Klevv	IM44GU48N21-FFFHAB	4GB	SS	Hynix	15-15-15-35	1.2	•
Klevv	IM4AGU88N21-FFFHMB	16GB	DS	Hynix	15-15-15-35	1.2	•
GEIL	GPR432GB2133C15QC	8GB	SS	Micron	15-15-15-36	1.2	•
SK HYNIX	HMA451U6AFR8N-TF	4*4GB	SS	Hynix	15-15-15-36	1.2	•
GLOWAY	STK4U2133D15041C/ PC4-17000	4GB	SS	N/A	15-15-15-35	1.2	•
G.SKILL	F4-2133C15Q-64GFX	4*16GB	DS	N/A	15-15-15-36	1.2	•
G.SKILL	F4-2133C15Q-32GFX	4*8GB	SS	N/A	15-15-15-36	1.2	•
G.SKILL	F4-2133C15S-8GDB	8GB	SS	Hynix	15-15-15-35	1.2	•
AVANT	AVW6451U67J5213N3-SAEP	4GB	SS	SEC 549	15-15-15-36	1.2	•
AVANT	AVW641GU67J5213N2-SAEP	8GB	DS	SEC 549	15-15-15-36	1.2	•
SanMax	SMD4-U4G28SE-21P	4GB	SS	SEC 534	15-15-15-36	1.2	•
ADATA	AD4U213338G15-B	8*8GB	SS	SpecTek	15-15-15-36	1.2	•
ADATA	AD4U2133W4G15-BP	8*4GB	SS	SpecTek	15-15-15-36	1.2	•
Ramsta	R2DD4N04G2133	4GB	SS	Micron	15-15-15-35	1.2	•
Ramsta	R2DD4N08G2133	8GB	SS	Micron	15-15-15-36	1.2	•
APACER	AU16GGB13CDYBGC	16GB	DS	APACER	15-15-15-36	1.2	•
silicon power	SP004GBLFU213N02	4GB	SS	Hynix	15-15-15-36	1.2	•
TEKISM	T4U2133B8G15-HYM	2* 8GB	DS	Hynix	15-15-15-36	1.2	•
TIGO	TMKU4G456-2133P	4GB	SS	Hynix	15-15-15-36	1.2	•
HYUNDAI	HYE16G21C1516GBSSHynix15-15-351.2●●						

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.

- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for best performance.
- Make sure to install the memory modules from the gray slots first.
- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default settings, the system will automatically adjust the memory frequency to the SPD value.
- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from the same manufacturer.
- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors.

PRIME H310M-C R2.0								
DDR4 Qualified Vendors List (QVL)								
Vendors	Part No.	Size	SS/DS	Chip Brand	Timing	Voltage(V)	Socket support (1 DIMM 2 DIMM)	
ADATA	AX4U2400W8G16-DRZ	8GB	DS	N/A	17-16-16-39	1.2	•	•
G.SKILL	F4-2400C15Q-32GRB	4*8GB	DS	N/A	15-15-15-35	1.2	•	•
GLOWAY	PC4-19200	4GB	DS	GLOWAY	16-16-16-35	1.2	•	•
PANRAM	PUD42400C154G4NJW	4*4GB	SS	N/A	15-15-15-35	1.2	•	•
PANRAM	PUD42400C158G4NJW	4*8GB	DS	N/A	15-15-15-35	1.2	•	•
CRUCIAL	BLS4K4G4D240FSA	4GB	SS	Micron	16-16-16-39	1.2	•	•
GEIL	GPR416GB2400C15QC	4GB	SS	N/A	15-15-15-35	1.2	•	•
MUSHKIN	997199F	2*8GB	DS	N/A	15-15-15-35	1.2	•	•
KINGSTON	HX424C15FBK4/32	4*8GB	DS	Hvnx	15-15-15-35	1.2	•	•
APACER	78.C1GMA.AF30B	8GB	DS	Hvnx	16-16-16-36	1.2	•	•
PNY	MD16GK2D4240015AB	2*8GB	DS	N/A	15-15-15-35	1.2	•	•
G.SKILL	F4-2400C15D-169GVR	2*8GB	DS	N/A	15-15-15-35	1.2	•	•
CORSAIR	CM4X8GE2400C14K4-CN (Ver4.24)	8GB	DS	N/A	14-16-16-31	1.2	•	•
CORSAIR	CMK8GX4M1A2400C14(Ver3.20)	8GB	DS	N/A	14-16-16-31	1.2	•	•
PATRIOT	PV416G240C5QK	4*4GB	SS	N/A	15-15-15-35	1.2	•	•
KINGSTON	HX424C15FBK4/16	4*4GB	SS	Hvnx	15-15-15-35	1.2	•	•
G.SKILL	F4-2400C14Q2-128GRK	8*16GB	DS	Samsung	14-14-14-34	1.2	•	•
G.SKILL	F4-2400C14Q-16GRK	4*4GB	SS	Hvnx	14-14-14-34	1.2	•	•
G.SKILL	F4-2400C15Q-16GRR	4*4GB	SS	Samsung	15-15-15-35	1.2	•	•
AVEXIR	AVD4UZ124001608G-4COR	4*8GB	DS	N/A	16-16-16-36	1.2	•	•
AVEXIR	AVD4UZ124001604G-4COB	4*4GB	SS	N/A	16-16-16-36	1.2	•	•
CRUCIAL	BLS8G4D240FSA.16FADG	8GB	DS	Micron	16-16-16-39	1.2	•	•
TEAM	TED48G2400C16BK	8GB	DS	Hvnx	16-16-16-39	1.2	•	•
KINGSTON	HX424C12PBK4/32	4*8GB	DS	Hvnx	12-13-13-35	1.35	•	•
G.SKILL	F4-2400C15Q-32GRR	4*8GB	DS	N/A	15-15-15-35	1.2	•	•
GEIL	DDR48GB2400C16QC	8GB	SS	Micron	17-16-16-36	1.2	•	•
CORSAIR	CM4X8GE2400C16K4-CN (Ver5.20)	8GB	DS	Hvnx	16-16-16-39	1.2	•	•
CORSAIR	CMD32GX4M4A2400C14 (Ver4.23)	4*8GB	DS	N/A	14-16-16-31	1.2	•	•
AMD	R748G2400U2S	8GB	DS	N/A	15-15-15-36	1.2	•	•
MICRON	MTA16ATF2G64AZ-2G3B1	16GB	DS	Micron	17-17-17-39	1.2	•	•
MICRON	MTA8ATF1G64AZ-2G3B1	8GB	SS	Micron	17-17-17-39	1.2	•	•
KINGSTON	HX424C12SB2K4/16	4*4GB	SS	Hvnx	12-14-14-35	1.35	•	•
KINGSTON	HX424C12SB2K4/32	4*8GB	DS	Hvnx	12-14-14-35	1.35	•	•
KINGSTON	HX424C15FBK2/16	2*8GB	DS	Hvnx	15-15-15-35	1.2	•	•
GALAXY	GAM4BXLBS240016JE164C	4*4GB	SS	N/A	16-16-16-36	1.2	•	•
APACER	AH08GGB24CDT5H	2*8GB	DS	N/A	16-16-16-36	1.2	•	•
CORSAIR	CMK8GX4M2A2400C14(Ver3.28)	2*4GB	SS	N/A	14-16-16-31	1.2	•	•
CORSAIR	CMK16GX4M2A2400C14	2*8GB	DS	N/A	14-16-16-31	1.2	•	•
AVEXIR	AVD4UZ124001608G-1COB	8GB	DS	N/A	16-16-16-36	1.2	•	•
AVEXIR	AVD4UZ124001608G-1BW	8GB	DS	N/A	16-16-16-36	1.2	•	•
APACER	AU08GGB24CETBGC	8GB	DS	APACER	17-17-17-39	1.2	•	•
AVEXIR	AVD4UZ124001608G-2COR	2*8GB	DS	N/A	16-16-16-36	1.2	•	•
V-COLOR	8GTC48G24S817-IMS	4*8GB	SS	V-COLOR	17-17-17-39	1.2	•	•
G.SKILL	F4-2400C15Q-64GIS	4*16GB	DS	Micron	15-15-15-35	1.2	•	•
CRUCIAL	BLS8G4D240FSB.16FARG	4*8GB	DS	Micron	16-16-16-39	1.2	•	•
GEIL	GLW416GB2400C15DC	8GB	SS	Hvnx	15-15-15-35	1.2	•	•
TEAM	TDTRD48G2400HC15ABK	8GB	SS	N/A	15-15-15-35	1.2	•	•
TEAM	TDRED48G2400HC14BK	8GB	DS	Hvnx	14-16-16-31	1.2	•	•
ADATA	AX4U2400W8G16-BRZ	8GB	DS	N/A	17-16-16-39	1.2	•	•
KINGSTON	HX424C15FB/16	16GB	DS	Micron	15-15-15-35	1.2	•	•
CRUCIAL	BLS8G4D240FSC.16FARG	8GB	DS	Micron	16-16-16-39	1.2	•	•
GALAXY	GAM4HFL1BM2400D15IE08IC	8GB	DS	N/A	15-15-15-35	1.2	•	•
CORSAIR	CMK32GX4M4A2400C16R(Ver3.31)	4*8GB	SS	Micron	16-16-16-39	1.2	•	•
CORSAIR	CMD16GX4M4B2400C10	4*4GB	SS	Hvnx	10-12-12-28	1.35	•	•
MUSHKIN	997199T	2*8GB	SS	N/A	15-15-15-35	1.2	•	•
GEIL	8G2133C151.2V	8GB	DS	Hvnx	14-16-16-35	1.2	•	•
TEAM	TED416G2400C16BK	16GB	DS	Micron	16-16-16-39	1.2	•	•
TEAM	TCD44G2400C14BK	4GB	SS	Hvnx	14-16-16-31	1.2	•	•
TIGO	TMKU8GF28-2400U	8GB	DS	N/A	17-17-17-39	1.2	•	•
APACER	AU08GGB24CEYBGC	8GB	SS	Hvnx	17-17-17-39	1.2	•	•
KINGSTON	HX424C12SB2K2/16	16GB	DS	Hvnx	12-14-14-35	1.35	•	•
GLOWAY	PC4-19200	8GB	SS	N/A	15-15-15-35	1.2	•	•
ADATA	AX4U240038G16-BWZ	8*8GB	SS	Hvnx	17-16-16-39	1.2	•	•
ADATA	AX4U2400316G16-SBF	16*16GB	DS	Hvnx	17-16-16-39	1.2	•	•
AVEXIR	AVD4UZ124001608G-4COR	4*8GB	SS	Micron	16-16-16-36	1.2	•	•
AVEXIR	AVD4UZ124001604G-4COR	4*4GB	SS	Micron	16-16-16-36	1.2	•	•
KINGSTON	TF24D4U7S8MB-8	8GB	SS	Micron	17-17-17-39	1.2	•	•
KINGSTON	TF24D4U7S8MBD-4	4GB	SS	Micron	17-17-17-39	1.2	•	•
RAMAXEL	RMUA5120MB86H9F-2400	4GB	SS	Micron	17-17-17-39	1.2	•	•
RAMAXEL	RMUA5120MB76H8F-2400	2GB	SS	Micron	17-17-17-39	1.2	•	•
V-COLOR	TC48G24S817	8GB	SS	V-COLOR	17-17-17-39	1.2	•	•
ADATA	AX4U240038G16-SBF	8*8GB	SS	Hvnx	17-17-17-39	1.2	•	•
ADATA	AX4U2400W8G16-DRD	8GB	DS	Hvnx	17-17-17-39	1.2	•	•

ADATA	AX4U2400316G16-DRD	16GB	DS	Hvnx	17-17-17-39	1.2	•	•
G.SKILL	F4-2400C15Q2-64GRK	8*8GB	SS	Hvnx	15-15-15-35	1.2	•	•
TEAM	TCD48G2400C14BK	8GB	SS	Micron	14-16-16-31	1.2	•	•
TEAM	TED44G2400C16BK	4GB	SS	Micron	16-16-16-39	1.2	•	•
CRUCIAL	BLS16G4D240FSE.16FAD	16GB	DS	Micron	16-16-16-39	1.2	•	•
CRUCIAL	BLS4G4D240FSA.8FARG	4GB	SS	Micron	16-16-16-39	1.2	•	•
PATRIOT	PV48G240C5	8GB	DS	N/A	15-15-15-35	1.2	•	•
TEAM	TFWD416G2400C15BBK	16GB	DS	TEAM	15-17-17-35	1.2	•	•
TEAM	TFRD44G2400C15ABK	4GB	SS	Hvnx	15-15-15-35	1.2	•	•
Klevv	IM44GU48N24-FFFHAZ	4GB	SS	Hvnx	15-15-15-35	1.2	•	•
Klevv	IM4AGU88N24-FFFHMZ	16GB	DS	Hvnx	15-15-15-35	1.2	•	•
Klevv	IM48GU88N24-FFFHMZ	8GB	SS	Hvnx	15-15-15-35	1.2	•	•
Klevv	IM4AGU88N24-FFFHMB	16GB	DS	Hvnx	15-15-15-35	1.2	•	•
Klevv	IM48GU88N24-FFFHMB	8GB	SS	Hvnx	15-15-15-35	1.2	•	•
Klevv	IM44GU48N24-FFFHAB	4GB	SS	Hvnx	15-15-15-35	1.2	•	•
G.SKILL	F4-2400C15D-16GTZR	8GB	SS	Hvnx	15-15-15-35	1.2	•	•
CRUCIAL	MTA16ATF1G64AZ-2G3A2	8GB	DS	Micron	17-17-17-39	1.2	•	•
G.SKILL	F4-2400C15Q-64GFX	4*16GB	DS	Hvnx	15-15-15-39	1.2	•	•
G.SKILL	F4-2400C15Q-32GFX	4*8GB	SS	Hvnx	15-15-15-39	1.2	•	•
G.SKILL	F4-2400C16Q-64GFX	4*16GB	DS	Hvnx	16-16-16-39	1.2	•	•
G.SKILL	F4-2400C16Q-32GFX	4*8GB	SS	Hvnx	16-16-16-39	1.2	•	•
CORSAIR	CMK16GX4M2Z2400C16(Ver3.31)	2*8GB	SS	Micron	16-16-16-18	1.2	•	•
CORSAIR	CMK128GX4M8A2400C14(Ver5.30)	8*16GB	DS	Hvnx	14-16-16-31	1.2	•	•
AMD	R744G2400U1S	4GB	SS	N/A	15-15-15-36	1.2	•	•
CORSAIR	CMK128GX4M8A2400C14(Ver5.30)	8*16GB	DS	Hvnx	14-16-16-31	1.2	•	•
CORSAIR	CMK16GX4M2Z2400C16(Ver3.31)	2*8GB	SS	Micron	16-16-16-39	1.2	•	•
Gell	GFR416GB2400C16S	16GB	SS	Micron	16-16-16-36	1.2	•	•
Gell	GFR432GB2400C16D	16GB	SS	Micron	16-16-16-36	1.2	•	•
HyperX	HX424C15FB2K4/32	4*8GB	SS	Hvnx	15-15-15-35	1.2	•	•
GLOWAY	STK4U2400D17081C	8GB	DS	Micron	17-17-17-39	1.2	•	•
GLOWAY	STK4U2400D17081C	8GB	SS	Micron	17-17-17-39	1.2	•	•
GLOWAY	STK4U2400D17161C	16GB	SS	Micron	17-17-17-39	1.2	•	•
PATRIOT	PSD48G240081	8GB	SS	SEC 710	17-17-17-39	1.2	•	•
PATRIOT	PSD44G240081	4GB	SS	SEC 707	16-16-16-39	1.2	•	•
PATRIOT	PSD416G24002	16GB	DS	SEC 707	17-17-17-39	1.2	•	•
PATRIOT	PVE48G240C5KRD	2*4GB	SS	N/A	15-15-15-35	1.2	•	•
PATRIOT	PVE416G240C5KBL	2*8GB	SS	N/A	15-15-15-35	1.2	•	•
SAMSUNG	M378A2K43CB1-CRC	16GB	DS	Samsung	17-17-17-39	1.2	•	•
Crucial	CT8G4DFS824A.C8FBD1	8GB	SS	Micron	17-17-17-39	1.2	•	•
ADATA	AD4X240038G17-BP	8*8GB	SS	SpecTek	17-17-17-39	1.2	•	•
APACER	AHU08GGB24CDU7S	8GB	SS	N/A	16-16-16-36	1.2	•	•
Crucial	BLS8G4D240FSC.16FBR2	8GB	DS	Micron	16-16-16-39	1.2	•	•
Asgard	VML41UG-MIC1U22ZG	8GB	SS	Micron	17-17-17-39	1.2	•	•
KINGMAX	GLLH22F-18KIIA CFBU2	16GB	DS	N/A	17-17-17-39	1.2	•	•
KINGMAX	GLL42F-D8KIBIA CFDU	8GB	DS	KINGMAX	17-17-17-39	1.2	•	•
GEIL	GP44GB2400C16SC	4GB	SS	Micron	17-16-16-36	1.2	•	•
Kingston	KVR24N17S8/4	4GB	SS	Micron	17-17-17-39	1.2	•	•
CRUCIAL	BLS16G4D240FSC.16FBR	16GB	DS	Micron	16-16-16-39	1.2	•	•
CRUCIAL	BLS8G4D240FSC.8FBD	8GB	SS	Micron	16-16-16-39	1.2	•	•
CRUCIAL	CT8G4DFB824A.C16FBD2	8GB	DS	Micron	17-17-17-39	1.2	•	•
CRUCIAL	CT16G4DFD824A.C16FHD1	16GB	DS	Micron	17-17-17-39	1.2	•	•
ADATA	AX4U240038G16-BRZ	8*8GB	SS	Hvnx	17-16-16-39	1.2	•	•
G.SKILL	F4-2400C15S-8GNT	8GB	SS	Hvnx	15-15-15-35	1.2	•	•
Crucial	CT8G4DFS824A.C8FHD1	8GB	SS	Micron	17-17-17-39	1.2	•	•
APACER	AU08GGB24CEYBGH	8GB	SS	N/A	17-17-17-39	1.2	•	•
GALAXY	GAMER D4-2400 8G C16 紅橙	8GB	DS	Hvnx	16-16-16-36	1.2	•	•
GALAXY	GAMER D4-2400 8G C16 綠橙	8GB	DS	Hvnx	16-16-16-36	1.2	•	•
GALAXY	GAMER III DDR4-2400 8G C16	8GB	SS	Micron	16-16-16-36	1.2	•	•
Ramsta	R2DD4N04G2400	4GB	SS	Micron	16-16-16-39	1.2	•	•
Ramsta	R2DD4N16G2400	16GB	SS	Micron	17-17-17-39	1.2	•	•
TIGO	TMKU8G868-2400U	8GB	SS	Micron	16-16-16-39	1.2	•	•
HyperX	HX424C15FB/4	4GB	SS	Micron	15-15-15-35	1.2	•	•
CRUCIAL	BLS8G4D240FSE.16FBR2	8GB	DS	Micron	16-16-16-39	1.2	•	•
APACER	AHU08GGB24CDU7G	8GB	SS	Micron	16-16-16-36	1.2	•	•
GEIL	GASB416GB2400C16QC	4GB	SS	Micron	16-16-16-36	1.2	•	•
GEIL	GASB432GB2400C16QC	8GB	SS	N/A	16-16-16-36	1.2	•	•
TIGO	TMKU8G868-2400U	8GB	SS	Hvnx	17-17-17-39	1.2	•	•
APACER	AU16GGB24CEYBGC	16GB	DS	APACER	17-17-17-39	1.2	•	•
GEIL	GLS48GB2400C16DC	4GB	SS	N/A	17-16-16-36	1.2	•	•
GLOWAY	TYP8U2400E17042C	8GB	SS	Micron	17-17-17-39	1.2	•	•
Asgard	VML41UG-MEC1U2BQ1	8GB	SS	N/A	17-17-17-39	1.2	•	•
silicon power	SP008GBLFU240B02	8GB	SS	Hvnx	17-17-17-39	1.2	•	•
Gell	GLS48GB2400C16DC	4GB	SS	Micron	17-16-16-36	1.2	•	•
TIGO	TMKU4G456-2400U	4GB	SS	TIGO	17-17-17-39	1.2	•	•
TIGO	TMKUF68-2400U	16GB	DS	TIGO	17-17-17-39	1.2	•	•
HYUNDAI	HYE4G24C17	4GB	SS	Hvnx	17-17-17-39	1.2	•	•
HYUNDAI	HYE8G24C17	8GB	SS	Hvnx	17-17-17-39	1.2	•	•
Apacer	AU16GGB24CEYBGH	16GB	DS	Micron	17-17-17-39	1.2	•	•
MAXSUN	MSD48G24Q3	8GB	DS	Micron	17-17-17-39	1.2	•	•
TECLAST	TLD44G24A30	4GB	DS	Micron	17-17-17-39	1.2	•	•
TECLAST	TLD48G24A30	8GB	SS	Micron	17-17-17-39	1.2	•	•
Kingston	KVR24N17S8/80-SP	8GB	SS	Micron	17-17-17-39	1.2	•	•
ADATA	AD4U2400W4G17-B	4GB	SS	SK Hvnx	15-15-15-35	1.2	•	•
ADATA	AD4U2400W8G17-B	8GB	DS	SK Hvnx	15-15-15-35	1.2	•	•
ADATA	AX4U2400316G16-DRD(XMP)	16GB	DS	SK Hvnx	16-16-16-39	1.2	•	•
ADATA	AX4U2400316G16-SBF(XMP)	16GB	DS	SK Hvnx	15-15-15-36	1.2	•	•
ADATA	AX4U240038G16-BRS-R(XMP)	8GB	SS	SK Hvnx	16-16-16-39	1.2	•	•
ADATA	AX4U240038G16-SBF(XMP)	8GB	SS	SK Hvnx	16-16-16-39	1.2	•	•
ADATA	AX4U2400W8G16-BRZ(XMP)	8GB	DS	SK Hvnx	15-15-15-36	1.2	•	•
ADATA	AX4U2400W8G16-DRD(XMP)	8GB	DS	SK Hvnx	16-16-16-39	1.2	•	•

Apacer	78.C1GMS.4010B	4x 8GB	DS	Samsung	17-17-17-39	-	•	•	
Apacer	EK.08G2T.GECC(XMP)	8GB	SS	Micron	17-17-17-39	-	•	•	Apacer EL.08G2T.GFM
CORSAIR	CMD16GX4M4A2400C14(Ver4.23)(XMP)	4x 4GB	SS	-	14-16-16-31	1.2	•	•	
CORSAIR	CMD32GX4M4A2400C14(Ver4.23)(XMP)	4x 8GB	DS	-	14-16-16-31	1.2	•	•	
CORSAIR	CMK16GX4M2D2400C14(Ver4.21)(XMP)	2x 8GB	DS	Samsung	14-16-16-31	1.2	•	•	
CORSAIR	CMK16GX4M2Z2400C16(Ver3.31)	2x 8GB	SS	Micron	16-16-16-39	1.2	•	•	CORSAIR CMK16GX4M4A2400C14(Ver4.2)
CORSAIR	CMK32GX4M4A2400C14(Ver4.23)(XMP)	4x 8GB	DS	-	14-16-16-31	1.2	•	•	
CORSAIR	CMK32GX4M4A2400C16(Ver3.31)(XMP)	4x 8GB	SS	Micron	15-15-15-36	1.2	•	•	
CORSAIR	CMK64GX4M4A2400C14(Ver3.31)(XMP)	4x 16GB	DS	Micron	15-15-15-36	1.2	•	•	
CORSAIR	CMK64GX4M4A2400C14(Ver4.31)(XMP)	4x 16GB	DS	Samsung	15-15-15-36	1.2	•	•	
CORSAIR	CMK8GX4M2D2400C14(Ver3.11)(XMP)	2x 4GB	DS	Micron	14-16-16-31	1.2	•	•	
crucial	BLS16G4D240FSB.16FBD(XMP)	16GB	DS	Micron	16-16-16-39	1.2	•	•	
crucial	BLS4G4D240FSB.8FBD(XMP)	4GB	SS	Micron	16-16-16-39	1.2	•	•	
crucial	BLS8G4D240FSBK.8FBD(XMP)	8GB	SS	Micron	16-16-16-39	1.2	•	•	
crucial	CT16G4DFD824A.C16FDR1	16GB	DS	Micron	17-17-17-39	1.2	•	•	
G.SKILL	F4-2400C14Q2-128GRK(XMP)	8x 16GB	DS	Samsung	14-14-14-34	1.2	•	•	
G.SKILL	F4-2400C14Q2-128GRK(XMP)	8x 16GB	DS	Samsung	15-15-15-36	1.2	•	•	
G.SKILL	F4-2400C15Q-16GRR(XMP)	4x 4GB	SS	Micron	15-15-15-35	1.2	•	•	
G.SKILL	F4-2400C15Q2-128GRK(XMP)	8x 16GB	DS	Samsung	15-15-15-35	1.2	•	•	
G.SKILL	F4-2400C15Q2-128GVK(XMP)	8x 16GB	DS	SK Hynix	15-15-15-36	1.2	•	•	
G.SKILL	F4-2400C15Q2-64GRK(XMP)	8x 8GB	DS	Samsung	15-15-15-35	1.2	•	•	
G.SKILL	F4-2400C15Q-32GRR(XMP)	4x 8GB	DS	Micron	15-15-15-35	1.2	•	•	
Gell	GASB416GB2400C16QC(XMP)	4GB	SS	Micron	16-16-16-36	1.2	•	•	
Gell	GFR432GB2400C16D(XMP)	16GB	SS	Micron	16-16-16-36	1.2	•	•	
Gell	GLS48GB2400C16DC(XMP)	4GB	SS	Micron	16-16-16-36	1.2	•	•	
Gell	GPR416GB2400C15OC(XMP)	4x 4GB	SS	Samsung	15-15-15-35	1.2	•	•	
Gell	GPR432GB2400C15QC(XMP)	4x 8GB	DS	SK Hynix	15-15-15-35	1.2	•	•	
Gell	GPR432GB2400C16QC(XMP)	4x 8GB	SS	Micron	16-16-16-36	1.2	•	•	
GLOWAY	TYP4U2400D17021C	2GB	SS	Micron	17-17-17-39	1.2	•	•	
Hyper X	HX424C12PB2K4/16(XMP)	4x 4GB	SS	SK Hynix	12-13-13-35	1.2	•	•	
Hyper X	HX424C12SB2/4(XMP)	4GB	SS	SK Hynix	15-15-15-36	1.35	•	•	
Hyper X	HX424C12SB2K2/16(XMP)	2x 8GB	DS	SK Hynix	15-15-15-36	1.35	•	•	
Hyper X	HX424C12SB2K4/16(XMP)	4x 4GB	SS	SK Hynix	15-15-15-36	1.35	•	•	
Hyper X	HX424C12SB2K4/32(XMP)	4x 8GB	DS	SK Hynix	15-15-15-36	1.35	•	•	
Hyper X	HX424C15B2K4/32(XMP)	4x 8GB	SS	Micron	15-15-15-35	1.2	•	•	
Hyper X	HX424C15FB/4	4GB	SS	SK Hynix	15-15-15-35	1.2	•	•	
Hyper X	HX424C15FB/8(XMP)	8GB	SS	SK Hynix	14-14-14-32	1.2	•	•	
Hyper X	HX424C15FBK2/16	2x 16GB	DS	SK Hynix	15-15-15-35	1.2	•	•	
Hyper X	HX424C15FBK2/8	2x 4GB	SS	SK Hynix	15-15-15-35	1.2	•	•	
Hyper X	HX424C15FBK4/16	4x 4GB	SS	SK Hynix	15-15-15-35	1.2	•	•	
Hyper X	HX424C15FBK4/16	4x 4GB	SS	SK Hynix	14-14-14-32	1.2	•	•	
Hyper X	HX424C15FBK4/32	4x 8GB	DS	SK Hynix	15-15-15-35	1.2	•	•	
Hyper X	HX424C15FBK4/32	4x 8GB	DS	SK Hynix	15-15-15-35	1.2	•	•	
Hyper X	HX424C15FBK4/64	4x 16GB	DS	Micron	15-15-15-35	1.2	•	•	
KINGMAX	GLLF62F-DAKZIG-CLBU	4GB	SS	KINGMAX	17-17-17-39	-	•	•	
KINGMAX	GLLH22F-18KIIA-CFBU2	16GB	DS	KINGMAX	17-17-17-39	-	•	•	
Kingston	KVR24N17D8/16	16GB	DS	Micron	17-17-17-39	1.2	•	•	
Kingston	KVR24N17D8/8	8GB	DS	Micron	17-17-17-39	1.2	•	•	
Kingston	KVR24N17S8/4	4GB	SS	Micron	17-17-17-39	1.2	•	•	
Kingston	KVR24N17S8/8	8GB	SS	Micron	17-17-17-39	1.2	•	•	
Klevv	IM44GU48N24-FFFHAB(XMP)	4GB	SS	SK Hynix	15-15-15-35	1.2	•	•	
Klevv	IM44GU48N24-FFFHAZ(XMP)	4GB	SS	SK Hynix	15-15-15-35	1.2	•	•	
Klevv	IM48GU88N24-FFFHMB(XMP)	8GB	SS	SK Hynix	15-15-15-35	1.2	•	•	
Klevv	IM48GU88N24-FFFHMZ(XMP)	8GB	SS	SK Hynix	15-15-15-35	1.2	•	•	
Klevv	IM4AGU88N24-FFFHMB(XMP)	16GB	DS	SK Hynix	15-15-15-35	1.2	•	•	
Micron	MTA16ATF2G64A2-ZG3B1	16GB	DS	Micron	17-17-17-39	1.2	•	•	
panram	W4U2400PS-8G	8GB	SS	SK Hynix	14-14-14-31	-	•	•	
PATRIOT	PSD44G240081	4GB	SS	Samsung	16-16-16-39	1.2	•	•	
PATRIOT	PSD44G240081	4GB	SS	PATRIOT	16-16-16-39	1.2	•	•	
PATRIOT	PSD48G240081	8GB	SS	Samsung	17-17-17-39	1.2	•	•	
PATRIOT	PV432G240C5QK(XMP)	4x 8GB	SS	-	15-15-15-35	1.2	•	•	
PATRIOT	PVE416G240C5KRD(XMP)	2x 8GB	SS	-	15-15-15-35	-	•	•	
PATRIOT	PVE48G240C5KRD(XMP)	2x 4GB	SS	-	15-15-15-35	-	•	•	

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.

- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for better compatibility.
- Make sure to install the memory modules from the gray slots first.
- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules may not be able to run at the default frequency.
- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from the same vendor. Check with your system manufacturer for more information.
- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors.

PRIME H310M-C R2.0

DDR4 Qualified Vendors List (QVL)									
Vendors	Part No.	Size	SS/DS	Chip Brand	Timing	Voltage (V)	Socket support (DIMM)		
							1 DIMM	2 DIMM	
CORSAIR	CMK16GX4M4A2666C16 (Ver5.29)	4*4GB	SS	N/A	16-18-18-35	1.2	•	•	
CORSAIR	CMD32GX4M4A2666C15(Ver5.29)	4*8GB	DS	N/A	15-17-17-35	1.2	•	•	
MUSHKIN	997192F	2*4GB	SS	N/A	15-15-15-35	1.2	•	•	
KINGSTON	HX426C13PBK4/32	4*8GB	DS	Hynix	15-15-15-36	1.35	•	•	
KINGSTON	HX426C15FBK4/32	4*8GB	DS	Hynix	15-17-17-35	1.2	•	•	
CORSAIR	CMD128GX4M8A2666C15	4*16GB	DS	N/A	15-17-17-35	1.2	•	•	

KINGSTON	HX426C15FBK4/16	4*4GB	SS	Hvnx	15-17-17-35	1.2	•	•
CRUCIAL	BLE4G4D26AFAE.8FAD	4GB	SS	Micron	16-16-17-36	1.2	•	•
CRUCIAL	BLE8G4D26AFAE.16FAD	8GB	DS	Micron	16-17-17-36	1.2	•	•
AVEXIR	AVD4UZ126661504G-4COB	4*4GB	SS	N/A	15-15-15-36	1.2	•	•
AVEXIR	AVD4UZ126661508G-4COB	4*8GB	DS	N/A	15-15-15-36	1.2	•	•
CRUCIAL	BLT4G4D26AFTA.8FADG	4GB	SS	Micron	16-17-17-36	1.2	•	•
KLEVV	IMA41G6MFR8N-C F0	8GB	DS	N/A	15-15-15-35	1.2	•	•
KINGSTON	HX426C13SB2K4/32	4*8GB	DS	Hvnx	15-15-15-36	1.35	•	•
KINGSTON	HX426C13SB2K4/16	4*4GB	SS	Hvnx	15-15-15-36	1.35	•	•
PNY	MD16GK4D4266615AXR	4*4GB	SS	N/A	15-15-15-35	1.2	•	•
AVEXIR	AVD4UZ126661504G-4IPROG	4*4GB	DS	N/A	15-15-15-35	1.2	•	•
AVEXIR	AVD4UZ126661504G	2*4GB	DS	N/A	15-15-15-35	1.2	•	•
CORSAIR	CMU32GX4M2A2666C16 (Ver5.20)	2*16GB	DS	Samsung	16-18-18-35	1.2	•	•
CORSAIR	CMK32GX4M4A2666C16(Ver3.20)	4*8GB	DS	N/A	16-18-18-35	1.2	•	•
CORSAIR	CMK16GX4M2A2666C16 (Ver3.31)	2*8GB	SS	Micron	16-18-18-35	1.2	•	•
CORSAIR	CMK32GX4M2A2666C16 (Ver5.39)	2*16GB	DS	N/A	16-18-18-35	1.2	•	•
CORSAIR	CMK16GX4M4A2666C15 (Ver5.20)	4*4GB	SS	N/A	15-17-17-35	1.2	•	•
CORSAIR	CMK64GX4M4A2666C16 (Ver5.3)	4*16GB	DS	Hvnx	16-18-18-35	1.2	•	•
CORSAIR	CMK32GX4M4A2666C15 (Ver5.20)	4*8GB	DS	Hvnx	15-17-17-35	1.2	•	•
TEAM	TFRD4162666C15BBK	16GB	DS	Samsung	15-17-17-35	1.2	•	•
TEAM	TFWD48G2666C15BBK	8GB	DS	Samsung	15-17-17-35	1.2	•	•
TEAM	TCD44G2666C15BBK	4GB	SS	Hvnx	15-17-17-35	1.2	•	•
HyperX	HX426C15FBK2/16	2*8GB	DS	Micron	15-17-17-35	1.2	•	•
Klevv	IM48GU88N26-FFFHMZ	8GB	SS	Hvnx	15-15-15-35	1.2	•	•
Klevv	IM4AGU88N26-FFFHMZ	16GB	DS	Hvnx	15-15-15-35	1.2	•	•
Klevv	IM44GU48N26-FFFHAZ	4GB	SS	Hvnx	15-15-15-35	1.2	•	•
CORSAIR	CMK16GX4M2A2666C16(Ver5.30)	8GB	SS	Hvnx	16-18-18-35	1.2	•	•
ADATA	AX4U2666W4G16-BRZ	4GB	SS	Hvnx	16-16-16-39	1.2	•	•
ADATA	AX4U2666W8G16-QRZ	4*8GB	DS	Hvnx	16-16-16-39	1.2	•	•
crucial	BLS8G4D26BFSC.16FBR2	8GB	DS	N/A	16-18-18-38	1.2	•	•
crucial	BLS16G4D26BFSC.16FBD	16GB	DS	Micron	16-18-18-38	1.2	•	•
crucial	BLS4G4D26BFSC.8FBR2	4GB	SS	N/A	16-18-18-38	1.2	•	•
CORSAIR	CMK128GX4M8A2666C16(Ver5.39)	8*16GB	DS	Hvnx	16-18-18-36	1.2	•	•
CORSAIR	CMR16GX4M2A2666C16(Ver5.30)	2*8GB	SS	Hvnx	16-18-18-35	1.2	•	•
CORSAIR	CMR64GX4M8A2666C16(Ver5.30)	8*8GB	SS	N/A	16-18-18-35	1.2	•	•
HyperX	HX426C16FB2K4/64	4*16GB	DS	Hvnx	16-18-18-39	1.2	•	•
G.SKILL	F4-2666C16Q2-64GRB	8*8GB	SS	Hvnx	16-16-16-36	1.2	•	•
HyperX	HX426C15SBK8/128	8*16GB	DS	N/A	15-16-16-35	1.2	•	•
HyperX	HX426C13PB3/8	4*8GB	SS	N/A	13-15-15-35	1.35	•	•
HyperX	HX426C13PB3K2/16	4*8GB	SS	N/A	13-15-15-35	1.35	•	•
HyperX	HX424C12PB3/8	4*8GB	SS	N/A	13-15-15-35	1.35	•	•
HyperX	HX424C12PB3K2/16	4*8GB	SS	N/A	13-15-15-35	1.35	•	•
HyperX	HX424C12PB3K4/32	4*8GB	SS	N/A	13-15-15-35	1.35	•	•
HyperX	HX426C13PB3/16	4*16GB	DS	Hvnx	13-15-15-35	1.35	•	•
HyperX	HX426C13PB3K2/32	4*16GB	DS	Hvnx	13-15-15-35	1.35	•	•
HyperX	HX424C12PB3K4/64	4*16GB	DS	Hvnx	13-15-15-35	1.35	•	•
HyperX	HX424C12PB3/16	4*16GB	DS	Hvnx	13-15-15-35	1.35	•	•
HyperX	HX424C12PB3K2/32	4*16GB	DS	Hvnx	13-15-15-35	1.35	•	•
CRUCIAL	BLS8G4D26BFSC.8FBR	8GB	SS	Micron	16-18-18-38	1.2	•	•
CRUCIAL	BLS8G4D26BFSC.8FBD	8GB	SS	Micron	16-18-18-38	1.2	•	•
MICRON	MTA8ATF1G64AZ-2G6H1	8GB	SS	Hvnx	19-19-19-43	1.2	•	•
TIGO	TMKG8G868-2666N	8GB	SS	N/A	19-19-19-43	1.2	•	•
ADATA	AX4U266638G16-BRS	8*8GB	SS	Hvnx	16-16-16-39	1.2	•	•
ADATA	AD4U266638G19-B	8*8GB	SS	N/A	19-19-19-43	1.2	•	•
ADATA	AD4U2666316G19-B	16*16GB	DS	N/A	19-19-19-43	1.2	•	•
PANRAM	W4U2666PS-16G	2*16GB	DS	Hvnx	16-18-18-35	1.2	•	•
PANRAM	W4U2666PS-8G	2*8GB	DS	panram	16-18-18-35	1.2	•	•
Team	TPD416G2666HC19BK	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TED416G2666C1901	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TPRD416G2666HC1901	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TPD416G2666HC1901	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TED432G2666C19DC01	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TPRD432G2666HC19DC01	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TPD432G2666HC19DC01	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TED464G2666C19OC01	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TPRD464G2666HC19OC01	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TPD464G2666HC19OC01	16GB	DS	Micron	19-19-19-43	1.2	•	•
Team	TPD48G2666HC19BK	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TED48G2666C1901	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPRD48G2666HC1901	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPD48G2666HC1901	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TED416G2666C19DC01	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPRD416G2666HC19DC01	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPD416G2666HC19DC01	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TED432G2666C19OC01	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPRD432G2666HC19OC01	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPD432G2666HC19OC01	8GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPD44G2666HC19BK	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TED44G2666C1901	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPRD44G2666HC1901	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPD44G2666HC1901	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TED48G2666C19DC01	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPRD48G2666HC19DC01	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPD48G2666HC19DC01	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TED416G2666C19OC01	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPRD416G2666HC19OC01	4GB	SS	N/A	19-19-19-43	1.2	•	•
Team	TPD416G2666HC19OC01	4GB	SS	N/A	19-19-19-43	1.2	•	•

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.

- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for best performance.
- Make sure to install the memory modules from the gray slots first.
- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules will run at 2666MHz.
- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from the same vendor. Check with your system administrator for more details.
- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors.

PRIME H310M-C R2.0

DDR4 2800 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Timing	Voltage(V)	Run@Speed	Socket support (1 DIMM)
CORSAIR	CMK16GX4M4A2800C16(Ver5.29)	4*4GB	SS	N/A	16-18-18-36	1.2	DDR4-2666	•
KINGSTON	HX428C14PB2K4/16	4*4GB	SS	Hynix	15-15-15-36	1.35	DDR4-2666	•
PATRIOT	PX416G280C6QK	4*4GB	SS	N/A	16-18-18-36	1.2	DDR4-2666	•
PANRAM	PUD42800C164G4NJW	4*4GB	SS	N/A	16-18-18-36	1.25	DDR4-2666	•
KINGSTON	HX428C14PBK4/32	4*8GB	DS	Hynix	15-15-15-36	1.35	DDR4-2666	•
AVEXIR	AVD4UZ128001604G-4COB	4*4GB	SS	N/A	15-15-15-36	1.2	DDR4-2666	•
AVEXIR	AVD4UZ128001608G-4COB	4*8GB	DS	N/A	15-15-15-36	1.2	DDR4-2666	•
CORSAIR	CMK32GX4M4A2800C16	4*8GB	DS	N/A	16-18-18-36	1.2	DDR4-2666	•
KINGSTON	HX428C14SB2K4/32	4*8GB	DS	N/A	15-15-15-36	1.35	DDR4-2666	•
KINGSTON	HX428C14SB2K4/16	4*4GB	SS	Hynix	15-15-15-36	1.35	DDR4-2666	•
TEAM	TDGED48G2800HC16ABK	2*8GB	SS	Hynix	16-16-16-36	1.2	DDR4-2666	•
PATRIOT	PV416G280C6QK	4*4GB	SS	N/A	16-18-18-36	1.2	DDR4-2666	•
G.SKILL	F4-2800C16D-16GRR	2*8GB	SS	Hynix	16-16-16-36	1.2	DDR4-2666	•
ADATA	AX4U280038G17-SBF	8*8GB	SS	Hynix	18-17-17-36	1.2	DDR4-2666	•
ADATA	AX4U2800316G16-SBF	16GB	DS	Hynix	17-16-16-36	1.2	DDR4-2666	•
CORSAIR	CMD32GX4M4A2800C16 (Ver5.20)	8GB	DS	Hynix	16-18-18-36	1.2	DDR4-2666	•
G.SKILL	F4-2800C14Q-64GVK	4*16GB	DS	Samsung	14-14-14-35	1.35	DDR4-2666	•
G.SKILL	F4-2800C16Q-32GVR	4*8GB	SS	Hynix	16-16-16-36	1.2	DDR4-2666	•
AVEXIR	AVD4UZ128001504G-4BZ1RR	4*4GB	SS	Samsung	15-15-15-35	1.35	DDR4-2666	•
AVEXIR	AVD4UZ128001508G-4BZ1RR	4*8GB	DS	Samsung	15-15-15-35	1.35	DDR4-2666	•
CORSAIR	CMD16GX4M4A2800C16(Ver3.21)	4*4GB	SS	Micron	16-18-18-36	1.2	DDR4-2666	•
TEAM	TFWD416G2800C16CBK	16GB	DS	TEAM	16-18-18-38	1.2	DDR4-2666	•
TEAM	TFRD48G2800C16CBK	8GB	DS	Samsung	16-18-18-38	1.2	DDR4-2666	•
FORZA	NFMUD416E8-2800EH2A	16GB	DS	Hynix	17-17-17-36	1.2	DDR4-2666	•
FORZA	NFMUD480E8-2800DH2A	8GB	SS	N/A	17-17-17-36	1.2	DDR4-2666	•
ADATA	AX4U2800W8G17-BRD	8GB	DS	N/A	17-17-17-36	1.2	DDR4-2666	•
G.SKILL	F4-2800C15Q-32GVR	4*8GB	SS	Hynix	15-15-15-35	1.25	DDR4-2666	•
ADATA	AX4U2800W4G17-BRZ	2*4GB	SS	Hynix	17-17-17-36	1.2	DDR4-2666	•
ADATA	AX4U280038G17-BWZ	8GB	SS	Hynix	17-17-17-36	1.2	DDR4-2666	•
KINGMAX	GLMG42F-18KIIA CJBR4	8GB	SS	KINGMAX	17-17-17-39	1.2	DDR4-2666	•

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.

- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for best performance.
- Make sure to install the memory modules from the gray slots first.
- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules will run at 2666MHz.
- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from the same vendor. Check with your system administrator for more details.
- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors.

PRIME H310M-C R2.0

DDR4 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Timing	Voltage(V)	Run@Speed	Socket support (1 2 DIMM)
CORSAIR	CMD32GX4M2B3000C15(Ver4.31)	2*16GB	DS	N/A	15-17-17-35	1.35	DDR4-2666	• •
KINGSTON	HX430C15PB2K4/16	4*4GB	SS	Hvnx	15-15-15-36	1.35	DDR4-2666	• •
G.SKILL	F4-3000C15Q-16GRR	4*4GB	SS	Hvnx	15-15-15-35	1.35	DDR4-2666	• •
PANRAM	PUD43000C154G4NJW	4*4GB	SS	N/A	15-17-17-35	1.35	DDR4-2666	• •
KINGSTON	HX430C15SB2K4/32	4*8GB	DS	Hvnx	15-15-15-36	1.35	DDR4-2666	• •
AVEXIR	AVD4UZ130001604G-4COB	4*4GB	SS	N/A	15-15-15-36	1.35	DDR4-2666	• •
AVEXIR	AVD4UZ130001608G-4COB	4*8GB	DS	N/A	15-15-15-36	1.35	DDR4-2666	• •
KINGSTON	HX430C15SBK2/16	2*8GB	DS	N/A	15-15-15-36	1.35	DDR4-2666	• •
KLEVV	IM44GU48A30-GIIHMC	4*4GB	SS	N/A	17-18-18-36	1.35	DDR4-2666	• •
CORSAIR	CMK16GX4M2B3000C15 (Ver4.24)	2*8GB	DS	Hvnx	15-17-17-35	1.35	DDR4-2666	• •
KINGSTON	HX430C15SB2K4/16	4*4GB	SS	Hvnx	15-15-15-36	1.35	DDR4-2666	• •
TEAM	TDGED48G3000HC16ABK	2*8GB	DS	Hynix	16-16-16-36	1.35	DDR4-2666	• •
PATRIOT	PV416G300C6QK	4*4GB	SS	N/A	16-16-16-36	1.35	DDR4-2666	• •
G.SKILL	F4-3000C15D-32GVR	2*16GB	DS	N/A	15-15-15-35	1.35	DDR4-2666	• •
CORSAIR	CMK64GX4M2B3000C15 (Ver4.31)	4*16GB	DS	Samsung	15-17-17-35	1.35	DDR4-2666	• •
TEAM	TCD48G300C16ABK	8GB	SS	Hvnx	16-16-16-36	1.35	DDR4-2666	• •
ADATA	AX4U300038G16-DBZ	8*8GB	DS	Hvnx	16-18-18-36	1.35	DDR4-2666	• •
ADATA	AX4U3000316G16-BGZ	16GB	DS	N/A	16-18-18-36	1.35	DDR4-2666	• •
CORSAIR	CMD16GX4M2B3000C15(Ver4.24)	4GB	SS	Samsung	15-17-17-35	1.35	DDR4-2666	• •
CORSAIR	CMK32GX4M2B3000C15(Ver5.39)	16GB	DS	Hvnx	15-17-17-35	1.35	DDR4-2666	• •
CORSAIR	CMU16GX4M2C3000C15 (Ver4.31)	8GB	SS	Samsung	15-17-17-35	1.35	DDR4-2666	• •
CORSAIR	CMK16GX4M4B3000C15(Ver3.21)	4GB	SS	Micron	15-17-17-35	1.35	DDR4-2666	• •
G.SKILL	F4-3000C15Q-32GRK	4*8GB	DS	Samsung	15-15-15-35	1.35	DDR4-2666	• •
CORSAIR	CMK8GX4M2B3000C15(Ver3.21)	2*4GB	SS	Micron	15-17-17-35	1.35	DDR4-2666	• •
CORSAIR	CMU32GX4M4C3000C15 (Ver5.3)	4*8GB	DS	Hvnx	15-17-17-35	1.35	DDR4-2666	• •
GEIL	GFR416GB3000C15ADC	8GB	SS	Hvnx	15-17-17-35	1.35	DDR4-2666	• •

TEAM	TFWD416G3000C16CBK	16GB	DS	Hvnx	16-18-18-38	1.35	DDR4-2666	•	•
TEAM	TFRD48G3000C16CBK	8GB	DS	Samsung	16-18-18-38	1.35	DDR4-2666	•	•
TEAM	TCD44G3000C16CBK	4GB	SS	Hynix	16-18-18-38	1.35	DDR4-2666	•	•
Klevv	IM4AGU88A30-FGGHMZ	16GB	DS	Hvnx	16-16-16-36	1.35	DDR4-2666	•	•
Klevv	IM48GU88A30-FGGHMZ	8GB	SS	Hvnx	16-16-16-36	1.35	DDR4-2666	•	•
Klevv	IM44GU48A30-FGGHAZ	4GB	SS	Hynix	16-16-16-36	1.35	DDR4-2666	•	•
Klevv	IM48GU88A30-FGGHMB	8GB	SS	Hvnx	16-16-16-36	1.35	DDR4-2666	•	•
Klevv	IM44GU48A30-FGGHAB	4GB	SS	Hvnx	16-16-16-36	1.35	DDR4-2666	•	•
Klevv	IM4AGU88A30-FGGHMB	16GB	DS	Hynix	16-16-16-36	1.35	DDR4-2666	•	•
CORSAIR	CMD16GX4M2B3000C15(Ver5.30)	2* 8GB	SS	Hvnx	15-17-17-35	1.35	DDR4-2666	•	•
CORSAIR	CMD32GX4M4C3000C15(Ver5.30)	4* 8GB	SS	N/A	15-17-17-35	1.35	DDR4-2666	•	•
FORZA	NFMUD480E8-3000DH2A	8GB	SS	Hynix	15-17-17-35	1.35	DDR4-2666	•	•
CORSAIR	CMR16GX4M2C3000C15(Ver4.31)	2* 8GB	SS	Hvnx	15-17-17-35	1.35	DDR4-2666	•	•
CORSAIR	CMR32GX4M4C3000C15	4* 8GB	DS	Hvnx	15-17-17-35	1.35	DDR4-2666	•	•
Team	TDRD48G3000HC16CBK	8GB	DS	Samsung	16-18-18-38	1.35	DDR4-2666	•	•
Team	TDRGD48G3000HC16CBK	8GB	DS	Samsung	16-18-18-38	1.35	DDR4-2666	•	•
GALAXY	HOF DDR4-3000	2* 8GB	SS	Hvnx	16-18-18-38	1.35	DDR4-2666	•	•
Gell	GLR416GB3000C15ADC	8GB	SS	Hvnx	15-17-17-35	1.35	DDR4-2666	•	•
G.SKILL	F4-3000C15S-16GVR	16GB	DS	Hvnx	15-15-15-35	1.35	DDR4-2666	•	•
FORZA	NMUD416E82-3000DB30	16GB	DS	Hvnx	15-17-17-35	1.35	DDR4-2666	•	•
FORZA	NMUD480E82-3000DB30	8GB	SS	Hynix	15-17-17-35	1.35	DDR4-2666	•	•
PATRIOT	PV432G300C6KQ	4* 8GB	SS	N/A	16-16-16-36	1.35	DDR4-2666	•	•
HyperX	HX430C15PB3K4/32	4* 8GB	SS	Hvnx	15-17-17-36	1.35	DDR4-2666	•	•
CRUCIAL	BLT8G4D30AETA.K16FE	8GB	DS	Samsung	15-16-16-35	1.35	DDR4-2666	•	•
PATRIOT	PVE416G300C6KBL	2* 8GB	SS	N/A	16-16-16-36	1.35	DDR4-2666	•	•
PATRIOT	PVE48G300C6KRD	2*4GB	SS	N/A	16-16-16-36	1.35	DDR4-2666	•	•
G.SKILL	F4-3000C14Q2-128GVKD	8*16GB	DS	Samsung	14-14-14-34	1.35	DDR4-2666	•	•
Team	TF4D48G3000HC16CBK	8GB	SS	Hvnx	16-18-18-38	1.35	DDR4-2666	•	•
GALAXY	N/A	2*8GB	SS	Hvnx	16-18-18-38	1.35	DDR4-2666	•	•
TIGO	TMKU8GF58-3000X	8GB	DS	Samsung	16-18-18-36	1.35	DDR4-2666	•	•
CORSAIR	CMK16GX4M2B3000C15R (Ver5.30)	8GB*2	SS	Hvnx	15-17-17-35	1.35	DDR4-2666	•	•
CORSAIR	CMK16GX4M2B3000C15R (Ver3.32)	8GB*2	SS	N/A	15-17-17-35	1.35	DDR4-2666	•	•
CORSAIR	CM4X8GD3000C15U4-CN(Ver.5.39)	8GB	SS	Hynix	15-17-17-35	1.35	DDR4-2666	•	•
ADATA	AX4U300038G16-BBG	8*8GB	SS	Hvnx	16-18-18-36	1.35	DDR4-2666	•	•
Hyper X	HX430C15PB3/8	8GB	SS	N/A	15-17-17-36	1.35	DDR4-2666	•	•
	HX430C15PB3K2/16	2*8GB							
TEKISM	T4X3000B8G17-HY	8GB	DS	N/A	17-17-17-36	1.35	DDR4-2666	•	•
CORSAIR	CMK16GX4M2B3000C15 (Ver5.39)	2*8GB	SS	N/A	15-17-17-35	1.35	DDR4-2666	•	•
G.SKILL	F4-3000C16D-16GTZR	2*8GB	SS	N/A	16-18-18-38	1.35	DDR4-2666	•	•
GALAXY	GAM4IRL1BMR3000G16LD162C	2*8GB	SS	Micron	16-18-18-38	1.35	DDR4-2666	•	•

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.

- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for better compatibility.

- Make sure to install the memory modules from the gray slots first.

- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default set

- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from

- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors.

PRIME H310M-C R2.0

DDR4 3200 Qualified Vendors List (QVL)		Size	SS/DS	Chip Brand	Timing	Voltage(V)	Run@Speed	ocket support (O)	
Vendors	Part No.							1 DIMM	2 DIMM
PANRAM	PUD43200C164G4NJW	4* 4GB	SS	N/A	16-18-18-39	1.35	DDR4-2666	•	•
MUSHKIN	997202F	2*4GB	SS	N/A	15-15-15-36	1.2	DDR4-2666	•	•
G.SKILL	F4-3200C16D-8GVKB	2*4GB	SS	Samsung	16-18-18-38	1.35	DDR4-2666	•	•
APACER	78.BAGMD.AF20B	2*4GB	SS	Hynix	16-16-16-36	1.35	DDR4-2666	•	•
PATRIOT	PV48G320C6K	2*4GB	SS	N/A	16-16-16-36	1.35	DDR4-2666	•	•
HyperX	HX432C16PB3K4/32	4*8GB	SS	Hynix	16-18-18-36	1.35	DDR4-2666	•	•
ADATA	AX4U3200W8G16-BGZ	8GB	DS	Samsung	16-16-16-36	1.35	DDR4-2666	•	•
TEAM	TFWD416G3200C16CBK	16GB	DS	Samsung	16-18-18-38	1.35	DDR4-2666	•	•
TEAM	TFWD48G3200C16CBK	8GB	DS	Samsung	16-18-18-38	1.35	DDR4-2666	•	•
G.SKILL	F4-3200C16D-16GTZR	2*8GB	SS	N/A	18-18-18-38	1.35	DDR4-2666	•	•
G.SKILL	CMD32GX4M2C3200C16(Ver5.39)	4*8GB	SS	Samsung	14-14-14-34	1.35	DDR4-2666	•	•
CORSAIR	CMK16GX4M2B3200C16(Ver4.24)	2*16GB	DS	Hynix	16-18-18-36	1.35	DDR4-2666	•	•
CORSAIR	CMU16GX4M2C3200C16(Ver5.39)	8*8GB	SS	N/A	16-18-18-36	1.35	DDR4-2666	•	•
Team	CMK32GX4M2B3200C16(Ver5.39)	8GB	SS	Hynix	16-18-18-38	1.35	DDR4-2666	•	•
CORSAIR	CMK64GX4M8B3200C16(Ver4.31)	2*8GB	DS	Samsung	16-18-18-36	1.35	DDR4-2666	•	•
G.SKILL	CMK16GX4M2B3200C16(Ver4.24)	2*8GB	DS	N/A	16-16-16-36	1.35	DDR4-2666	•	•
CORSAIR	CMU16GX4M2C3200C16(Ver5.39)	2*8GB	SS	Hynix	16-18-18-36	1.35	DDR4-2666	•	•
G.SKILL	F4-3200C16S-8GRKB	8GB	SS	N/A	16-18-18-38	1.35	DDR4-2666	•	•
CORSAIR	CMU32GX4M2C3200C16(Ver5.39)	2*16GB	DS	Hynix	16-18-18-36	1.35	DDR4-2666	•	•
Hyper X	HX432C16PB3K2/16	2*8GB	SS	Hynix	16-18-18-36	1.35	DDR4-2666	•	•

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.

- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for better compatibility.

- Make sure to install the memory modules from the gray slots first.

- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules fo

- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from the same vendor. Check with th

- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors .

DIMM Slots

• 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration

• 2 DIMM: Supports one pair of modules inserted into either the **Gray** slots or the **Black** slots as one pair of Dual-channel memory configuration

• 4 DIMM: Supports 4 modules inserted into both the **Gray** and **Black** slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is rec

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some

PRIME H310M-C R2.0

DDR4 3300 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Timing	Voltage(V)	Run@Speed	ocket support (O)	
								1 DIMM	2 DIMM
ADATA	AX4U333W4G16-QGZ	4*8GB	SS	N/A	16-16-16-36	1.35	DDR4-2666	•	•
HyperX	HX433C16PB3K2/16	2*8GB	SS	N/A	16-18-18-36	1.35	DDR4-2666	•	•
G.SKILL	F4-3300C16Q-16GRKD	4*4GB	SS	Hynix	16-16-16-36	1.35	DDR4-2666	•	•
CORSAIR	CMR32GX4M4C3333C16(Ver4.31)	4*8GB	SS	Samsung	16-18-18-35	1.35	DDR4-2666	•	•

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.

- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for better compatibility.
- Make sure to install the memory modules from the gray slots first.
- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules fo
- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from the same vendor. Check with th
- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors .

DIMM Slots

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
- 2 DIMM: Supports one pair of modules inserted into either the Gray slots or the Black slots as one pair of Dual-channel memory configuration
- 4 DIMM: Supports 4 modules inserted into both the Gray and Black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is rec

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some

PRIME H310M-C R2.0

DDR4 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/D	Chip Brand	Timing	Voltage(V)	Run@Speed	ocket support	
								1 DIMM	2
GEIL	GLWR416GB3400C16AQC	4*4GB	SS	N/A	16-18-18-36	1.35	DDR4-2666	•	•
G.SKILL	F4-3400C16Q-16GRBD	4*4GB	SS	Samsung	16-18-18-38	1.35	DDR4-2666	•	•
G.SKILL	F4-3466C16Q-16GVK	4*4GB	SS	N/A	16-18-18-38	1.35	DDR4-2666	•	•
CORSAIR	CMD16GX4M4B3466C18 (Ver4.23)	4*4GB	SS	N/A	18-19-19-39	1.35	DDR4-2666	•	•
PATRIOT	CMD32GX4M2B3466C16(Ver4.31)	2*4GB	SS	Samsung	17-18-18-36	1.35	DDR4-2666	•	•
CORSAIR	CMU32GX4M4C3400C16R (Ver5.20)	4*8GB	SS	Samsung	16-18-18-36	1.35	DDR4-2666	•	•
CORSAIR	CMD32GX4M2B3466C16(Ver4.31)	2*16GB	DS	Samsung	16-18-18-36	1.35	DDR4-2666	•	•
CORSAIR	CMR16GX4M2C3466C16(Ver4.31)	2*8GB	SS	Samsung	16-18-18-36	1.35	DDR4-2666	•	•

G.SKILL F4-3466C16Q-16GVK 2*8GBSS/A16-18-18-38 1.35DDR4-2666

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.

- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for better compatibility.
- Make sure to install the memory modules from the gray slots first.
- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules fi
- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from the same vendor. Check with th
- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors.

DIMM Slots

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
- 2 DIMM: Supports one pair of modules inserted into either the Gray slots or the Black slots as one pair of Dual-channel memory configuration
- 4 DIMM: Supports 4 modules inserted into both the Gray and Black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is re

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, sor

PRIME H310M-C R2.0

DDR4 3600 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Timing	Voltage(V)	Run@Speed	ocket support	
								1	2 DIMM
G.SKILL	F4-3600-C17Q-16GVK	4*4GB	SS	N/A	17-18-18-38	1.35	DDR4-2666	•	•
GALAXY	HOF4CALCS3600K17LD162C	2*8GB	SS	Samsung	17-18-18-38	1.35	DDR4-2666	•	•
CORSAIR	CMD8GX4M2B3600C18 (Ver4.24)	2*4GB	SS	Samsung	18-19-19-39	1.35	DDR4-2666	•	•
CORSAIR	CMD8GX4M2B3733C17 (Ver4.24)	2*4GB	SS	N/A	17-19-19-39	1.35	DDR4-2666	•	•
G.SKILL	F4-3866C18Q-16GTZ	4*4GB	SS	Samsung	18-22-22-42	1.35	DDR4-2666	•	•
G.SKILL	F4-4000C19D-8GTZ	2*4GB	SS	Samsung	19-21-21-41	1.35	DDR4-2666	•	•
G.SKILL	F4-4000C19D-16GTZSW	2*8GB	SS	Samsung	19-21-21-41	1.35	DDR4-2666	•	•
G.SKILL	F4-4266C19D-16GTZKW	2*8GB	SS	Samsung	19-19-19-39	1.4	DDR4-2666	•	•
G.SKILL	F4-4400C19D-16GTZSW	2*8GB	SS	Samsung	19-19-19-39	1.4	DDR4-2666	•	•
G.SKILL	F4-4600C19D-16GTZSWC	2*8GB	SS	Samsung	19-23-23-43	1.5	DDR4-2666	•	•
G.SKILL	F4-4600C19D-16GTZKKA	2*8GB	SS	Samsung	19-19-19-39	1.45	DDR4-2666	•	•
GALAXY	HOF4CXL1BSR3600K17LD162C	2*8GB	SS	Samsung	17-18-18-38	1.35	DDR4-2666	•	•

KINGSTONHX436C17PB3K4/32*8GBSS/Samsung/17-18-18-39 1.35DDR4-2666

2 DIMM Slots

For each DRAM channel (A,B), make sure to install the DRAM module to gray slot first.


- 1 DIMM: Supports one (1) module inserted into any gray slot as Single-channel memory configuration. Install the module into the A2 or B2 slot for better compatibility.
- 2 DIMMs: Supports two (2) modules inserted into one pair of gray slots as one pair of Dual-channel memory configuration. Install the modules into slots A2 and B2 for better compatibility.
- Make sure to install the memory modules from the gray slots first.
- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules fo
- Always install DIMMs with the same CAS latency. For optimal compatibility, we recommend that you install memory modules of the same version or date code (D/C) from the same vendor. Check with th
- DDR4 2666MHz and higher memory modules will run at max. 2666MHz on Intel® 8th Generation 6-core or higher processors .

DIMM Slots

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
- 2 DIMM: Supports one pair of modules inserted into either the Gray slots or the Black slots as one pair of Dual-channel memory configuration

- **4 DIMM:** Supports 4 modules inserted into both the **Gray** and **Black** slots as two pairs of Dual-channel memory configuration
- When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
- It is recommended to install the memory modules from the **Black** slots for better overclocking capability.
- The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some

support (Optio
2 DIMM



ter compatibility.

late, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value the same vendor. Check with the retailer to get the correct memory modules.

8GB SS SK Hynix 17-17-17-39 - • •Asgard VML41UE-MIC1U22Q1 2GB SS Micron 17-17-


3)XMP 4x 4GB SS - 14-16-16-31 1.2 • •CORSAIR CMK16GX4M4A2400C14(Ver5.20)XMP 4x 4GB SS SK Hynix 14-16

ter compatibility.

for overclocking may operate at a lower frequency than the vendor-marked value
h the retailer to get the correct memory modules.

ter compatibility.

for overclocking may operate at a lower frequency than the vendor-marked value
h the retailer to get the correct memory modules.



ter compatibility.

the same vendor. Check with the retailer to get the correct memory modules.

late, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value the same vendor. Check with the retailer to get the correct memory modules.

r overclocking may operate at a lower frequency than the vendor-marked value
ie retailer to get the correct memory modules.

commended.

Some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

For overclocking, you may operate at a lower frequency than the vendor-marked value.
Please contact your retailer to get the correct memory modules.

Not recommended.

Some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

For overclocking, you may operate at a lower frequency than the vendor-marked value.
Please contact your retailer to get the correct memory modules.

Not recommended.

Some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

For overclocking, you may operate at a lower frequency than the vendor-marked value.
Please contact your retailer to get the correct memory modules.

commended.

Some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

-17-39 1.2 • •

-16-31 1.2 • •