

### Overview

### HPE FlexFabric 5940 Switch Series



### Models

HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch	JH395A
HPE FlexFabric 5940 32QSFP+ Switch	JH396A
HPE FlexFabric 5940 48XGT 6QSFP+ Switch	JH394A
HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch	JH390A
HPE FlexFabric 5940 48XGT 6QSFP28 Switch	JH391A
HPE FlexFabric 5940 2-slot Switch	JH397A
HPE FlexFabric 5940 4-slot Switch	JH398A
HPE FlexNetwork 5940 48p 10GbE SFP/SFP+ and 6p 40/100GbE QSFP28 with 2 Fans 2 PS Switch	JH684A
HPE FlexNetwork 5940 48p 10GBaseT and 6p 40/100GbE QSFP28 with 2 Fans 2 Power Supply Switch	JH685A
HPE FlexNetwork 5940 32-port 40GbE QSFP+ with 2 Fans 2 Power Supply Switch	JH686A
HPE FlexNetwork 5940 2-slot Chassis with 2 Fans 2 Power Supply Bundle	JH691A
HPE FlexNetwork 5940 4-slot Chassis with 2 Fans 4 Power Supply Bundle	JH692A

### Key features

- VXLAN L2 and L3 and EVPN support for virtualized environments
- OpenFlow support for investment protection and SDN environments
- High-density 10GbE, 40GbE with 40G or 100G uplink and modular for spine-and-leaf deployments
- Unify management of virtual and physical network with VEPA and IMC
- Data center convergence and resiliency with SPB, ISSU, DCB, FC/FCoE, IRF, and TRILL

### Product overview

The HPE FlexFabric 5940 Switch Series is a family of high performance and low-latency 10GbE, 40GbE top-of-rack (ToR) data center switches. The switch series include also 100G uplink technology and also a 2-slot and 4-slot modular form factor providing

## Overview

ultimate flexibility for an ever-changing Data Center requirements. This entire series is part of the Hewlett Packard Enterprise FlexFabric data center solution, which is a cornerstone of the FlexNetwork architecture.

The FlexFabric 5940 Switch Series is ideally suited for deployment at the aggregation or server access layer of large enterprise data centers, or at the core layer of medium-sized enterprises.

With the increase pace of deploying virtualized applications, adopting software-defined networking, and the server-to-server traffic, many data centers now require spine and ToR switch innovations that will meet their requirements. The HPE FlexFabric 5940 is optimized to meet the increasing requirements for higher-performance server connectivity, convergence of Ethernet and storage traffic, the capability to handle virtual environments, and low-latency.

---

## Features and benefits

### Quality of Service (QoS)

- **Powerful QoS features**
  - **Flexible queue scheduling:** including Strict Priority (SP), WRR, WDRR, WFQ, SP+WRR, SP+WDRR, SP+WFQ, Configurable Buffer, Time range, Queue Shaping, CAR with 8kbps granularity.
  - **Packet filtering and remarking:** Packet filtering at L2 (Layer 2) through L4 (Layer 4); flow classification based on source MAC address, destination MAC address, source IP (IPv4/IPv6) address, destination IP (IPv4/IPv6) address, port, protocol, and VLAN. provides nonblocking, lossless Clos architecture with VOQs and large buffers with the flexibility and scalability for future growth

### Data center optimized

- **Flexible high port density**

5940 switch enables customers to scale their server-edge 10/40/100 GbE ToR deployments to new heights with high-density 48 x 10 GbE ports with 6 ports of 40G, 48 x 10 GbE ports with 6 ports of 100G and 32 x 40 GbE delivered in a 1RU design; the 5940 32 ports of 40G switch can also be configured as a 72 x 10 GbE port device by using a 40G-to-10 GbE splitter cable that turns each 40 GbE port into four 10-GbE ports. The 48 ports models comes in SFP+ or BASE-T
- **High-performance switching**

cut-through and nonblocking architecture delivers low latency (~1 microsecond for 10GbE) for very demanding enterprise applications; the switch delivers high-performance switching capacity and wire-speed packet forwarding
- **Higher scalability**

Hewlett Packard Enterprise Intelligent Resilient Fabric (IRF) technology simplifies the architecture of server access networks; up to nine HPE 5940 switches can be combined to deliver unmatched scalability of virtualized access layer switches and flatter two-tier networks using IRF, which reduces cost and complexity
- **Advanced modular operating system**

Comware v7 software's modular design and multiple processes bring native high stability, independent process monitoring, and restart; the OS also allows individual software modules to be upgraded for higher availability and supports enhanced serviceability functions like hitless software upgrades
- **Reversible airflow**

enhanced for data center hot-cold aisle deployment with reversible airflow—for either front-to-back or back-to-front airflow
- **Redundant fans and power supplies**

Internal redundant and hot-pluggable power supplies and dual fan trays enhance reliability and availability
- **Lower OPEX and greener data center**

provide reversible airflow and advanced chassis power management
- **Data Center Bridging (DCB) protocols**

provides support for IEEE 802.1Qbb Priority Flow Control (PFC), Data Center Bridging Exchange (DCBX), IEEE 802.1Qaz Enhanced Transmission Selection (ETS), Explicit Congestion Notification (ECN) for converged FCoE, iSCSI and RoCE environments
- **FCoE support**

provides support for T11 standards-compliant FC-BB-5 Fibre Channel over Ethernet (FCoE), including FCoE initialization

## Overview

protocol (FIP), FCP, Fiber Channel enhanced port types VE, TE and VF, NPV, NPIV, fabric name server, RSCN, login services, and name-server zoning, per-VSAN fabric services, FSPF, standard zoning and fiber channel ping

- **Jumbo frames**  
with frame sizes of up to 10,000 bytes on Gigabit Ethernet and 10-Gigabit ports, allows high-performance remote backup and disaster-recovery services to be enabled
- **VXLAN hardware support**  
VXLAN Layer 2 and Layer 3 gateway support for up to 4k tunnels
- **Dynamic VXLAN configuration**  
OVSDB & ML2 support for dynamic VXLAN configuration
- **EVPN**  
Control plane protocol for VXLAN based on industry standards. It enables Layer-2 and Layer-3 control-plane learning of end-host reachability information, enabling organizations to scale their VXLAN infrastructure better. Integration with Openstack Neutron plugin for overlay automation/orchestration

## Manageability

- **Full-featured console**  
provides complete control of the switch with a familiar CLI
- **Troubleshooting**
  - **Ingress and egress port monitoring:** enable network problem solving
  - **Traceroute and ping:** enable testing of network connectivity
- **Multiple configuration files**  
allow multiple configuration files to be stored to a flash image
- **SNMP v1, v2c and v3**  
facilitate centralized discovery, monitoring, and secure management of networking devices
- **Out-of-band interface**  
isolates management traffic from user data plane traffic for complete isolation and total reachability, no matter what happens in the data plane
- **Remote configuration and management**  
delivered through a secure command-line interface (CLI) over Telnet and SSH; role-based access control (RBAC) provides multiple levels of access; configuration rollback and multiple configurations on the flash provide ease of operation; remote visibility is provided with sFlow and SNMP v1/v2/v3, and is fully supported in HPE Intelligent Management Center (IMC)
- **ISSU and hot patching**  
In Services Software Upgrade (ISSU) provides hitless software upgrades and hitless patching of the modular operating system
- **Autoconfiguration**  
provides automatic configuration via DHCP autoconfiguration
- **NTP, SNTP and PTP Support**  
synchronize timekeeping among distributed time servers and clients; Support for Network Time Protocol (NTP), Secure Network Time Protocol (SNTP) and Precision Time Protocol (PTP) IEEE 1588v2 (2008)

## Resiliency and high availability

- **IRF technology**  
enables an Hewlett Packard Enterprise FlexFabric to deliver resilient, scalable, and secured data center networks for physical and virtualized environments; groups up to nine HPE 5940 switches in an IRF configuration, allowing them to be configured and managed as a single switch with a single IP address; simplifies ToR deployment and management, reducing data center deployment and operating expenses
- **IEEE 802.1w Rapid Convergence Spanning Tree Protocol**  
increases network uptime through faster recovery from failed links
- **IEEE 802.1s Multiple Spanning Tree**  
provides high link availability in multiple VLAN environments by allowing multiple spanning trees
- **Virtual Router Redundancy Protocol (VRRP)**  
allows groups of two routers to back each other up dynamically to create highly available routed environments

## Overview

- **Hitless patch upgrades**  
allows patches and new service features to be installed without restarting the equipment, increasing network uptime and facilitating maintenance
- **Ultrafast protocol convergence (< 50 ms) with standard-based failure detection—Bidirectional Forwarding Detection (BFD)**  
enables link connectivity monitoring and reduces network convergence time for RIP, OSPF, BGP, IS-IS, VRRP, MPLS, and IRF
- **Device Link Detection Protocol (DLDP)**  
monitors link connectivity and shuts down ports at both ends if unidirectional traffic is detected, preventing loops in STP-based networks
- **Graceful restart**  
allows routers to indicate to others their capability to maintain a routing table during a temporary shutdown and significantly reduces convergence times upon recovery; supports OSPF, BGP, and IS-IS

## Layer 2 switching

- **MAC-based VLAN**  
provides granular control and security; uses RADIUS to map a MAC address/user to specific VLANs
- **Address Resolution Protocol (ARP)**  
supports static, dynamic, and reverse ARP and ARP proxy
- **IEEE 802.3x Flow Control**  
provides intelligent congestion management via PAUSE frames
- **Ethernet Link Aggregation**  
provides IEEE 802.3ad Link Aggregation of up to 128 groups of 32 ports; support for LACP, LACP Local Forwarding First, and LACP Short-time provides a fast, resilient environment that is ideal for the data center
- **Spanning Tree Protocol (STP)**  
supports STP (IEEE 802.1D), Rapid STP (RSTP, IEEE 802.1w), and Multiple STP (MSTP, IEEE 802.1s)
- **VLAN support**  
provides support for 4,096 VLANs based on port, MAC address, IPv4 subnet, protocol, and guest VLAN; supports VLAN mapping
- **IGMP support**  
provides support for IGMP Snooping, Fast-Leave, and Group-Policy; IPv6 IGMP Snooping provides Layer 2 optimization of multicast traffic
- **DHCP support at Layer 2**  
provides full DHCP Snooping support for DHCP Snooping Option 82, DHCP Relay Option 82, DHCP Snooping trust, and DHCP Snooping item backup

## Layer 3 services

- **Address Resolution Protocol (ARP)**  
determines the MAC address of another IP host in the same subnet; supports static ARPs; gratuitous ARP allows detection of duplicate IP addresses; proxy ARP allows normal ARP operation between subnets or when subnets are separated by a Layer 2 network
- **Dynamic Host Configuration Protocol (DHCP)**  
simplifies the management of large IP networks and supports client and server; DHCP Relay enables DHCP operation across subnets
- **Operations, administration and maintenance (OAM) support**  
provides support for Connectivity Fault Management (IEEE 802.1AG) and Ethernet in the First Mile (IEEE 802.3AH); provides additional monitoring that can be used for fast fault detection and recovery

## Layer 3 routing

- **Virtual Router Redundancy Protocol (VRRP) and VRRP Extended**  
allow quick failover of router ports

## Overview

- **Policy-based routing**  
makes routing decisions based on policies set by the network administrator
- **Equal-Cost Multipath (ECMP)**  
enables multiple equal-cost links in a routing environment to increase link redundancy and scale bandwidth
- **Layer 3 IPv4 routing**  
provides routing of IPv4 at media speed; supports static routes, RIP and RIPv2, OSPF, BGP, and IS-IS
- **Open shortest path first (OSPF)**  
delivers faster convergence; uses this link-state routing Interior Gateway Protocol (IGP), which supports ECMP, NSSA, and MD5 authentication for increased security and graceful restart for faster failure recovery
- **Border Gateway Protocol 4 (BGP-4)**  
delivers an implementation of the Exterior Gateway Protocol (EGP) utilizing path vectors; uses TCP for enhanced reliability for the route discovery process; reduces bandwidth consumption by advertising only incremental updates; supports extensive policies for increased flexibility; scales to very large networks
- **Intermediate system to intermediate system (IS-IS)**  
uses a path vector Interior Gateway Protocol (IGP), which is defined by the ISO organization for IS-IS routing and extended by IETF RFC 1195 to operate in both TCP/IP and the OSI reference model (Integrated IS-IS)
- **Static IPv6 routing**  
provides simple manually configured IPv6 routing
- **Dual IP stack**  
maintains separate stacks for IPv4 and IPv6 to ease the transition from an IPv4-only network to an IPv6-only network design
- **Routing Information Protocol next generation (RIPng)**  
extends RIPv2 to support IPv6 addressing
- **OSPFv3**  
provides OSPF support for IPv6
- **BGP+**  
extends BGP-4 to support Multiprotocol BGP (MBGP), including support for IPv6 addressing
- **IS-IS for IPv6**  
extends IS-IS to support IPv6 addressing
- **IPv6 tunneling**  
allows IPv6 packets to traverse IPv4-only networks by encapsulating the IPv6 packet into a standard IPv4 packet; supports manually configured, 6to4, and Intra-Site Automatic Tunnel Addressing Protocol (ISATAP) tunnels; is an important element for the transition from IPv4 to IPv6
- **Policy routing**  
allows custom filters for increased performance and security; supports ACLs, IP prefix, AS paths, community lists, and aggregate policies
- **Bidirectional Forwarding Detection (BFD)**  
enables link connectivity monitoring and reduces network convergence time for RIP, OSPF, BGP, IS-IS, VRRP, MPLS, and IRF
- **Multicast Routing PIM Dense and Sparse modes**  
provides robust support of multicast protocols
- **Layer 3 IPv6 routing**  
provides routing of IPv6 at media speed; supports static routing, RIPng, OSPFv3, BGP4+ for IPv6, and IS-ISv6

## Additional information

- **Green IT and power**  
improves energy efficiency through the use of the latest advances in silicon development; shuts off unused ports and utilizes variable-speed fans, reducing energy costs

## Management

- **USB support**
  - **File copy:** allows users to copy switch files to and from a USB flash drive

## Overview

- **Port mirroring**  
enables traffic on a port to be simultaneously sent to a network analyzer for monitoring
- **Remote configuration and management**  
is available through a CLI
- **IEEE 802.1AB Link Layer Discovery Protocol (LLDP)**  
advertises and receives management information from adjacent devices on a network, facilitating easy mapping by network management applications
- **sFlow (RFC 3176)**  
provides scalable ASIC-based wirespeed network monitoring and accounting with no impact on network performance; this allows network operators to gather a variety of sophisticated network statistics and information for capacity planning and real-time network monitoring purposes
- **Command authorization**  
leverages RADIUS to link a custom list of CLI commands to an individual network administrator's login; an audit trail documents activity
- **Dual flash images**  
provides independent primary and secondary operating system files for backup while upgrading
- **Command-line interface (CLI)**  
provides a secure, easy-to-use CLI for configuring the module via SSH or a switch console; provides direct real-time session visibility
- **Logging**  
provides local and remote logging of events via SNMP (v2c and v3) and syslog; provides log throttling and log filtering to reduce the number of log events generated
- **Management interface control**  
provides management access through a modem port and terminal interface, as well as in-band and out-of-band Ethernet ports; provides access through terminal interface, Telnet, or secure shell (SSH)
- **Industry-standard CLI with a hierarchical structure**  
reduces training time and expenses, and increases productivity in multivendor installations
- **Management security**  
restricts access to critical configuration commands; offers multiple privilege levels with password protection; ACLs provide Telnet and SNMP access; local and remote syslog capabilities allow logging of all access
- **Information center**  
provides a central repository for system and network information; aggregates all logs, traps, and debugging information generated by the system and maintains them in order of severity; outputs the network information to multiple channels based on user-defined rules
- **Network management**  
HPE IMC centrally configures, updates, monitors, and troubleshoots
- **Remote intelligent mirroring**  
mirrors ingress/egress ACL-selected traffic from a switch port or VLAN to a local or remote switch port anywhere on the network

## Security

- **Access control lists (ACLs)**  
provide IP Layer 3 filtering based on source/destination IP address/subnet and source/destination TCP/UDP port number
- **RADIUS/TACACS+**  
eases switch management security administration by using a password authentication server
- **Secure shell**  
encrypts all transmitted data for secure remote CLI access over IP networks
- **IEEE 802.1X and RADIUS network logins**  
controls port-based access for authentication and accountability
- **Port security**  
allows access only to specified MAC addresses, which can be learned or specified by the administrator

## Convergence

## Overview

- **LLDP-MED (Media Endpoint Discovery)**  
defines a standard extension of LLDP that stores values for parameters such as QoS and VLAN to configure automatically network devices such as IP phones

## Warranty and support

- **1-year warranty**  
see <http://www.hpe.com/networking/warrantysummary> for warranty and support information included with your product purchase.
- **Software releases**  
to find software for your product, refer to <http://www.hpe.com/networking/support>; for details on the software releases available with your product purchase, refer to <http://www.hpe.com/networking/warrantysummary>

## Configuration

**Build To Order:** BTO is a standalone unit with no integration. BTO products ship standalone are not part of a CTO or Rack-Shippable solution.

### Standard Switch Enclosures

HPE FlexNetwork 5940 48p 10GbE SFP/SFP+ and 6p 40/100GbE QSFP28 with 2 Fans 2 PS Switch	JH684A
<ul style="list-style-type: none"> <li>• 48 SFP+ ports (min=0 \ max=48)</li> <li>• 6 QSFP+ ports (min=0 \ max=6)</li> <li>• 6 QSFP28 ports (min=0 \ max=6)</li> <li>• Includes 2 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JG552A)</li> <li>• 1U - Height</li> </ul>	See Configuration <b>NOTE: 1, 2, 3, 6</b>
PDU Cable NA/MEX/TW/JP	JH684A #B2B
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
PDU Cable ROW	JH684A #B2C
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	
HPE FlexNetwork 5940 48p 10GBaseT and 6p 40/100GbE QSFP28 with 2 Fans 2 Power Supply Switch	JH685A
<ul style="list-style-type: none"> <li>• 48 1/10BaseT GbE ports (min=0 \ max=48)</li> <li>• 6 QSFP+ ports (min=0 \ max=6)</li> <li>• OR, 6 QSFP28 ports (min=0 \ max=6)</li> <li>• Includes 2 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JC552A)</li> <li>• 1U - Height</li> </ul>	See Configuration <b>NOTE: 2, 3, 6</b>
PDU Cable NA/MEX/TW/JP	JH685A #B2B
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
PDU Cable ROW	JH685A #B2C
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	
HPE FlexNetwork 5940 32-port 40GbE QSFP+ with 2 Fans 2 Power Supply Switch	JH686A
<ul style="list-style-type: none"> <li>• 32 QSFP+ ports (min=0 \ max=32)</li> <li>• Includes 2 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JG552A)</li> <li>• 1U - Height</li> </ul>	See Configuration <b>NOTE: 2, 6</b>
PDU Cable NA/MEX/TW/JP	JH686A #B2B
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
PDU Cable ROW	JH686A #B2C
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	
HPE FlexNetwork 5940 2-slot Chassis with 2 Fans 2 Power Supply Bundle	JH691A



## Configuration

<ul style="list-style-type: none"> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> <li>• Must select modules JH689A or JH690A only</li> <li>• Includes 2 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JG552A)</li> <li>• 1U - Height</li> </ul>	See Configuration <b>NOTE: 2, 6</b>
PDU Cable NA/MEX/TW/JP <ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	JH691A #B2B
PDU Cable ROW <ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	JH691A #B2C
HPE FlexNetwork 5940 4-slot Chassis with 2 Fans 4 Power Supply Bundle <ul style="list-style-type: none"> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> <li>• Must select modules JH689A or JH690A only</li> <li>• Includes 4 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JH186A)</li> <li>• 2U - Height</li> </ul>	JH692A See Configuration <b>NOTE: 2, 6</b>
PDU Cable NA/MEX/TW/JP <ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	JH692A #B2B
PDU Cable ROW <ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	JH692A #B2C
HPE FlexFabric 5940 32QSFP+ Switch <ul style="list-style-type: none"> <li>• 32 QSFP+ ports (min=0 \ max=32)</li> <li>• Must select min 1 Power Supply</li> <li>• Must select min 2 Fan Trays</li> <li>• 1U - Height</li> </ul>	JH396A See Configuration <b>NOTE: 2</b>
HPE FlexFabric 5940 2-slot Switch <ul style="list-style-type: none"> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> <li>• 2 port expansion module slots</li> <li>• Must select min 1 Power Supply</li> <li>• Must select min 2 Fan Trays</li> <li>• 1U - Height</li> </ul>	JH397A See Configuration <b>NOTE: 2</b>
HPE FlexFabric 5940 4-slot Switch <ul style="list-style-type: none"> <li>• 4 port expansion module slots</li> <li>• Must select min 2 Power Supply</li> <li>• Must select min 2 Fan Trays</li> <li>• 2U - Height</li> </ul>	JH398A
HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch <ul style="list-style-type: none"> <li>• 48 SFP+ ports (min=0 \ max=48)</li> <li>• 6 QSFP+ ports (min=0 \ max=6)</li> <li>• Must select min 1 Power Supply</li> <li>• Must select min 2 Fan Trays</li> </ul>	JH395A See Configuration <b>NOTE: 1, 2, 4, 5</b>

## Configuration

- 1U - Height

### HPE FlexFabric 5940 48XGT 6QSFP+ Switch

- 48 1/10BaseT GbE ports (min=0 \ max=48)
- 6 QSFP+ ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH394A

See Configuration

**NOTE: 2**

### HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch

- 48 SFP+ ports (min=0 \ max=48)
- 6 QSFP28 ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH390A

See Configuration

**NOTE: 1, 3, 5, 7**

### HPE FlexFabric 5940 48XGT 6QSFP28 Switch

- 48 1/10BaseT GbE ports (min=0 \ max=48)
- 6 QSFP28 ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH391A

See Configuration

**NOTE: 3, 5, 7**

## Configuration Rules

### Note 1 The following SFP+ Transceivers install into this Switch:

HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
HPE X130 10G SFP+ LC LRM Data Center Transceiver	JL438A
HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Campus-Cable	JH693A
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Campus-Cable	JH694A
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Campus-Cable	JH695A
HPE X240 10G SFP+ to SFP+ 7m Direct Attach Copper Campus-Cable	JH696A

### Note 2 The following QSFP+ Transceivers install into this switch:

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A

## Configuration

HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver	JH680A

**Note 3** The following QSFP28 Transceivers install into this switch:

HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
HPE X150 100G QSFP28 MPO SR4 100m MM Campus-Transceiver	JH682A
HPE X150 100G QSFP28 LC LR4 10km SM Campus-Transceiver	JH683A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Campus-Cable	JH701A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Campus-Cable	JH702A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Campus-Cable	JH703A

**Note 4** If this switch is configured for an NFV solution(Q0F04A - HPE NFV System V1.3 3Par Storage Block), default no less than the quantities specified below for the following components:

Qty 2 - JG553A (min 2)  
 Qty 2 - JC680A (min 2)  
 Qty 4 - JD092B (min 4)  
 Qty 1 - JG326A (min 1)

**Note 5** The following SFP Transceivers install into this Switch:

HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A

## Configuration

HPE X125 1G SFP LC LH70 Transceiver JD063B

**Note 6** Localization (Wall Power Cord) required on orders without #B2B, #B2C (PDU Power Cord) . (See Localization Menu)  
REMARK: When Switches/Routers are Factory Racked, Then #B2B, or #B2C should be the Defaulted Power Cable option on the Switches/Routers.

**Note 7** The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver	JH680A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A

### Remarks:

Drop down under power supply should offer the following options and results:  
Switch/Router to PDU Power Cord - #B2B in NA, Mexico, Taiwan, and Japan or #B2C ROW. (Watson Default B2B or B2C for Rack Level CTO)  
Switch/Router/Power Supply to Wall Power Cord - Localized Option (Watson Default for BTO and Box Level CTO)

## Box Level Integration CTO Models

### CTO Solution Sku

HPE 59xx CTO Switch Solution

- SSP trigger sku

JG505A  
See Configuration  
**NOTE: 1**

### Configuration Rules

**Note 1** Clic UNB - Min/Max 1 CTO switch per SSP.

### CTO Switch Chassis

HPE FlexFabric 5940 32QSFP+ Switch

JH396A

## Configuration

- 32 QSFP+ ports (min=0 \ max=32)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

See Configuration  
**NOTE: 2, 4**

### HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch

- 48 SFP+ ports (min=0 \ max=48)
- 6 QSFP+ ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH395A  
See Configuration  
**NOTE: 1, 2, 4, 5, 6**

### HPE FlexFabric 5940 48XGT 6QSFP+ Switch

- 48 1/10BaseT GbE ports (min=0 \ max=48)
- 6 QSFP+ ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH394A  
See Configuration  
**NOTE: 2, 4**

### HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch

- 48 SFP+ ports (min=0 \ max=48)
- 6 QSFP28 ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH390A  
See Configuration  
**NOTE: 1, 3, 4, 6, 7**

### HPE FlexFabric 5940 48XGT 6QSFP28 Switch

- 48 1/10BaseT GbE ports (min=0 \ max=48)
- 6 QSFP28 ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH391A  
See Configuration  
**NOTE: 3, 4, 6, 7**

## Configuration Rules

**Note 1** The following SFP+ Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
HPE X130 10G SFP+ LC LRM Data Center Transceiver	JL438A
HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A

## Configuration

HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Campus-Cable	JH693A
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Campus-Cable	JH694A
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Campus-Cable	JH695A
HPE X240 10G SFP+ to SFP+ 7m Direct Attach Copper Campus-Cable	JH696A

**Note 2** The following QSFP+ Transceivers install into this switch:

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A

**Note 3** The following QSFP28 Transceivers install into this switch:

HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A

**Note 4** If the Switch Chassis is to be Box Level Factory Integrated (CTO), Then the #0D1 is required on the Switch Chassis and integrated to the JG505A - HP 59xx CTO Switch Solution. (Min 1/Max 1 Router per SSP)

**Note 5** If this switch is configured for an NFV solution(Q0F04A - HPE NFV System V1.3 3Par Storage Block), default no less than the quantities specified below for the following components:

Qty 2 - JG553A (min 2)

Qty 2 - JC680A (min 2)

Qty 4 - JD092B (min 4)

Qty 1 - JG326A (min 1)

**Note 6** The following SFP Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B

## Configuration

HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B

**Note 7** The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver	JH680A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A

## Rack Level Integration CTO Models

### CTO Switch Chassis

HPE FlexNetwork 5940 48p 10GbE SFP/SFP+ and 6p 40/100GbE QSFP28 with 2 Fans 2 PS Switch	JH684A
<ul style="list-style-type: none"> <li>48 SFP+ ports (min=0 \ max=48)</li> <li>6 QSFP+ ports (min=0 \ max=6)</li> <li>6 QSFP28 ports (min=0 \ max=6)</li> <li>Includes 2 PS (JC680A)</li> <li>Includes 2 Fan Trays (JG552A)</li> <li>1U - Height</li> </ul>	See Configuration <b>NOTE: 1, 2, 3, 6</b>
HPE FlexNetwork 5940 48p 10GbE SFP/SFP+ and 6p 40/100GbE QSFP28 with 2 Fans 2 PS Switch	JH684A
<ul style="list-style-type: none"> <li>C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
HPE FlexNetwork 5940 48p 10GbE SFP/SFP+ and 6p 40/100GbE QSFP28 with 2 Fans 2 PS Switch	JH684A
<ul style="list-style-type: none"> <li>C15 PDU Jumper Cord (ROW)</li> </ul>	
HPE FlexNetwork 5940 48p 10GBaseT and 6p 40/100GbE QSFP28 with 2 Fans 2 Power Supply Switch	JH685A
<ul style="list-style-type: none"> <li>48 1/10BaseT GbE ports (min=0 \ max=48)</li> <li>6 QSFP+ ports (min=0 \ max=6)</li> <li>OR, 6 QSFP28 ports (min=0 \ max=6)</li> </ul>	See Configuration <b>NOTE: 2, 3, 6</b>

## Configuration

<ul style="list-style-type: none"> <li>• Includes 2 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JC552A)</li> <li>• 1U - Height</li> </ul>	
PDU Cable NA/MEX/TW/JP	JH685A#B2B
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP) 32 QSFP+ ports (min=0 \ max=32)</li> <li>• Includes 2 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JG552A)</li> <li>• 1U - Height</li> </ul>	
PDU Cable ROW	JH685A#B2C
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	
HPE FlexNetwork 5940 32-port 40GbE QSFP+ with 2 Fans 2 Power Supply Switch	JH686A
<ul style="list-style-type: none"> <li>• 32 QSFP+ ports (min=0 \ max=32)</li> <li>• Includes 2 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JG552A)</li> <li>• 1U - Height</li> </ul>	See Configuration <b>NOTE: 2, 6</b>
PDU Cable NA/MEX/TW/JP	JH686A#B2B
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
PDU Cable ROW	JH686A#B2C
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	
HPE FlexNetwork 5940 2-slot Chassis with 2 Fans 2 Power Supply Bundle	JH691A
<ul style="list-style-type: none"> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> <li>• Must select modules JH689A or JH690A ONLY</li> <li>• Includes 2 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JG552A)</li> <li>• 1U - Height</li> </ul>	See Configuration <b>NOTE: 2, 6</b>
PDU Cable NA/MEX/TW/JP	JH691A#B2B
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
PDU Cable ROW	JH691A#B2C
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	
HPE FlexNetwork 5940 4-slot Chassis with 2 Fans 4 Power Supply Bundle	JH692A
<ul style="list-style-type: none"> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> <li>• Must select modules JH689A or JH690A ONLY</li> <li>• Includes 4 PS (JC680A)</li> <li>• Includes 2 Fan Trays (JH186A)</li> <li>• 2U - Height</li> </ul>	See Configuration <b>NOTE: 2, 6</b>
PDU Cable NA/MEX/TW/JP	JH692A#B2B
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
PDU Cable ROW	JH692A#B2C
<ul style="list-style-type: none"> <li>• C15 PDU Jumper Cord (ROW)</li> </ul>	



## Configuration

### HPE FlexFabric 5940 32QSFP+ Switch

- 32 QSFP+ ports (min=0 \ max=32)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH396A  
See Configuration  
**NOTE: 2, 4**

### HPE FlexFabric 5940 2-slot Switch

- 2 QSFP+ ports (min=0 \ max=2)
- 2 port expansion module slots
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH397A  
See Configuration  
**NOTE: 2**

### HPE FlexFabric 5940 4-slot Switch

- 4 port expansion module slots
- Must select min 2 Power Supply
- Must select min 2 Fan Trays
- 2U - Height

JH398A

### HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch

- 48 SFP+ ports (min=0 \ max=48)
- 6 QSFP+ ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH395A  
See Configuration  
**NOTE: 1, 2, 4, 5, 6**

### HPE FlexFabric 5940 48XGT 6QSFP+ Switch

- 48 1/10BaseT GbE ports (min=0 \ max=48)
- 6 QSFP+ ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH394A  
See Configuration  
**NOTE: 2, 4**

### HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch

- 48 SFP+ ports (min=0 \ max=48)
- 6 QSFP28 ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH390A  
See Configuration  
**NOTE: 1, 3, 4, 6, 7**

### HPE FlexFabric 5940 48XGT 6QSFP28 Switch

- 48 1/10BaseT GbE ports (min=0 \ max=48)
- 6 QSFP28 ports (min=0 \ max=6)
- Must select min 1 Power Supply
- Must select min 2 Fan Trays
- 1U - Height

JH391A  
See Configuration  
**NOTE: 3, 4, 6, 7**

## Configuration

**Note 1** The following SFP+ Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
HPE X130 10G SFP+ LC LRM Data Center Transceiver	JL438A
HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Campus-Cable	JH693A
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Campus-Cable	JH694A
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Campus-Cable	JH695A
HPE X240 10G SFP+ to SFP+ 7m Direct Attach Copper Campus-Cable	JH696A

**Note 2** The following QSFP+ Transceivers install into this switch:

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A

**Note 3** The following QSFP28 Transceivers install into this switch:

HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A

## Configuration

HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable JL273A

**Note 4** If HPE CTO Switch Chassis is selected for Rack Level Integration, Then the Switch needs to integrate (with #0D1) to the Rack.

**Note 5** If this switch is configured for an NFV solution(Q0F04A - HPE NFV System V1.3 3Par Storage Block), default no less than the quantities specified below for the following components:

Qty 2 - JG553A (min 2)

Qty 2 - JC680A (min 2)

Qty 4 - JD092B (min 4)

Qty 1 - JG326A (min 1)

**Note 6** The following SFP Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X120 1G SFP RJ45 T Transceiver JD089B

HPE X120 1G SFP LC SX Transceiver JD118B

HPE X120 1G SFP LC LX Transceiver JD119B

HPE X125 1G SFP LC LH40 1310nm Transceiver JD061A

HPE X120 1G SFP LC LH40 1550nm Transceiver JD062A

HPE X125 1G SFP LC LH70 Transceiver JD063B

**Note 7** The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver JG661A

HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver JL251A

HPE X140 40G QSFP+ MPO SR4 Transceiver JG325B

HPE X140 40G QSFP+ LC ER4 40km SM Transceiver JL306A

HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver JG709A

HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver JL286A

HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable JG326A

HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable JG327A

HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable JG328A

HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver JH679A

HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver JH681A

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver JH677A

HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable JH697A

HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable JH698A

HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable JH699A

HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver JH678A

HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver JH680A

HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable JL287A

HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable JL288A

HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable JL289A

**Enter the following menu selections as integrated to the CTO Model X server above if order is factory built.**

## Switch Options

(JH397A) System (std 0 // max 2) User Selection (min 0 // max 2)

(JH398A) System (std 0 // max 4) User Selection (min 0 // max 4)

(JH691A) System (std 0 // max 2) User Selection (min 0 // max 2)

(JH692A) System (std 0 // max 4) User Selection (min 0 // max 4)

## Configuration

HPE FlexNetwork 5930 24-port 10GbE SFP/SFP+ and 2-port 40GbE QSFP+ Module	JH689A
<ul style="list-style-type: none"> <li>• 24 SFP+ ports (min=0 \ max=24)</li> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> </ul>	See Configuration <b>NOTE: 1, 3, 4, 6, 7, 8</b>
HPE FlexNetwork 5930 24-port 10GBASE-T and 2-port 40GbE QSFP+ MACsec Module	JH690A
<ul style="list-style-type: none"> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> </ul>	See Configuration <b>NOTE: 3, 4, 6, 8</b>
HPE 5940 2-port QSFP+ and 2-port QSFP28 Module	JH409A
<ul style="list-style-type: none"> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> <li>• 2 QSFP28 ports (min=0 \ max=2)</li> </ul>	See Configuration <b>NOTE: 3, 6, 8, 9, 10</b>
HPE 5930 24-port SFP+ and 2-port QSFP+ Module	JH180A
<ul style="list-style-type: none"> <li>• 24 SFP+ ports (min=0 \ max=24)</li> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> </ul>	See Configuration <b>NOTE: 1, 3, 6, 7, 8</b>
HPE 5930 24-port SFP+ and 2-port QSFP+ with MACsec Module	JH181A
<ul style="list-style-type: none"> <li>• 24 SFP+ ports (min=0 \ max=24)</li> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> </ul>	See Configuration <b>NOTE: 1, 3, 5, 6, 7, 8</b>
HPE 5930 24-port 10GBASE-T and 2-port QSFP+ with MACsec Module	JH182A
<ul style="list-style-type: none"> <li>• 24 1/10GBase-T ports</li> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> </ul>	See Configuration <b>NOTE: 3, 6, 8</b>
HPE 5930 8-port QSFP+ Module	JH183A
<ul style="list-style-type: none"> <li>• 8 QSFP+ ports (min=0 \ max=8)</li> </ul>	See Configuration <b>NOTE: 2, 3, 8</b>
HPE 5930 24-port Converged Port and 2-port QSFP+ Module	JH184A
<ul style="list-style-type: none"> <li>• 24 Converged SFP+/FC ports (min=0 \ max=24)</li> <li>• 2 QSFP+ ports (min=0 \ max=2)</li> </ul>	See Configuration <b>NOTE: 1, 2, 3, 5, 8</b>

### Configuration Rules

**Note 1** The following SFP+ Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A

## Configuration

HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Campus-Cable	JH693A
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Campus-Cable	JH694A
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Campus-Cable	JH695A
HPE X240 10G SFP+ to SFP+ 7m Direct Attach Copper Campus-Cable	JH696A

**Note 2** The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver	JH680A

**Note 3** This Module can install into the following Switches: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE FlexNetwork 5940 2-slot Chassis with 2 Fans 2 Power Supply Bundle	JH691A
HPE FlexNetwork 5940 4-slot Chassis with 2 Fans 4 Power Supply Bundle	JH692A

**Note 4** This Module can install into the following Switches: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch	JH390A
HPE FlexFabric 5940 48XGT 6QSFP28 Switch	JH391A

**Note 5** The following Transceivers install into this Module's SFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LRM Data Center Transceiver	JL438A

**Note 6** The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A

## Configuration

HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver	JH680A

**Note 7** The following 10G Transceivers install into this Module's SFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A

**Note 8** The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A

**Note 9** The following QSFP28 Transceivers install into this Module's QSFP28 Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
HPE X150 100G QSFP28 MPO SR4 100m MM Campus-Transceiver	JH682A
HPE X150 100G QSFP28 LC LR4 10km SM Campus-Transceiver	JH683A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Campus-Cable	JH701A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Campus-Cable	JH702A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Campus-Cable	JH703A

**Note 10** The following 40G Cables install into this Module's QSFP+ Ports ONLY: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A

## Transceivers

## Configuration

### SFP Transceivers

HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
<b>NOTE: Only supported on PHY switch ports</b>	
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
<b>NOTE: Only supported on PHY switch ports</b>	
HPE X125 1G SFP LC LH70 Transceiver	JD063B

#### Remarks:

Watson Blue Note - The SFP Transceivers (JD061A, JD062A) are only supported in ports 1-8 for the JG390A Switch and ports 1-16 for the JG395A Switch.

### SFP+ Transceivers

HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
<b>NOTE: Only supported on PHY switch ports</b>	
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
HPE X130 10G SFP+ LC LRM Data Center Transceiver	JL438A
HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
<b>NOTE: Only supported on PHY switch ports</b>	
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
<b>NOTE: Only supported on PHY switch ports</b>	
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
<b>NOTE: Only supported on PHY switch ports</b>	
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Campus-Cable	JH693A
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Campus-Cable	JH694A
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Campus-Cable	JH695A
HPE X240 10G SFP+ to SFP+ 7m Direct Attach Copper Campus-Cable	JH696A

#### Remarks:

Watson Blue Note - The SFP+ Transceivers(JL250A, JG915A, JG234A) are supported in PHY Switch Port  
 Watson Blue Note - The SFP+ Transceivers(JD093B) is supported on the MSec Module(JH181A) and CP Module(JH184A)

### QSFP+ Transceivers

HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A

## Configuration

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver	JH680A

Watson Blue Note - The QSFP+ Splitter Cables(JG329A, JG330A, JG331A, JH700A) are only supported in ports 5-28 for the JG396A Switch. Valid on all 40/100GbE ports for other 5940 Switches.

The QSFP+ Splitter Cables(JG329A, JG330A, JG331A, JH700A) are only supported on the first 6 ports of the JH183A Module when used in a 4 slot switch(JH398A).

These modules(JH180A, JH181A, JH183A, JH184A, JH182A) do not support the QSFP+ Splitter Cables(JG329A, JG330A, JG331A, JH700A) when used in a 4 slot switch(JH398A).

### QSFP28 Transceivers

HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
HPE X150 100G QSFP28 MPO SR4 100m MM Campus-Transceiver	JH682A
HPE X150 100G QSFP28 LC LR4 10km SM Campus-Transceiver	JH683A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Campus-Cable	JH701A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Campus-Cable	JH702A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Campus-Cable	JH703A

## Cables

### Multi-Mode Cables



## Configuration

HPE LC to LC Multi-mode OM3 2-Fiber 0.5m 1-Pack Fiber Optic Cable	AJ833A
HPE LC to LC Multi-mode OM3 2-Fiber 1.0m 1-Pack Fiber Optic Cable	AJ834A
HPE LC to LC Multi-mode OM3 2-Fiber 2.0m 1-Pack Fiber Optic Cable	AJ835A
HPE LC to LC Multi-mode OM3 2-Fiber 5.0m 1-Pack Fiber Optic Cable	AJ836A
HPE LC to LC Multi-mode OM3 2-Fiber 15.0m 1-Pack Fiber Optic Cable	AJ837A
HPE LC to LC Multi-mode OM3 2-Fiber 30.0m 1-Pack Fiber Optic Cable	AJ838A
HPE LC to LC Multi-mode OM3 2-Fiber 50.0m 1-Pack Fiber Optic Cable	AJ839A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 1m Cable	QK732A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 2m Cable	QK733A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 5m Cable	QK734A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 15m Cable	QK735A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 30m Cable	QK736A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 50m Cable	QK737A

### MPO Cables

HPE Multi Fiber Push On to 4 x Lucent Connector 5m Cable	K2Q46A
HPE Multi Fiber Push On to 4 x Lucent Connector 15m Cable	K2Q47A
HPE Premier Flex MPO/MPO Multi-mode OM4 12 fiber 10m Cable	QK729A
HPE Premier Flex MPO/MPO Multi-mode OM4 8 fiber 50m Cable	QK731A
HPE Premier Flex MPO/MPO OM4 100m (12ft) Cable	H6Z30A

## Internal Power Supplies

(JH684A, JH685A, JH686A, JH691A) System (std 2 // max 2) User Selection (min 0 // max 0)  
 (JH692A) System (std 4 // max 4) User Selection (min 0 // max 0)  
 (JH390A, JH391A, JH394A, JH395A, JH396A, JH397A) System (std 0 // max 2) User Selection (min 1 // max 2)  
 (JH398A) System (std 0 // max 4) User Selection (min 2 // max 4)

HPE A58x0AF Back (Power Side) to Front (Port Side) Airflow 300W AC Power Supply	JG900A
<ul style="list-style-type: none"> <li>includes 1 x c13, 300w</li> </ul>	See Configuration <b>NOTE: 1, 2, 3</b>
PDU Cable NA/MEX/TW/JP	JG900A#B2B
<ul style="list-style-type: none"> <li>C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
HPE A58x0AF Back (Power Side) to Front (Port Side) Airflow 300W DC Power Supply	JG901A
<ul style="list-style-type: none"> <li>includes 1 x c13, 300w</li> </ul>	See Configuration <b>NOTE: 1, 3</b>
HPE 58x0AF 650W AC Power Supply	JC680A
<ul style="list-style-type: none"> <li>includes 1 x c13, 300w</li> </ul>	See Configuration <b>NOTE: 1, 2</b>
PDU Cable NA/MEX/TW/JP	JC680A#B2B
<ul style="list-style-type: none"> <li>C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
HPE 58x0AF 650W AC Power Supply	JC680A
<ul style="list-style-type: none"> <li>includes 1 x c13, 300w</li> </ul>	See Configuration <b>NOTE: 1, 2</b>

## Configuration

PDU Cable NA/MEX/TW/JP	JC680A#B2B
<ul style="list-style-type: none"> <li>C15 PDU Jumper Cord (NA/MX/TW/JP)</li> </ul>	
PDU Cable ROW	JC680A#B2C
<ul style="list-style-type: none"> <li>C15 PDU Jumper Cord (ROW)</li> </ul>	
High Volt Switch to Wall Power Cord	JC680A#B2E
<ul style="list-style-type: none"> <li>HPE 2.3M C13 to NEMA L6-20P Power Cord(J9936A)</li> </ul>	
No Power Cord Selected	JC680A#AC3
<ul style="list-style-type: none"> <li>No Localized Power Cord Selected</li> </ul>	
HP 58x0AF 650W DC Power Supply	JC681A See Configuration <b>NOTE: 1</b>
HPE FlexFabric Switch 650W 48V Hot Plug NEBS-compliant DC Power Supply	JH336A See Configuration <b>NOTE: 1</b>
<ul style="list-style-type: none"> <li>includes 1 x c13, 650w</li> </ul>	

### Configuration Rules

**Note 1** If 2 power supplies are selected they must be the same SKU number.

**Note 2** Localization (Wall Power Cord) required on orders without #B2B, #B2C (PDU Power Cord) . (See Localization Menu)  
REMARK: When Switches/Routers are Factory Racked, Then #B2B, or #B2C should be the Defaulted Power Cable option on the Switches/Routers.

**Note 3** This power supply is only compatible with the following Switches:  
JH390A  
JH395A

**Remarks:** Drop down under power supply should offer the following options and results:  
Switch/Router to PDU Power Cord - #B2B in NA, Mexico, Taiwan, and Japan or #B2C ROW. (Watson Default B2B or B2C for Rack Level CTO)  
Switch/Router/Power Supply to Wall Power Cord - Localized Option (Watson Default for BTO and Box Level CTO)

### Fan Trays

(JH684A, JH685A, JH686A, JH691A, JH692A) System (std 2 // max 2) User Selection (min 0 // max 0)  
(JH390A, JH391A, JH394A, JH395A, JH396A, JH397A) System (std 0 // max 2) User Selection (min 2 // max 2)  
(JH398A) System (std 0 // max 2) User Selection (min 2 // max 2)

HPE 58x0AF Back (Power Side) to Front (Port Side) Airflow Fan Tray	JC682A See Configuration <b>NOTE: 1, 6</b>
HPE 58x0AF Front (Port Side) to Back (Power Side) Airflow Fan Tray	JC683A See Configuration <b>NOTE: 1, 6</b>

## Configuration

HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A See Configuration <b>NOTE: 1, 2, 4</b>
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A See Configuration <b>NOTE: 1, 2</b>
HPE 5930 4-slot Back (Power Side) to Front (Port Side) Airflow Fan Tray	JH185A See Configuration <b>NOTE: 1, 3</b>
HPE 5930 4-slot Front (Port Side) to Back (Power Side) Airflow Fan Tray	JH186A See Configuration <b>NOTE: 1, 3, 5</b>

### Configuration Rules

- Note 1** Fan Trays cannot be mixed in the same switch enclosure
- Note 2** This fan tray is only supported on JH390A, JH391A, JH394A, JH395A, JH396A, JH397A.
- Note 3** This fan tray is only supported on JH398A.
- Note 4** This fan tray is only supported on: JH684A, JH685A, JH686A, JH691A
- Note 5** This fan tray is only supported on: JH692A
- Note 6** This power supply is only compatible with the following Switches:  
JH390A  
JH395A

### Remarks: Watson Blue Text:

If there is any empty space below the switch in a rack when using Back to Front Fan Trays, JG553A, JH185A and JC682A, the rack will receive an Air Plenum kit that takes up 1U of additional space in the rack. The Air Plenum kit is not required on fully configured racks. This only applies for CTO Rack Level Integration. The Air Plenum Kit is a non-saleable SKU, and is brought in automatically for CTO Factory Rack Level Integration.

## Technical Specifications

### HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch (JH395A)

<b>I/O ports and slots</b>	48 fixed 1000/10000 SFP+ ports 6 QSFP+ 40GbE ports	
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0 1 Mini USB 2.0	
<b>Power supplies</b>	2 power supply slots 1 minimum power supply required (ordered separately)	
<b>Fan tray</b>	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 18.11(d) x 1.72(h) in (44 x 46 x 4.36 cm)
	<b>Weight</b>	22.05 lb (10 kg) shipping weight
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM	
<b>Performance</b>	<b>10 Gbps Latency</b>	< 1 $\mu$ s (64-byte packets)
	<b>Throughput</b>	up to 1071 Mpps
	<b>Routing/Switching capacity</b>	1440 Gbps
	<b>Routing table size</b>	120000 entries (IPv4), 60000 entries (IPv6)
	<b>MAC address table size</b>	288000 entries
	<b>Environment</b>	<b>Operating temperature</b>
	<b>Operating relative humidity</b>	10% to 90%, noncondensing
	<b>Acoustic</b>	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB
<b>Electrical characteristics</b>	<b>Maximum heat dissipation</b>	887 BTU/hr (935.79 kJ/hr)
	<b>Voltage</b>	100 - 240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen)
	<b>Maximum power rating</b>	213 W
	<b>Frequency</b>	50/60 Hz
	<b>Notes</b>	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2 IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance	
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	

## Technical Specifications

<b>Immunity</b>	<b>Generic</b>	ETSI EN 300 386 V1.3.3
	<b>EN</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>ESD</b>	EN 61000-4-2; IEC 61000-4-2
	<b>Radiated</b>	EN 61000-4-3; IEC 61000-4-3
	<b>EFT/Burst</b>	EN 61000-4-4; IEC 61000-4-4
	<b>Surge</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Conducted</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
	<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Notes</b>	The customer must order a power supply, as the device does not come with one. At least one JC680A or JC681A is required.	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

---

### HPE FlexFabric 5940 32QSFP+ Switch (JH396A)

<b>I/O ports and slots</b>	32 QSFP+ 40GbE ports	
<b>Additional ports and slots</b>	1 RJ-45 serial console port	
	1 RJ-45 out-of-band management port	
	1 USB 2.0	
	1 Mini USB 2.0	
<b>Power supplies</b>	2 power supply slots 1 minimum power supply required (ordered separately)	
<b>Fan tray</b>	2 fan tray slots	
	The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 25.98(d) x 1.74(h) in (44.00 x 66.0 x 4.42 cm)
	<b>Weight</b>	35.27 lb (16 kg) shipping weight
	<b>Full configuration weight</b>	28.66 lb (13 kg)
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM	
<b>Performance</b>	<b>10 Gbps Latency</b>	< 1 μs (64-byte packets)
	<b>Throughput</b>	up to 1904Mpps
	<b>Routing/Switching capacity</b>	2560 Gbps
	<b>Routing table size</b>	120000 entries (IPv4), 60000 entries (IPv6)
	<b>MAC address table size</b>	288000 entries
<b>Environment</b>	<b>Operating temperature</b>	32°F to 113°F (0°C to 45°C)

## Technical Specifications

	<b>Operating relative humidity</b>	10% to 90%, noncondensing
	<b>Acoustic</b>	Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB
<b>Electrical characteristics</b>	<b>Maximum heat dissipation</b>	597/1361 BTU/hr (629.83/1435.86 kJ/hr)
	<b>Voltage</b>	90 - 264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen)
	<b>Maximum power rating</b>	409 W
	<b>Frequency</b>	50/60 Hz
	<b>Notes</b>	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2 IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance	
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	
<b>Immunity</b>	<b>Generic</b>	ETSI EN 300 386 V1.3.3
	<b>EN</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>ESD</b>	EN 61000-4-2; IEC 61000-4-2
	<b>Radiated</b>	EN 61000-4-3; IEC 61000-4-3
	<b>EFT/Burst</b>	EN 61000-4-4; IEC 61000-4-4
	<b>Surge</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Conducted</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
	<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Notes</b>	The customer must order a power supply, as the device does not come with one. At least one JC680A or JC681A is required.	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

### HPE FlexFabric 5940 48XGT 6QSFP+ Switch (JH394A)

<b>I/O ports and slots</b>	48 1/10GBASE-T ports 6 QSFP+ 40GbE ports
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0

## Technical Specifications

	1 Mini USB 2.0
<b>Power supplies</b>	2 power supply slots 1 minimum power supply required (ordered separately)
<b>Fan tray</b>	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.
<b>Physical characteristics</b>	<b>Dimensions</b> 17.32(w) x 25.98(d) x 1.72(h) in (44 x 66 x 4.36 cm) <b>Weight</b> 28.66 lb (13 kg) shipping weight
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM
<b>Performance</b>	<b>10 Gbps Latency</b> < 1 μs (64-byte packets) <b>Throughput</b> up to 1071 Mpps <b>Routing/Switching capacity</b> 1440 Gbps <b>Routing table size</b> 120000 entries (IPv4), 60000 entries (IPv6) <b>MAC address table size</b> 288000 entries
<b>Environment</b>	<b>Operating temperature</b> 32°F to 113°F (0°C to 45°C) <b>Operating relative humidity</b> 10% to 90%, noncondensing <b>Acoustic</b> Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB
<b>Electrical characteristics</b>	<b>Maximum heat dissipation</b> 887 BTU/hr (935.79 kJ/hr) <b>Voltage</b> 100 - 240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen) <b>Maximum power rating</b> 370 W <b>Frequency</b> 50/60 Hz <b>Notes</b> <b>Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.</b>
<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2 IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)
<b>Immunity</b>	<b>Generic</b> ETSI EN 300 386 V1.3.3 <b>EN</b> EN 55024:1998+ A1:2001 + A2:2003 <b>ESD</b> EN 61000-4-2; IEC 61000-4-2 <b>Radiated</b> EN 61000-4-3; IEC 61000-4-3 <b>EFT/Burst</b> EN 61000-4-4; IEC 61000-4-4 <b>Surge</b> EN 61000-4-5; IEC 61000-4-5 <b>Conducted</b> EN 61000-4-6; IEC 61000-4-6

## Technical Specifications

	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
	<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Notes</b>	The customer must order a power supply, as the device does not come with one. At least one JC680A or JC681A is required.	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

---

### HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch (JH390A)

<b>I/O ports and slots</b>	48 fixed 1000/10000 SFP+ ports 6 QSFP28 100GbE ports	
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 SFP GbE port 1 USB 2.0 1 Mini USB 2.0	
<b>Power supplies</b>	2 power supply slots 1 minimum power supply required (ordered separately)	
<b>Fan tray</b>	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 18.11(d) x 1.72(h) in (44 x 46 x 4.36 cm)
	<b>Weight</b>	24.25 lb (11 kg) shipping weight
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM	
<b>Performance</b>	<b>10 Gbps Latency</b>	< 1 μs (64-byte packets)
	<b>Throughput</b>	up to 1607 Mpps
	<b>Routing/Switching capacity</b>	2160 Gbps
	<b>Routing table size</b>	120000 entries (IPv4), 60000 entries (IPv6)
	<b>MAC address table size</b>	288000 entries
<b>Environment</b>	<b>Operating temperature</b>	32°F to 113°F (0°C to 45°C)
	<b>Operating relative humidity</b>	10% to 90%, noncondensing
	<b>Acoustic</b>	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB
<b>Electrical characteristics</b>	<b>Maximum heat dissipation</b>	887 BTU/hr (935.79 kJ/hr)
	<b>Voltage</b>	100 - 240 VAC, rated



## Technical Specifications

-40 to -60 VDC, rated  
(depending on power supply chosen)

**Maximum power rating** 196 W

**Frequency** 50/60 Hz

**Notes** Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.

**Safety** UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance

**Emissions** VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)

**Immunity**

**Generic** ETSI EN 300 386 V1.3.3

**EN** EN 55024:1998+ A1:2001 + A2:2003

**ESD** EN 61000-4-2; IEC 61000-4-2

**Radiated** EN 61000-4-3; IEC 61000-4-3

**EFT/Burst** EN 61000-4-4; IEC 61000-4-4

**Surge** EN 61000-4-5; IEC 61000-4-5

**Conducted** EN 61000-4-6; IEC 61000-4-6

**Power frequency magnetic field** IEC 61000-4-8; EN 61000-4-8

**Voltage dips and interruptions** EN 61000-4-11; IEC 61000-4-11

**Harmonics** EN 61000-3-2, IEC 61000-3-2

**Flicker** EN 61000-3-3, IEC 61000-3-3

**Management** IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP

**Notes** The customer must order a power supply, as the device does not come with one. At least one JC680A or JC681A is required.

**Services** Refer to the Hewlett Packard Enterprise website at: <http://www.hpe.com/networking/services> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

---

### HPE FlexFabric 5940 48XGT 6QSFP28 Switch (JH391A)

**I/O ports and slots** 48 1/10GBASE-T ports  
6 QSFP28 100GbE ports

**Additional ports and slots** 1 RJ-45 serial console port  
1 RJ-45 out-of-band management port  
1 SFP GbE port  
1 USB 2.0  
1 Mini USB 2.0

**Power supplies** 2 power supply slots  
1 minimum power supply required (ordered separately)

**Fan tray** 2 fan tray slots  
The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with

## Technical Specifications

only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.

<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 25.98(d) x 1.72(h) in (44 x 66 x 4.36 cm)
	<b>Weight</b>	28.66 lb (13 kg) shipping weight
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM	
<b>Performance</b>	<b>10 Gbps Latency</b>	< 1 $\mu$ s (64-byte packets)
	<b>Throughput</b>	up to 1607 Mpps
	<b>Routing/Switching capacity</b>	2160 Gbps
	<b>Routing table size</b>	120000 entries (IPv4), 60000 entries (IPv6)
	<b>MAC address table size</b>	288000 entries
<b>Environment</b>	<b>Operating temperature</b>	32°F to 113°F (0°C to 45°C)
	<b>Operating relative humidity</b>	10% to 90%, noncondensing
	<b>Acoustic</b>	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB
<b>Electrical characteristics</b>	<b>Maximum heat dissipation</b>	887 BTU/hr (935.79 kJ/hr)
	<b>Voltage</b>	100 - 240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen)
	<b>Maximum power rating</b>	320 W
	<b>Frequency</b>	50/60 Hz
	<b>Notes</b>	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
	<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	
<b>Immunity</b>	<b>Generic</b>	ETSI EN 300 386 V1.3.3
	<b>EN</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>ESD</b>	EN 61000-4-2; IEC 61000-4-2
	<b>Radiated</b>	EN 61000-4-3; IEC 61000-4-3
	<b>EFT/Burst</b>	EN 61000-4-4; IEC 61000-4-4
	<b>Surge</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Conducted</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3	

## Technical Specifications

<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP
<b>Notes</b>	The customer must order a power supply, as the device does not come with one. At least one JC680A or JC681A is required.
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

---

### HPE FlexFabric 5940 2-slot Switch (JH397A)

<b>I/O ports and slots</b>	2 module slots 2 QSFP+ 40GbE ports Supports a maximum of 18 40GbE ports or 48 1/10GBASE-T ports or 48 SFP+ ports or 48 Converged ports, or a combination
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0 1 Mini USB 2.0
<b>Power supplies</b>	2 power supply slots 1 minimum power supply required (ordered separately)
<b>Fan tray</b>	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.
<b>Physical characteristics</b>	<b>Dimensions</b> 17.32(w) x 25.98(d) x 1.74(h) in (44.00 x 66.0 x 4.42 cm) (1U height) <b>Weight</b> 39.68 lb (18 kg) shipping weight <b>Full configuration weight</b> 35.27 lb (16 kg)
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM
<b>Performance</b>	<b>10 Gbps Latency</b> < 1 μs (64-byte packets) <b>Throughput</b> up to 1071 Mpps <b>Routing/Switching capacity</b> 1440 Gbps <b>Routing table size</b> 128000 entries (IPv4), 64000 entries (IPv6) <b>MAC address table size</b> 288000 entries
<b>Reliability</b>	<b>MTBF (years)</b> 47.2 <b>MTTR (hours)</b> 1
<b>Environment</b>	<b>Operating temperature</b> 32°F to 113°F (0°C to 45°C) <b>Operating relative humidity</b> 10% to 90%, noncondensing <b>Acoustic</b> Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB
<b>Electrical characteristics</b>	<b>Voltage</b> 90 - 264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen) <b>Maximum power rating</b> 508 W <b>Idle power</b> 105 W <b>Frequency</b> 50/60 Hz

## Technical Specifications

	<b>Notes</b>	Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance	
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	
<b>Immunity</b>	<b>Generic</b>	ETSI EN 300 386 V1.3.3
	<b>EN</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>ESD</b>	EN 61000-4-2; IEC 61000-4-2
	<b>Radiated</b>	EN 61000-4-3; IEC 61000-4-3
	<b>EFT/Burst</b>	EN 61000-4-4; IEC 61000-4-4
	<b>Surge</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Conducted</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
	<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Notes</b>	The customer must order a power supply, as the device does not come with one. At least one JC680A or JC681A is required.	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

---

### HPE FlexFabric 5940 4-slot Switch (JH398A)

<b>I/O ports and slots</b>	4 module slots Supports a maximum of 32 40GbE ports or 96 1/10GBASE-T ports or 96 SFP+ ports or 96 Converged ports, or a combination
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0 1 Mini USB 2.0
<b>Power supplies</b>	4 power supply slots 2 minimum power supply required (ordered separately)
<b>Fan tray</b>	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of

## Technical Specifications

32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.

<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 25.98(d) x 3.47(h) in (44.00 x 66.0 x 8.81 cm) (2U height)	
	<b>Weight</b>	66.14 lb (30 kg) shipping weight	
	<b>Full configuration weight</b>	59.52 lb (27 kg)	
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM		
<b>Performance</b>	<b>10 Gbps Latency</b>	< 1 μs (64-byte packets)	
	<b>Throughput</b>	up to 1429 Mpps	
	<b>Routing/Switching capacity</b>	2560 Gbps	
	<b>Routing table size</b>	128000 entries (IPv4), 64000 entries (IPv6)	
	<b>MAC address table size</b>	288000 entries	
<b>Reliability</b>	<b>MTBF (years)</b>	35.8	
	<b>MTTR (hours)</b>	1	
<b>Environment</b>	<b>Operating temperature</b>	32°F to 113°F (0°C to 45°C)	
	<b>Operating relative humidity</b>	10% to 90%, noncondensing	
	<b>Acoustic</b>	Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB	
<b>Electrical characteristics</b>	<b>Voltage</b>	90 - 264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen)	
	<b>Maximum power rating</b>	888 W	
	<b>Idle power</b>	139 W	
	<b>Frequency</b>	50/60 Hz	
	<b>Notes</b>	Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.	
	<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance	
	<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	
<b>Immunity</b>	<b>Generic</b>	ETSI EN 300 386 V1.3.3	
	<b>EN</b>	EN 55024:1998+ A1:2001 + A2:2003	
	<b>ESD</b>	EN 61000-4-2; IEC 61000-4-2	
	<b>Radiated</b>	EN 61000-4-3; IEC 61000-4-3	
	<b>EFT/Burst</b>	EN 61000-4-4; IEC 61000-4-4	
	<b>Surge</b>	EN 61000-4-5; IEC 61000-4-5	
	<b>Conducted</b>	EN 61000-4-6; IEC 61000-4-6	
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8	
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11	

## Technical Specifications

	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
	<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	
<hr/>		
<b>HPE FlexNetwork 5940 48p 10GbE SFP/SFP+ and 6p 40/100GbE QSFP28 with 2 Fans 2 PS Switch (JH684A)</b>		
<b>Includes</b>	1 HPE FlexFabric 5940 2-slot Switch (JH390A) 2 HPE 58x0AF 650W AC Power Supplies (JC680A) (2) HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Trays (JG552A)	
<b>I/O ports and slots</b>	48 fixed 1000/10000 SFP+ ports 6 QSFP28 100GbE ports	
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 SFP GbE port 1 USB 2.0 1 Mini USB 2.0	
<b>Power supplies</b>	2 power supply slots	
<b>Fan tray</b>	2 fan tray slots This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 18.11(d) x 1.72(h) in (44 x 46 x 4.36 cm)
	<b>Weight</b>	24.25 lb (11 kg) shipping weight
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM	
<b>Performance</b>	<b>10 Gbps Latency</b>	< 1 μs (64-byte packets)
	<b>Throughput</b>	up to 1607 Mpps
	<b>Routing/Switching capacity</b>	2160 Gbps
	<b>Routing table size</b>	120000 entries (IPv4), 60000 entries (IPv6)
	<b>MAC address table size</b>	288000 entries
<b>Environment</b>	<b>Operating temperature</b>	32°F to 113°F (0°C to 45°C)
	<b>Operating relative humidity</b>	10% to 90%, noncondensing
	<b>Acoustic</b>	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB
<b>Electrical characteristics</b>	<b>Maximum heat dissipation</b>	887 BTU/hr (935.79 kJ/hr)
	<b>Voltage</b>	100 - 240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen)
	<b>Maximum power rating</b>	196 W
	<b>Frequency</b>	50/60 Hz
	<b>Notes</b>	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the

## Technical Specifications

infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.

<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance	
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	
<b>Immunity</b>	<b>Generic</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>EN</b>	EN 61000-4-2; IEC 61000-4-2
	<b>ESD</b>	EN 61000-4-3; IEC 61000-4-3
	<b>Radiated</b>	EN 61000-4-4; IEC 61000-4-4
	<b>EFT/Burst</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Surge</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Conducted</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
	<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

### HPE FlexNetwork 5940 48p 10GBaseT and 6p 40/100GbE QSFP28 with 2 Fans 2 Power Supply Switch (JH685A)

<b>Includes</b>	1 HPE FlexFabric 5940 48XGT 6QSFP28 Switch (JH391A) 2 HPE 58xOAF 650W AC Power Supplies (JC680A) 2 HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Trays (JG552A)	
<b>I/O ports and slots</b>	48 1/10GBASE-T ports 6 QSFP28 100GbE ports	
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 SFP GbE port 1 USB 2.0 1 Mini USB 2.0	
<b>Power supplies</b>	2 power supply slots	
<b>Fan tray</b>	2 fan tray slots This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 25.98(d) x 1.72(h) in (44 x 66 x 4.36 cm)
	<b>Weight</b>	28.66 lb (13 kg) shipping weight
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM	

## Technical Specifications

<b>Performance</b>	<b>10 Gbps Latency</b>	< 1 $\mu$ s (64-byte packets)
	<b>Throughput</b>	up to 1607 Mpps
	<b>Routing/Switching capacity</b>	2160 Gbps
	<b>Routing table size</b>	120000 entries (IPv4), 60000 entries (IPv6)
	<b>MAC address table size</b>	288000 entries
<b>Environment</b>	<b>Operating temperature</b>	32°F to 113°F (0°C to 45°C)
	<b>Operating relative humidity</b>	10% to 90%, noncondensing
	<b>Acoustic</b>	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB
<b>Electrical characteristics</b>	<b>Maximum heat dissipation</b>	887 BTU/hr (935.79 kJ/hr)
	<b>Voltage</b>	100 - 240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen)
	<b>Maximum power rating</b>	320 W
	<b>Frequency</b>	50/60 Hz
	<b>Notes</b>	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
	<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	
<b>Immunity</b>	<b>Generic</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>EN</b>	EN 61000-4-2; IEC 61000-4-2
	<b>ESD</b>	EN 61000-4-3; IEC 61000-4-3
	<b>Radiated</b>	EN 61000-4-4; IEC 61000-4-4
	<b>EFT/Burst</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Surge</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Conducted</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3	
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	



## Technical Specifications

<b>Includes</b>	1 HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch (JH396A) 2 HPE 58x0AF 650W AC Power Supplies (JC680A) 2 HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Trays (JG552A)
<b>I/O ports and slots</b>	32 QSFP+ 40GbE ports
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0 1 Mini USB 2.0
<b>Power supplies</b>	2 power supply slots
<b>Fan tray</b>	2 fan tray slots This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.
<b>Physical characteristics</b>	<b>Dimensions</b> 17.32(w) x 25.98(d) x 1.74(h) in (44.00 x 66.0 x 4.42 cm) <b>Weight</b> 35.27 lb (16 kg) shipping weight <b>Full configuration weight</b> 28.66 lb (13 kg)
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM
<b>Performance</b>	<b>10 Gbps Latency</b> < 1 μs (64-byte packets) <b>Throughput</b> up to 1904Mpps <b>Routing/Switching capacity</b> 2560 Gbps <b>Routing table size</b> 120000 entries (IPv4), 60000 entries (IPv6) <b>MAC address table size</b> 288000 entries
<b>Environment</b>	<b>Operating temperature</b> 32°F to 113°F (0°C to 45°C) <b>Operating relative humidity</b> 10% to 90%, noncondensing <b>Acoustic</b> Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB
<b>Electrical characteristics</b>	<b>Maximum heat dissipation</b> 597/1361 BTU/hr (629.83/1435.86 kJ/hr) <b>Voltage</b> 90 - 264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen) <b>Maximum power rating</b> 409 W <b>Frequency</b> 50/60 Hz <b>Notes</b> Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)
<b>Immunity</b>	<b>Generic</b> EN 55024:1998+ A1:2001 + A2:2003 <b>EN</b> EN 61000-4-2; IEC 61000-4-2

## Technical Specifications

	<b>ESD</b>	EN 61000-4-3; IEC 61000-4-3
	<b>Radiated</b>	EN 61000-4-4; IEC 61000-4-4
	<b>EFT/Burst</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Surge</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Conducted</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
	<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

---

**HPE FlexNetwork 5940 2-slot Chassis with 2 Fans 2 Power Supply Bundle (JH691A)**

<b>Includes</b>	1 HPE FlexFabric 5940 2-slot Switch (JH397A) 2 HPE 58x0AF 650W AC Power Supplies (JC680A) 2 HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Trays (JG552A)	
<b>I/O ports and slots</b>	2 module slots 1 QSFP+ 40GbE ports Supports a maximum of 18 40GbE ports or 48 1/10GBASE-T ports or 48 SFP+ ports or 48 Converged ports, or a combination	
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0 1 Mini USB 2.0	
<b>Power supplies</b>	2 power supply slots	
<b>Fan tray</b>	2 fan tray slots This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 25.98(d) x 1.74(h) in (44.00 x 66.0 x 4.42 cm) (1U height)
	<b>Weight</b>	39.68 lb (18 kg) shipping weight
	<b>Full configuration weight</b>	35.27 lb (16 kg)
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM	
<b>Performance</b>	<b>10 Gbps Latency</b>	< 1 μs (64-byte packets)
	<b>Throughput</b>	up to 1071 Mpps
	<b>Routing/Switching capacity</b>	1440 Gbps
	<b>Routing table size</b>	128000 entries (IPv4), 64000 entries (IPv6)
	<b>MAC address table size</b>	288000 entries

## Technical Specifications

<b>Reliability</b>	<b>MTBF (years)</b>	47.2
	<b>MTTR (hours)</b>	1
<b>Environment</b>	<b>Operating temperature</b>	32°F to 113°F (0°C to 45°C)
	<b>Operating relative humidity</b>	10% to 90%, noncondensing
	<b>Acoustic</b>	Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB
<b>Electrical characteristics</b>	<b>Voltage</b>	90 - 264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen)
	<b>Maximum power rating</b>	508 W
	<b>Idle power</b>	105 W
	<b>Frequency</b>	50/60 Hz
	<b>Notes</b>	Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
	<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance
	<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)
<b>Immunity</b>	<b>Generic</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>EN</b>	EN 61000-4-2; IEC 61000-4-2
	<b>ESD</b>	EN 61000-4-3; IEC 61000-4-3
	<b>Radiated</b>	EN 61000-4-4; IEC 61000-4-4
	<b>EFT/Burst</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Surge</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Conducted</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3	
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

### HPE FlexNetwork 5940 4-slot Chassis with 2 Fans 4 Power Supply Bundle (JH692A)

<b>Includes</b>	1 HPE FlexFabric 5940 4-slot Switch (JH398A)
	4 HPE 58x0AF 650W AC Power Supplies (JC680A)
	2 HPE 5930 4-slot Front (Port Side) to Back (Power Side) Airflow Fan Trays (JH186A)

## Technical Specifications

<b>I/O ports and slots</b>	4 module slots Supports a maximum of 32 40GbE ports or 96 1/10GBASE-T ports or 96 SFP+ ports or 96 Converged ports, or a combination
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0 1 Mini USB 2.0
<b>Power supplies</b>	4 power supply slots
<b>Fan tray</b>	2 fan tray slots This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.
<b>Physical characteristics</b>	<b>Dimensions</b> 17.32(w) x 25.98(d) x 3.47(h) in (44.00 x 66.0 x 8.81 cm) (2U height) <b>Weight</b> 66.14 lb (30 kg) shipping weight <b>Full configuration weight</b> 59.52 lb (27 kg)
<b>Memory and processor</b>	1 GB flash; Packet buffer size: 12.2 MB, 4 GB SDRAM
<b>Performance</b>	<b>10 Gbps Latency</b> < 1 μs (64-byte packets) <b>Throughput</b> up to 1429 Mpps <b>Routing/Switching capacity</b> 2560 Gbps <b>Routing table size</b> 128000 entries (IPv4), 64000 entries (IPv6) <b>MAC address table size</b> 288000 entries
<b>Reliability</b>	<b>MTBF (years)</b> 35.8 <b>MTTR (hours)</b> 1
<b>Environment</b>	<b>Operating temperature</b> 32°F to 113°F (0°C to 45°C) <b>Operating relative humidity</b> 10% to 90%, noncondensing <b>Acoustic</b> Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB
<b>Electrical characteristics</b>	<b>Voltage</b> 90 - 264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen) <b>Maximum power rating</b> 888 W <b>Idle power</b> 139 W <b>Frequency</b> 50/60 Hz <b>Notes</b> Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
<b>Safety</b>	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance
<b>Emissions</b>	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)

## Technical Specifications

<b>Immunity</b>	<b>Generic</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>EN</b>	EN 61000-4-2; IEC 61000-4-2
	<b>ESD</b>	EN 61000-4-3; IEC 61000-4-3
	<b>Radiated</b>	EN 61000-4-4; IEC 61000-4-4
	<b>EFT/Burst</b>	EN 61000-4-5; IEC 61000-4-5
	<b>Surge</b>	EN 61000-4-6; IEC 61000-4-6
	<b>Conducted</b>	EN 55024:1998+ A1:2001 + A2:2003
	<b>Power frequency magnetic field</b>	IEC 61000-4-8; EN 61000-4-8
	<b>Voltage dips and interruptions</b>	EN 61000-4-11; IEC 61000-4-11
	<b>Harmonics</b>	EN 61000-3-2, IEC 61000-3-2
	<b>Flicker</b>	EN 61000-3-3, IEC 61000-3-3
<b>Management</b>	IMC - Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Services</b>	Refer to the Hewlett Packard Enterprise website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

---

### Standards and protocols (applies to all products in series)

<b>BGP</b>	RFC 1163 Border Gateway Protocol (BGP) RFC 1771 BGPv4 RFC 1997 BGP Communities Attribute RFC 2918 Route Refresh Capability RFC 3392 Capabilities Advertisement with BGP-4 RFC 4271 A Border Gateway Protocol 4 (BGP-4) RFC 4360 BGP Extended Communities Attribute RFC 4456 BGP Route Reflection: An Alternative to Full Mesh Internal BGP (IBGP) RFC 4760 Multiprotocol Extensions for BGP-4 RFC 7432 BGP MPLS-Based Ethernet VPN
<b>Device Management</b>	RFC 1157 SNMPv1/v2c RFC 1305 NTPv3 RFC 1591 DNS (client) RFC 1902 (SNMPv2) RFC 1908 (SNMP v1/2 Coexistence) RFC 2573 (SNMPv3 Applications) RFC 2576 (Coexistence between SNMP V1, V2, V3) RFC 2819 RMON Multiple Configuration Files Multiple Software Images SSHv1/SSHv2 Secure Shell TACACS/TACACS+
<b>General Protocols</b>	IEEE 802.1ad Q-in-Q IEEE 802.1AX-2008 Link Aggregation IEEE 802.1D MAC Bridges IEEE 802.1p Priority IEEE 802.1Q VLANs

## Technical Specifications

IEEE 802.1s Multiple Spanning Trees  
IEEE 802.1w Rapid Reconfiguration of Spanning Tree  
IEEE 802.3ad Link Aggregation Control Protocol (LACP)  
IEEE 802.3ae 10-Gigabit Ethernet  
IEEE 802.3ag Ethernet OAM  
IEEE 802.3ah Ethernet in First Mile over Point to Point Fiber - EFMF  
IEEE 802.3x Flow Control  
RFC 768 UDP  
RFC 783 TFTP Protocol (revision 2)  
RFC 791 IP  
RFC 792 ICMP  
RFC 793 TCP  
RFC 826 ARP  
RFC 854 TELNET  
RFC 856 TELNET  
RFC 868 Time Protocol  
RFC 896 Congestion Control in IP/TCP Internetworks  
RFC 950 Internet Standard Subnetting Procedure  
RFC 1027 Proxy ARP  
RFC 1058 RIPv1  
RFC 1091 Telnet Terminal-Type Option  
RFC 1141 Incremental updating of the Internet checksum  
RFC 1142 OSI IS-IS Intra-domain Routing Protocol  
RFC 1191 Path MTU discovery  
RFC 1213 Management Information Base for Network Management of TCP/IP-based internets  
RFC 1253 (OSPF v2)  
RFC 1531 Dynamic Host Configuration Protocol  
RFC 1533 DHCP Options and BOOTP Vendor Extensions  
RFC 1534 DHCP/BOOTP Interoperation  
RFC 1541 DHCP  
RFC 1542 Clarifications and Extensions for the Bootstrap Protocol  
RFC 1591 DNS (client only)  
RFC 1624 Incremental Internet Checksum  
RFC 1723 RIP v2  
RFC 1812 IPv4 Routing  
RFC 2030 Simple Network Time Protocol (SNTP) v4  
RFC 2131 DHCP  
RFC 2236 IGMP Snooping  
RFC 2338 VRRP  
RFC 2453 RIPv2  
RFC 2581 TCP Congestion Control  
RFC 2644 Directed Broadcast Control  
RFC 2767 Dual Stack Hosts using BIS  
RFC 2865 Remote Authentication Dial In User Service (RADIUS)  
RFC 2868 RADIUS Attributes for Tunnel Protocol Support  
RFC 2890 Key and Sequence Number Extensions to GRE  
RFC 2929 DNS IANA Considerations  
RFC 3046 DHCP Relay Agent Information Option  
RFC 3411 An Architecture for Describing Simple Network Management Protocol (SNMP) Management Frameworks  
RFC 3412 Message Processing and Dispatching for the Simple Network Management Protocol (SNMP)  
RFC 3413 Simple Network Management Protocol (SNMP) Applications  
RFC 3416 Protocol Operations for SNMP  
RFC 3417 Transport Mappings for the Simple Network Management Protocol (SNMP)

## Technical Specifications

RFC 3418 Management Information Base (MIB) for the Simple Network Management Protocol (SNMP)  
RFC 3768 Virtual Router Redundancy Protocol (VRRP)  
RFC 4250 The Secure Shell (SSH) Protocol Assigned Numbers  
RFC 4251 The Secure Shell (SSH) Protocol Architecture  
RFC 4252 The Secure Shell (SSH) Authentication Protocol  
RFC 4253 The Secure Shell (SSH) Transport Layer Protocol  
RFC 4254 The Secure Shell (SSH) Connection Protocol  
RFC 4292 IP Forwarding Table MIB  
RFC 4293 Management Information Base for the Internet Protocol (IP)  
RFC 4364 BGP/MPLS IP Virtual Private Networks (VPNs)  
RFC 4419 Diffie-Hellman Group Exchange for the Secure Shell (SSH) Transport Layer Protocol  
RFC 4594 Configuration Guidelines for DiffServ Service Classes  
RFC 4601 Protocol Independent Multicast - Sparse Mode (PIM-SM): Protocol Specification (Revised)  
RFC 4604 Using Internet Group Management Protocol Version 3 (IGMPv3) and Multicast Listener Discovery Protocol Version 2 (MLDv2) for Source-Specific Multicast  
RFC 4607 Source-Specific Multicast for IP  
RFC 4941 Privacy Extensions for Stateless Address Autoconfiguration in IPv6  
RFC 5340 OSPF for IPv6  
RFC 5905 Network Time Protocol Version 4: Protocol and Algorithms Specification

### IPv6

RFC 2080 RIPng for IPv6  
RFC 2460 IPv6 Specification  
RFC 2461 IPv6 Neighbor Discovery  
RFC 2462 IPv6 Stateless Address Auto-configuration  
RFC 2463 ICMPv6  
RFC 2464 Transmission of IPv6 over Ethernet Networks  
RFC 2473 Generic Packet Tunneling in IPv6  
RFC 2545 Use of MP-BGP-4 for IPv6  
RFC 2563 ICMPv6  
RFC 2711 IPv6 Router Alert Option  
RFC 2740 OSPFv3 for IPv6  
RFC 2767 Dual Stack Hosts using BIS  
RFC 3315 DHCPv6 (client and relay)  
RFC 3484 Default Address Selection for IPv6  
RFC 3810 Multicast Listener Discovery Version 2 (MLDv2) for IPv6  
RFC 4213 Basic Transition Mechanisms for IPv6 Hosts and Routers  
RFC 4291 IP Version 6 Addressing Architecture  
RFC 4443 ICMPv6  
RFC 4552 Authentication/Confidentiality for OSPFv3  
RFC 4862 IPv6 Stateless Address Auto-configuration  
RFC 5095 Deprecation of Type 0 Routing Headers in IPv6

### MIBs

RFC 1213 MIB II  
RFC 1907 SNMPv2 MIB  
RFC 2571 SNMP Framework MIB  
RFC 2572 SNMP-MPD MIB  
RFC 2573 SNMP-Notification MIB  
RFC 2573 SNMP-Target MIB  
RFC 2574 SNMP USM MIB  
RFC 2737 Entity MIB (Version 2)  
RFC 3414 SNMP-User based-SM MIB  
RFC 3415 SNMP-View based-ACM MIB  
LLDP-EXT-DOT1-MIB  
LLDP-EXT-DOT3-MIB

## Technical Specifications

LLDP-MIB

**Network Management** RFC 2580 Conformance Statements for SMIv2  
RFC 3164 BSD syslog Protocol

**OSPF** RFC 1587 OSPF NSSA  
RFC 2328 OSPFv2  
RFC 3101 OSPF NSSA  
RFC 3137 OSPF Stub Router Advertisement  
RFC 3623 Graceful OSPF Restart  
RFC 4577 OSPF as the Provider/Customer Edge Protocol for BGP/MPLS IP Virtual Private Networks (VPNs)  
RFC 4811 OSPF Out-of-Band LSDB Resynchronization  
RFC 4812 OSPF Restart Signaling  
RFC 4813 OSPF Link-Local Signaling

**QoS/CoS** IEEE 802.1p (CoS)  
RFC 2475 DiffServ Architecture  
RFC 2597 DiffServ Assured Forwarding (AF)  
RFC 3247 Supplemental Information for the New Definition of the EF PHB (Expedited Forwarding Per-Hop Behavior)  
RFC 3260 New Terminology and Clarifications for DiffServ

**Security** RFC 1321 The MD5 Message-Digest Algorithm  
RFC 2818 HTTP Over TLS  
RFC 6192 Partial Support - Protecting the Router Control Plane  
Access Control Lists (ACLs)  
SSHv2 Secure Shell



## Accessories

### HPE FlexFabric 5940 Switch Series accessories

#### HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch (JH395A)

HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE A58x0AF Back (Power Side) to Front (Port Side) Airflow 300W AC Power Supply	JG900A
HPE A58x0AF Back (Power Side) to Front (Port Side) Airflow 300W DC Power Supply	JG901A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE 58x0AF Back (Power Side) to Front (Port Side) Airflow Fan Tray	JC682A
HPE 58x0AF Front (Port Side) to Back (Power Side) Airflow Fan Tray	JC683A
HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A

#### HPE FlexFabric 5940 32QSFP+ Switch (JH396A)

## Accessories

HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE X711 Front	
HPE X712 Back	

### HPE FlexFabric 5940 48XGT 6QSFP+ Switch (JH394A)

HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A

### HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch (JH390A)

HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A

## Accessories

HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X240 QSFP28 4xSFP28 1m Direct Attach Copper Cable	JL282A
HPE X240 QSFP28 4xSFP28 3m Direct Attach Copper Cable	JL283A
HPE X240 QSFP28 4xSFP28 5m Direct Attach Copper Cable	JL284A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE A58x0AF Back (Power Side) to Front (Port Side) Airflow 300W AC Power Supply	JG900A
HPE A58x0AF Back (Power Side) to Front (Port Side) Airflow 300W DC Power Supply	JG901A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE 58x0AF Back (Power Side) to Front (Port Side) Airflow Fan Tray	JC682A
HPE 58x0AF Front (Port Side) to Back (Power Side) Airflow Fan Tray	JC683A
HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A

### HPE FlexFabric 5940 48XGT 6QSFP28 Switch (JH391A)

HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A

## Accessories

HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A

### HPE FlexFabric 5940 2-slot Switch (JH397A)

HPE 5940 2-port QSFP+ and 2-port QSFP28 Module	JH409A
HPE 5930 24-port SFP+ and 2-port QSFP+ Module	JH180A
HPE 5930 24-port SFP+ and 2-port QSFP+ with MACsec Module	JH181A
HPE 5930 24-port 10GBASE-T and 2-port QSFP+ with MACsec Module	JH182A
HPE 5930 8-port QSFP+ Module	JH183A
HPE 5930 24-port Converged Port and 2-port QSFP+ Module	JH184A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A

## Accessories

HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X240 QSFP28 4xSFP28 1m Direct Attach Copper Cable	JL282A
HPE X240 QSFP28 4xSFP28 3m Direct Attach Copper Cable	JL283A
HPE X240 QSFP28 4xSFP28 5m Direct Attach Copper Cable	JL284A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A

### HPE FlexFabric 5940 4-slot Switch (JH398A)

HPE 5940 2-port QSFP+ and 2-port QSFP28 Module	JH409A
HPE 5930 24-port SFP+ and 2-port QSFP+ Module	JH180A
HPE 5930 24-port SFP+ and 2-port QSFP+ with MACsec Module	JH181A
HPE 5930 24-port 10GBASE-T and 2-port QSFP+ with MACsec Module	JH182A
HPE 5930 8-port QSFP+ Module	JH183A
HPE 5930 24-port Converged Port and 2-port QSFP+ Module	JH184A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A

## Accessories

HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X240 QSFP28 4xSFP28 1m Direct Attach Copper Cable	JL282A
HPE X240 QSFP28 4xSFP28 3m Direct Attach Copper Cable	JL283A
HPE X240 QSFP28 4xSFP28 5m Direct Attach Copper Cable	JL284A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE 5930 4-slot Back (Power Side) to Front (Port Side) Airflow Fan Tray	JH185A
HPE 5930 4-slot Front (Port Side) to Back (Power Side) Airflow Fan Tray	JH186A

### **HPE FlexNetwork 5940 48p 10GbE SFP/SFP+ and 6p 40/100GbE QSFP28 with 2 Fans 2 PS Switch (JH684A)**

HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X240 10G SFP+ to SFP+ 7m Direct Attach Copper Campus-Cable	JH696A
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Campus-Cable	JH694A
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Campus-Cable	JH695A
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X240 QSFP28 4xSFP28 1m Direct Attach Copper Cable	JL282A
HPE X240 QSFP28 4xSFP28 3m Direct Attach Copper Cable	JL283A
HPE X240 QSFP28 4xSFP28 5m Direct Attach Copper Cable	JL284A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Campus-Cable	JH703A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Campus-Cable	JH701A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Campus-Cable	JH702A

## Accessories

HPE X150 100G QSFP28 MPO SR4 100m MM Campus-Transceiver	JH682A
HPE X150 100G QSFP28 LC LR4 10km SM Campus-Transceiver	JH683A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Campus-Cable	JH693A
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE A58x0AF Back (Power Side) to Front (Port Side) Airflow 300W AC Power Supply	JG900A
HPE A58x0AF Back (Power Side) to Front (Port Side) Airflow 300W DC Power Supply	JG901A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE 58x0AF Back (Power Side) to Front (Port Side) Airflow Fan Tray	JC682A
HPE 58x0AF Front (Port Side) to Back (Power Side) Airflow Fan Tray	JC683A
HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A

### **HPE FlexNetwork 5940 48p 10GBaseT and 6p 40/100GbE QSFP28 with 2 Fans 2 Power Supply Switch (JH685A)**

HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Campus-Cable	JH703A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Campus-Cable	JH701A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Campus-Cable	JH702A
HPE X150 100G QSFP28 MPO SR4 100m MM Campus-Transceiver	JH682A
HPE X150 100G QSFP28 LC LR4 10km SM Campus-Transceiver	JH683A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A

## Accessories

HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A

### HPE FlexNetwork 5940 32-port 40GbE QSFP+ with 2 Fans 2 Power Supply Switch (JH686A)

HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A

### HPE FlexNetwork 5940 2-slot Chassis with 2 Fans 2 Power Supply Bundle (JH691A)

HPE 5940 2-port QSFP+ and 2-port QSFP28 Module	JH409A
HPE FlexNetwork 5930 24-port 10GbE SFP/SFP+ and 2-port 40GbE QSFP+ Module	JH689A
HPE 5930 24-port SFP+ and 2-port QSFP+ with MACsec Module	JH181A
HPE FlexNetwork 5930 24-port 10GBASE-T and 2-port 40GbE QSFP+ MACsec Module	JH690A
HPE 5930 8-port QSFP+ Module	JH183A
HPE 5930 24-port Converged Port and 2-port QSFP+ Module	JH184A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Campus-Cable	JH694A
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Campus-Cable	JH695A
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A



## Accessories

HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver	JH680A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume Fan Tray	JG552A
HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume Fan Tray	JG553A

### **HPE FlexNetwork 5940 4-slot Chassis with 2 Fans 4 Power Supply Bundle (JH692A)**

HPE 5940 2-port QSFP+ and 2-port QSFP28 Module	JH409A
HPE FlexNetwork 5930 24-port 10GbE SFP/SFP+ and 2-port 40GbE QSFP+ Module	JH689A
HPE 5930 24-port SFP+ and 2-port QSFP+ with MACsec Module	JH181A
HPE FlexNetwork 5930 24-port 10GBASE-T and 2-port 40GbE QSFP+ MACsec Module	JH690A
HPE 5930 8-port QSFP+ Module	JH183A
HPE 5930 24-port Converged Port and 2-port QSFP+ Module	JH184A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LRM Data Center Transceiver	JL438A
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Campus-Cable	JH694A
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Campus-Cable	JH695A
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A

**Accessories**

HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
HPE X140 40G QSFP+ MPO SR4 Campus-Transceiver	JH679A
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Campus-Cable	JH697A
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Campus-Cable	JH698A
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Campus-Cable	JH699A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Campus-Cable	JH700A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Campus-Transceiver	JH677A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Campus-Transceiver	JH681A
HPE X140 40G QSFP+ LC BiDi 100m MM Campus-Transceiver	JH678A
HPE X140 40G QSFP+ LC LR4L 2km SM Campus-Transceiver	JH680A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE 58x0AF 650W AC Power Supply	JC680A
HP 58x0AF 650W DC Power Supply	JC681A
HPE 5930 4-slot Back (Power Side) to Front (Port Side) Airflow Fan Tray	JH185A
HPE 5930 4-slot Front (Port Side) to Back (Power Side) Airflow Fan Tray	JH186A

## Summary of Changes

Date	Version History	Action	Description of Change
03-Apr-2017	Form Version 6 to 7	Changed	Changes made on Configuration section
06-Mar-2017	From Version 5 to 6	Added	SKUs added: JL437A; JL438A; JL439A
		Changed	Configuration Section updated
06-Feb-2017	From Version 4 to 5	Changed	Accessories updated
09-Jan-2017	From Version 3 to 4	Added	Models added: JH684A, JH685A, JH686A, JH691A, JH692A  SKUs added: JH689A, JH690A, JH409A, JH677A, JH678A, JH679A, JH680A, JH681A, JH682A, JH683A, JH693A, JH694A, JH695A, JH696A, JH697A, JH698A, JH699A, JH700A, JH701A, JH702A, JH703A
07-Nov-2016	From Version 2 to 3	Added	Models added: JH397A; JH398A
		Changed	Edits made on Configuration and Accessories sections
05-Sep-2016	From Version 1 to 2	Added	SKUs added: JL273A, JL282A, JL283A, JL284A
		Changed	Overview and Technical Specifications updated
01-Aug-2016	Version 1	Creation	Document creation

---

## Summary of Changes



---

**Sign up for updates**



**Hewlett Packard  
Enterprise**

---

© Copyright 2017 Hewlett Packard Enterprise Development L.P. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

To learn more, visit: <http://www.hpe/networking>

c05158726 - 15632 - Worldwide - V7 - 3-April-2017