

## Cisco Catalyst 3750E-48TD Switch

The Cisco® Catalyst® 3750E-48TD Switch with StackWise Plus (Figure 1) is an enterprise-class stackable wiring closet switch that facilitates the deployment of secure converged applications while maximizing investment protection for evolving network and application requirements. Combining 10/100/1000 with 10 Gigabit Ethernet uplinks, the Cisco Catalyst 3750E-48TD enhances worker productivity by enabling applications such as IP telephony, wireless, and video.

### Cisco Catalyst 3750E-48TD Primary Features

- Cisco TwinGig converter module for migrating uplinks from Gigabit Ethernet to 10 Gigabit Ethernet
- StackWise Plus for ease of use and resiliency with 64 Gbps of throughput
- Modular power supply with externally available backup
- Multicast routing, IPv6 routing, and access control list in hardware
- Out-of-band Ethernet management port along with RS-232 console port

**Figure 1.** Cisco Catalyst 3750E-48TD Switch



### Switch Configurations

Table 1 shows the Cisco Catalyst 3750E-48TD configurations:

**Table 1.** Switch Configurations

| Feature                   | Description  |
|---------------------------|--|
| Cisco Catalyst 3750E-48TD | 48 Ethernet 10/100/1000 ports and 2 X2 10 Gigabit Ethernet uplinks |

### Cisco Catalyst 3750-E Software

Cisco Catalyst 3750-E Series is available with either the IP Base or the IP Services feature set. The IP Base feature set includes advanced quality of service (QoS), a suite of security features, rate-limiting, access control lists, and basic static and Routing Information Protocol (RIP) routing capability. The IP Services feature set provides a richer set of enterprise-class features, including advanced hardware-based IP unicast and multicast routing—Enhanced Interior Gateway Routing Protocol (EIGRP), Open Shortest Path First (OSPF), Border Gateway Protocol (BGP), Protocol Independent Multicast (PIM), and so on. An Advanced IP Services feature set is also available for IPv6 routing.

Customers can transparently upgrade the software feature set in the Cisco Catalyst 3750-E Series Switches through Cisco IOS® Software Activation. Software activation authorizes and enables the Cisco IOS Software feature sets. A special file contained in the switch, called a license file, is examined by Cisco IOS Software when the switch is powered on. Based on the license's type, Cisco IOS Software activates the appropriate feature set. License types can be changed, or upgraded, to activate a different feature set. For detailed information about Software Activation, visit <http://www.cisco.com/go/sa>.

### **Investment Protection**

The Cisco Catalyst 3750-E Series Switches are compatible with the Cisco Catalyst 3750 Series Switches, enabling customers to stack them together and thereby protect existing investment in the Cisco Catalyst 3750 Series Switches. The Cisco TwinGig Small Form-Factor Pluggable (SFP) converter module further protects customers' investment in Cisco Catalyst 3750-E Series Switches by enabling migration from Gigabit Ethernet to 10 Gigabit Ethernet uplinks, as business needs require, without having to upgrade the switches.

### **Cisco StackWise Plus Technology**

Cisco StackWise Plus technology is built on the highly successful StackWise™ technology, which is a premium stacking architecture optimized for Gigabit Ethernet. StackWise technology was designed to respond to additions, deletions, and redeployment while maintaining constant performance. The stack behaves as a single switching unit that is managed by a master switch elected from one of the member switches. The master switch automatically creates and updates all the switching and optional routing tables. A working stack can accept new members or delete old ones without service interruption. StackWise creates a highly resilient single unified system of up to nine switches, providing simplified management using a single IP address, single telnet session, single command-line interface (CLI), auto-version checking, autoconfiguration, and more. StackWise Plus supports all the features of StackWise and provides backward compatibility with the existing Cisco Catalyst 3750 Series Switches while enhancing the throughput of the system up to 64 Gbps. StackWise Plus also enables local switching in Cisco Catalyst 3750-E Series Switches. Local switching packets coming into a port in the Cisco Catalyst 3750-E Series Switch destined for another port in the same switch do not have to traverse through the stack ring, thus increasing the forwarding capacity of the switch.

### **10 Gigabit Ethernet Uplinks and the Cisco TwinGig SFP Converter**

The Cisco Catalyst 3750-E features wire-speed 10 Gigabit Ethernet uplink ports for high-bandwidth applications, relieving congestion and ensuring smooth delivery of data. The TwinGig SFP converter (see Figure 2) converts a 10 Gigabit Ethernet X2 interface into two Gigabit Ethernet SFP ports. This way, customers can initially use the switch with Gigabit Ethernet uplinks and later implement 10 Gigabit Ethernet uplinks as business demands change, without having to upgrade the access layer.

**Figure 2.** Cisco TwinGig Adapter Converting 10 Gigabit Ethernet X2 Interface into Two Gigabit Ethernet SFP Interfaces



### Modular Power Supplies

The Cisco Catalyst 3750E-48TD Switch has one power supply slot and supports the following power supplies.

- C3K-PWR-265WAC: 265WAC power supply for 48-port or 24-port switch without PoE
- C3K-PWR-265WDC: 265WDC power supply for 48-port or 24-port switch without PoE

Maximum power availability for converged voice and data networks is attainable when a Cisco Catalyst 3750E-48TD Switch is combined with the Cisco RPS 2300 Redundant Power System for transparent protection against internal power supply failures and an uninterruptible power supply (UPS) system to safeguard against power outages. Using the RPS 2300 to provide backup power, the Cisco Catalyst 3750E-48TD Switch power supply becomes hot swappable. Table 4 shows the power supply compatibility matrix.

### Redundant Power System

The Cisco Catalyst 3750-E Series Switches support the new generation of Redundant Power Supply (RPS) 2300. The RPS 2300 increases availability in a converged data, voice, and video network by providing transparent power backup to two of six attached Cisco Catalyst 3750-E Series Switches at the same time. The failed power supply can be swapped out while the switch is being powered up by the RPS 2300.

### Primary Features and Benefits

#### Ease of Use: Deployment

A working stack is self-managing and self-configuring. When switches are added or removed, the master switch automatically loads the Cisco IOS Software version running on the stack to the new switch, loads the global configuration parameters, and updates all the routing tables to reflect changes. Upgrades are applied universally and simultaneously to all members of the stack.

The Cisco Catalyst 3750-E Series stacks up to nine switches as a single logical unit for a total of 468 Ethernet 10/100/1000 ports or 18 10 Gigabit Ethernet ports. Individual 10/100/1000 units can be joined in any combination to evolve with network needs.

Other ease of use features include but are not limited to:

- Smartports enable fast and easy configuration of Cisco recommended best practice security and QoS features, encapsulating years of Cisco networking expertise.

- Dynamic Host Configuration Protocol (DHCP) autoconfiguration of multiple switches through a boot server eases switch deployment.
- Automatic QoS (AutoQoS) simplifies QoS configuration in voice over IP (VoIP) networks by issuing interface and global switch commands to detect Cisco IP phones, classify traffic, and help enable egress queue configuration.
- Master configuration management helps ensure that all switches are automatically upgraded when the master switch receives a new software version. Automatic software version checking and updating help ensure that all stack members have the same software version.
- Autonegotiation on all ports automatically selects half- or full-duplex transmission mode to optimize bandwidth.
- Dynamic Trunking Protocol (DTP) facilitates dynamic trunk configuration across all switch ports.
- Port Aggregation Protocol (PAgP) automates the creation of Cisco Fast EtherChannel<sup>®</sup> groups or Gigabit EtherChannel groups to link to another switch, router, or server.
- Link Aggregation Control Protocol (LACP) allows the creation of Ethernet channeling with devices that conform to IEEE 802.3ad. This feature is similar to Cisco EtherChannel technology and PAgP.
- Automatic media-dependent interface crossover (MDIX) automatically adjusts transmit and receive pairs if an incorrect cable type (crossover or straight-through) is installed.
- Unidirectional Link Detection Protocol (UDLD) and Aggressive UDLD allow unidirectional links caused by incorrect fiber-optic wiring or port faults to be detected and disabled on fiber-optic interfaces.

### High Availability

The Cisco Catalyst 3750-E Series increases availability for stackable switches. Each switch can operate both as master controller and as forwarding processor. Each switch in the stack can serve as a master, creating a 1:N availability scheme for network control. In the unlikely event of a single unit failure, all other units continue to forward traffic and maintain operation.

Other high-availability features include but are not limited to:

- Cross-Stack EtherChannel provides the ability to configure Cisco EtherChannel technology across different members of the stack for high resiliency.
- Flexlink provides link redundancy with convergence time less than 100 ms.
- IEEE 802.1s/w Rapid Spanning Tree Protocol (RSTP) and Multiple Spanning Tree Protocol (MSTP) provide rapid spanning-tree convergence independent of spanning-tree timers and also offers the benefit of Layer 2 load balancing and distributed processing. Stacked units behave as a single spanning-tree node.
- Per-VLAN Rapid Spanning Tree (PVRST+) allows rapid spanning-tree reconvergence on a per-VLAN spanning-tree basis, without requiring the implementation of spanning-tree instances.
- Cisco Hot Standby Router Protocol (HSRP) is supported to create redundant, failsafe routing topologies.
- Switch-port autorecovery (Errdisable) automatically attempts to reactivate a link that is disabled because of a network error.



- The Cisco committed information rate (CIR) function provides bandwidth in increments as low as 8 Kbps.
- Rate limiting is provided based on source and destination IP address, source and destination MAC address, Layer 4 TCP/UDP information, or any combination of these fields, using QoS ACLs (IP ACLs or MAC ACLs), class maps, and policy maps.
- Up to 64 aggregate or individual policers are available per Fast Ethernet or Gigabit Ethernet port.

### **Advanced Security**

The Cisco Catalyst 3750-E Series supports a comprehensive set of security features for connectivity and access control, including ACLs, authentication, port-level security, and identity-based network services with 802.1x and extensions. This set of comprehensive features not only helps prevent external attacks, but defends the network against “man-in-the-middle” attacks, a primary concern in today’s business environment. The switch also supports the Network Admission Control (NAC) security framework.

- Dynamic ARP Inspection (DAI) helps ensure user integrity by preventing malicious users from exploiting the insecure nature of the ARP protocol.
- DHCP Snooping prevents malicious users from spoofing a DHCP server and sending out bogus addresses. This feature is used by other primary security features to prevent a number of other attacks such as ARP poisoning.
- IP source guard prevents a malicious user from spoofing or taking over another user’s IP address by creating a binding table between the client’s IP and MAC address, port, and VLAN.
- Private VLANs restrict traffic between hosts in a common segment by segregating traffic at Layer 2, turning a broadcast segment into a nonbroadcast multi-access-like segment.
- Private VLAN Edge provides security and isolation between switch ports, which helps ensure that users cannot snoop on other users’ traffic.
- Unicast RPF feature helps mitigate problems caused by the introduction of malformed or forged (spoofed) IP source addresses into a network by discarding IP packets that lack a verifiable IP source address.
- IEEE 802.1x allows dynamic, port-based security, providing user authentication.
- IEEE 802.1x with VLAN assignment allows a dynamic VLAN assignment for a specific user regardless of where the user is connected.
- IEEE 802.1x with voice VLAN permits an IP phone to access the voice VLAN irrespective of the authorized or unauthorized state of the port.
- IEEE 802.1x and port security are provided to authenticate the port and manage network access for all MAC addresses, including that of the client.
- IEEE 802.1x with an ACL assignment allows for specific identity-based security policies regardless of where the user is connected.
- IEEE 802.1x with guest VLAN allows guests without 802.1x clients to have limited network access on the guest VLAN.
- Web authentication for non-802.1x clients allows non-802.1x clients to use an SSL-based browser for authentication.

- Multi-Domain Authentication allows an IP phone and a PC to authenticate on the same switch port while placing them on appropriate Voice and Data VLAN.
- MAC Auth Bypass (MAB) for voice allows third-party IP phones without an 802.1x supplicant to get authenticated using the MAC address.
- Cisco security VLAN ACLs on all VLANs prevents unauthorized data flows from being bridged within VLANs.
- Cisco standard and extended IP security router ACLs define security policies on routed interfaces for control-plane and data-plane traffic. IPv6 ACLs can be applied to filter IPv6 traffic.
- Port-based ACLs for Layer 2 interfaces allow security policies to be applied on individual switch ports.
- Secure Shell (SSH) Protocol, Kerberos, and Simple Network Management Protocol Version 3 (SNMPv3) provide network security by encrypting administrator traffic during Telnet and SNMP sessions. SSH Protocol, Kerberos, and the cryptographic version of SNMPv3 require a special cryptographic software image because of U.S. export restrictions.
- Bidirectional data support on the Switched Port Analyzer (SPAN) port allows Cisco Intrusion Detection System (IDS) to take action when an intruder is detected.
- TACACS+ and RADIUS authentication facilitates centralized control of the switch and restricts unauthorized users from altering the configuration.
- MAC Address Notification allows administrators to be notified of users added to or removed from the network.
- Port Security secures the access to an access or trunk port based on MAC address.
- Multilevel security on console access prevents unauthorized users from altering the switch configuration.
- Bridge protocol data unit (BPDU) Guard shuts down Spanning Tree PortFast-enabled interfaces when BPDUs are received to avoid accidental topology loops.
- Spanning Tree Root Guard (STRG) prevents edge devices not in the network administrator's control from becoming Spanning Tree Protocol root nodes.
- IGMP filtering provides multicast authentication by filtering out nonsubscribers and limits the number of concurrent multicast streams available per port.
- Dynamic VLAN assignment is supported through implementation of VLAN Membership Policy Server client capability to provide flexibility in assigning ports to VLANs. Dynamic VLAN facilitates the fast assignment of IP addresses.

### Management and Control Features

Each Cisco Catalyst 3750-E Series stack is managed as a single object and has a single IP address. The primary management and control features in the Cisco Catalyst 3750E-E Switches include:

- Cisco IOS Software CLI support provides common user interface and command set with all Cisco routers and Cisco Catalyst desktop switches.
- Switching Database Manager Templates for access, routing, and VLAN deployment allow the administrator to easily maximize memory allocation to the desired features based on deployment-specific requirements.

- Generic On-Line Diagnostic (GOLD) checks the health of hardware components and verifies proper operation of the system data and control plane at run time and boot time.
- Virtual routing and forwarding (VRF)-Lite enables a service provider to support two or more VPNs, with overlapping IP addresses.
- Local Proxy Address Resolution Protocol (ARP) works in conjunction with Private VLAN Edge to minimize broadcasts and maximize available bandwidth.
- VLAN1 minimization allows VLAN1 to be disabled on any individual VLAN trunk.
- Smart Multicast, with Cisco StackWise Plus technology, allows the Cisco Catalyst 3750-E Series to offer greater efficiency and support for more multicast data streams such as video by putting each data packet onto the backplane only once.
- Internet Group Management Protocol (IGMP) Snooping for IPv4 and IPv6 MLD v1 and v2 Snooping provide fast client joins and leaves of multicast streams and limit bandwidth-intensive video traffic to only the requestors.
- Multicast VLAN Registration (MVR) continuously sends multicast streams in a multicast VLAN while isolating the streams from subscriber VLANs for bandwidth and security reasons.
- Per-port broadcast, multicast, and unicast storm control prevents faulty end stations from degrading overall systems performance.
- Voice VLAN simplifies telephony installations by keeping voice traffic on a separate VLAN for easier administration and troubleshooting.
- Cisco VLAN Trunking Protocol (VTP) supports dynamic VLANs and dynamic trunk configuration across all switches.
- Remote Switch Port Analyzer (RSPAN) allows administrators to remotely monitor ports in a Layer 2 switch network from any other switch in the same network.
- For enhanced traffic management, monitoring, and analysis, the Embedded Remote Monitoring (RMON) software agent supports four RMON groups (history, statistics, alarms, and events).
- Layer 2 traceroute eases troubleshooting by identifying the physical path that a packet takes from source to destination.
- Trivial File Transfer Protocol (TFTP) reduces the cost of administering software upgrades by downloading from a centralized location.
- Network Timing Protocol (NTP) provides an accurate and consistent timestamp to all intranet switches.
- Multifunction LEDs per port for port status; half-duplex and full-duplex mode; and 10BASE-T, 100BASE-TX, and 1000BASE-T indication as well as switch-level status LEDs for system, redundant-power supply, and bandwidth utilization provide a comprehensive and convenient visual management system.
- Jumbo frames (9216 bytes) are available on the 10/100/1000 configurations for advanced data and video applications requiring very large frames.

### **Network Management Tools**

The Cisco Catalyst 3750-E Series offers both a superior CLI for detailed configuration and Cisco Network Assistant Software, a PC-based tool for quick configuration based on preset templates. In addition, CiscoWorks LAN Management Solution (LMS) supports the Cisco Catalyst 3750-E Series for networkwide management.



### **Cisco Network Assistant**

A PC-based network management application designed for small and medium-sized business (SMB) networks with up to 250 users, Cisco Network Assistant offers centralized network management and configuration capabilities. Cisco Network Assistant uses Cisco Smartports technology to simplify both initial deployment and ongoing maintenance. This application also features an intuitive GUI where users can easily apply common services across Cisco switches, routers, and access points, such as:

- Configuration management
- Troubleshooting advice
- Inventory reports
- Event notification
- Network security settings
- Password synchronization
- Drag-and-drop Cisco IOS Software upgrades
- Secure wireless

For detailed information about Cisco Network Assistant, visit <http://www.cisco.com/go/cna>.

### **CiscoWorks LAN Management Solution (LMS)**

CiscoWorks LMS is a suite of powerful management tools that simplify the configuration, administration, monitoring and troubleshooting of Cisco networks. It integrates these capabilities into a world-class solution for improving the accuracy and efficiency of your operations staff, while increasing the overall availability of your network. LMS supports over 400 different device types including the 3750-E and 3560-E series switches and it provides:

- Network discovery, topology views, end-station tracking and VLAN management
- Real-time network fault analysis with easy-to-deploy device specific best-practice templates
- Hardware and software inventory management, centralized configuration tools, and Syslog monitoring
- Network response time and availability monitoring and tracking
- Real-time device, link, and port traffic management, analysis, and reporting

For detailed information about CiscoWorks LMS, go to

<http://www.cisco.com/en/US/products/sw/cscowork/ps2425/index.html>

## Product Specifications

Table 2 lists product specifications for the Cisco Catalyst 3750E-48TD Switch.

**Table 2.** Descriptions and Specifications

| Description                             | Specification  |        |         |         |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
|---|--|--------|---------|---------|------|---------|--------------------|----|----|-----|----|---|----|----|----|----|-----------------------------|----|----|---|-----|---------------------------------|----|----|---|----|------------------------|----|----|---|----|----------------------|----|----|----|----|-----------------|------|------|------|------|-----------------|---|------|---|------|
| <b>Performance</b>                      | <ul style="list-style-type: none"> <li>160-Gbps switching fabric capacity</li> <li>Stack-forwarding rate of 95 Mpps for 64-byte packets</li> <li>Forwarding rate:               <ul style="list-style-type: none"> <li>3750E-48TD—101.2 Mpps</li> </ul> </li> <li>Memory:               <ul style="list-style-type: none"> <li>256 MB DRAM and 64 MB FLASH</li> </ul> </li> <li>Feature resources:               <ul style="list-style-type: none"> <li>1005 VLANs</li> <li>4K VLAN IDs</li> <li>1000 switched virtual interfaces (SVIs)</li> <li>468 routed ports per stack</li> <li>9216 byte jumbo frames</li> </ul> </li> </ul> <p><b>MAC, routing, security, and QoS scalability numbers depend on the type template used in the switch:</b></p> <table border="1"> <thead> <tr> <th></th> <th>Default</th> <th>Access</th> <th>VLAN</th> <th>Routing</th> </tr> </thead> <tbody> <tr> <td><b>MAC address</b></td> <td>6K</td> <td>4K</td> <td>12K</td> <td>3K</td> </tr> <tr> <td><b>IGMP groups and multicast routes</b></td> <td>1K</td> <td>1K</td> <td>1K</td> <td>1K</td> </tr> <tr> <td><b>Total unicast routes</b></td> <td>8K</td> <td>6K</td> <td>0</td> <td>11K</td> </tr> <tr> <td><b>Directly connected hosts</b></td> <td>6K</td> <td>4K</td> <td>0</td> <td>3K</td> </tr> <tr> <td><b>Indirect routes</b></td> <td>2K</td> <td>2K</td> <td>0</td> <td>8K</td> </tr> <tr> <td><b>Security ACEs</b></td> <td>1K</td> <td>2K</td> <td>1K</td> <td>1K</td> </tr> <tr> <td><b>QoS ACEs</b></td> <td>0.5K</td> <td>0.5K</td> <td>0.5K</td> <td>0.5K</td> </tr> <tr> <td><b>PBR ACEs</b></td> <td>0</td> <td>0.5K</td> <td>0</td> <td>0.5K</td> </tr> </tbody> </table> |        | Default | Access  | VLAN | Routing | <b>MAC address</b> | 6K | 4K | 12K | 3K | <b>IGMP groups and multicast routes</b> | 1K | 1K | 1K | 1K | <b>Total unicast routes</b> | 8K | 6K | 0 | 11K | <b>Directly connected hosts</b> | 6K | 4K | 0 | 3K | <b>Indirect routes</b> | 2K | 2K | 0 | 8K | <b>Security ACEs</b> | 1K | 2K | 1K | 1K | <b>QoS ACEs</b> | 0.5K | 0.5K | 0.5K | 0.5K | <b>PBR ACEs</b> | 0 | 0.5K | 0 | 0.5K |
|   | Default  | Access | VLAN    | Routing |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>MAC address</b>                      | 6K   | 4K     | 12K     | 3K      |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>IGMP groups and multicast routes</b> | 1K   | 1K     | 1K      | 1K      |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>Total unicast routes</b>             | 8K   | 6K     | 0       | 11K     |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>Directly connected hosts</b>         | 6K   | 4K     | 0       | 3K      |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>Indirect routes</b>                  | 2K   | 2K     | 0       | 8K      |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>Security ACEs</b>                    | 1K   | 2K     | 1K      | 1K      |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>QoS ACEs</b>                         | 0.5K   | 0.5K   | 0.5K    | 0.5K    |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>PBR ACEs</b>                         | 0  | 0.5K   | 0       | 0.5K    |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>Connectors and Cabling</b>           | <ul style="list-style-type: none"> <li>1000BASE-T ports: RJ-45 connectors, 2-pair Cat-5E UTP cabling</li> <li>1000BASE-T SFP-based ports: RJ-45 connectors, 2-pair Cat-5E UTP cabling</li> <li>100BASE-FX, 1000BASE-SX, -LX/LH, -ZX, -BX10, and CWDM SFP-based ports: LC fiber connectors (single-mode or multimode fiber)</li> <li>10GBASE-SR, LR, ER, LX4, CX4 X2-based ports: SC fiber connectors (single-mode or multimode fiber)</li> <li>Cisco StackWise stacking ports: copper-based Cisco StackWise cabling</li> <li>Ethernet Management port: RJ-45 connectors, 2-pair Cat-5 UTP cabling</li> <li>Management console port: RJ-45-to-DB9 cable for PC connections</li> </ul>   |        |         |         |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>Power Connectors</b>                 | <ul style="list-style-type: none"> <li>Customers can provide power to a switch by using either the internal power supply or the Cisco RPS 2300. The connectors are located at the back of the switch.</li> <li>Internal power supply connector: The internal power supply is an autoranging unit. The internal power supply supports input voltages between 100 and 240VAC. Use the supplied AC power cord to connect the AC power connector to an AC power outlet.</li> <li>Cisco RPS connector: The connector offers connection for an optional Cisco RPS 2300 that uses AC input and supplies DC output to the switch.</li> <li>Only the Cisco RPS 2300 (model PWR2300-AC-RPS-N1=) should be attached to the redundant-power-supply receptacle.</li> </ul>  |        |         |         |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |
| <b>Indicators</b>                       | <ul style="list-style-type: none"> <li>Per-port status LEDs: link integrity, disabled, activity, speed, and full-duplex indications</li> <li>System-status LEDs: system, RPS, and bandwidth-utilization indications</li> </ul>   |        |         |         |      |         |                    |    |    |     |    |   |    |    |    |    |                             |    |    |   |     |                                 |    |    |   |    |                        |    |    |   |    |                      |    |    |    |    |                 |      |      |      |      |                 |   |      |   |      |

| Description                      | Specification   |                    |                    |
|----------------------------------|---|--------------------|--------------------|
| Dimensions (H x W x D)           |   | Inches             | Centimeters        |
|                                  | 3750E-48TD  | 1.75 x 17.5 x 18.1 | 4.45 x 44.5 x 46.0 |
| Weight                           |   | Pounds             | Kilograms          |
|                                  | 3750E-48TD  | 18.8               | 8.6                |
| Environmental Ranges             | <ul style="list-style-type: none"> <li>Operating temperature: 32 to 113°F (0 to 45°C)</li> <li>Storage temperature: -13 to 158°F (-25 to 70°C)</li> <li>Relative humidity operating: 10 to 85% (noncondensing)</li> <li>Relative humidity nonoperating: 0 to 95% (noncondensing)</li> <li>Operating altitude: up to 10,000 ft (3049 m)</li> <li>Storage altitude: up to 15,000 ft (4573 m)</li> </ul> |                    |                    |
| Acoustic Noise                   | International Organization for Standardization (ISO) 7779: bystander position operating to an ambient temperature of 30°C   |                    |                    |
|                                  | 3750E-48TD  | 45 dB              |                    |
| Mean Time Between Failure (MTBF) | 3750E-48TD  | 166,369 hours      |                    |

Table 3 lists the management and standards support for the Cisco Catalyst 3750E-48TD Switch.

**Table 3.** Management and Standards Support for the Cisco Catalyst 3750-E Series Switch

| Description | Specification  |   |
|-------------|--|---|
| Management  | <ul style="list-style-type: none"> <li>BRIDGE-MIB</li> <li>CISCO-CDP-MIB</li> <li>CISCO-CLUSTER-MIB</li> <li>CISCO-CONFIG-MAN-MIB</li> <li>CISCO-ENTITY-FRU-CONTROL-MIB</li> <li>CISCO-ENVMON-MIB</li> <li>CISCO-FLASH-MIB</li> <li>CISCO-FTP-CLIENT-MIB</li> <li>CISCO-HSRP-MIB</li> <li>CISCO-HSRP-EXT-MIB</li> <li>CISCO-IGMP-FILTER-MIB</li> <li>CISCO-IMAGE-MIB</li> <li>CISCO-IP-STAT-MIB</li> <li>CISCO-L2L3-INTERFACE-CONFIG-MIB</li> <li>CISCO-POE-EXTENSIONS-MIB</li> <li>CISCO-MAC-NOTIFICATION-MIB</li> <li>CISCO-MEMORY-POOL-MIB</li> <li>CISCO-PAGP-MIB</li> <li>CISCO-PING-MIB</li> <li>CISCO-PROCESS-MIB</li> <li>CISCO-RTTMON-MIB</li> <li>CISCO-STP-EXTENSIONS-MIB</li> <li>CISCO-SYSLOG-MIB</li> <li>CISCO-TCP-MIB</li> <li>CISCO-VLAN-IFTABLE-RELATIONSHIP-MIB</li> <li>CISCO-VLAN-MEMBERSHIP-MIB</li> </ul> | <ul style="list-style-type: none"> <li>CISCO-VTP-MIB</li> <li>ENTITY-MIB</li> <li>ETHERLIKE-MIB</li> <li>IF-MIB</li> <li>IGMP-MIB</li> <li>IPMROUTE-MIB</li> <li>OLD-CISCO-CHASSIS-MIB</li> <li>OLD-CISCO-FLASH-MIB</li> <li>OLD-CISCO-INTERFACES-MIB</li> <li>OLD-CISCO-IP-MIB</li> <li>OLD-CISCO-SYS-MIB</li> <li>OLD-CISCO-TCP-MIB</li> <li>OLD-CISCO-TS-MIB</li> <li>OSPF-MIB (RFC 1253)</li> <li>PIM-MIB</li> <li>RFC1213-MIB</li> <li>RFC1253-MIB</li> <li>RMON-MIB</li> <li>RMON2-MIB</li> <li>SNMP-FRAMEWORK-MIB</li> <li>SNMP-MPD-MIB</li> <li>SNMP-NOTIFICATION-MIB</li> <li>SNMP-TARGET-MIB</li> <li>SNMPv2-MIB</li> <li>TCP-MIB</li> <li>UDP-MIB</li> </ul> |
| Standards   | <ul style="list-style-type: none"> <li>IEEE 802.1s</li> <li>IEEE 802.1w</li> <li>IEEE 802.1x</li> <li>IEEE 802.3ad</li> <li>IEEE 802.3af</li> <li>IEEE 802.3x full duplex on 10BASE-T, 100BASE-TX, and 1000BASE-T ports</li> <li>IEEE 802.1D Spanning Tree Protocol</li> <li>IEEE 802.1p CoS Prioritization</li> <li>IEEE 802.1Q VLAN</li> </ul>   | <ul style="list-style-type: none"> <li>1000BASE-BX10-U</li> <li>1000BASE-BX10-D</li> <li>1000BASE-ZX</li> <li>1000BASE-CWDM SFP 1470 nm</li> <li>1000BASE-CWDM SFP 1490 nm</li> <li>1000BASE-CWDM SFP 1510 nm</li> <li>1000BASE-CWDM SFP 1530 nm</li> <li>1000BASE-CWDM SFP 1550 nm</li> <li>1000BASE-CWDM SFP 1570 nm</li> <li>1000BASE-CWDM SFP 1590 nm</li> </ul>  |

| Description | Specification   |   |
|-------------|---|---|
|             | <ul style="list-style-type: none"> <li>• IEEE 802.3 10BASE-T specification</li> <li>• IEEE 802.3u 100BASE-TX specification</li> <li>• IEEE 802.3ab 1000BASE-T specification</li> <li>• IEEE 802.3z 1000BASE-X specification</li> <li>• 100BASE-FX</li> <li>• 1000BASE-T</li> <li>• 1000BASE-SX</li> <li>• 1000BASE-LX/LH</li> </ul> | <ul style="list-style-type: none"> <li>• 1000BASE-CWDM SFP 1610 nm</li> <li>• 10GBASE-SR</li> <li>• 10GBASE-LR</li> <li>• 10GBASE-ER</li> <li>• RMON I and II standards</li> <li>• SNMPv1, SNMPv2c, and SNMPv3</li> </ul> |

Table 4 lists the power supply compatibility matrix for the Cisco Catalyst 3750E-48TD Switch.

**Table 4.** Power Supply Compatibility Matrix

| Cisco Catalyst 3750-E Series Switch Type | Power Supply   |                |                |
|--|----------------|----------------|----------------|
|  | C3K-PWR-750WAC | C3K-PWR-265WAC | C3K-PWR-265WDC |
| 48-Port Switch                           | X              | X              | X              |
| RPS 2300                                 | X              |                |                |

Table 5 lists the power specifications for the Cisco Catalyst 3750E-48TD Switch based on the kind of power supply used.

**Table 5.** Power Specifications

| Description                       | Specification                 |                               |                           |
|-----------------------------------|-------------------------------|-------------------------------|---------------------------|
|                                   | C3K-PWR-750WAC                | C3K-PWR-265WAC                | C3K-PWR-265WDC            |
| Max Output Power                  | 750W                          | 265W                          | 265W                      |
| Input-Voltage Range and Frequency | 100–240VAC,<br>50–60 Hz       | 100–240VAC,<br>50–60 Hz       | -36VDC to -72VDC          |
| Input Current                     | 10–5A                         | 5–2.5A                        | <5A@-72VDC<br><10A@-36VDC |
| Output Ratings                    | 12V@25A<br>-52V@8.75A         | 12V@22A                       | 12V@22A                   |
| Output Holdup Time                | 20 ms minimum                 | 20 ms minimum                 | > 2ms@-48VDC              |
| Power-Supply Input Receptacles    | IEC 320-C13<br>(IEC60320-C13) | IEC 320-C13<br>(IEC60320-C13) |                           |
| Power Cord Rating                 | 15A                           | 15A                           | 12A@-100VDC               |

Table 6 lists the specifications of all the power supplies supported in the Cisco Catalyst 3750E-48TD Switch.

**Table 6.** Power Supply Specifications

| Product Specifications                               | Power Supply   |  |  |
|--|--|--|--|
|  | C3K-PWR-750WAC   | C3K-PWR-265WAC   | C3K-PWR-265WDC   |
| <b>Physical Specifications</b>                       | (H x W x D): 1.65 X 6.0 X 11.4 in<br>Weight: 3.9 lb (1.8 kg)   | (H x W x D): 1.65 X 6.0 X 11.4 in<br>Weight: 3.3 lb (1.5 kg) | (H x W x D): 1.65 X 6.0 X 11.4 in<br>Weight: 3.5 lb (1.6 kg) |
| <b>Total Output BTU (Note: 1000 BTU/hr = 293W)</b>   | 2568 BTU/hr, 765W  | 907BTU/hr, 265W  | 907BTU/hr, 265W  |
| <b>Operating Temperature</b>                         | 23 to 113°F (–5 to 45°C)   |  |  |
| <b>Storage Temperature</b>                           | –40 to 158°F (–40 to 70°C)   |  |  |
| <b>Relative Humidity Operating, Noncondensing</b>    | 10 to 85% noncondensing  |  |  |
| <b>Relative Humidity Nonoperating, Noncondensing</b> | 0 to 95% noncondensing   |  |  |
| <b>Altitude</b>                                      | 10,000 ft. (3000 meters), up to 45°C   |  |  |
| <b>MTBF</b>  | Calculated MTBF must be greater than 300,000 using Telcordia SR-332, Method 1, Case 3. Demonstrated MTBF is 500,000 hr (with 90% confidence level).  |  |  |
| <b>EMI and EMC Compliance</b>                        | <ul style="list-style-type: none"> <li>• FCC Part 15 (CFR 47) Class A</li> <li>• ICES-003 Class A</li> <li>• EN 55022 Class A</li> <li>• CISPR 22 Class A</li> <li>• AS/NZS 3548 Class A</li> <li>• VCCI Class A</li> <li>• EN 55024</li> <li>• EN300 386</li> <li>• EN 50082-1</li> <li>• EN 61000-3-2</li> <li>• EN 61000-3-3</li> <li>• EN 61000-6-1</li> </ul> |  |  |
| <b>Safety Compliance</b>                             | <ul style="list-style-type: none"> <li>• UL 60950-1 1<sup>st</sup> Edition</li> <li>• CAN/CSA-C22.2 No. 60950-1 1<sup>st</sup> Edition</li> <li>• EN 60950-1 1<sup>st</sup> Edition</li> <li>• IEC 60950-1 1<sup>st</sup> Edition</li> </ul>   |  |  |
| <b>LED Indicators</b>                                | “AC OK”: Input power to the power supply is OK.<br>“PS OK”: Output power from the power supply is OK.  |  |  |

Table 7 lists the safety and compliance information for the Cisco Catalyst 3750-E Series.

**Table 7.** Safety and Compliance

| Description                                     | Specification   |
|---|---|
| <b>Safety Certifications</b>                    | <ul style="list-style-type: none"> <li>• UL60950-1</li> <li>• C-UL to CAN/CSA 22.2 No.60950-1</li> <li>• TUV/GS to EN 60950-1</li> <li>• CB to IEC 60950-1 with all country deviations</li> <li>• AS/NZS 60950-1</li> <li>• CE Marking</li> <li>• CCC for PS FRU</li> <li>• NOM (through partners and distributors)</li> <li>• GOST (Russia Safety Mark)</li> </ul> |
| <b>Electromagnetic Emissions Certifications</b> | <ul style="list-style-type: none"> <li>• FCC Part 15 Class A</li> <li>• EN 55022B Class A (CISPR22 Class A)</li> <li>• VCCI Class A</li> <li>• AS/NZS 3548 Class A or AS/NZS CISPR22 Class A</li> <li>• MIC</li> <li>• CE Marking</li> <li>• GOST (Russian mark—Post FCS thru partners)</li> <li>• CCC for PS FRU</li> </ul>  |
| <b>Environmental</b>                            | Reduction of Hazardous Substances (ROHS) 5  |
| <b>Noise Specifications</b>                     | Office Product Spec: 48dBA at 30°C (refer to ISO 7779)  |
| <b>Telco</b>                                    | CLEI code   |
| <b>Warranty</b>                                 | Standard 90 Day Limited Hardware and Software Warranty  |

### Hardware Warranty

The Cisco Catalyst 3750-E Series Switches come with the Standard Cisco 90-day Limited Warranty for hardware and software, as described at

[http://www.cisco.com/en/US/products/prod\\_warranties\\_item09186a00805f005b.html](http://www.cisco.com/en/US/products/prod_warranties_item09186a00805f005b.html)

### Service and Support

Cisco and Dell can help you deploy a robust, dependable Cisco Desktop Switching solution by taking a lifecycle approach that addresses all aspects of deploying, operating, and optimizing a complex solution, including people, processes, and technology.

Whether you are migrating your existing Cisco Desktop Switching solution or deploying a new solution, this approach helps align business and technical goals throughout the solution lifecycle. Upgrading from one IOS feature set (IP Base or IP Services) to another (IP Services or Advanced IP Services) involves the software activation process described in this document. Customers must purchase a feature set-specific SMARTnet contract to ensure service coverage for newly activated Cisco IOS feature sets.

Cisco and its partners are specialists in Cisco Desktop Switching products and technologies, business analysis, and project management. Cisco services are available through various service programs designed to help accelerate customer success throughout the network lifecycle. For more information about Cisco services for Cisco Desktop Switching, visit:

[http://www.cisco.com/en/US/products/svcs/ps3034/ps2827/serv\\_category\\_home.html](http://www.cisco.com/en/US/products/svcs/ps3034/ps2827/serv_category_home.html) or contact your local account representative.

## Ordering Information

Table 8 lists ordering information for the Cisco Catalyst 3750-E Series. To place an order, visit [www.dell.com/ciscosolutions](http://www.dell.com/ciscosolutions).

**Table 8.** Cisco Catalyst 3750E-48TD Switch Ordering Info

| Product Number   | Product Description   |
|--|---|
| <b>Catalyst 3750-E Series</b>                                  |   |
| <b>WS-C3750E-48TD-S</b>  | <ul style="list-style-type: none"> <li>• 48 10/100/1000 ports + 2 X2-based 10 Gigabit Ethernet ports</li> <li>• 64-Gbps, high-speed StackWise Plus stacking</li> <li>• 160-Gbps wire rate, nonblocking switching fabric capacity</li> <li>• Field-replaceable 265WAC power supply and fan tray</li> <li>• 1 rack unit (RU) stackable multilayer switch</li> <li>• IPv6</li> <li>• IP Base software feature set (IPB)</li> </ul>   |
| <b>WS-C3750E-48TD-E</b>  | <ul style="list-style-type: none"> <li>• 48 10/100/1000 ports + 2 X2-based 10 Gigabit Ethernet ports</li> <li>• 64-Gbps, high-speed StackWise Plus stacking</li> <li>• 160-Gbps wire rate, nonblocking switching fabric capacity</li> <li>• Field-replaceable 265WAC power supply and fan tray</li> <li>• 1 rack unit (RU) stackable multilayer switch</li> <li>• IPv6</li> <li>• IP Services software feature set (IPS)</li> <li>• Provides full IPv6 dynamic routing</li> </ul> |
| <b>Catalyst 3750-E Series Product Activation Keys</b>          |   |
| <b>3750E-LIC=</b>  |   |
| <b>Catalyst 3750-E Series Product Activation Keys</b>          |   |
| <b>3750E-IPSLCB-QTY</b>  | IP Services for 3750-E 24 ports, upgrade from IP Base   |
| <b>3750E48-IPSLCB-QTY</b>                                      | IP Services for 3750-E 48 ports, upgrade from IP Base   |
| <b>3750E-AISK9LCBQTY</b>                                       | Advanced IP Services for 3750-E 24ports, upgrade IP Base  |
| <b>3750E-AISK9LCSQTY</b>                                       | Advanced IP Services for 3750-E 24ports, upgrade IP Services  |
| <b>3750E48-AISK9LCBQ</b>                                       | Advanced IP Services for 3750-E 48ports, upgrade IP Base  |
| <b>3750E48-AISK9LCSQ</b>                                       | Advanced IP Services for 3750-E 48ports, upgrade IP Services  |
| <b>Power Supplies for the Catalyst 3750-E Series</b>           |   |
| <b>C3K-PWR-265WAC=</b>   | Catalyst 3750-E/3560-E 265WAC power supply  |
| <b>C3K-PWR-265WDC=</b>   | Catalyst 3750-E/3560-E 265WDC power supply  |
| <b>C3K-PWR-750WAC=</b>   | Catalyst 3750-E/3560-E/RPS 2300 750WAC power supply   |
| <b>C3K-BLWR-60CFM=</b>   | Fan Module for the Catalyst 3750-E/3560-E   |
| <b>Redundant Power System for the Catalyst 3750-E Series</b>   |   |
| <b>PWR-RPS2300</b>   | RPS 2300  |
| <b>ACC-RPS2300=</b>  | Spare Accessory Kit   |
| <b>BLNK-RPS2300=</b>   | Spare Bay Insert  |
| <b>CAB-RPS2300=</b>  | Spare RPS Cable for Cisco Redundant Power System 2300   |
| <b>CAB-RPS2300-E=</b>  | Spare RPS 2300 cable  |
| <b>PWR-RPS2300=</b>  | Spare RPS Cable RPS 2300 Cat 3750E/3560E Switches   |
| <b>BLWR-RPS2300=</b>   | Spare RPS 2300 Blower   |
| <b>C3K-PWR-750WAC=</b>   | Catalyst 3750-E/3560-E/RPS 2300 750WAC power supply   |
| <b>TwinGig Converter Module for the Catalyst 3750-E Series</b> |   |
| <b>CVR-X2-SFP</b>  | TwinGig Converter Module  |
| <b>CVR-X2-SFP=</b>   | TwinGig Converter Module  |

| <b>SFPs for the Catalyst 3750-E Series</b>            |  |
|---|--|
| <b>GLC-GE-100FX=</b>                                  | 100FX SFP on GE SFP ports for DSBU switches                |
| <b>GLC-LH-SM=</b>                                     | GE SFP, LC connector LX/LH transceiver                     |
| <b>GLC-SX-MM=</b>                                     | GE SFP, LC connector SX transceiver                        |
| <b>GLC-T=</b>   | 1000BASE-T SFP   |
| <b>GLC-ZX-SM=</b>                                     | 1000BASE-ZX SFP  |
| <b>GLC-BX-D=</b>                                      | 1000BASE-BX SFP, 1490NM                                    |
| <b>GLC-BX-U=</b>                                      | 1000BASE-BX SFP, 1310NM                                    |
| <b>CWDM-SFP-1470=</b>                                 | CWDM 1470 NM SFP Gigabit Ethernet and 1G/2G FC             |
| <b>CWDM-SFP-1490=</b>                                 | CWDM 1490 NM SFP Gigabit Ethernet and 1G/2G FC             |
| <b>CWDM-SFP-1510=</b>                                 | CWDM 1510 NM SFP Gigabit Ethernet and 1G/2G FC             |
| <b>CWDM-SFP-1530=</b>                                 | CWDM 1530 NM SFP Gigabit Ethernet and 1G/2G FC             |
| <b>CWDM-SFP-1550=</b>                                 | CWDM 1550 NM SFP Gigabit Ethernet and 1G/2G FC             |
| <b>CWDM-SFP-1570=</b>                                 | CWDM 1570 NM SFP Gigabit Ethernet and 1G/2G FC             |
| <b>CWDM-SFP-1590=</b>                                 | CWDM 1590 NM SFP Gigabit Ethernet and 1G/2G FC             |
| <b>CWDM-SFP-1610=</b>                                 | CWDM 1610 NM SFP Gigabit Ethernet and 1G/2G FC             |
| <b>DWDM-SFP-3033=</b>                                 | DWDM SFP 1530.33 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3112=</b>                                 | DWDM SFP 1531.12 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3190=</b>                                 | DWDM SFP 1531.90 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3268=</b>                                 | DWDM SFP 1532.68 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3425=</b>                                 | DWDM SFP 1534.25 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3504=</b>                                 | DWDM SFP 1535.04 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3582=</b>                                 | DWDM SFP 1535.82 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3661=</b>                                 | DWDM SFP 1536.61 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3819=</b>                                 | DWDM SFP 1538.19 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3898=</b>                                 | DWDM SFP 1538.98 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-3977=</b>                                 | DWDM SFP 1539.77 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-4056=</b>                                 | DWDM SFP 1540.56 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-4214=</b>                                 | DWDM SFP 1542.14 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-4294=</b>                                 | DWDM SFP 1542.94 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-4373=</b>                                 | DWDM SFP 1543.73 nm SFP (100 GHz ITU grid)                 |
| <b>DWDM-SFP-4453=</b>                                 | DWDM SFP 1544.53 nm SFP (100 GHz ITU grid)                 |
| <b>X2 for Catalyst 3750-E Series</b>                  |  |
| <b>X2-10GB-ER=</b>                                    | 10GBASE-ER X2 Module                                       |
| <b>X2-10GB-LR=</b>                                    | 10GBASE-LR X2 Module                                       |
| <b>X2-10GB-SR=</b>                                    | 10GBASE-SR X2 Module                                       |
| <b>X2-10GB-CX4=</b>                                   | 10GBASE-CX4 X2 Module                                      |
| <b>X2-10GB-LX4=</b>                                   | 10GBASE-LX4 X2 Module                                      |
| <b>X2-10GB-LRM=</b>                                   | 10GBASE-LRM X2 Module                                      |
| <b>LC to SC Cables for the Catalyst 3750-E Series</b> |  |
| <b>CSS5-CABLX-LCSC=</b>                               | CSS11500 10-Meter Fiber Single Mode LX LC-to-SC Connectors |
| <b>CSS5-CABSX-LC=</b>                                 | CSS11500 10-Meter Fiber Multimode SX LC Connectors         |
| <b>CSS5-CABSX-LCSC=</b>                               | CSS11500 10-Meter Fiber Multimode SX LC-to-SC Connectors   |



| <b>StackWise Cables</b>                               |   |
|---|---|
| <b>CAB-STACK-50CM=</b>                                | Cisco StackWise 50CM Stacking Cable                             |
| <b>CAB-STACK-1M=</b>                                  | Cisco StackWise 1M Stacking Cable                               |
| <b>CAB-STACK-3M=</b>                                  | Cisco StackWise 3M Stacking Cable                               |
| <b>CAB-STACK-50CM-NH=</b>                             | Cisco StackWise 50CM Non-Halogen Lead Free Stacking Cable       |
| <b>CAB-STACK-1M-NH=</b>                               | Cisco StackWise 1M Non-Halogen Lead Free Stacking Cable         |
| <b>CAB-STACK-3M-NH=</b>                               | Cisco StackWise 3M Non-Halogen Lead Free Stacking Cable         |
| <b>Power Cords for the Catalyst 3750-E Series</b>     |   |
| <b>CAB-AC</b>   | Power Cord, 110V  |
| <b>CAB-AC=</b>  | Power Cord, 110V  |
| <b>CAB-16AWG-AC</b>                                   | AC Power cord, 16AWG  |
| <b>CAB-16AWG-AC=</b>                                  | AC Power cord, 16AWG  |
| <b>CAB-ACA</b>  | Plug, Power Cord, Australian, 10A                               |
| <b>CAB-ACA=</b>                                       | Plug, Power Cord, Australian, 10A                               |
| <b>CAB-ACE</b>  | Power Cord Europe   |
| <b>CAB-ACE=</b>                                       | Power Cord Europe   |
| <b>CAB-ACI</b>  | Power Cord-Italian  |
| <b>CAB-ACI=</b>                                       | Power Cord-Italian  |
| <b>CAB-ACR</b>  | Power Cord Argentina  |
| <b>CAB-ACR=</b>                                       | Power Cord Argentina  |
| <b>CAB-ACS</b>  | Power Cord for Switzerland                                      |
| <b>CAB-ACS=</b>                                       | Power Cord for Switzerland                                      |
| <b>CAB-ACU</b>  | Power Cord UK   |
| <b>CAB-ACU=</b>                                       | Power Cord UK   |
| <b>CAB-JPN</b>  | Power Cord-Japan  |
| <b>CAB-JPN=</b>                                       | Power Cord-Japan  |
| <b>CAB-IND</b>  | Power Cord India  |
| <b>CAB-IND=</b>                                       | Power Cord India  |
| <b>Spare Rack Mount Kits for the 3750-E Series</b>    |   |
| <b>RCKMNT-E-1RU=</b>                                  | Rack Mount Kit (1RU) for Catalyst 3750-E and 3560-E             |
| <b>Catalyst 3750-E Relicensing for Used Equipment</b> |   |
| <b>LL-3750E-IPB=</b>                                  | IP Base SW Feature set license for Catalyst 3750-E Series       |
| <b>LL-3750E-IPS=</b>                                  | IP Services SW Feature set license for Catalyst 3750-E Series   |
| <b>LL-3750E-AIS=</b>                                  | Advanced IP Services SW Feature set license for Catalyst 3750-E |

## For More Information

For more information about the Cisco Catalyst 3750E-48TD Switch visit <http://www.dell.com/ciscosolutions>.

The information contained in this document, including all instructions, cautions, and regulatory approvals and certifications, is provided by Cisco and has not been independently verified or tested by Dell. Dell cannot be responsible for damage caused as a result of either following or failing to follow these instructions. All statements or claims regarding the properties, capabilities, speeds, or qualifications of the part referenced in this document are made by Cisco and not by Dell. Dell specifically disclaims knowledge of the accuracy, completeness, or substantiation for any such statements. All questions or comments relating to such statements or claims should be directed to Cisco. Visit [www.dell.com](http://www.dell.com) for more information.



**Americas Headquarters**  
Cisco Systems, Inc.  
San Jose, CA

**Asia Pacific Headquarters**  
Cisco Systems (USA) Pte. Ltd.  
Singapore

**Europe Headquarters**  
Cisco Systems International BV  
Amsterdam, The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

CCDE, CCENT, Cisco Eos, Cisco HealthPresence, the Cisco logo, Cisco Lumin, Cisco Nexus, Cisco StadiumVision, Cisco TelePresence, Cisco WebEx, DCE, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn and Cisco Store are service marks; and Access Registrar, Aironet, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, EtherFast, EtherSwitch, Event Center, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, iQuick Study, IronPort, the IronPort logo, LightStream, Linksys, MediaTone, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, Network Registrar, PCNow, PIX, PowerPanels, ProConnect, ScriptShare, SenderBase, SMARTnet, Spectrum Expert, StackWise, The Fastest Way to Increase Your Internet Quotient, TransPath, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0812R)