

DDR3 1067 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	MM socket support (Options)		
								1 DIMM	2 DIMM	4 DIMM
KINGSTON	KVR1066D3N7/1G(矮版)	1GB	SS	ELPIDA	J1108BFSE-DJ-F	7	1.5V	●	●	●
Vendor	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing - Dimm	Vol.	0	0	0

DDR3 1333 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	MM socket support (Options)		
								1 DIMM	2 DIMM	4 DIMM
A-Data	AD631B0823EV	2GB	SS	A-Data	3CCA-1509A	-	-	●	●	●
A-DATA	AM2U139C2P1	2GB	SS	ADATA	3CCD-1509A EL1127T	-	-	●	●	●
A-Data	AXDU1333GC2G9-2G(XMP)	4GB(2 x 2GB)	SS	-	-	9-9-9-24	1.25V- 1.35V(low voltage)	●	●	●
A-Data	AD631C1624EV	4GB	DS	A-Data	3CCA-1509A	-	-	●	●	●
A-DATA	AM2U139C4P2	4GB	DS	ADATA	3CCD-1509A EL1127T	-	-	●	●	●
A-DATA	SU3U1333W8G9-B	8GB	DS	ELPIDA	J4208BASE-DJ-F	-	-	●	●	●
Apacer	78.B1GDE.9L10C	4GB	DS	Apacer	AM5D5908CEHSG	-	-	●	●	●
CORSAIR	TR3X6G1333C9 G	6GB(3x 2GB)	SS	-	-	9-9-9-24	1.50V	●	●	●
CORSAIR	CMD24GX3M6A1333C9(XMP)	24GB(6x4GB)	DS	-	-	9-9-9-24	1.60V	●	●	●
CORSAIR	CMD8GX3M4A1333C7	8GB(4 x 2GB)	DS	-	-	7-7-7-20	1.60V	●	●	●
G.SKILL	F3-10600CL9D-2GBNQ	2GB(2 x 1GB)	SS	-	-	9-9-9-24	1.5V	●	●	●
G.SKILL	F3-10666CL8D-4GBECO(XMP)	4GB(2 x 2GB)	DS	-	-	8-8-8-8-24	XMP 1.35V	●	●	●
GEIL	GVP34GB1333C7DC	4GB(2 x 2GB)	DS	-	-	7-7-7-24	1.5V	●	●	●
KINGMAX	FLFE85F-C8KL9 NAES	2GB	SS	KINGMAX	KFC8FNLXF-DXX- 15A	-	-	●	●	●
KINGMAX	FLFF65F-C8KL9 NEES	4GB	DS	KINGMAX	KFC8FNLXF-DXX- 15A	-	-	●	●	●
KINGSTON	KVR1333D3N9/1G(矮版)	1GB	SS	ELPIDA	J1108BDHG-DJ-F	9	1.5V	●	●	●
KINGSTON	KVR1333D3S8N9/2G	2GB	SS	Micron	IID77 D9LGK	-	1.5V	●		
KINGSTON	KVR1333D3S8N9/2G-SP(矮版)	2GB	SS	ELPIDA	J2108BCSE-DJ-F	-	1.5V	●		
KINGSTON	KVR1333D3N9/2G(矮版)	2GB	DS	ELPIDA	J1108BFHG-DJ-F	9	1.5V	●	●	●
KINGSTON	KVR1333D3N9/2G-SP(矮版)	2GB	DS	KTC	D1288JEMFNGD9U	-	1.5V	●	●	●
KINGSTON	KVR1333D3N9/2G-SP(矮版)	2GB	DS	KINGSTON	D1288JPSFPGD9U	-	1.5V	●	●	●
KINGSTON	KVR1333D3N9/4G(矮版)	4GB	DS	ELPIDA	J2108BCSE-DJ-F	9	1.5V	●	●	●
KINGSTON	KVR1333D3N9/4G(矮版)	4GB	DS	ELPIDA	J2108BCSE-DJ-F	-	1.5V	●	●	●
KINGSTON	KVR1333D3N9/4G	4GB	DS	KTC	D2568JENCNGD9U	-	1.5V	●	●	●
KINGSTON	KVR1333D3N9/4G-SP(矮版)	4GB	DS	KINGSTON	D2568JENCPGD9U	-	1.5V	●	●	●
Micron	MT8JTF25664AZ-1G4M1	2GB	SS	MICRON	IJM22 D9PFJ	-	-	●	●	●
NANYA	NT4GC64B8HG0NF-CG	4GB	DS	NANYA	NT5CB256M8GN- CG	-	-	●	●	●
SAMSUNG	M378B5773DH0-CH9	2GB	SS	SAMSUNG	K4B2G0846D	-	-	●	●	●
Transcend	JM1333KLN-2G	2GB	SS	Micron	0YD77D9LGK	-	-	●		
Transcend	JM1333KLN-2G	2GB	SS	Hynix	H5TQ2G83BZRH9C	-	-	●	●	●
Transcend	JM1333KLU-2G	2GB	DS	Transcend	TK243PDF3	-	-	●	●	●
Elixir	M2F2G64CB88D7N-CG	2GB	SS	Elixir	N2CB2G80DN-CG	-	-	●	●	●
Elixir	M2F2G64CB88G7N-CG	2GB	SS	Elixir	N2CB2G80GN-CG	-	-	●	●	●
Elixir	M2F4G64CB8HD5N-CG	4GB	DS	Elixir	N2CB2G80DN-CG	-	-	●	●	●
RiDATA	C304627CB1AG22Fe	2GB	DS	RiDATA	N/A	9	-	●	●	●
RiDATA	E304459CB1AG32Cf	4GB	DS	RiDATA	N/A	9	-	●	●	●
Vendor	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing - Dimm	Vol.	0	0	0

DDR3 1600 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	MM socket support (Options)		
								1 DIMM	2 DIMM	4 DIMM
A-Data	AX3U1600XB2G79-2X(XMP)	4GB(2 x 2GB)	DS	-	-	7-9-7-21	1.55V-1.75V	●	●	●
A-Data	AX3U1600GC4G9-2G(XMP)	8GB(2 x 4GB)	DS	-	-	9-9-9-24	1.55V-1.75V	●	●	●
A-Data	AX3U1600XC4G79-2X(XMP)	8GB(2 x 4GB)	DS	-	-	7-9-7-21	1.55V-1.75V	●	●	●
CORSAIR	CMD12GX3M6A1600C8(XMP)	12GB(6x2GB)	DS	-	-	8-8-8-24	1.65V	●		

CORSAIR	CMP4GX3M2A1600C8(XMP)	4GB(2 x 2GB)	DS	-	-	8-8-8-24	1.65V	•	•	•
CORSAIR	TR3X6G1600C9 G(XMP)	6GB(3 x 2GB)	DS	-	-	9-9-9-24	1.65V	•		
CORSAIR	CMP8GX3M2A1600C9(XMP)	8GB(2 x 4GB)	DS	-	-	9-9-9-24	1.65V	•	•	•
G.SKILL	F3-12800CL9D-4GBRL(XMP)	4GB(2 x 2GB)	DS	-	-	9-9-9-24	1.5V	•	•	•
KINGSTON	KHX1600C9D3P1K2/4G	4GB(2 x 2GB)	SS	-	-	-	1.5V	•	•	•
KINGSTON	KHX1600C9AD3/2G	2GB	DS	-	-	-	1.65V	•	•	
KINGSTON	KHX1600C9D3T1BK3/6GX(XMP)	6GB(3 x 2GB)	DS	-	-	9-9-9-27	1.65V	•	•	•
KINGSTON	KHX1600C9D3P1K2/8G	8GB(2 x 4GB)	DS	-	-	-	1.5V	•	•	•
Elixir	M2P2G64CB8HC9N-DG(XMP)	2GB	DS	-	-	-	-	•	•	•
Vendor	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing - Dimm	Vol.	0	0	0

4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports one pair of modules inserted into either the **blue** slots or the **black** slots as one pair of Dual-channel memory configuration
- **4 DIMM:** Supports 4 modules inserted into both the **blue** and **black** slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.