

HP Networking Legacy ProCurve Product Family 10-GbE Transceiver Support Matrix

		Genuine HP ProCurve SFP+ Transceivers and Cables						
HP Networking Switch Series	Product Name	Product Number	10GBASE-SR, LR, LRM	10GBASE-ER	10-GbE SFP+ Direct Attach Cables		10-GbE XFP-SFP+ Direct Attach Cables	
			(J9150A, J9151A, J9152A)	(J9153A)	1m, 3m, 7m (J9281A, J9283A, J9285A)	10m, 15m (J9281B, J9283B, J9285B)	(J9286B, J9287B)	1m, 3m, 5m (J9300A, J9301A, J9302A)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
2530	2530-24G-2SFP+ Switch 2530-48G-2SFP+ Switch 2530-24G-PoE+-2SFP+ Switch 2530-48G-PoE+-2SFP+ Switch	J9856A J9855A J9854A J9853A	all software versions	all software versions	all software versions	all software versions	all software versions	all software versions
2910al	2910al-24G Switch 2910al-48G Switch 2910al-24G-PoE+ Switch 2910al-48G-PoE+ Switch 2-Port 10-GbE SFP+ al Module	J9145A J9147A J9146A J9148A J9008A	-- -- -- -- all software versions	-- -- -- -- W.15.07.0002 and later	-- -- -- -- all software versions	-- -- -- -- W.14.28 and later	-- -- -- -- W.15.07.0002 and later	-- -- -- -- W.14.28 and later
2920	2920-24G Switch 2920-48G Switch 2920-24G-PoE+ Switch 2920-48G-PoE+ Switch 2920-48G-POE+ 740W Switch 2-Port 10GbE SFP+ Module	J9726A J9728A J9727A J9729A J9836A J9731A	-- -- -- -- -- all software versions	-- -- -- -- -- all software versions	-- -- -- -- -- all software versions	-- -- -- -- -- all software versions	-- -- -- -- -- all software versions	-- -- -- -- -- all software versions
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR 3500yl-24G-PoE+ Switch 3500yl-48G-PoE+ Switch 10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J8692A J8693A J9310A J9311A J9312A	-- -- -- -- K.14.50 and later	-- -- -- -- K.15.02.0004 and later	-- -- -- -- K.14.50 and later	-- -- -- -- K.14.50 and later	-- -- -- -- K.15.05.0001 and later	-- -- -- -- K.14.50 and later
3800	3800-24G-2SFP+ Switch 3800-48G-4SFP+ Switch 3800-24G-PoE+-2SFP+ Switch 3800-48G-PoE+-4SFP+ Switch 3800-24SFP-2SFP+ Switch	J9575A J9576A J9573A J9574A J9584A	all software versions	all software versions	all software versions	all software versions	KA.15.09.0003 and later	all software versions
5400zl	4-Port 10-GbE SFP+ zl Module 8-Port 10-GbE SFP+ v2 zl Module 20-Port Gig-T / 2-Port SFP+ v2 zl Module 20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9309A J9538A J9548A J9536A	K.14.39 and later	K.15.02.0004 and later	K.14.39 and later	K.14.39 and later	K.15.05.0001 and later	K.14.39 and later
			K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.05.0001 and later	K.15.02.0004 and later

HP Networking Legacy ProCurve Product Family 10-GbE Transceiver Support Matrix (cont'd)

			Genuine HP ProCurve SFP+ Transceivers and Cables					
HP Networking Switch Series	Product Name	Product Number	10GBASE-SR, LR, LRM	10GBASE-ER	10-GbE SFP+ Direct Attach Cables		10-GbE XFP-SFP+ Direct Attach Cables	
			(J9150A, J9151A, J9152A)	(J9153A)	1m, 3m, 7m (J9281A, J9283A, J9285A)	10m, 15m (J9286B, J9287B)	1m, 3m, 5m (J9300A, J9301A, J9302A)	
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
5400R	8-Port 10-GbE SFP+ v2 zl Module	J9538A	all software versions	all software versions	all software versions	all software versions	all software versions	all software versions
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						
6120	6120G/XG Blade Switch	498358-B21	--	--	--	--	--	all software versions
	6120XG Blade Switch	516733-B21	all software versions	(not supported)	all software versions	all software versions	Z.14.28 and later	
6200yl	Switch 6200yl-24G-mGBIC	J8992A	--	--	--	--	--	--
	10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J9312A	K.14.50 and later	K.15.02.0004 and later	K.14.50 and later	K.14.50 and later	K.15.05.0001 and later	K.14.50 and later
6600	6600-24G-4XG Switch	J9264A	K.14.03 and later	K.15.02.0004 and later	K.14.03 and later	K.14.32 and later	K.15.05.0001 and later	K.14.32 and later
	6600-24XG Switch	J9265A						
	6600-48G-4XG Switch	J9452A						
8200zl	4-Port 10-GbE SFP+ zl Module	J9309A	K.14.39 and later	K.15.02.0004 and later	K.14.39 and later	K.14.39 and later	K.15.05.0001 and later	K.14.39 and later
	8-Port 10-GbE SFP+ v2 zl Module	J9538A						
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.05.0001 and later	K.15.02.0004 and later

HP Networking Legacy ProCurve Product Family 10-GbE Transceiver Support Matrix (cont'd)

HP Networking Switch Series	Product Name	Product Number	Genuine HP ProCurve X2 Transceivers					Genuine HP ProCurve Optical Media Converter (OMC) for CX4 ¹ (J8439A)
			10GBASE-SR, LR (J8436A, J8437A)	10GBASE-LRM (J9144A)	10GBASE-ER (J8438A)	10GBASE-CX4 (J8440A) (J8440B/C)		
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
2900	Switch 2900-24G Switch 2900-48G	J9049A J9050A	all software versions	T.13.18 and later	all software versions	all software versions	all software versions	all software versions, OMC for fixed CX4 ports only
2910al	2910al-24G Switch 2910al-48G Switch 2910al-24G-PoE+ Switch 2910al-48G-PoE+ Switch 2-Port 10-GbE CX4 al Module	J9145A J9147A J9146A J9148A J9149A	--	--	--	--	--	-- all software versions
3400cl	Switch 3400cl-24G Switch 3400cl-48G Switch cl 10-GbE CX4 Copper Module Switch cl 10-GbE Media Flex Module	J4905A J4906A J8434A J8435A	--	--	--	--	--	-- M.08.54 and later, OMC for J8434A & J8440A/B
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR 3500yl-24G-PoE+ Switch 3500yl-48G-PoE+ Switch Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module 10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J8692A J8693A J9310A J9311A J8694A J9312A	--	--	--	--	--	-- all software versions, OMC for fixed CX4 ports only K.14.50 and later
4200vl	Switch vl 1-Port 10-GbE X2 Module	J8766A	L.11.08 and later	L.11.11 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later
5300xl	Switch xl 1-Port 10-GbE X2 Module	J8988A	E.11.02 and later	(not supported)	E.11.02 and later	E.11.02 and later	E.11.02 and later	E.11.02 and later
5400zl	Switch zl 4-Port 10-GbE X2 Module Switch zl 4-Port 10-GbE CX4 Module	J8707A J8708A	all software versions	K.13.20 and later	all software versions	all software versions	K.11.17 and later	K.11.33 and later, OMC for J8708A & J8440A/B
6200yl	Switch 6200yl-24G-mGBIC Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module 10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J8992A J8694A J9312A	--	--	--	--	--	-- K.11.33 and later, OMC for fixed CX4 ports only K.14.50 and later
6400cl	Switch 6400cl (CX4) Switch 6410cl (X2) Switch cl 10-GbE CX4 Copper Module Switch cl 10-GbE Media Flex Module	J8433A J8474A J8434A J8435A	--	--	--	--	--	M.08.62 and later, OMC for J8433A & J8440A/B M.08.62 and later, OMC for J8434A & J8440A/B
8100fl	Switch fl 1-Port 10-GbE X2 Interface Module Switch fl 2-Port 10-GbE X2 Interface Module	J8736A J8737A	CY.02.03.0005 and later	(not supported)	CY.02.03.0005 and later	CY.02.03.0005 and later	CY.02.03.0005 and later	CY.02.03.0005 and later, OMC for J8440A/B CY.02.05.0001 and later, OMC for J8440A/B
8200zl	Switch zl 4-Port 10-GbE X2 Module Switch zl 4-Port 10-GbE CX4 Module	J8707A J8708A	all software versions	K.13.20 and later	all software versions	all software versions	all software versions	all software versions, OMC for J8708A & J8440A/B

HP Networking Legacy ProCurve Product Family 10-GbE Transceiver Support Matrix (cont'd)

HP Networking Switch Series	Product Name	Product Number	Supported with This Software
9300m	9300 2-Port 10-GbE Module	J8174A	07.6.04 and later
9408sl	9400sl 4-Port 10-GbE Module	J8682A	all software versions

Genuine HP ProCurve XENPAK Transceivers

10GBASE-SR, LR, ER
(J8175A, J8173A, J8176A)

Footnotes

¹ The J8439A Optical Media Converter is supported in the J8440A and J8440B CX4 transceivers, but not in the J8440C.

