

Overview

HPE FlexNetwork HSR6600 Router Series



Models

HPE FlexNetwork HSR6602 G Router

JG353A

HPE FlexNetwork HSR6602 XG Router

JG354A

Key features

- High-performance WAN routing up to 15 Mpps
- Compact, multi-core centralized processing architecture
- Comprehensive routing, VPN and security
- Modular WAN and LAN connectivity options
- Robust high availability and resiliency

Product overview

The HPE FlexNetwork HSR6600 Router Series is made up of high-performance services WAN routers that are ideal for small- to medium-sized campus WAN edge and aggregation, as well as high-end branch deployments.

These routers are built with a high performance multi-core networking processor that delivers, in a 2 RU form factor, robust routing, security, and modular WAN and LAN interface options, all integrated in a single compact and powerful routing platform.

In addition, these routers feature robust carrier-class reliability capabilities to reduce disruption from network or system failures.

Features and benefits

Connectivity

- **Multiple WAN interfaces**
support Fast Ethernet/Gigabit Ethernet/10GbE ports, OC3~OC48 POS/CPOS, and ATM ports
- **Flexible port selection**

Overview

provides a combination of fiber/copper interface modules, 100/1000BASE-X auto-speed selection, and 10/100/1000BASE-T auto-speed detection plus auto duplex and MDI/MDI-X; is speed adaptable between 155 M POS/622 M POS/Gigabit Eth

- **Loopback**

supports internal loopback testing for maintenance purposes and an increase in availability; loopback detection protects against incorrect cabling or network configurations and can be enabled on a per-port or per-VLAN basis for added flexibility

Performance

- **High-performance platform**

provides up to 15 Mpps forwarding performance

Resiliency and high availability

- **Separate data and control planes**

provide greater flexibility and enable continual services

- **Hot-swappable modules**

facilitates the replacement of hardware interface modules without impacting the traffic flow through the system

- **Optional redundant power supply**

provides uninterrupted power; allows hot-swapping of one of the two supplies when installed

- **Virtual Router Redundancy Protocol (VRRP)**

allows groups of two routers to dynamically back each other up to create highly available routed environments

- **Graceful restart**

supports graceful restart for OSPF, IS-IS, BGP, LDP, and RSVP; the network remains stable during the active-standby switchover; after the switchover, the device quickly learns the network routes by communicating with adjacent routers; forwarding remains uninterrupted during the switchover to achieve nonstop forwarding (NSF)

- **Hitless software upgrades**

allow patches to be installed without restarting the device, increasing network uptime and simplifying maintenance

- **IP Fast Reroute Framework (FRR)**

nodes are configured with backup ports and routes; local implementation requires no cooperation of adjacent devices, simplifying the deployment; solves the traditional convergence faults in IP forwarding; achieves restoration within 50 ms, with the restoration time independent of the number of routes and fast link switchovers without route convergence

Product architecture

- **Multi-core CPU**

delivers multi-threaded processing, with eight cores and 32 hardware threads

- **Distributed processing**

two kinds of engines are hardware separated: main controller engine (routing engine) and service engines (Flexible Interface Platform [FIP]); the main controller engine is used for route computing and system management, and service engines are used for processing services

Layer 3 routing

- **Static IPv4 routing**

provides simple manually configured IPv4 routing

- **Routing Information Protocol (RIP)**

uses a distance vector algorithm with UDP packets for route determination; supports RIPv1 and RIPv2 routing; includes

Overview

loop protection

- **Open shortest path first (OSPF)**

delivers faster convergence; uses this link-state routing Interior Gateway Protocol (IGP), which supports ECMP, NSSA, and MD5 authentication for increased security and graceful restart for faster failure recovery

- **Border Gateway Protocol 4 (BGP-4)**

delivers an implementation of the Exterior Gateway Protocol (EGP) utilizing path vectors; uses TCP for enhanced reliability for the route discovery process; reduces bandwidth consumption by advertising only incremental updates; supports extensive policies for increased flexibility; scales to very large networks

- **Intermediate system to intermediate system (IS-IS)**

uses a path vector Interior Gateway Protocol (IGP), which is defined by the ISO organization for IS-IS routing and extended by IETF RFC 1195 to operate in both TCP/IP and the OSI reference model (Integrated IS-IS)

- **Static IPv6 routing**

provides simple manually configured IPv6 routing

- **Dual IP stack**

maintains separate stacks for IPv4 and IPv6 to ease the transition from an IPv4-only network to an IPv6-only network design

- **Routing Information Protocol next generation (RIPng)**

extends RIPv2 to support IPv6 addressing

- **OSPFv3**

provides OSPF support for IPv6

- **BGP+**

extends BGP-4 to support Multiprotocol BGP (MBGP), including support for IPv6 addressing

- **IS-IS for IPv6**

extends IS-IS to support IPv6 addressing

- **IPv6 tunneling**

allows IPv6 packets to traverse IPv4-only networks by encapsulating the IPv6 packet into a standard IPv4 packet; supports manually configured, 6to4, and Intra-Site Automatic Tunnel Addressing Protocol (ISATAP) tunnels; is an important element for the transition from IPv4 to IPv6

- **Multiprotocol Label Switching (MPLS)**

uses BGP to advertise routes across Label Switched Paths (LSPs), but uses simple labels to forward packets from any Layer 2 or Layer 3 protocol, which reduces complexity and increases performance; supports graceful restart for reduced failure impact; supports LSP tunneling and multilevel stacks

- **Multiprotocol Label Switching (MPLS) Layer 3 VPN**

allows Layer 3 VPNs across a provider network; uses MP-BGP to establish private routes for increased security; supports RFC 2547bis multiple autonomous system VPNs for added flexibility

- **Multiprotocol Label Switching (MPLS) Layer 2 VPN**

establishes simple Layer 2 point-to-point VPNs across a provider network using only MPLS Label Distribution Protocol (LDP); requires no routing and therefore decreases complexity, increases performance, and allows VPNs of non-routable protocols; uses no routing information for increased security; supports Circuit Cross Connect (CCC), Static Virtual Circuits (SVCs), Martini draft, and Kompella-draft technologies

- **Policy routing**

allows custom filters for increased performance and security; supports ACLs, IP prefix, AS paths, community lists, and aggregate policies

- **Multicast VPN**

supports Multicast Domain (MD) multicast VPN, which can be distributed on separate service cards, providing high performance and flexible configuration

- **Virtual Private LAN Service (VPLS)**

establishes point-to-multipoint Layer 2 VPNs across a provider network

- **Bidirectional Forwarding Detection (BFD)**

Overview

enables link connectivity monitoring and reduces network convergence time for RIP, OSPF, BGP, IS-IS, VRRP, MPLS, and IRF

- **IGMPv1, v2, and v3**

allow individual hosts to be registered on a particular VLAN

- **PIM-SSM, PIM-DM, and PIM-SM (for IPv4 and IPv6)**

support IP Multicast address management and inhibition of DoS attacks

- **Equal-Cost Multipath (ECMP)**

enables multiple equal-cost links in a routing environment to increase link redundancy and scale bandwidth

- **OSPFv3 MCE**

Multi-VPN-Instance CE (MCE) binds different VPNs to different interfaces on one single CE; the OSPFv3 MCE feature creates and maintains separate OSPFv3 routing tables for each IPv6 VPN to isolate VPN services in the device

Layer 3 services

- **Address Resolution Protocol (ARP)**

determines the MAC address of another IP host in the same subnet; supports static ARPs; gratuitous ARP allows detection of duplicate IP addresses; proxy ARP allows normal ARP operation between subnets or when subnets are separated by a Layer 2 network

- **User Datagram Protocol (UDP) helper**

redirects UDP broadcasts to specific IP subnets to prevent server spoofing

- **Domain Name System (DNS)**

provides a distributed database that translates domain names and IP addresses, which simplifies network design; supports client and server

- **Dynamic Host Configuration Protocol (DHCP)**

simplifies the management of large IP networks

Security

- **Dynamic Virtual Private Network (DVPN)**

collects, maintains, and distributes dynamic public addresses through the VPN Address Management (VAM) protocol, making VPN establishment available between enterprise branches that use dynamic addresses to access the public network; compared to traditional VPN technologies, DVPN technology is more flexible and has richer features, such as NAT traversal of DVPN packets, AAA identity authentication, IPSec protection of data packets, and multiple VPN domains

- **Group Domain Virtual Private Network (GDVPN)**

a tunnel-less VPN technology that allows for native end-to-end security for a full meshed network; suitable for an enterprise

running encryption over a private Multiprotocol Label Switching (MPLS)/IP-based core network, as well as to encrypt multicast traffic

- **Stateful VPN Firewall**

provides enhanced stateful packet inspection and filtering; supports flexible security zones and virtual firewall containment; provides advanced VPN services with Triple DES (3DES) and Advanced Encryption Standard (AES) encryption at high performance and low latency, Web content filtering, and application prioritization and enhancement

- **Access control list (ACL)**

supports powerful ACLs for both IPv4 and IPv6; ACLs are used for filtering traffic to prevent unauthorized users from accessing the network, or for controlling network traffic to save resources; rules can either deny or permit traffic to be forwarded; rules can be based on a Layer 2 header or a Layer 3 protocol header; rules can be set to operate on specific dates or times

- **Unicast Reverse Path Forwarding (URPF)**

allows normal packets to be forwarded correctly, but discards the attaching packet due to lack of reverse path route or

Overview

incorrect inbound interface; prevents source spoofing and distributed attacks; supports distributed UPF

- **Secure shell (SSHv2)**

uses external servers to securely log in to a remote device; with authentication and encryption, it protects against IP spoofing and plain-text password interception; increases the security of Secure FTP (SFTP) transfers

- **Remote Authentication Dial-In User Service (RADIUS)**

eases switch security access administration by using a password authentication server

- **Terminal Access Controller Access-Control System (TACACS+)**

delivers an authentication tool using TCP with encryption of the full authentication request, providing additional security

- **Network address translation (NAT)**

supports repeated multiplexing of a port and automatic 5-tuple collision detection, enabling NAPT to support unlimited connections; supports blacklist in NAT/NAPT/internal server, a limit on the number of connections, session log, and multi-instance

Quality of Service (QoS)

- **HQoS / Nested QoS**

allows for precise and flexible traffic classification and scheduling

- **Traffic policing**

supports Committed Access Rate (CAR) and line rate

- **Congestion management**

supports FIFO, PQ, CQ, WFQ, CBQ, and RTPQ

- **Weighted random early detection (WRED)/random early detection (RED)**

delivers congestion avoidance capabilities through the use of queue management algorithms

- **Other QoS technologies**

support traffic shaping, FR QoS, MPLS QoS, and MP QoS/LFI

Management

- **Industry-standard CLI with a hierarchical structure**

reduces training time and expenses, and increases productivity in multivendor installations

- **SNMPv1, v2, and v3**

provide complete support of SNMP; provide full support of industry-standard Management Information Base (MIB) plus private extensions; SNMPv3 supports increased security using encryption

- **Management interface control**

enables or disables each of the following interfaces depending on security preferences: console port, Telnet port, or reset button

- **Remote monitoring (RMON)**

uses standard SNMP to monitor essential network functions; supports events, alarm, history, and statistics group plus a private alarm extension group

- **Management security**

restricts access to critical configuration commands; offers multiple privilege levels with password protection; ACLs provide Telnet and SNMP access; local and remote syslog capabilities allow logging of all access

- **FTP, TFTP, and SFTP support**

offers different mechanisms for configuration updates; FTP allows bidirectional transfers over a TCP/IP network; trivial FTP (TFTP) is a simpler method using User Datagram Protocol (UDP); Secure File Transfer Protocol (SFTP) runs over an SSH tunnel to provide additional security

- **Debug and sampler utility**

supports ping and traceroute for both IPv4 and IPv6

- **Network Quality Analyzer (NQA)**

Overview

analyzes network performance and service quality by sending test packets, and provides network performance and service quality parameters such as jitter, TCP, or FTP connection delays and file transfer rates; allows a network manager to determine overall network performance and to diagnose and locate network congestion points or failures

- **Network Time Protocol (NTP)**

synchronizes timekeeping among distributed time servers and clients; keeps timekeeping consistent among all clock-dependent devices within the network so that the devices can provide diverse applications based on the consistent time

- **Information center**

provides a central repository for system and network information; aggregates all logs, traps, and debugging information generated by the system and maintains them in order of severity; outputs the network information to multiple channels based on user-defined rules

Multicast support

- **Internet Group Management Protocol (IGMP)**

utilizes Any-Source Multicast (ASM) or Source-Specific Multicast (SSM) to manage IPv4 multicast networks; supports IGMPv1, v2, and v3

- **Protocol Independent Multicast (PIM)**

defines modes of Internet IPv4 and IPv6 multicasting to allow one-to-many and many-to-many transmission of information; PIM Dense Mode (DM), Sparse Mode (SM), and Source-Specific Mode (SSM) are supported

- **Multicast Source Discovery Protocol (MSDP)**

allows multiple PIM-SM domains to interoperate; is used for inter-domain multicast applications

- **Multicast Border Gateway Protocol (MBGP)**

allows multicast traffic to be forwarded across BGP networks separately from unicast traffic

Additional information

- **Green initiative support**

provides support for RoHS and WEEE regulations

Warranty and support

- **1-year warranty**

See <http://www.hpe.com/networking/warrantysummary> for warranty and support information included with your product purchase.

- **Software releases**

to find software for your product, refer to <http://www.hpe.com/networking/support>; for details on the software releases available with your product purchase, refer to <http://www.hpe.com/networking/warrantysummary>

Configuration

Build To Order: BTO is a standalone unit with no integration. BTO products ship standalone are not part of a CTO or Rack-Shippable solution.

HPE FlexNetwork HSR6602 G Router	JG353A
<ul style="list-style-type: none">• 4 SFP ports (Min 0 // Max 4 SFP 1G Transceivers)• 1 Service Module Slot (FIP10 or FIP20 Modules only)• 1 - 2G DDR3 SDRAM included (JG482A)• 2 CF Memory slots: (Min 0 // Max 1)• Must select min 1 Power Supply• 2U High	See Configuration NOTE:1, 3

HPE HSR6602 G Router	JG353A#A59
----------------------	------------

HPE FlexNetwork HSR6602 XG Router	JG354A
<ul style="list-style-type: none">• 4 SFP ports (Min 0 // Max 4 SFP 1G Transceivers)• 2 10GbE SFP+ ports (Min 0 // Max 2 SFP+ 10G Transceivers)• 1 Service Module Slot (FIP10 or FIP20 Modules only)• 2 - 2G DDR3 SDRAM included (JG482A)• 2 CF Memory slots: (Min 0 // Max 1)• Must select min 1 Power Supply• 2U High	See Configuration NOTE:1, 2, 3

HPE HSR6602 XG Router	JG354A#A59
-----------------------	------------

Configuration Rules:

Note 1 The following Transceivers install into this Router:

HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B

Note 2 The following Transceivers install into this Router:

HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A

Configuration

Note 3 If this product is ordered for delivery to Russia, it must be ordered with the A59 option (also allowed for other countries desiring Low Encryption), then #A59 is the required option for BTO, and must be added in addition to #0D1 for CTO.

Box Level Integration CTO Models

CTO Solution Sku

HPE 66xx CTO Router Solution	JG498A
• SSP trigger sku	

CTO Base Sku

HPE FlexNetwork HSR6602 G Router	JG353A
• 4 SFP ports (Min 0 // Max 4 SFP 1G Transceivers) • 1 Service Module Slot (FIP10 or FIP20 Modules only) • 1 - 2G DDR3 SDRAM included (JG482A) • 2 CF Memory slots: (Min 0 // Max 1) • Must select min 1 Power Supply • 2U High	See Configuration NOTE:2, 10

HPE FlexNetwork HSR6602 XG Router	JG354A
• 4 SFP ports (Min 0 // Max 4 SFP 1G Transceivers) • 2 10GbE SFP+ ports (Min 0 // Max 2 SFP+ 10G Transceivers) • 1 Service Module Slot (FIP10 or FIP20 Modules only) • 2 - 2G DDR3 SDRAM included (JG482A) • 2 CF Memory slots: (Min 0 // Max 1) • Must select min 1 Power Supply • 2U High	See Configuration NOTE: 2, 3, 10

Configuration Rules:

Note 2 The following Transceivers install into this Router:

HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B

Note 3 The following Transceivers install into this Router:

HPE X130 10G SFP+ LC SR Transceiver	JD092B
-------------------------------------	--------

Configuration

HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A

Note 10 If the Router Chassis is Box Level Factory Integrated (CTO), Then the #0D1 is required on the Router Chassis and integrated to the JG498A - HPE 6600 CTO Enablement.(Min 1/Max 1 Router per SSP)

Rack Level Integration CTO Models

HPE FlexNetwork HSR6602 G Router	JG353A
<ul style="list-style-type: none"> • 4 SFP ports (Min 0 // Max 4 SFP 1G Transceivers) • 1 Service Module Slot (FIP10 or FIP20 Modules only) • 1 - 2G DDR3 SDRAM included (JG482A) • 2 CF Memory slots: (Min 0 // Max 1) • Must select min 1 Power Supply • 2U High 	See Configuration NOTE:1, 4
HPE HSR6602 G Router	JG353A#A59
HPE FlexNetwork HSR6602 XG Router	JG354A
<ul style="list-style-type: none"> • 4 SFP ports (Min 0 // Max 4 SFP 1G Transceivers) • 2 10GbE SFP+ ports (Min 0 // Max 2 SFP+ 10G Transceivers) • 1 Service Module Slot (FIP10 or FIP20 Modules only) • 2 - 2G DDR3 SDRAM included (JG482A) • 2 CF Memory slots: (Min 0 // Max 1) • Must select min 1 Power Supply • 2U High 	See Configuration NOTE:1, 2, 4
HPE HSR6602 XG Router	JG354A#A59

Configuration Rules:

Note 1 The following Transceivers install into this Router:

HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B

Note 2 The following Transceivers install into this Router:

HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A

Configuration

Note 4 If this product is ordered for delivery to Russia, it must be ordered with the A59 option (also allowed for other countries desiring Low Encryption), then #A59 is the required option for BTO, and must be added in addition to #0D1 for CTO.

Modules

Management Module slots

(JG353A, JG776A, JG354A, JG777A Routers Only) // Not Supported

(JC496A, JC177B, JC178B Router) System (std 0 // max 2) User Selection (min 1 // max 2) install in Service Engine Module

HPE FlexNetwork 6600 MCP-X1 Router Main Processing Unit

JG355A

- Min 0 // Max 4 SFP 1G Transceivers
- 1 - 2GB DDR3 SDRAM Included (JG482A)

See Configuration
NOTE:1, 4, 7, 8

HPE 6600 MCP-X1 Router MPU

JG355A#A59

HPE FlexNetwork 6600 MCP-X2 Router Main Processing Unit

JG356A

- Min 0 // Max 4 SFP 1G Transceivers
- Min 0 // Max 2 SFP+ 10G Transceivers
- 2 - 2GB DDR3 SDRAM Included (JG482A)

See Configuration
NOTE:1, 4, 6, 7, 8

HPE 6600 MCP-X2 Router MPU

JG356A#A59

HPE FlexNetwork 6600 RPE-X1 Router Module

JC165A

- 1 - 1GB DDR2 SDRAM Included (JC701A)

See Configuration
NOTE:1, 2, 4, 9

HPE 6600 RPE-X1 Router Module

JC165A#A59

HPE FlexNetwork 6600 RSE-X1 Main Processing Unit

JC566A

- 2 - 1GB DDR2 SDRAM Included (JC701A)

See Configuration
NOTE:1, 4, 9

HPE 6600 RSE-X1 Main Processing Unit

JC566A#A59

Configuration Rules:

Note 1 No mixing of any type of MPU. Must all be the same sku.

Note 2 If the RPE-X1 (JC165A or JG781A) is selected then the HPE 6600RPE-X1 Carrier Card (JC497A) must be added to order as well.

Configuration

Note 4 If this product is ordered for delivery to Russia, it must be ordered with the A59 option (also allowed for other countries desiring Low Encryption), then #A59 is the required option for BTO, and must be added in addition to #0D1 for CTO.

Note 6 The following Transceivers install into this Module: (Use #0D1 if switch is CTO)

HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A

Note 7 The following Transceivers install into this Module: (Use #0D1 if switch is CTO)

HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B

Note 8 FIP-10 or FIP-20 Modules Only work with these MPUs: JG355A, JG778A, JG356A

Note 9 FIP-110 or FIP-210 Modules Only work with these MPUs: JC165A, JG781A, JC566A, JG780A

Remark: RSE-X1 (JC566A, JG780A) occupies a full-width slot.
RPE-X1 (JC165A, JG781A) occupies half-width slot.

Service Module slots

(JG353A, JG776A, JG354A, JG777A Routers Only) System (std 0 // max 1) User Selection (min 0 // max 1) per router

(JC178B Router Only) System (std 0 // max 2) User Selection (min 0 // max 2) per router

(JC177B Router Only) System (std 0 // max 4) User Selection (min 0 // max 4) per router

(JC496A Router Only) System (std 0 // max 8) User Selection (min 0 // max 8) per router

HPE FlexNetwork 6600 FIP-10 Flexible Interface Platform Router Module

JG357A

See Configuration

NOTE:4, 8

HPE FlexNetwork 6600 FIP-20 Flexible Interface Platform Router Module

JG358A

See Configuration

NOTE:8, 9

HPE FlexNetwork 6600 FIP-110 Flexible Interface Platform Module

JC166B

See Configuration

NOTE: 2, 4, 7

- min=0 \ max=2 SFP 1G \\ Min=0 \ Max=4 MIM Modules
- 2 - 1GB DDR2 SDRAM Included (JC071A)

Configuration

HPE FlexNetwork 6600 FIP-210 Flexible Interface Platform Module	JC167B See Configuration NOTE:2, 5, 7
<ul style="list-style-type: none"> • min=0 \ max=2 SFP 1G \\ Min=0 \ Max=2 HIM Modules or 2 MIM Modules or 1 Each • 2 - 1GB DDR2 SDRAM Included (JC071A) 	
HPE FlexNetwork 6600 48-port Gig-T Service Aggregation Platform Module	JC567A See Configuration NOTE:6, 7
<ul style="list-style-type: none"> • min=0 \ max=2 SFP 1G \\ Min=0 \ Max=2 HIM Modules or 2 MIM Modules or 1 Each • 2 - 1GB DDR2 SDRAM Included (JC071A) 	
HPE FlexNetwork 6600 24-port GbE SFP Service Aggregation Platform Module	JC568A See Configuration NOTE:3, 6, 7
<ul style="list-style-type: none"> • min=0 \ max=2 SFP 1G \\ Min=0 \ Max=2 HIM Modules or 2 MIM Modules or 1 Each • 2 - 1GB DDR2 SDRAM Included (JC071A) 	
HPE FlexNetwork 6600 48-port GbE SFP Service Aggregation Platform Module	JG556A See Configuration NOTE:3, 6, 7
<ul style="list-style-type: none"> • min=0 \ max=2 SFP 1G \\ Min=0 \ Max=2 HIM Modules or 2 MIM Modules or 1 Each • 2 - 1GB DDR2 SDRAM Included (JC071A) 	
Configuration Rules:	
Note 2	The following Transceivers installs into this Service Module: (Use #0D1 if router is CTO) - if applicable
	HPE X120 1G SFP LC SX Transceiver JD118B
	HPE X120 1G SFP LC LX Transceiver JD119B
	HPE X125 1G SFP LC LH40 1310nm Transceiver JD061A
	HPE X120 1G SFP LC LH40 1550nm Transceiver JD062A
	HPE X125 1G SFP LC LH70 Transceiver JD063B
	HPE X120 1G SFP LC LH100 Transceiver JD103A
	HPE X120 1G SFP LC BX 10-U Transceiver JD098B
	HPE X120 1G SFP LC BX 10-D Transceiver JD099B
Note 3	The following Transceivers install into this Service Module: (Use #0D1 if router is CTO) - if applicable
	HPE X120 1G SFP LC SX Transceiver JD118B
	HPE X120 1G SFP LC LX Transceiver JD119B
	HPE X125 1G SFP LC LH40 1310nm Transceiver JD061A
	HPE X120 1G SFP LC LH40 1550nm Transceiver JD062A
	HPE X125 1G SFP LC LH70 Transceiver JD063B
	HPE X120 1G SFP LC LH100 Transceiver JD103A
	HPE X120 1G SFP LC BX 10-U Transceiver JD098B
	HPE X120 1G SFP LC BX 10-D Transceiver JD099B
	HPE X115 100M SFP LC FX Transceiver JD102B
	HPE X110 100M SFP LC LX Transceiver JD120B
	HPE X110 100M SFP LC LH40 Transceiver JD090A
	HPE X110 100M SFP LC LH80 Transceiver JD091A
	HPE X115 100M SFP LC BX 10-U Transceiver JD100A

Configuration

HPE X115 100M SFP LC BX 10-D Transceiver	JD101A
HPE X120 1G SFP RJ45 T Transceiver	JD089B

Note 4 **The following Modules installs into this Service Module: Max = 4 (Use #0D1 if router is CTO) - if applicable**

HPE FlexNetwork MSR 2-port Enhanced Serial MIM Module	JD540A
HPE FlexNetwork MSR 4-port Enhanced Serial MIM Module	JD541A
HPE FlexNetwork MSR 8-port Sync/Async Interface Enhanced Module	JD552A
HP MSR 1-port FT3/CT3 MIM Module	JD628A
HPE FlexNetwork 6600 8-port T1 MIM Router Module	JC160A
HPE FlexNetwork 6600 8-port Fractional T1 MIM Router Module	JC159A
HPE FlexNetwork MSR 8-port E1/CE1/PRI (75ohm) MIM Module	JD563A
HPE MSR 8-port Fractional E1 MIM Module	JF255A
HP MSR 1-port FE3/CE3 MIM Module	JD630A

Note 5 **The following Modules installs into this Service Module: Max = 2 (Use #0D1 if router is CTO) - if applicable**

HPE FlexNetwork MSR 2-port Enhanced Serial MIM Module	JD540A
HPE FlexNetwork MSR 4-port Enhanced Serial MIM Module	JD541A
HPE FlexNetwork 6600 8-port T1 MIM Router Module	JC160A
HPE FlexNetwork 6600 8-port Fractional T1 MIM Router Module	JC159A
HPE FlexNetwork 6600 1-port OC-3 (E1/T1) CPOS HIM Router Module	JC161A
HPE FlexNetwork 6600 2-port OC-3 E1/T1 CPOS HIM Router Module	JC162A
HPE FlexNetwork 6600 4GbE WAN HIM Router Module	JC163A
HPE FlexNetwork 6600 8GbE WAN HIM Router Module	JC164A
HPE FlexNetwork 6600 4-port GbE SFP HIM Router Module	JC171A
HPE FlexNetwork 6600 4-port OC-3/2-port OC-12 POS HIM Router Module	JC172A
HPE FlexNetwork 6600 1-port OC-48/STM-16 POS (SFP) Router Module	JC494A
HPE FlexNetwork 6600 2-port OC-3/1-port OC-12 POS HIM Router Module	JC173A
HPE FlexNetwork 6600 8-port GbE SFP HIM Router Module	JC174A
HPE FlexNetwork 6600 1-port 10GbE XFP HIM Router Module	JC168A
HP 6600 2-port OC-3c/STM-1c ATM SFP Router Module	JC495A
HPE FlexNetwork 6600 8-port 10/100BASE-T HIM Module	JC575A
HPE MSR 8-port Fractional E1 MIM Module	JF255A
HP MSR 1-port FE3/CE3 MIM Module	JD630A
HPE FlexNetwork MSR 8-port E1/CE1/PRI (75ohm) MIM Module	JD563A
HPE FlexNetwork 6600 8-port OC-3c/OC-12c POS/GbE SFP HIM Module	JG673A

Note 6 **If this Module is selected, Then the JC566A - HPE A6600 RSE-X1 Main Processing Unit or JG780A - HPE 6600 RSE-X1 Router TAA MPU is required.**

Note 7 **This module is only supported in the following routers:**

HPE FlexNetwork 6616 Router Chassis	JC496A
HPE FlexNetwork 6608 Router Chassis	JC177B

Configuration

HPE FlexNetwork 6604 Router Chassis JC178B

Note 8 If this Module is selected with a legacy router (JC178B, JC177B, and JC496A), then one of the following Management Module is required:

HPE FlexNetwork 6600 MCP-X1 Router Main Processing Unit	JG355A
HPE FlexNetwork 6600 MCP X2 Router TAA-compliant Main Processing Unit	JG778A
HPE FlexNetwork 6600 MCP-X2 Router Main Processing Unit	JG356A

Note 9 The following Modules installs into this Service Module: Max = 2 (Use #OD1 if router is CTO) - if applicable

HPE FlexNetwork MSR 2-port Enhanced Serial MIM Module	JD540A
HPE FlexNetwork MSR 4-port Enhanced Serial MIM Module	JD541A
HPE FlexNetwork 6600 8-port T1 MIM Router Module	JC160A
HPE FlexNetwork 6600 8-port Fractional T1 MIM Router Module	JC159A
HPE FlexNetwork 6600 1-port OC-3 (E1/T1) CPOS HIM Router Module	JC161A
HPE FlexNetwork 6600 2-port OC-3 E1/T1 CPOS HIM Router Module	JC162A
HPE FlexNetwork 6600 4GbE WAN HIM Router Module	JC163A
HPE FlexNetwork 6600 8GbE WAN HIM Router Module	JC164A
HPE FlexNetwork 6600 4-port GbE SFP HIM Router Module	JC171A
HPE FlexNetwork 6600 4-port OC-3/2-port OC-12 POS HIM Router Module	JC172A
HPE FlexNetwork 6600 1-port OC-48/STM-16 POS (SFP) Router Module	JC494A
HPE FlexNetwork 6600 2-port OC-3/1-port OC-12 POS HIM Router Module	JC173A
HPE FlexNetwork 6600 8-port GbE SFP HIM Router Module	JC174A
HPE FlexNetwork 6600 1-port 10GbE XFP HIM Router Module	JC168A
HP 6600 2-port OC-3c/STM-1c ATM SFP Router Module	JC495A
HPE FlexNetwork 6600 8-port 10/100BASE-T HIM Module	JC575A
HPE MSR 8-port Fractional E1 MIM Module	JF255A
HP MSR 1-port FE3/CE3 MIM Module	JD630A
HPE FlexNetwork MSR 8-port E1/CE1/PRI (75ohm) MIM Module	JD563A
HPE FlexNetwork 6600 8-port OC-3c/OC-12c POS/GbE SFP HIM Module	JG673A
HPE FlexNetwork HSR6800 16-port GbE SFP HIM Module	JH142A
HPE FlexNetwork HSR6800 2-port 10GbE SFP+ HIM Module	JH143A

Remarks: CONFIGURATOR BLUE TEXT:

JG357A - HPE 6600 FIP-10 Flex Intf Pltfrm Rtr Mod is only supported on Comware V5.
It is not supported when using Comware V7.

CONFIGURATOR BLUE TEXT:

Him Modules JH142A – HPE HSR6800 16-p GbE SFP HIM Mod and JH143A - HP
HSR6800 2-p 10GbE SFP+ HIM Mod are only supported in JG358A - HPE 6600 FIP-20
Flex Intf Pltfrm Rtr Mod when using Comware V7.

MIM and HIM router Modules

System (std 0 // max 2 or 4) User Selection (min 0 // max 2 or 4) per Service Module (See Service Modules for Port information)

Configuration

HP 6600 1p OC-3 (E1/T1) CPOS HIM Rtr Mod	JC161A
• min=0 \ max=1 SFP	See Configuration NOTE:1, 2
HPE FlexNetwork 6600 2-port OC-3 E1/T1 CPOS HIM Router Module	JC162A
• min=0 \ max=2 SFP	See Configuration NOTE:1, 2
HPE FlexNetwork 6600 4-port GbE SFP HIM Router Module	JC171A
• min=0 \ max=4 SFP	See Configuration NOTE:1, 3
HPE FlexNetwork 6600 4-port OC-3/2-port OC-12 POS HIM Router Module	JC172A
• min=0 \ max=4 SFP	See Configuration NOTE:1, 2, 4, 7
HPE FlexNetwork 6600 2-port OC-3/1-port OC-12 POS HIM Router Module	JC173A
• min=0 \ max=2 SFP	See Configuration NOTE:1, 2, 4, 8
HPE FlexNetwork 6600 1-port OC-48/STM-16 POS (SFP) Router Module	JC494A
• min=0 \ max=1 SFP	See Configuration NOTE:1, 5
HPE FlexNetwork 6600 8-port GbE SFP HIM Router Module	JC174A
• min=0 \ max=8 SFP	See Configuration NOTE:1, 3
HPE FlexNetwork HSR6800 16-port GbE SFP HIM Module	JH142A
• min=0 \ max=1 SFP	See Configuration NOTE:3, 14
HP 6600 2-port OC-3c/STM-1c ATM SFP Router Module	JC495A
• min=0 \ max=2 SFP	See Configuration NOTE:1, 2
HPE FlexNetwork 6600 1-port 10GbE XFP HIM Router Module	JC168A
• min=0 \ max=1 XFP	See Configuration NOTE:1, 6
HPE FlexNetwork HSR6800 2-port 10GbE SFP+ HIM Module	JH143A
• min=0 \ max=2 SFP+	See Configuration NOTE:5, 14

Configuration

HPE FlexNetwork MSR 2-port Enhanced Serial MIM Module	JD540A
• min=0 \ max=2 Serial Port Cable	See Configuration NOTE:1, 9
HPE FlexNetwork MSR 4-port Enhanced Serial MIM Module	JD541A
• min=0 \ max=4 Serial Port Cable	See Configuration NOTE:1, 9
HPE FlexNetwork MSR 8-port Sync/Async Interface Enhanced Module	JD552A
• min=0 \ max=8 Serial Port Cable	See Configuration NOTE:1, 9
HP MSR 1-port FT3/CT3 MIM Module	JD628A
• min=0 \ max=2 E3/T3 Cable	See Configuration NOTE:1, 11
HPE FlexNetwork 6600 8-port T1 MIM Router Module	JC160A
• No Transceivers	See Configuration NOTE:1
HPE FlexNetwork 6600 8-port Fractional T1 MIM Router Module	JC159A
• No Transceivers	See Configuration NOTE:1
HPE FlexNetwork 6600 4GbE WAN HIM Router Module	JC163A
• No Transceivers	See Configuration NOTE:1
HPE FlexNetwork 6600 8GbE WAN HIM Router Module	JC164A
• No Transceivers	See Configuration NOTE:1
HPE FlexNetwork 6600 8-port 10/100BASE-T HIM Module	JC575A
• No Transceivers	See Configuration NOTE:1
HP A-MSR 8-p E1/CE1/PRI (75ohm) MIM Mod	JD563A
• must select 1 8-port E1 Cable	See Configuration NOTE:1, 10
HP MSR 8-port E1/Fractional E1 (75ohm) MIM Module	JF255A
• must select 1 8-port E1 Cable	See Configuration NOTE:1, 10
HP MSR 1-port FE3/CE3 MIM Module	JD630A

Configuration

- min=0 \ max=2 E3/T3 Cable See Configuration
NOTE:1, 11

HPE FlexNetwork 6600 8-port OC-3c/OC-12c POS/GbE SFP HIM Module

- min=0 \ max=8 SFP See Configuration
NOTE:1, 4, 13

Configuration Rules:

Note 1 Routers JC177B, JC178B, JC496A Requires JC166B, JC167B, JG357A or JG358A Flex Int Platform Module to install HIM or MIM modules.
Routers JG353A, JG776A, JG354A, JG777A Requires the JG357A or JG358A Flex Int Platform Module to install HIM or MIM modules.

Note 2 The following Transceivers install into this Module: (Use #0D1 if router is CTO) - if applicable

HPE X115 100M SFP LC FX Transceiver	JD102B
HPE X110 100M SFP LC LX Transceiver	JD120B
HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A

Note 3 The following Transceivers install into this Module: (Use #0D1 if router is CTO) - if applicable

HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X115 100M SFP LC BX 10-U Transceiver	JD100A
HPE X115 100M SFP LC BX 10-D Transceiver	JD101A
HPE X115 100M SFP LC FX Transceiver	JD102B
HPE X110 100M SFP LC LX Transceiver	JD120B
HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A
HPE X120 1G SFP RJ45 T Transceiver	JD089B

Note 4 The following Transceivers install into this Module (Use #0D1 if router is CTO) - if applicable

HPE X120 622M SFP LC LX 15km Transceiver	JF829A
HPE X120 622M SFP LC LH 40km 1310 Transceiver	JF830A

Configuration

Note 5	The following Transceivers install into this Module: (Use #0D1 if router is CTO) - if applicable	
	HPE X130 10G SFP+ LC SR Transceiver	JD092B
	HPE X130 10G SFP+ LC LR Transceiver	JD094B
	HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
Note 6	The following Transceivers install into this Module: (Use #0D1 if router is CTO) - if applicable	
	HPE X135 10G XFP LC ER Transceiver	JD121A
	HPE X130 10G XFP LC LR Single Mode 10km 1310nm Transceiver	JD108B
	HPE X130 10G XFP LC SR Transceiver	JD117B
Note 7	min=0 \ max=4 SFP (JD102B,JD120B,JD090A,JD091A) min=0 \ max=2 SFP (JF829A,JF830A) X110 100M LC Transceiver (JD102B,JD120B,JD090A and JD091A) and X120 622M LC Transceiver (JF829A and JF830A) cannot be used at the same time	
Note 8	min=0 \ max=2 SFP (JD102B,JD120B,JD090A,JD091A) min=0 \ max=1 SFP (JF829A,JF830A) X110 100M LC Transceiver (JD102B,JD120B,JD090A and JD091A) and X120 622M LC Transceiver (JF829A and JF830A) cannot be used at the same time	
Note 9	The following Cables install into this Module:	
	HPE FlexNetwork X200 V.24 DTE 3m Serial Port Cable	JD519A
	HPE FlexNetwork X200 V.24 DCE 3m Serial Port Cable	JD521A
	HPE FlexNetwork X200 V.35 DTE 3m Serial Port Cable	JD523A
	HPE FlexNetwork X200 V.35 DCE 3m Serial Port Cable	JD525A
	HPE FlexNetwork X260 RS449 3m DTE Serial Port Cable	JF825A
	HPE FlexNetwork X260 RS449 3m DCE Serial Port Cable	JF826A
	HPE FlexNetwork X260 RS530 3m DTE Serial Port Cable	JF827A
	HPE FlexNetwork X260 RS530 3m DCE Serial Port Cable	JF828A
Note 10	The following Cable install into this Module:	
	HPE FlexNetwork X260 8E1 BNC 75 ohm 3m Router Cable	JD512A
Note 11	The following E3/T3 Cable and Connector install into this Module:	
	HPE FlexNetwork X260 T3/E3 Router Cable	JD531A
	HP X260 E3-30 E3/T3 Router Cable	JD533A
Note 12	If this Module is selected, Then one of the following routers is required:	
	HPE FlexNetwork 6616 Router Chassis	JC496A
	HPE FlexNetwork 6608 Router Chassis	JC177B
	HPE FlexNetwork 6604 Router Chassis	JC178B
Note 13	The following Transceivers install into this Module: (Use #0D1 if router is CTO) - if applicable	

Configuration

applicable

HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X115 100M SFP LC FX Transceiver	JD102B
HPE X110 100M SFP LC LX Transceiver	JD120B
HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A
HPE X115 100M SFP LC BX 10-U Transceiver	JD100A
HPE X115 100M SFP LC BX 10-D Transceiver	JD101A

Note 14 Routers JG353A, JG354A, JG776A, JG777A Requires JG358A - HP 6600 FIP-20 Flex Intf Pltfrm Rtr Mod to install Him Modules JH142A - HP HSR6800 16-p GbE SFP HIM Mod and JH143A - HP HSR6800 2-p 10GbE SFP+ HIM Mod.

Transceivers

SFP Transceivers

HPE X110 100M SFP LC LX Transceiver	JD120B
HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A
HPE X115 100M SFP LC BX 10-U Transceiver	JD100A
HPE X115 100M SFP LC BX 10-D Transceiver	JD101A
HPE X115 100M SFP LC FX Transceiver	JD102B
HPE X120 622M SFP LC LX 15km Transceiver	JF829A
HPE X120 622M SFP LC LH 40km 1310 Transceiver	JF830A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B

SFP+ Transceivers

Configuration

HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A

XFP Transceivers

HPE X135 10G XFP LC ER Transceiver	JD121A
HPE X130 10G XFP LC LR Single Mode 10km 1310nm Transceiver	JD108B
HPE X130 10G XFP LC SR Transceiver	JD117B

Internal Power Supplies

(JC496A Only) System (std 0 // max 4) User Selection (min 2 // max 4) per router
 (JC177B and JC178B Only) - System (std 0 // max 2) User Selection (min 1 // max 2) per router
 (JG353A, JG776A, JG354A, JG777A Only) - System (std 0 // max 2) User Selection (min 1 // max 2) per router

HPE FlexNetwork 7500 650W DC Power Supply	JD209A
	See Configuration
	NOTE:1, 2
HPE FlexNetwork 7500 650W AC Power Supply	JD217A
• includes 1 x c13, 650w	See Configuration
	NOTE:1, 2, 5
PDU Cable NA/MEX/TW/JP	JD217A#B2B
• C15 PDU Jumper Cord (NA/MEX/TW/JP)	
PDU Cable ROW	JD217A#B2C
• C15 PDU Jumper Cord (ROW)	
High Volt Switch/Router to Wall Power Cord	JD217A#B2E
• NEMA L6-20P Cord (NA/MEX/JP/TW)	
HPE FlexNetwork 6616 650W DC Router Power Supply	JC493A
	See Configuration
	NOTE:1, 3
HPE FlexNetwork 6616 650W AC Router Power Supply	JC492A
• includes 1 x c13, 650w	See Configuration
	NOTE:1, 3, 5
PDU Cable NA/MEX/TW/JP	JD492A#B2B
• C15 PDU Jumper Cord (NA/MEX/TW/JP)	

Configuration

PDU Cable ROW	JC492A#B2C
• C15 PDU Jumper Cord (ROW)	
High Volt Switch/Router to Wall Power Cord	JC492A#B2E
• NEMA L6-20P Cord (NA/MEX/JP/TW)	
HPE 5800 300W DC Power Supply	JC090A
	See Configuration
	NOTE:4
HPE 5800 300W AC Power Supply	JC087A
• includes 1 x c13, 650w	See Configuration
	NOTE:1, 4, 5, 6
PDU Cable NA/MEX/TW/JP	JC087A#B2B
• C15 PDU Jumper Cord (NA/MEX/TW/JP)	
PDU Cable ROW	JC087A#B2C
• C15 PDU Jumper Cord (ROW)	

Configuration Rules:

- Note 1 If 2 power supplies are selected they must be the same SKU number.
- Note 2 Only supported on the 6604 (JC178B) and (JC177B) 6608 routers. (Watson Default JD217A)
- Note 3 Only supported on the 6616 (JC496A) routers. (Watson Default JC492A)
- Note 4 Only supported on the new JG353A, JG776A, JG354A, JG777A routers. (Watson Default JC087A)
- Note 5 Localization (Wall Power Cord) required on orders without #B2B, #B2C (PDU Power Cord) or #B2E. (See Localization Menu)
- Note 6 When Switches/Routers are Factory Racked, Then #B2B, or #B2C should be the Defaulted Power Cable option on the Switches/Routers.

Remarks: Drop down under power supply should offer the following options and results:
 Switch/Router/Power Supply to PDU Power Cord - #B2B in North America, Mexico, Taiwan, and Japan or #B2C ROW. (Watson Default B2B or B2C for Rack Level CTO)
 Switch/Router/Power Supply to Wall Power Cord - Localized Option (Watson Default for BTO and Box Level CTO)
 High Volt Switch/Router/Power Supply to Wall Power Cord - #B2E Option. (Offered only in North America, Mexico, Taiwan, and Japan)

Configuration

Cables

HPE FlexNetwork X200 V.24 DTE 3m Serial Port Cable	JD519A
HPE FlexNetwork X200 V.24 DCE 3m Serial Port Cable	JD521A
HPE FlexNetwork X200 V.35 DTE 3m Serial Port Cable	JD523A
HPE FlexNetwork X200 V.35 DCE 3m Serial Port Cable	JD525A
HPE FlexNetwork X260 RS449 3m DTE Serial Port Cable	JF825A
HPE FlexNetwork X260 RS449 3m DCE Serial Port Cable	JF826A
HPE FlexNetwork X260 RS530 3m DTE Serial Port Cable	JF827A
HPE FlexNetwork X260 RS530 3m DCE Serial Port Cable	JF828A
HPE FlexNetwork X260 E1 RJ45 BNC 75-120 ohm Conversion Router Cable	JD511A
HPE FlexNetwork X260 8E1 BNC 75 ohm 3m Router Cable	JD512A
HPE FlexNetwork X260 T3/E3 Router Cable	JD531A
HP X260 E3-30 E3/T3 Router Cable	JD533A

Remarks: The following cable is used for RJ45 BNC Conversion

JD511A - HPE FlexNetwork X260 E1 RJ45 BNC 75-120 ohm Conversion Router Cable

Router Enclosure Options

Carrier Card

System (std 0 // max 1) User Selection (min 0 // max 1) per routers

HPE FlexNetwork 6616 Router Chassis Accessory Kit	JC497A
	See Configuration NOTE:1

Configuration Rules:

Note 1 RPE-X1 (JC165A, JG781A) is supported with HPE 6600RPE-X1 Carrier Card (JC497A)

Dustproof Frames

User Selection (min 0 // max 1) per router

HPE FlexNetwork 6604 Dustproof Frame	JC572A
	See Configuration NOTE:3

HPE FlexNetwork 6608 Dustproof Frame	JC573A
	See Configuration NOTE:2

HPE FlexNetwork 6616 Dustproof Frame	JC574A
--------------------------------------	--------

Configuration

See Configuration

NOTE:1

Configuration Rules:

Note 1 This Frame installs to the following routers only:

HPE FlexNetwork 6616 Router Chassis

JC496A

Note 2 This Frame installs to the following routers only:

HPE FlexNetwork 6608 Router Chassis

JC177B

Note 3 This Frame installs to the following routers only:

HPE FlexNetwork 6604 Router Chassis

JC178B

Router Software License

User Selection (min 1 // max 1) per router

HPE FlexNetwork 6600 Router Software LTU

JC180A

See Configuration

NOTE:1

Configuration Rules:

Note 1 This License installs to the following routers only:

HPE FlexNetwork 6616 Router Chassis

JC496A

HPE FlexNetwork 6608 Router Chassis

JC177B

HPE FlexNetwork 6604 Router Chassis

JC178B

Spare Fan Assembly

User Selection (min 0 // max 1) per router

HPE FlexNetwork HSR6602 Router Spare Fan Assembly

JG359A

See Configuration

NOTE:4

HPE FlexNetwork 6604 Spare Fan Assembly

JC569A

See Configuration

NOTE:3

HPE FlexNetwork 6608 Spare Fan Assembly

JC570A

See Configuration

NOTE:2

HPE FlexNetwork 6616 Spare Fan Assembly

JC571A

See Configuration

Configuration

NOTE:1

Configuration Rules:

Note 1 This Fan Assembly installs to the following routers only:

HPE FlexNetwork 6616 Router Chassis

JC496A

Note 2 This Fan Assembly installs to the following routers only:

HPE FlexNetwork 6608 Router Chassis

JC177B

Note 3 This Fan Assembly installs to the following routers only:

HPE FlexNetwork 6604 Router Chassis

JC178B

Note 4 This Fan Assembly installs to the following routers only:

HPE FlexNetwork HSR6602 G Router

JG353A

HPE FlexNetwork HSR6602 G TAA-compliant Router

JG776A

HPE FlexNetwork HSR6602 XG Router

JG354A

HPE FlexNetwork HSR6602 XG TAA-compliant Router

JG777A

Memory

HPE X610 2G VLP DDR3 SDRAM Memory

JG482A

See Configuration

NOTE:1

HPE FlexNetwork 6600 1GB SDRAM

JC179A

See Configuration

NOTE:2

HP X610 1GB DDR2 SDRAM Memory

JC071A

See Configuration

NOTE:3

Configuration Rules:

Note 1 System (std 1 // max 2) User Selection (min 0 // max 1)

Only supported on:

HPE FlexNetwork HSR6602 G Router

JG353A

HPE FlexNetwork HSR6602 G TAA-compliant Router

JG776A

HPE FlexNetwork 6600 MCP-X1 Router Main Processing Unit

JG355A

Note 2 This memory installs to the following routers only:

HPE FlexNetwork 6616 Router Chassis

JC496A

HPE FlexNetwork 6608 Router Chassis

JC177B

HPE FlexNetwork 6604 Router Chassis

JC178B

Configuration

Note 3 System (std 1 // max 2) User Selection (min 0 // max 1)

Only supported on:

HPE FlexNetwork 6600 RPE-X1 Router Module

JC165A

HPE FlexNetwork 6600 RPE-X1 TAA-compliant Main Processing Unit

JG781A

Compact Flash

JG353A, JG776A, JG354A, JG777A only - System (std 1 // max 2) User Selection (min 0 // max 1) per router

HPE X600 512M Compact Flash Card

JC685A

See Configuration

NOTE:1

HPE X600 1G Compact Flash Card

JC684A

See Configuration

NOTE:1

Configuration Rules:

Note 1 This Compact Flash installs to the following routers only:

HPE FlexNetwork HSR6602 G Router

JG353A

HPE FlexNetwork HSR6602 G TAA-compliant Router

JG776A

HPE FlexNetwork HSR6602 XG Router

JG354A

HPE FlexNetwork HSR6602 XG TAA-compliant Router

JG777A

Opacity Shield Kit

System (std 0 // max 1) User Selection (min 0 // max 1)

HPE FlexNetwork HSR6602 Router Opacity Shield Kit

JG674A

See Configuration

NOTE:1

HPE 6616 Router Opacity Shield Kit

JG576A

See Configuration

NOTE:2

HPE 6608 Router Opacity Shield Kit

JG577A

See Configuration

NOTE:1

HPE 6604 Router Opacity Shield Kit

JG578A

See Configuration

NOTE:1

Configuration

Configuration Rules:

- Note 1 If selected with a CTO Router Solution, Quantity 1 of JG585A#B01 must also be ordered.
- Note 2 If selected with a CTO Router Solution, Quantity 1 of JG586A#B01 must also be ordered.

Tamper Evidence Labels

System (std 0 // max 1) User Selection (min 0 // max 1)

HP 12mm x 60mm Tmpr-Evidence (30) Lbl

JG585A

- Supported on JG776A, JG777A, JC496A, JC177B, JC178B

See Configuration

NOTE:1

HP 12mm x 60mm Tmpr-Evidence (100) Lbl

JG586A

- Supported on JC496A

See Configuration

NOTE:2

Configuration Rules:

- Note 1 If selected with a CTO Router Solution, Quantity 1 of JG674#B01, JG577A#B01 or JG578A#B01 must also be ordered.
- Note 2 If selected with a CTO Router Solution, Quantity 1 of JG576A#B01 must also be ordered.

Remarks: Each JG674A, JG575A, JG577A or JG578A would use 1 of JG585A.
Each JG576A would use 1 of JG586A.

Technical Specifications

HPE FlexNetwork HSR6602 G Router (JG353A)

I/O ports and slots	4 Combo GbE (SFP and RJ45) 1 port expansion module slot
Additional ports and slots	2 RJ-45 serial console ports 1 USB 2.0 1 RJ-45 out-of-band management port 1 Compact Flash port
Physical characteristics	Dimensions 17.32(w) x 18.9(d) x 3.46(h) in (44 x 48 x 8.8 cm) (2U height) Weight 26.68 lb (12.1 kg) shipping weight
Memory and processor	Processor Multi-core PowerPC @ 1500 MHz, 8 MB flash, 2 GB SDRAM, 512 MB compact flash
Mounting and enclosure	EIA standard 19 in. rack
Performance	IPv6 Ready Certified Latency 13.5 µs (FIFO 64-byte packets) Throughput up to 9 Mpps (64-byte packets) Switch fabric speed 80 Gbps Routing table size 1000000 entries (IPv4), 1000000 entries (IPv6) Forwarding table size 1000000 entries (IPv4), 1000000 entries (IPv6) Backplane bandwidth 80 Gbps
Environment	Operating temperature 32°F to 113°F (0°C to 45°C) Operating relative humidity 5% to 95%, noncondensing Altitude up to 13,123 ft (4 km)
Electrical characteristics	Frequency 50/60 Hz Maximum heat dissipation 505 BTU/hr (532.78 kJ/hr) Voltage 100 - 240 VAC, rated -48 to -60 VDC, rated (depending on power supply chosen) Maximum power rating 300 W Notes Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
Safety	UL 1950; UL 60950; CAN/CSA 22.2 No. 60950; EN 60825; AS/NZS 60950; KN 60950; GOST R MEK60950; IEC 60950; EN 60950; IEC 60825; ROHS Compliance
Emissions	VCCI Class A; EN 55022 Class A; CISPR 22 Class A; ICES-003 Class A; AS/NZS CISPR 22 Class A; CSA 2.22 60950; EN 61000-3-2; EN 61000-3-3; UL 60950; EN 60950-1; IEC 60950-1; FCC (CFR 47, Part 15) Subpart B Class A; ETSI EN 300 386 Class A; KN22 Class A; GB 9254 Class A; AS/NZS 60950-1

Technical Specifications

Immunity	Generic	ETSI EN 300 386 V1.3.3; KN24
	EN	EN 55024, CISPR 24
Management		command-line interface; out-of-band management; SNMP Manager; Telnet; RMON1; terminal interface (serial RS-232C); Ethernet Interface MIB
Services		Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE FlexNetwork HSR6602 XG Router (JG354A)

I/O ports and slots	4 Combo GbE (SFP and RJ45) 2 SFP+ 10GbE ports (IEEE 802.3ae Type 10GBASE-SR) 1 port expansion module slot
Additional ports and slots	2 RJ-45 serial console ports 1 USB 2.0 1 RJ-45 out-of-band management port 1 Compact Flash port
Physical characteristics	Dimensions 17.32(w) x 18.9(d) x 3.46(h) in (44 x 48 x 8.8 cm) (2U height) Weight 26.68 lb (12.1 kg) shipping weight
Memory and processor	Processor Multi-core PowerPC @ 1500 MHz, 8 MB flash, 4 GB SDRAM, 512 MB compact flash
Mounting and enclosure	EIA standard 19 in. rack
Performance	IPv6 Ready Certified Latency 13.5 µs (FIFO 64-byte packets) Throughput up to 15 Mpps (64-byte packets) Switch fabric speed 80 Gbps Routing table size 4000000 entries (IPv4), 2000000 entries (IPv6) Forwarding table size 1000000 entries (IPv4), 1000000 entries (IPv6) Backplane bandwidth 80 Gbps
Environment	Operating temperature 32°F to 113°F (0°C to 45°C) Operating relative humidity 5% to 95%, noncondensing Altitude up to 13,123 ft (4 km)
Electrical characteristics	Frequency 50/60 Hz Maximum heat dissipation 512 BTU/hr (540.16 kJ/hr) Voltage 100 - 240 VAC, rated -48 to -60 VDC, rated (depending on power supply chosen) Maximum power rating 300 W Notes Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.

Technical Specifications

Safety	UL 60950; CAN/CSA 22.2 No. 60950; EN 60825; AS/NZS 60950; GOST R MEK60950; IEC 60950; EN 60950; IEC 60825; ROHS Compliance
Emissions	VCCI Class A; EN 55022 Class A; CISPR 22 Class A; ICES-003 Class A; AS/NZS CISPR 22 Class A; CSA 2.22 60950; EN 61000-3-2; EN 61000-3-3; UL 60950; EN 60950-1; IEC 60950-1; FCC (CFR 47, Part 15) Subpart B Class A; ETSI EN 300 386 Class A; KN22 Class A; GB 9254 Class A; AS/NZS 60950-1
Immunity	Generic ETSI EN 300 386 V1.3.3; KN24 EN EN 55024, CISPR 24
Management	command-line interface; out-of-band management; SNMP Manager; Telnet; RMON1; terminal interface (serial RS-232C); Ethernet Interface MIB
Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

Standards and protocols (applies to all products in series)

BGP	RFC 1657 Definitions of Managed Objects for BGPv4 RFC 1772 Application of the BGP RFC 1773 Experience with the BGP-4 Protocol RFC 1774 BGP-4 Protocol Analysis RFC 1965 BGP-4 confederations RFC 1966 BGP Route Reflection An alternative to full mesh IBGP RFC 1997 BGP Communities Attribute RFC 1998 An Application of the BGP Community Attribute in Multi-home Routing RFC 2385 BGP Session Protection via TCP MD5 RFC 2439 BGP Route Flap Damping RFC 2842 Capability Advertisement with BGP-4 RFC 2858 BGP-4 Multi-Protocol Extensions RFC 2918 Route Refresh Capability RFC 4271 A Border Gateway Protocol 4 (BGP-4) RFC 4272 BGP Security Vulnerabilities Analysis RFC 4274 BGP-4 Protocol Analysis RFC 4275 BGP-4 MIB Implementation Survey RFC 4276 BGP-4 Implementation Report RFC 4277 Experience with the BGP-4 Protocol RFC 4360 BGP Extended Communities Attribute RFC 4451 BGP MULTI_EXIT_DISC (MED) Considerations RFC 4456 BGP Route Reflection: An Alternative to Full Mesh Internal BGP (IBGP) RFC 4486 Subcodes for BGP Cease Notification Message RFC 4724 Graceful Restart Mechanism for BGP RFC 4760 Multiprotocol Extensions for BGP-4 RFC 4893 BGP Support for Four-octet AS Number Space RFC 5065 Autonomous System Confederations for BGP RFC 5291 Outbound Route Filtering Capability for BGP-4 RFC 5292 Address-Prefix-Based Outbound Route Filter for BGP-4
------------	---

Technical Specifications

RFC 5398 Autonomous System (AS) Number Reservation for Documentation Use
RFC 5883 BFD for Multihop Paths

Denial of service protection

CPU DoS Protection
Rate Limiting by ACLs

Device Management

RFC 1155 Structure and Mgmt Information (SMIv1)
RFC 1157 SNMPv1/v2c
RFC 1305 NTPv3
RFC 1901 (Community based SNMPv2)
RFC 1901-1907 SNMPv2c, SMIv2 and Revised MIB-II
RFC 1902 (SNMPv2)
RFC 1908 (SNMP v1/2 Coexistence)
RFC 1945 Hypertext Transfer Protocol -- HTTP/1.0
RFC 2068 Hypertext Transfer Protocol -- HTTP/1.1
RFC 2271 Framework
RFC 2452 MIB for TCP6
RFC 2454 MIB for UDP6
RFC 2573 (SNMPv3 Applications)
RFC 2576 (Coexistence between SNMP V1, V2, V3)
RFC 2578-2580 SMIv2
RFC 2579 (SMIv2 Text Conventions)
RFC 2580 (SMIv2 Conformance)
RFC 2819 (RMON groups Alarm, Event, History and Statistics only)
RFC 2819 RMON
RFC 3410 (Management Framework)
RFC 3416 (SNMP Protocol Operations v2)
RFC 3417 (SNMP Transport Mappings)
Multiple Configuration Files
Multiple Software Images
SNMP v3 and RMON RFC support
SSHv1/SSHv2 Secure Shell
TACACS/TACACS+

General Protocols

IEEE 802.1ad Q-in-Q
IEEE 802.1ag Service Layer OAM
IEEE 802.1ah Provider Backbone Bridges
IEEE 802.1AX-2008 Link Aggregation
IEEE 802.1D MAC Bridges
IEEE 802.1p Priority
IEEE 802.1Q (GVRP)
IEEE 802.1Q VLANs
IEEE 802.1s (MSTP)
IEEE 802.1s Multiple Spanning Trees
IEEE 802.1v VLAN classification by Protocol and Port
IEEE 802.1w Rapid Reconfiguration of Spanning Tree
IEEE 802.1X PAE

Technical Specifications

IEEE 802.3 Type 10BASE-T
IEEE 802.3ab 1000BASE-T
IEEE 802.3ac (VLAN Tagging Extension)
IEEE 802.3ad Link Aggregation (LAG)
IEEE 802.3ad Link Aggregation Control Protocol (LACP)
IEEE 802.3ae 10-Gigabit Ethernet
IEEE 802.3ag Ethernet OAM
IEEE 802.3ah Ethernet in First Mile over Point to Point Fiber - EFMF
IEEE 802.3i 10BASE-T
IEEE 802.3u 100BASE-X
IEEE 802.3x Flow Control
IEEE 802.3z 1000BASE-X
RFC 768 UDP
RFC 783 TFTP Protocol (revision 2)
RFC 791 IP
RFC 792 ICMP
RFC 793 TCP
RFC 826 ARP
RFC 854 TELNET
RFC 855 Telnet Option Specification
RFC 856 TELNET
RFC 857 Telnet Echo Option
RFC 858 Telnet Suppress Go Ahead Option
RFC 894 IP over Ethernet
RFC 896 Congestion Control in IP/TCP Internetworks
RFC 906 TFTP Bootstrap
RFC 925 Multi-LAN Address Resolution
RFC 950 Internet Standard Subnetting Procedure
RFC 951 BOOTP
RFC 959 File Transfer Protocol (FTP)
RFC 1006 ISO transport services on top of the TCP: Version 3
RFC 1027 Proxy ARP
RFC 1034 Domain Concepts and Facilities
RFC 1035 Domain Implementation and Specification
RFC 1042 IP Datagrams
RFC 1058 RIPv1
RFC 1071 Computing the Internet Checksum
RFC 1091 Telnet Terminal-Type Option
RFC 1093 NSFNET routing architecture
RFC 1122 Host Requirements
RFC 1141 Incremental updating of the Internet checksum
RFC 1142 OSI IS-IS Intra-domain Routing Protocol
RFC 1144 Compressing TCP/IP headers for low-speed serial links
RFC 1191 Path MTU discovery
RFC 1195 OSI ISIS for IP and Dual Environments
RFC 1213 Management Information Base for Network Management of TCP/IP-based internets
RFC 1256 ICMP Router Discovery Protocol (IRDP)
RFC 1305 NTPv3

Technical Specifications

- RFC 1315 Management Information Base for Frame Relay DTEs
- RFC 1321 The MD5 Message-Digest Algorithm
- RFC 1332 The PPP Internet Protocol Control Protocol (IPCP)
- RFC 1333 PPP Link Quality Monitoring
- RFC 1334 PPP Authentication Protocols (PAP)
- RFC 1349 Type of Service
- RFC 1350 TFTP Protocol (revision 2)
- RFC 1377 The PPP OSI Network Layer Control Protocol (OSINLCP)
- RFC 1381 SNMP MIB Extension for X.25 LAPB
- RFC 1382 SNMP MIB Extension for the X.25 Packet Layer
- RFC 1471 The Definitions of Managed Objects for the Link Control Protocol of the Point-to-Point Protocol
- RFC 1473 The Definitions of Managed Objects for the IP Network Control Protocol of the Point-to-Point Protocol
- RFC 1483 Multiprotocol Encapsulation over ATM Adaptation Layer 5
- RFC 1490 Multiprotocol Interconnect over Frame Relay
- RFC 1519 CIDR
- RFC 1534 DHCP/BOOTP Interoperation
- RFC 1542 BOOTP Extensions
- RFC 1542 Clarifications and Extensions for the Bootstrap Protocol
- RFC 1552 The PPP Internetworking Packet Exchange Control Protocol (IPXCP)
- RFC 1577 Classical IP and ARP over ATM
- RFC 1613 Cisco Systems X.25 over TCP (XOT)
- RFC 1619 PPP over SONET/SDH (Synchronous Optical Network/Synchronous Digital Hierarchy)
- RFC 1624 Incremental Internet Checksum
- RFC 1631 NAT
- RFC 1638 PPP Bridging Control Protocol (BCP)
- RFC 1661 The Point-to-Point Protocol (PPP)
- RFC 1662 PPP in HDLC-like Framing
- RFC 1695 Definitions of Managed Objects for ATM Management Version 8.0 using SMIv2
- RFC 1700 Assigned Numbers
- RFC 1701 Generic Routing Encapsulation
- RFC 1702 Generic Routing Encapsulation over IPv4 networks
- RFC 1721 RIP-2 Analysis
- RFC 1722 RIP-2 Applicability
- RFC 1723 RIP v2
- RFC 1795 Data Link Switching: Switch-to-Switch Protocol AIW DLSw RIG: DLSw Closed Pages, DLSw Standard Version 1
- RFC 1812 IPv4 Routing
- RFC 1829 The ESP DES-CBC Transform
- RFC 1853 IP in IP Tunneling
- RFC 1877 PPP Internet Protocol Control Protocol Extensions for Name Server Addresses
- RFC 1944 Benchmarking Methodology for Network Interconnect Devices
- RFC 1945 Hypertext Transfer Protocol -- HTTP/1.0
- RFC 1973 PPP in Frame Relay
- RFC 1974 PPP Stac LZS Compression Protocol
- RFC 1981 Path MTU Discovery for IP version 6
- RFC 1990 The PPP Multilink Protocol (MP)

Technical Specifications

- RFC 1994 PPP Challenge Handshake Authentication Protocol (CHAP)
- RFC 2003 IP Encapsulation within IP
- RFC 2082 RIP-2 MD5 Authentication
- RFC 2091 Trigger RIP
- RFC 2104 HMAC: Keyed-Hashing for Message Authentication
- RFC 2131 DHCP
- RFC 2132 DHCP Options and BOOTP Vendor Extensions
- RFC 2138 Remote Authentication Dial In User Service (RADIUS)
- RFC 2205 Resource ReSerVation Protocol (RSVP) - Version 1 Functional Specification
- RFC 2209 Resource ReSerVation Protocol (RSVP) -- Version 1 Message Processing Rules
- RFC 2225 Classical IP and ARP over ATM
- RFC 2236 IGMP Snooping
- RFC 2246 The TLS Protocol Version 1.0
- RFC 2251 Lightweight Directory Access Protocol (v3)
- RFC 2252 Lightweight Directory Access Protocol (v3): Attribute Syntax Definitions
- RFC 2283 MBGP
- RFC 2284 EAP over LAN
- RFC 2338 VRRP
- RFC 2364 PPP Over AAL5
- RFC 2374 An Aggregatable Global Unicast Address Format
- RFC 2390 Inverse Address Resolution Protocol
- RFC 2427 Multiprotocol Interconnect over Frame Relay
- RFC 2451 The ESP CBC-Mode Cipher Algorithms
- RFC 2453 RIPv2
- RFC 2510 Internet X.509 Public Key Infrastructure Certificate Management Protocols
- RFC 2514 Definitions of Textual Conventions and OBJECT-IDENTITIES for ATM Management
- RFC 2515 Definitions of Managed Objects for ATM Management
- RFC 2516 A Method for Transmitting PPP Over Ethernet (PPPoE)
- RFC 2519 A Framework for Inter-Domain Route Aggregation
- RFC 2529 Transmission of IPv6 over IPv4 Domains without Explicit Tunnels
- RFC 2544 Benchmarking Methodology for Network Interconnect Devices
- RFC 2581 TCP Congestion Control
- RFC 2615 PPP over SONET/SDH (Synchronous Optical Network/Synchronous Digital Hierarchy)
- RFC 2616 HTTP Compatibility v1.1
- RFC 2617 HTTP Authentication: Basic and Digest Access Authentication
- RFC 2622 Routing Policy Specification Language (RPSL)
- RFC 2644 Directed Broadcast Control
- RFC 2661 L2TP
- RFC 2663 NAT Terminology and Considerations
- RFC 2684 Multiprotocol Encapsulation over ATM Adaptation Layer 5
- RFC 2694 DNS extensions to Network Address Translators (DNS_ALG)
- RFC 2702 Requirements for Traffic Engineering Over MPLS
- RFC 2716 PPP EAP TLS Authentication Protocol
- RFC 2747 RSVP Cryptographic Authentication
- RFC 2763 Dynamic Name-to-System ID mapping
- RFC 2765 Stateless IP/ICMP Translation Algorithm (SIIT)
- RFC 2766 Network Address Translation - Protocol Translation (NAT-PT)
- RFC 2782 A DNS RR (DNS Resource Record) for specifying the location of services (DNS SRV) Domain

Technical Specifications

- Name System Server
- RFC 2784 Generic Routing Encapsulation (GRE)
- RFC 2787 Definitions of Managed Objects for VRRP
- RFC 2833 RTP Payload for DTMF Digits, Telephony Tones and Telephony Signals
- RFC 2856 Textual Conventions for Additional High Capacity Data Types
- RFC 2865 Remote Authentication Dial In User Service (RADIUS)
- RFC 2866 RADIUS Accounting
- RFC 2868 RADIUS Attributes for Tunnel Protocol Support
- RFC 2869 RADIUS Extensions
- RFC 2878 PPP Bridging Control Protocol (BCP)
- RFC 2915 The Naming Authority Pointer (NAPTR) DNS Resource Record
- RFC 2916 E.164 number and DNS P. Faltstrom
- RFC 2961 RSVP Refresh Overhead Reduction Extensions
- RFC 2965 HTTP State Management Mechanism
- RFC 2966 Domain-wide Prefix Distribution with Two-Level IS-IS
- RFC 2973 IS-IS Mesh Groups
- RFC 2976 The SIP INFO Method
- RFC 3022 Traditional IP Network Address Translator (Traditional NAT)
- RFC 3027 Protocol Complications with the IP Network Address Translator
- RFC 3031 Multiprotocol Label Switching Architecture
- RFC 3032 MPLS Label Stack Encoding
- RFC 3036 LDP Specification
- RFC 3046 DHCP Relay Agent Information Option
- RFC 3063 MPLS Loop Prevention Mechanism
- RFC 3065 Support AS confederation
- RFC 3137 OSPF Stub Router Advertisement
- RFC 3209 RSVP-TE Extensions to RSVP for LSP Tunnels
- RFC 3210 Applicability Statement for Extensions to RSVP for LSP-Tunnels
- RFC 3212 Constraint-Based LSP setup using LDP (CR-LDP)
- RFC 3214 LSP Modification Using CR-LDP
- RFC 3215 LDP State Machine
- RFC 3246 Expedited Forwarding PHB
- RFC 3268 Advanced Encryption Standard (AES) Ciphersuites for Transport Layer Security (TLS)
- RFC 3272 Overview and Principles of Internet Traffic Engineering
- RFC 3277 IS-IS Transient Blackhole Avoidance
- RFC 3279 Algorithms and Identifiers for the Internet X.509 Public Key Infrastructure Certificate and Certificate Revocation List (CRL) Profile
- RFC 3280 Internet X.509 Public Key Infrastructure Certificate and Certificate Revocation List (CRL) Profile
- RFC 3359 Reserved Type, Length and Value (TLV) Codepoints in Intermediate System to Intermediate System
- RFC 3392 Support BGP capabilities advertisement
- RFC 3410 Applicability Statements for SNMP
- RFC 3416 Protocol Operations for SNMP
- RFC 3417 Transport Mappings for the Simple Network Management Protocol (SNMP)
- RFC 3442 The Classless Static Route Option for Dynamic Host Configuration Protocol (DHCP) version 4
- RFC 3479 Fault Tolerance for the Label Distribution Protocol (LDP)

Technical Specifications

- RFC 3509 OSPF ABR Behavior
- RFC 3526 More Modular Exponential (MODP) Diffie-Hellman groups for Internet Key Exchange (IKE)
- RFC 3562 Key Management Considerations for the TCP MD5 Signature Option
- RFC 3564 Requirements for Support of Differentiated Services-aware MPLS Traffic Engineering
- RFC 3567 Intermediate System to Intermediate System (IS-IS) Cryptographic Authentication
- RFC 3590 Source Address Selection for the Multicast Listener Discovery (MLD) Protocol
- RFC 3602 The AES-CBC Cipher Algorithm and Its Use with IPsec
- RFC 3623 Graceful OSPF Restart
- RFC 3706 A Traffic-Based Method of Detecting Dead Internet Key Exchange (IKE) Peers
- RFC 3768 Virtual Router Redundancy Protocol (VRRP)
- RFC 3784 ISIS TE support
- RFC 3786 Extending the Number of IS-IS LSP Fragments Beyond the 256 Limit
- RFC 3811 Definitions of Textual Conventions (TCs) for Multiprotocol Label Switching (MPLS) Management
- RFC 3812 Multiprotocol Label Switching (MPLS) Traffic Engineering (TE) Management Information Base (MIB)
- RFC 3847 Restart signaling for IS-IS
- RFC 3879 Deprecating Site Local Addresses
- RFC 3906 Calculating Interior Gateway Protocol (IGP) Routes Over Traffic Engineering Tunnels
- RFC 3917 Requirements for IP Flow Information Export (IPFIX)
- RFC 3954 Cisco Systems NetFlow Services Export Version 9
- RFC 4213 Basic IPv6 Transition Mechanisms
- RFC 4884 Extended ICMP to Support Multi-Part Messages
- RFC 5082 The Generalized TTL Security Mechanism (GTSM)
- RFC 5286 Basic Specification for IP Fast Reroute: Loop-Free Alternates
- RFC 5880 Bidirectional Forwarding Detection
- RFC 5882 Generic Application of BFD

IP Multicast

- RFC 1112 IGMP
- RFC 2236 IGMPv2
- RFC 2283 Multiprotocol Extensions for BGP-4
- RFC 2362 PIM Sparse Mode
- RFC 2365 Administratively Scoped IP Multicast
- RFC 2934 Protocol Independent Multicast MIB for IPv4
- RFC 3376 IGMPv3
- RFC 3446 Anycast Rendezvous Point (RP) mechanism using Protocol Independent Multicast (PIM) and Multicast Source Discovery Protocol (MSDP)
- RFC 3569 An Overview of Source-Specific Multicast (SSM)
- RFC 3618 Multicast Source Discovery Protocol (MSDP)
- RFC 3973 PIM Dense Mode
- RFC 4601 PIM Sparse Mode
- RFC 4604 Using Internet Group Management Protocol Version 3 (IGMPv3) and Multicast Listener Discovery Protocol Version 2 (MLDv2) for Source-Specific Multicast
- RFC 4605 IGMP/MLD Proxying
- RFC 4607 Source-Specific Multicast for IP
- RFC 4608 Source-Specific Protocol Independent Multicast in 232/8 (PIM SSM)
- RFC 4611 Multicast Source Discovery Protocol (MSDP) Deployment Scenarios

Technical Specifications

RFC 4950 ICMP Extensions for Multiprotocol Label Switching
RFC 5015 Bidirectional Protocol Independent Multicast (BIDIR-PIM)
RFC 5059 Bootstrap Router (BSR) Mechanism for Protocol Independent Multicast (PIM)
RFC 5060 Protocol Independent Multicast MIB
RFC 5240 Protocol Independent Multicast (PIM) Bootstrap Router MIB

IPv6

RFC 1350 TFTP
RFC 1886 DNS Extension for IPv6
RFC 1887 IPv6 Unicast Address Allocation Architecture
RFC 1981 IPv6 Path MTU Discovery
RFC 2080 RIPng for IPv6
RFC 2292 Advanced Sockets API for IPv6
RFC 2373 IPv6 Addressing Architecture
RFC 2375 IPv6 Multicast Address Assignments
RFC 2460 IPv6 Specification
RFC 2461 IPv6 Neighbor Discovery
RFC 2462 IPv6 Stateless Address Auto-configuration
RFC 2463 ICMPv6
RFC 2464 Transmission of IPv6 over Ethernet Networks
RFC 2472 IP Version 6 over PPP
RFC 2473 Generic Packet Tunneling in IPv6
RFC 2475 IPv6 DiffServ Architecture
RFC 2529 Transmission of IPv6 Packets over IPv4
RFC 2545 Use of MP-BGP-4 for IPv6
RFC 2553 Basic Socket Interface Extensions for IPv6
RFC 2710 Multicast Listener Discovery (MLD) for IPv6
RFC 2711 IPv6 Router Alert Option
RFC 2740 OSPFv3 for IPv6
RFC 2893 Transition Mechanisms for IPv6 Hosts and Routers
RFC 2894 Router Renumbering for IPv6
RFC 2925 Definitions of Managed Objects for Remote Ping, Traceroute, and Lookup Operations (Ping only)
RFC 3056 Connection of IPv6 Domains via IPv4 Clouds
RFC 3162 RADIUS and IPv6
RFC 3306 Unicast-Prefix-based IPv6 Multicast Addresses (v2 models only)
RFC 3307 IPv6 Multicast Address Allocation
RFC 3315 DHCPv6 (client and relay)
RFC 3363 DNS support
RFC 3484 Default Address Selection for IPv6
RFC 3493 Basic Socket Interface Extensions for IPv6 (v2 models only)
RFC 3513 IPv6 Addressing Architecture
RFC 3542 Advanced Sockets API for IPv6
RFC 3587 IPv6 Global Unicast Address Format
RFC 3596 DNS Extension for IPv6
RFC 3646 DNS Configuration options for Dynamic Host Configuration Protocol for IPv6
RFC 3736 Stateless Dynamic Host Configuration Protocol (DHCP) Service for IPv6
RFC 3810 MLDv2 (host joins only)

Technical Specifications

RFC 3810 MLDv2 for IPv6
RFC 3810 Multicast Listener Discovery Version 2 (MLDv2) for IPv6
RFC 3956 Embedding the Rendezvous Point (RP) Address in an IPv6 Multicast Address
RFC 4001 Textual Conventions for Internet Network Addresses
RFC 4007 IPv6 Scoped Address Architecture
RFC 4022 MIB for TCP
RFC 4113 MIB for UDP
RFC 4251 SSHv6 Architecture
RFC 4252 SSHv6 Authentication
RFC 4252 SSHv6 Transport Layer
RFC 4253 SSHv6 Transport Layer
RFC 4254 SSHv6 Connection
RFC 4291 IP Version 6 Addressing Architecture
RFC 4293 MIB for IP
RFC 4419 Key Exchange for SSH
RFC 4443 ICMPv6
RFC 4541 IGMP & MLD Snooping Switch
RFC 4552 Authentication/Confidentiality for OSPFv3
RFC 4798 Connecting IPv6 Islands over IPv4 MPLS Using IPv6 Provider Edge Routers (6PE)
RFC 4861 IPv6 Neighbor Discovery
RFC 4862 IPv6 Stateless Address Auto-configuration
RFC 4940 IANA Considerations for OSPF
RFC 5072 IP Version 6 over PPP
RFC 5095 Deprecation of Type 0 Routing Headers in IPv6
RFC 5340 OSPF for IPv6
RFC 5340 OSPFv3 for IPv6
RFC 5722 Handling of Overlapping IPv6 Fragments
RFC 5881 BFD for IPv4 and IPv6 (Single Hop)

MIBs

IEEE 8021-PAE-MIB
IEEE 8023-LAG-MIB
RFC 1156 (TCP/IP MIB)
RFC 1212 Concise MIB Definitions
RFC 1213 MIB II
RFC 1229 Interface MIB Extensions
RFC 1286 Bridge MIB
RFC 1493 Bridge MIB
RFC 1573 SNMP MIB II
RFC 1643 Ethernet MIB
RFC 1650 Ethernet-Like MIB
RFC 1657 BGP-4 MIB
RFC 1724 RIPv2 MIB
RFC 1757 Remote Network Monitoring MIB
RFC 1850 OSPFv2 MIB
RFC 1907 SNMPv2 MIB
RFC 2011 SNMPv2 MIB for IP
RFC 2012 SNMPv2 MIB for TCP

Technical Specifications

RFC 2013 SNMPv2 MIB for UDP
RFC 2021 RMONv2 MIB
RFC 2096 IP Forwarding Table MIB
RFC 2233 Interfaces MIB
RFC 2273 SNMP-NOTIFICATION-MIB
RFC 2452 IPV6-TCP-MIB
RFC 2454 IPV6-UDP-MIB
RFC 2465 IPv6 MIB
RFC 2466 ICMPv6 MIB
RFC 2571 SNMP Framework MIB
RFC 2572 SNMP-MPD MIB
RFC 2574 SNMP USM MIB
RFC 2618 RADIUS Client MIB
RFC 2620 RADIUS Accounting Client MIB
RFC 2665 Ethernet-Like-MIB
RFC 2668 802.3 MAU MIB
RFC 2674 802.1p and IEEE 802.1Q Bridge MIB
RFC 2688 MAU-MIB
RFC 2737 Entity MIB (Version 2)
RFC 2787 VRRP MIB
RFC 2819 RMON MIB
RFC 2863 The Interfaces Group MIB
RFC 2925 Ping MIB
RFC 2932IP (Multicast Routing MIB)
RFC 2933 IGMP MIB
RFC 3273 HC-RMON MIB
RFC 3414 SNMP-User based-SM MIB
RFC 3415 SNMP-View based-ACM MIB
RFC 3418 MIB for SNMPv3
RFC 3813 MPLS LSR MIB
RFC 3814 MPLS FTN MIB
RFC 3815 MPLS LDP MIB
RFC 3826 AES for SNMP's USM MIB
RFC 4113 UDP MIB
RFC 4133 Entity MIB (Version 3)
RFC 4221 MPLS FTN MIB
LLDP-EXT-DOT1-MIB
LLDP-EXT-DOT3-MIB
LLDP-MIB

MPLS

RFC 3037 LDP (Label Distribution Protocol) Applicability
RFC 3270 Multi-Protocol Label Switching (MPLS) Support of Differentiated Services
RFC 3429 Assignment of the 'OAM Alert Label' for Multiprotocol Label Switching
RFC 3443 Time To Live (TTL) Processing in Multi-Protocol Label Switching (MPLS) Networks
RFC 3478 Graceful Restart Mechanism for Label Distribution Protocol
RFC 3612 Applicability Statement for Restart Mechanisms for the Label Distribution
RFC 3916 Requirements for Pseudo-Wire Emulation Edge-to-Edge (PWE3)

Technical Specifications

- RFC 3985 Pseudo Wire Emulation Edge-to-Edge (PWE3) Architecture
- RFC 4023 Encapsulating MPLS in IP or Generic Routing Encapsulation (GRE)
- RFC 4090 Fast Reroute Extensions to RSVP-TE for LSP Tunnels
- RFC 4105 Requirements for Inter-Area MPLS Traffic Engineering
- RFC 4124 Protocol Extensions for Support of Diffserv-aware MPLS Traffic Engineering
- RFC 4125 Maximum Allocation Bandwidth Constraints Model for Diffserv-aware MPLS Traffic
- RFC 4127 Russian Dolls Bandwidth Constraints Model for Diffserv-aware MPLS Traffic
- RFC 4182 Removing a Restriction on the use of MPLS Explicit NULL
- RFC 4216 MPLS Inter-Autonomous System (AS) Traffic Engineering (TE) Requirements
- RFC 4364 BGP/MPLS IP Virtual Private Networks (VPNs)
- RFC 4365 Applicability Statement for BGP/MPLS IP Virtual Private Networks (VPNs)
- RFC 4381 Analyses of the Security of BGP/MPLS IP VPNs
- RFC 4385 Pseudowire Emulation Edge-to-Edge (PWE3) Control Word for Use over an MPLS PSN
- RFC 4446 IANA Allocations for Pseudowire Edge to Edge Emulation (PWE3)
- RFC 4448 Encapsulation Methods for Transport of Ethernet over MPLS Networks
- RFC 4576 Using a Link State Advertisement (LSA) Options Bit to Prevent Looping in BGP/MPLS
- RFC 4618 Encapsulation Methods for Transport of PPP/High-Level Data Link Control (HDLC) over MPLS Networks
- RFC 4619 Encapsulation Methods for Transport of Frame Relay over Multiprotocol Label
- RFC 4659 BGP-MPLS IP Virtual Private Network (VPN) Extension for IPv6 VPN
- RFC 4664 Framework for Layer 2 Virtual Private Networks
- RFC 4665 Service Requirements for Layer 2 Provider Provisioned Virtual Private Networks
- RFC 4717 Encapsulation Methods for Transport of Asynchronous Transfer Mode (ATM) over MPLS
- RFC 4761 Virtual Private LAN Service (VPLS) Using BGP for Auto-Discovery and Signaling
- RFC 4762 Virtual Private LAN Service (VPLS) Using Label Distribution Protocol (LDP) Signaling
- RFC 4764 Framework for Layer 2 Virtual Private Networks (L2VPNs)
- RFC 4765 Service Requirements for Layer 2 Provider Provisioned Virtual Private Networks
- RFC 4816 Pseudowire Emulation Edge-to-Edge (PWE3) Asynchronous Transfer Mode (ATM)
- RFC 4941 Privacy Extensions for Stateless Address Autoconfiguration in IPv6
- RFC 5085 Pseudowire Virtual Circuit Connectivity Verification (VCCV): A Control Channel
- RFC 5443 LDP IGP Synchronization
- RFC 5601 Pseudowire (PW) Management Information Base (MIB)
- RFC 5602 Pseudowire (PW) over MPLS PSN Management Information Base (MIB)

Network Management

- IEEE 802.1AB Link Layer Discovery Protocol (LLDP)
- IEEE 802.1D (STP)
- RFC 1098 A Simple Network Management Protocol (SNMP)
- RFC 1155 Structure of Management Information
- RFC 1157 SNMPv1
- RFC 1215 SNMP Generic traps
- RFC 1757 RMON 4 groups: Stats, History, Alarms and Events
- RFC 1901 SNMPv2 Introduction
- RFC 1902 SNMPv2 Structure
- RFC 1903 SNMPv2 Textual Conventions
- RFC 1904 SNMPv2 Conformance
- RFC 1905 SNMPv2 Protocol Operations
- RFC 1906 SNMPv2 Transport Mappings

Technical Specifications

- RFC 1918 Private Internet Address Allocation
- RFC 2272 SNMPv3 Management Protocol
- RFC 2273 SNMPv3 Applications
- RFC 2274 USM for SNMPv3
- RFC 2275 VACM for SNMPv3
- RFC 2570 SNMPv3 Overview
- RFC 2571 SNMP Management Frameworks
- RFC 2572 SNMPv3 Message Processing
- RFC 2573 SNMPv3 Applications
- RFC 2574 SNMPv3 User-based Security Model (USM)
- RFC 2575 SNMPv3 View-based Access Control Model (VACM)
- RFC 2575 VACM for SNMP
- RFC 2576 Coexistence between SNMP versions
- RFC 2578 SMIv2
- RFC 2819 Four groups of RMON: 1 (statistics), 2 (history), 3 (alarm) and 9 (events)
- RFC 2819 Remote Network Monitoring Management Information Base
- RFC 3164 BSD syslog Protocol
- RFC 3176 sFlow
- RFC 3411 SNMP Management Frameworks
- RFC 3412 SNMPv3 Message Processing
- RFC 3413 Simple Network Management Protocol (SNMP) Applications
- RFC 3414 SNMPv3 User-based Security Model (USM)
- RFC 3415 SNMPv3 View-based Access Control Model (VACM)
- RFC 3584 Coexistence between Version 1 and Version 2 of the Internet-standard Network
- RFC 3593 Textual Conventions for MIB Modules Using Performance History Based on 15 Minute
- RFC 3636 Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs)
- RFC 4292 IP Forwarding Table MIB
- RFC 4502 Remote Network Monitoring Management Information Base Version 2
- RFC 4878 Definitions and Managed Objects for Operations, Administration, and Maintenance (OAM) Functions on
- ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)
- SNMPv1/v2
- SNMPv1/v2c
- SNMPv1/v2c (read only)
- SNMPv1/v2c/v3

OSPF

- RFC 1245 OSPF protocol analysis
- RFC 1246 Experience with OSPF
- RFC 1253 OSPFv2 MIB
- RFC 1583 OSPFv2
- RFC 1587 OSPF NSSA
- RFC 1745 OSPF Interactions
- RFC 1765 OSPF Database Overflow
- RFC 1850 OSPFv2 Management Information Base (MIB), traps
- RFC 2154 OSPF w/ Digital Signatures (Password, MD-5)
- RFC 2178 OSPFv2
- RFC 2328 OSPFv2

Technical Specifications

- RFC 2370 OSPF Opaque LSA Option
- RFC 3101 OSPF NSSA
- RFC 3623 Graceful OSPF Restart
- RFC 3630 Traffic Engineering Extensions to OSPF Version 2
- RFC 4061 Benchmarking Basic OSPF Single Router Control Plane Convergence
- RFC 4062 OSPF Benchmarking Terminology and Concepts
- RFC 4063 Considerations When Using Basic OSPF Convergence Benchmarks
- RFC 4222 Prioritized Treatment of Specific OSPF Version 2 Packets and Congestion Avoidance
- RFC 4577 OSPF as the Provider/Customer Edge Protocol for BGP/MPLS IP Virtual Private Networks (VPNs)
- RFC 4811 OSPF Out-of-Band LSDB Resynchronization
- RFC 4812 OSPF Restart Signaling
- RFC 4813 OSPF Link-Local Signaling
- RFC 5187 OSPFv3 Graceful Restart
- RFC 5340 OSPF for IPv6
- RFC 5340 OSPFv3 for IPv6
- RFC 5613 OSPF Link-Local Signaling

QoS/CoS

- IEEE 802.1p (CoS)
- RFC 2309 Recommendations on queue management and congestion avoidance in the Internet
- RFC 2474 DiffServ Precedence, including 8 queues/port
- RFC 2474 DiffServ precedence, with 4 queues per port
- RFC 2474 DS Field in the IPv4 and IPv6 Headers
- RFC 2474 DSCP DiffServ
- RFC 2474, with 4 queues per port
- RFC 2475 DiffServ Architecture
- RFC 2597 DiffServ Assured Forwarding (AF)
- RFC 2597 DiffServ Assured Forwarding (AF)- partial support
- RFC 2598 DiffServ Expedited Forwarding (EF)
- RFC 2697 A Single Rate Three Color Marker
- RFC 2698 A Two Rate Three Color Marker
- RFC 2751 Signaled Preemption Priority Policy Element
- RFC 3247 Supplemental Information for the New Definition of the EF PHB (Expedited Forwarding Per-Hop Behavior)
- RFC 3260 New Terminology and Clarifications for DiffServ
- RFC 3662 A Lower Effort Per-Domain Behavior (PDB) for Differentiated Services
- RFC 4594 Configuration Guidelines for DiffServ Service Classes

Security

- IEEE 802.1X Port Based Network Access Control
- RFC 1321 The MD5 Message-Digest Algorithm
- RFC 1492 TACACS+
- RFC 2082 RIP-2 MD5 Authentication
- RFC 2104 Keyed-Hashing for Message Authentication
- RFC 2138 RADIUS Authentication
- RFC 2139 RADIUS Accounting
- RFC 2209 RSVP-Message Processing
- RFC 2246 Transport Layer Security (TLS)

Technical Specifications

RFC 2408 Internet Security Association and Key Management Protocol (ISAKMP)
RFC 2409 The Internet Key Exchange (IKE)
RFC 2459 Internet X.509 Public Key Infrastructure Certificate and CRL Profile
RFC 2548 Microsoft Vendor-specific RADIUS Attributes
RFC 2716 PPP EAP TLS Authentication Protocol
RFC 2818 HTTP Over TLS
RFC 2865 RADIUS (client only)
RFC 2865 RADIUS Authentication
RFC 2866 RADIUS Accounting
RFC 2867 RADIUS Accounting Modifications for Tunnel Protocol Support
RFC 2868 RADIUS Attributes for Tunnel Protocol Support
RFC 2869 RADIUS Extensions
RFC 2993 Architectural Implications of NAT
RFC 3567 Intermediate System (IS) to IS Cryptographic Authentication
RFC 3576 Dynamic Authorization Extensions to RADIUS
RFC 3579 RADIUS Support For Extensible Authentication Protocol (EAP)
RFC 3580 IEEE 802.1X Remote Authentication Dial In User Service (RADIUS) Usage Guidelines
RFC 4250 The Secure Shell (SSH) Protocol Assigned Numbers
RFC 5214 Intra-Site Automatic Tunnel Addressing Protocol (ISATAP)
Access Control Lists (ACLs)
Guest VLAN for 802.1X
MAC Authentication
Port Security
Secure Sockets Layer (SSL)
SSHv1 Secure Shell
SSHv1.5 Secure Shell
SSHv1/SSHv2 Secure Shell
SSHv2 Secure Shell

VPN

RFC 2403 - HMAC-MD5-96
RFC 2404 - HMAC-SHA1-96
RFC 2405 - DES-CBC Cipher algorithm
RFC 2407 - Domain of interpretation
RFC 2547 BGP/MPLS VPNs
RFC 2764 A Framework for IP Based Virtual Private Networks
RFC 2796 BGP Route Reflection - An Alternative to Full Mesh IBGP
RFC 2842 Capabilities Advertisement with BGP-4
RFC 2858 Multiprotocol Extensions for BGP-4
RFC 2917 A Core MPLS IP VPN Architecture
RFC 2918 Route Refresh Capability for BGP-4
RFC 3107 Carrying Label Information in BGP-4
RFC 4302 - IP Authentication Header (AH)
RFC 4303 - IP Encapsulating Security Payload (ESP)
RFC 4305 - Cryptographic Algorithm Implementation Requirements for ESP and AH

IPSec

RFC 1828 IP Authentication using Keyed MD5
RFC 2401 IP Security Architecture

Technical Specifications

RFC 2402 IP Authentication Header
RFC 2406 IP Encapsulating Security Payload
RFC 2407 - Domain of interpretation
RFC 2408 - Internet Security Association and Key Management Protocol (ISAKMP)
RFC 2409 - The Internet Key Exchange
RFC 2410 - The NULL Encryption Algorithm and its use with IPSec
RFC 2411 IP Security Document Roadmap
RFC 2412 – OAKLEY
RFC 2865 - Remote Authentication Dial In User Service (RADIUS)
RFC 4835 Cryptographic Algorithm Implementation Requirements for Encapsulating Security

IKEv1

RFC 2865 - Remote Authentication Dial In User Service (RADIUS)
RFC 3748 - Extensible Authentication Protocol (EAP)
RFC 4109 Algorithms for Internet Key Exchange version 1 (IKEv1)

PKI

RFC 5280 Internet X.509 Public Key Infrastructure Certificate and Certificate Revocation List (CRL) Profile

Accessories

HPE HSR6600 Router Series accessories

Modules

HPE FlexNetwork 6600 16-port GbE SFP and 12-port Combo GbE Service Aggregation Platform Module	JH138A
HPE FlexNetwork 6600 16-port GbE SFP 4-port GbE Combo and 2-port 10GbE SFP+Svc Agg Pltfrm Mod	JH139A

Transceivers

HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A
HPE X115 100M SFP LC FX Transceiver	JD102B
HPE X110 100M SFP LC LX Transceiver	JD120B
HPE X120 622M SFP LC LX 15km Transceiver	JF829A
HPE X120 622M SFP LC LH 40km 1310 Transceiver	JF830A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X135 10G XFP LC ER Transceiver	JD121A
HPE X130 10G XFP LC LR Single Mode 10km 1310nm Transceiver	JD108B
HPE X130 10G XFP LC SR Transceiver	JD117B
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A

Cables

HPE FlexNetwork X200 V.24 DTE 3m Serial Port Cable	JD519A
HPE FlexNetwork X200 V.24 DCE 3m Serial Port Cable	JD521A
HPE FlexNetwork X200 V.35 DTE 3m Serial Port Cable	JD523A
HPE FlexNetwork X200 V.35 DCE 3m Serial Port Cable	JD525A
HPE FlexNetwork X260 RS449 3m DTE Serial Port Cable	JF825A
HPE FlexNetwork X260 RS449 3m DCE Serial Port Cable	JF826A
HPE FlexNetwork X260 RS530 3m DTE Serial Port Cable	JF827A
HPE FlexNetwork X260 RS530 3m DCE Serial Port Cable	JF828A
HPE FlexNetwork X260 8E1 BNC 75 ohm 3m Router Cable	JD512A
HPE FlexNetwork X260 E1 RJ45 BNC 75-120 ohm Conversion Router Cable	JD511A

Accessories

Power Supply

HPE 5800 300W AC Power Supply	JC087A
HPE 5800 300W DC Power Supply	JC090A

Fan Tray

HPE FlexNetwork HSR6602 Router Spare Fan Assembly	JG359A
---	--------

Router Modules

HPE FlexNetwork 6600 8-port 10/100BASE-T HIM Module	JC575A
HPE FlexNetwork 6600 4GbE WAN HIM Router Module	JC163A
HPE FlexNetwork 6600 8GbE WAN HIM Router Module	JC164A
HPE FlexNetwork 6600 4-port GbE SFP HIM Router Module	JC171A
HPE FlexNetwork 6600 8-port GbE SFP HIM Router Module	JC174A
HPE FlexNetwork 6600 1-port 10GbE XFP HIM Router Module	JC168A
HP 6600 1-port OC-3 (E1/T1) CPOS HIM Router Module	JC161A
HPE FlexNetwork 6600 2-port OC-3 E1/T1 CPOS HIM Router Module	JC162A
HPE FlexNetwork 6600 4-port OC-3/2-port OC-12 POS HIM Router Module	JC172A
HPE FlexNetwork 6600 2-port OC-3/1-port OC-12 POS HIM Router Module	JC173A
HPE FlexNetwork 6600 1-port OC-3c/STM-1c ATM HIM Router Module	JC175A
HP 6600 1-port OC-48/STM-16 POS (SFP) Router Module	JC494A
HPE FlexNetwork MSR 2-port Enhanced Serial MIM Module	JD540A
HPE FlexNetwork 6600 8-port Fractional T1 MIM Router Module	JC159A
HPE FlexNetwork 6600 8-port T1 MIM Router Module	JC160A
HPE FlexNetwork MSR 4-port Enhanced Serial MIM Module	JD541A
HPE FlexNetwork MSR 8-port Sync/Async Interface Enhanced Module	JD552A
HP MSR 8-port E1/CE1/PRI (75ohm) MIM Module	JD563A
HPE MSR 8-port Fractional E1 MIM Module	JF255A
HPE FlexNetwork 6600 FIP-10 Flexible Interface Platform Router Module	JG357A
HPE FlexNetwork 6600 FIP-20 Flexible Interface Platform Router Module	JG358A

Memory

HPE X610 2G VLP DDR3 SDRAM Memory	JG482A
-----------------------------------	--------

HPE FlexNetwork HSR6602 G Router (JG353A)

HPE FlexNetwork HSR6800 16-port GbE SFP HIM Module	JH142A
HPE FlexNetwork HSR6800 2-port 10GbE SFP+ HIM Module	JH143A

HPE FlexNetwork HSR6602 XG Router (JG354A)

HPE FlexNetwork HSR6800 16-port GbE SFP HIM Module	JH142A
HPE FlexNetwork HSR6800 2-port 10GbE SFP+ HIM Module	JH143A

Accessory Product Details

NOTE: Details are not available for all accessories. The following specifications were available at the time of publication.

HPE X125 1G SFP LC LH40 1310nm Transceiver (JD061A) A small form-factor pluggable SFP Gigabit LH40 transceiver that provides a full duplex Gigabit solution up to 40km on a single-mode fiber.	Ports	1 LC 1000Base-LH port (no IEEE standard exists for 1550 nm optics)
	Connectivity	Connector type LC
		Wavelength 1310 nm
	Physical characteristics	Dimensions 2.17(d) x 0.6(w) x 0.46(h) in. (5.51 x 1.52 x 1.17 cm)
		Full configuration weight 0.04 lb. (0.02 kg)
	Electrical characteristics	Power consumption typical 0.8 W
		Power consumption 1.0 W maximum
	Cabling	Cable type: Single-mode fiber optic, complying with ITU-T G.652;
		Maximum distance: <ul style="list-style-type: none">• 40km distance
HPE X120 1G SFP LC LH40 1550nm Transceiver (JD062A) A small form-factor pluggable (SFP) Gigabit LH40 transceiver that provides a full-duplex Gigabit solution up to 40 km on a single mode fiber.	Fiber type	Single Mode
	Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.
	Ports	1 LC 1000BASE-LH port (no IEEE standard exists for 1550 nm optics)
	Connectivity	Connector type LC
		Wavelength 1550 nm
	Physical characteristics	Dimensions 2.17(d) x 0.6(w) x 0.46(h) in. (5.51 x 1.52 x 1.17 cm)
		Full configuration weight 0.04 lb. (0.02 kg)
	Electrical characteristics	Power consumption typical 0.8 W
		Power consumption 1.0 W maximum
Cabling	Cable type: Single-mode fiber optic, complying with ITU-T G.652;	
		Maximum distance: <ul style="list-style-type: none">• 40km distance
	Fiber type	Single Mode
	Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-

Accessory Product Details

level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE X120 1G SFP LC BX Ports	1 LC 1000BASE-BX10 port (IEEE 802.3ah Type 1000BASE-BX10-U); Duplex: full only		
10-U Transceiver			
(JD098B)	Connectivity	Connector type	LC
A small form-factor pluggable (SFP) Gigabit LX-BX10-U transceiver that provides a full duplex Gigabit solution up to 10km on a single mode cable.	Physical characteristics	Dimensions	2.17(d) x 0.6(w) x 0.46(h) in. (5.51 x 1.52 x 1.17 cm)
		Full configuration weight	0.04 lb. (0.02 kg)
	Electrical characteristics	Power consumption typical	0.8 W
		Power consumption maximum	1.0 W
	Cabling	Maximum distance:	
		• 10km	
		Fiber type	Single Mode
Notes	TX 1310nm RX 1490nm		
Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.		

HPE X120 1G SFP LC BX Ports	1 LC 1000BASE-BX10 port (IEEE 802.3ah Type 1000BASE-BX10-D); Duplex: full only		
10-D Transceiver			
(JD099B)	Connectivity	Connector type	LC
A small form-factor pluggable (SFP) Gigabit LX-BX10-D transceiver that provides a full duplex Gigabit solution up to 10km on a single mode cable.	Physical characteristics	Dimensions	2.17(d) x 0.6(w) x 0.46(h) in. (5.51 x 1.52 x 1.17 cm)
		Full configuration weight	0.04 lb. (0.02 kg)
	Electrical characteristics	Power consumption typical	0.8 W
		Power consumption maximum	1.0 W
	Cabling	Maximum distance:	
		• Up to 10km	
		Fiber type	Single Mode
Notes	TX 1490nm RX 1310nm		
Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.		

Accessory Product Details

HPE X120 1G SFP LC LH100 Transceiver (JD103A)	Ports	1 LC 1000BASE-LH port (no IEEE standard exists for 1550 nm optics)
A small form factor pluggable (SFP) Gigabit LH100 transceiver that provides a full-duplex Gigabit solution up to 100km on a single mode fiber.	Connectivity	Connector type LC Wavelength 1550 nm
	Electrical characteristics	Power consumption typical 0.8 W Power consumption maximum 1.0 W
	Cabling	Cable type: Single-mode fiber optic, complying with ITU-T G.652; Maximum distance: <ul style="list-style-type: none"> • Up to 100km Fiber type Single Mode
	Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE X120 1G SFP LC SX Transceiver (JD118B)	Ports	1 LC 1000BASE-SX port
A small form-factor pluggable (SFP) Gigabit SX transceiver that provides a full-duplex Gigabit solution up to 550m on a Multimode fiber.	Connectivity	Connector type LC Wavelength 850 nm
	Physical characteristics	Dimensions 2.17(d) x 0.6(w) x 0.46(h) in. (5.51 x 1.52 x 1.17 cm) Full configuration weight 0.04 lb. (0.02 kg)
	Electrical characteristics	Power consumption typical 0.8 W Power consumption maximum 1.0 W
	Cabling	Maximum distance: <ul style="list-style-type: none"> • FDDI Grade distance = 220m • OM1 = 275m • OM2 = 500m • OM3 = Not Specified by standard Cable length up to 550m Fiber type Multi Mode
	Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

Accessory Product Details

Transceiver (JD119B) A small form-factor pluggable (SFP) Gigabit LX transceiver that provides a full duplex Gigabit solution up to 550m on MMF or 10Km on SMF	Connectivity	Connector type	LC
	Physical characteristics	Wavelength	1300 nm
		Dimensions	2.17(d) x 0.6(w) x 0.46(h) in. (5.51 x 1.52 x 1.17 cm)
		Full configuration weight	0.04 lb. (0.02 kg)
	Electrical characteristics	Power consumption typical	0.8 W
		Power consumption maximum	1.0 W
	Cabling	Cable type: Either single mode or multimode;	
		Maximum distance: • 550m for Multimode • 10km for Singlemode	
		Fiber type	Both
Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.		

HPE X125 1G SFP LC LH70 Transceiver (JD063B) A small form-factor pluggable (SFP) Gigabit LH70 transceiver that provides a full-duplex Gigabit solution up to 70km on a single-mode fiber.	Ports	1 LC 1000BASE-LH port (no IEEE standard exists for 1550 nm optics)	
	Connectivity	Connector type	LC
		Wavelength	1550 nm
	Physical characteristics	Dimensions	2.17(d) x 0.6(w) x 0.46(h) in. (5.51 x 1.52 x 1.17 cm)
		Full configuration weight	0.04 lb. (0.02 kg)
	Electrical characteristics	Power consumption typical	0.8 W
		Power consumption maximum	1.0 W
	Cabling	Cable type: Single-mode fiber optic, complying with ITU-T G.652;	
		Maximum distance: • 70km	
Services	Fiber type	Single Mode	
	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.		

Accessory Product Details

HPE X120 1G SFP RJ45 T Transceiver (JD089B) A small form factor pluggable (SFP) Gigabit 1000Base-T transceiver that provides a full duplex Gigabit solution up to 100m on a Cat-5+ cable.	Ports Connectivity Physical characteristics Electrical characteristics Cabling Services	1 RJ-45 1000BASE-T port (IEEE 802.3ab Type 1000BASE-T) Connector type RJ-45 Dimensions 2.71(d) x 0.54(w) x 0.55(h) in. (6.88 x 1.37 x 1.4 cm) Full configuration weight 0.07 lb. (0.03 kg) Power consumption typical 0.8 W Power consumption maximum 1.0 W Cable type: 1000BASE-T: Category 5 (5E or better recommended), 100 °U differential 4-pair unshielded twisted pair (UTP) or shielded twisted pair (STP) balanced, complying with IEEE 802.3ab 1000BASE-T; Maximum distance: • 100m Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.
---	--	--

Summary of Changes

Date	Version History	Action	Description of Change:
06-June-2016	From Version 5 to 6	Changed	SKU descriptions fixed
27-May-2016	From Version 4 to 5	Added	Configuration section added
		Changed	Technical Specifications, Overview and Product descriptions updated.
01-Dec-2015	From Version 3 to 4	Changed	Overview and Technical Specifications updated
01-Jun-2015	From Version 2 to 3	Added	SKU's added: JH138A, JH139A Product image added.
		Changed	Overview and Technical Specifications updated.
13-Feb-2014	From Version 1 to 2	Changed	Updates were made throughout the document.



[Sign up for updates](#)

© Copyright 2016 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

To learn more, visit: <http://www.hpe.com/networking>

c04111430 - 14500 - Worldwide - V6 - 6-June-2016

