



# Pair 60w Active Loudspeakers

SP-1800PBT EU SAP: 4313061 US SAP: 12928308

[visionaudiovisual.com/sp-1800p](http://visionaudiovisual.com/sp-1800p)

Integrated 2 x 30 watt (RMS) analogue amplifier

Two inputs, IR remote included

RS-232 Control

Bluetooth input

Vision's premium powered bookshelf speakers are purpose-built for any audio-visual presentation environments such as classrooms and meeting rooms, or bars and restaurants. They are simple to install and sound great! Perfect for meeting spaces.

**VISION**



### **Serial Control**

RS-232 control means the SP-1800P can be controlled by a control system such as Crestron or AMX, or by Vision's own Techconnect Control.

### **Auto Standby**

SP-1800P feature auto standby which saves power. This feature can be disabled via the remote control or a control system.

### **Remote Control**

A full range of options are presented on the IR remote control, including bass and treble adjustment.

### **Bass Reflex**

A bass reflex port allows greater excursion of the woofer, allowing the woofer to produce lower frequencies, and the phase-delayed movement of air from behind the woofer to the front reinforces the bass even more.

### **5.25" Woofer**

They are 240mm tall and use a 5.25 inch woofer – the most popular size for classroom, meeting room, and boardroom applications.

### **Horizontal C bracket**

The adjustable brackets allow the installer to easily angle up 30° or down 30°. Or leave the brackets off and use as shelf speakers.

### **Rugged Grille**

Attractive and robust, the thick metal grille protects the drivers from physical interference.

### **Big Sound**

These loudspeakers use three drivers; a woofer, a squawker, and a tweeter. Asking a driver to produce a wide range of frequencies is always a compromise, so dividing the sonic range into three means each driver has a narrower range of frequencies to produce, resulting in less distortion and clearer sound.

### **Memory**

When power is connected the SP-1800P automatically comes on and remembers the previous volume setting. Restoring power brings the loudspeakers back to life automatically.

### **Summed Inputs**


The two inputs are summed to avoid the need to switch.

### **Bluetooth**

Connect from your phone or laptop wirelessly. Speakers can auto-switch from line-level input when Bluetooth is paired if user chooses.

### **Rename Bluetooth**

Connect to a PC via USB to rename and set the pin.



## MANUAL

Manual en v2

**EN PDF 2.40 MB**

[files.visionaudiovisual.com/products/SP-1800P/manuals/SP-1800PBT\\_manual\\_en\\_v2.pdf](https://files.visionaudiovisual.com/products/SP-1800P/manuals/SP-1800PBT_manual_en_v2.pdf)

## CAD

CAD

**ZIP 276.80 KB**

[files.visionaudiovisual.com/products/SP-1800P/cad/SP-1800P.zip](https://files.visionaudiovisual.com/products/SP-1800P/cad/SP-1800P.zip)

CAD

**VND.DWG 329.01 KB**

[files.visionaudiovisual.com/products/SP-1800P/manuals/SP-1800P.dwg](https://files.visionaudiovisual.com/products/SP-1800P/manuals/SP-1800P.dwg)

## SOFTWARE

InstallBlueSuite 2 6 4 1046

**X-DOSEXEC 30.42 MB**

[files.visionaudiovisual.com/products/SP-1800P/software/InstallBlueSuite\\_2\\_6\\_4\\_1046.exe](https://files.visionaudiovisual.com/products/SP-1800P/software/InstallBlueSuite_2_6_4_1046.exe)

## IMAGE

Product Images

**ZIP 8.05 MB**

[files.visionaudiovisual.com/products/SP-1800P/images/SP-1800P.zip](https://files.visionaudiovisual.com/products/SP-1800P/images/SP-1800P.zip)

## SPECIFICATIONS

### PRODUCT DIMENSIONS

244 x 180 x 174 mm / 9.61" x 7.1" x 6.85" (tall x wide x deep for each speaker)

### PACKAGED DIMENSIONS

465 x 205 x 270 mm / 18.3" x 8.1" x 10.63"

### PRODUCT WEIGHT

4.78 kg / 10.54 lbs (per pair)

### PACKAGED WEIGHT

5.25 kg / 11.57 lbs (per pair)

### CONSTRUCTION MATERIAL

ABS

### COLOUR

White

### AMPLIFIER OUTPUT

2 x 30 watts (RMS)

### WOOFER

5.25"

### TWEETER

0.5" + Piezo 1"

### INPUT 1

Minijack (3.5mm)

### INPUT 2

2-Phono (RCA)

### SPEAKER OUTPUT

Removable Phoenix type

### SPEAKER INPUT (ON SLAVE)

Bare-wire screw type

### OUTPUT IMPEDANCE

4 ohms

### SENSITIVITY

85 dB (1w/1m)

### FREQUENCY RESPONSE

50Hz-20kHz

### POWER CONSUMPTION

≤ 100 w

### POWER SUPPLY

100-240v 50/60Hz AC External Power Supply – 16 volt / 5.4 amp

### LAPTOP-STYLE TRANSFORMER

**INCLUDES 4 X 0.5M (1.6 FT) FIGURE-8 POWER CABLES**

UK/EU/US/AU

### DC TAIL LENGTH

1.5 m (4.9 ft)

### TRANSFORMER DIMENSIONS

149 x 59 x 35 mm / 5.9" x 2.3" x 1.4"

### ACCESSORIES INCLUDED

2 x Wall brackets 1 x Euro Figure-8 Power cable 0.5 m (1.6') long 1 x UK Figure-8 Power cable 0.5 m (1.6') long 1 x AU Figure-8 Power cable 0.5 m (1.6') long 1 x US Figure-8 Power cable 0.5 m (1.6') long Speaker Cable 5 m (16.4') long 1 x Remote Control (Battery included: CR2025 3V Li-Mn) 1 x Male to Male 9-Pin Serial adaptor

### WARRANTY

Lifetime return-to-base

### COMPLIANCE

RoHS, CE/EMC, FCC, RCM, RCM/TVC, RCM-SDOC, REACH

### ORDER PART CODE

SP-1800PBT [EU SAP: 4313061 / US SAP: 12928308]

### SPARE REMOTE CONTROL

SP-1800P RC [EU SAP: 3940954 / US SAP: 12928050]

### SPARE POWER SUPPLY UNIT (PSU)

TC2 P16V5.4A [US SAP: 3824152/ US SAP: 13445525]

**VISION**