

C9120AXI-E

Datasheet

Check its price: [Click Here](#)



Overview

Cisco® Catalyst® 9115 Series Wi-Fi 6 Access Points are the next generation of enterprise access points. They are resilient, secure, and intelligent. C9120AXI-E is the Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, E Domain.

Product Details

Cisco AP 9120 series provides these features:

- 802.11ax (Wi-Fi 6)
- Cisco RF ASIC
- Uplink/downlink OFDMA
- MU-MIMO technology
- Target wake time
- BSS coloring
- Intelligent Capture
- Flexible Radio Assignment
- Dual 5-GHz radio support
- Smart antenna connector
- Cisco Mobility Express
- Multigigabit Ethernet support
- Bluetooth 5.0
- Container support for applications
- Apple Features

Supported Platforms

Table 1 shows the supported platforms and software.

Supported wireless LAN controllers and Software	Recommended Model
Cisco 3500 Series Wireless Controllers	AIR-CT3504-K9
Cisco 5520 Series Wireless Controllers	AIR-CT3504-K9
Cisco 8540 Series Wireless Controllers	AIR-CT8540-K9 AIR-CT8540-1K-K9
Cisco 9800 series Wireless Controllers	C9800-40-K9 C9800-80-K9
Cisco Virtual Wireless Controller	/
Cisco Unified Wireless Network Software Release 8.9 or later	/
Cisco IOS ® XE Software Release 16.11 or later	/

Compare to Similar Items

Table 2 shows the comparison of Cisco AP 9120I series.

SKU	Description
-----	-------------

C9120AXI-A	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, A Domain
C9120AXI-B	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, B Domain
C9120AXI-B-EDU	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, B Domain
C9120AXI-D	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, D Domain
<u>C9120AXI-E</u>	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, E Domain
C9120AXI-H	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, H Domain
C9120AXI-I	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, I Domain
C9120AXI-K	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, K Domain
C9120AXI-Q	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, Q Domain
C9120AXI-S	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, S Domain
C9120AXI-Z	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, Z Domain

Get More Information

Do you have any question about the C9120AXI-E?

Contact us now at sales@gntme.com.

Specification

C9120AXI-E Specification	
Description	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, E Domain
Software	<ul style="list-style-type: none"> • Cisco Unified Wireless Network Software Release 8.9.x or later • Cisco IOS ® XE Software Release 16.11 with AP Device Pack, or later
Supported wireless LAN controllers	<ul style="list-style-type: none"> • Cisco Catalyst 9800 Series Wireless Controllers • Cisco 3500, 5520, and 8540 Series Wireless Controllers and Cisco Virtual Wireless Controller
802.11n version 2.0 (and related) capabilities	<ul style="list-style-type: none"> • 4x4 MIMO with four spatial streams • Maximal Ratio Combining (MRC) • 802.11n and 802.11a/g beamforming • 20- and 40-MHz channels • PHY data rates up to 890 Mbps (40 MHz with 5 GHz and 20 MHz with 2.4 GHz) • Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive) • 802.11 Dynamic Frequency Selection (DFS) • Cyclic Shift Diversity (CSD) support
802.11ac	<ul style="list-style-type: none"> • 4x4 downlink MU-MIMO with four spatial streams • MRC • 802.11ac beamforming • 20-, 40-, 80-, and 160-MHz channels • PHY data rates up to 3.47 Gbps (160 MHz with 5 GHz) • Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive) • 802.11 DFS • CSD support

802.11ax	<ul style="list-style-type: none"> • 4x4 downlink MU-MIMO with four spatial streams • Uplink/downlink OFDMA • TWT • BSS coloring • MRC • 802.11ax beamforming • 20-, 40-, 80-, and 160-MHz channels • PHY data rates up to 5.38 Gbps (160 MHz with 5 GHz and 20 MHz with 2.4 GHz) • Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive) • 802.11 DFS • CSD support
Integrated antenna	<p>Flexible radio (either on 2.4GHz or on 5GHz)</p> <ul style="list-style-type: none"> • 2.4 GHz, peak gain 4 dBi, internal antenna, omnidirectional in azimuth • 5 GHz, peak gain 5 dBi, internal antenna, omnidirectional in azimuth • 5 GHz, peak gain 4 dBi, internal antenna, omnidirectional in azimuth
External antenna (sold separately)	<ul style="list-style-type: none"> • Cisco Catalyst 9120E Access Points are certified for use with antenna gains up to 6 dBi (2.4 GHz and 5 GHz) • Cisco Catalyst 9120P Access Points are certified for use with antenna gains up to 13 dBi (2.4 GHz and 5 GHz) with the AIR-ANT2513-P4M-N= antenna • Cisco offers the industry's broadest selection of antennas, delivering optimal coverage for a variety of deployment scenarios • Supports Self-Identifiable Antennas (SIA) on one RP-TNC port
Smart Antenna Connector	<ul style="list-style-type: none"> • Available on the 9120E and on the 9120P only • Compact multi RF connector with DART interface • Requires the AIR-CAB002-DART-R= 2 ft smart antenna connector when used with antennas with RP-TNC connector • Required when running the flexible radio as either a second 5-GHz serving radio or a Wireless Security Monitoring radio
Interfaces	<ul style="list-style-type: none"> • 1x 100, 1000, 2500 Multigigabit Ethernet (RJ-45) – IEEE 802.3bz • Management console port (RJ-45) • USB 2.0 @ 3.75W (enabled via future software)
Indicators	<ul style="list-style-type: none"> • Status LED indicates boot loader status, association status, operating status, boot loader warnings, and boot loader errors
Dimensions (W x L x H)	<ul style="list-style-type: none"> • Access point (without mounting brackets): C9120I: 8.5 x 8.5 x 1.7" (21.6 x 21.6 x 4.3 cm)
Input power requirements	<ul style="list-style-type: none"> • 802.3at Power over Ethernet Plus (PoE+), 802.3bt Cisco Universal PoE (Cisco UPOE+, Cisco UPOE®) • Cisco power injector, AIR-PWRINJ6= • 802.3af PoE • Cisco power injector, AIR-PWRINJ5= (Note: This injector supports only 802.3af)
Environmental	<p>Cisco Catalyst 9120AXI</p> <ul style="list-style-type: none"> • Nonoperating (storage) temperature: -22° to 158°F (-30° to 70°C) • Nonoperating (storage) altitude test: 25°C, 15,000 ft. • Operating temperature: 32° to 122°F (0° to 50°C) • Operating humidity: 10% to 90% (noncondensing) • Operating altitude test: 40°C, 9843 ft.
System memory	<ul style="list-style-type: none"> • 2048 MB DRAM • 1024 MB flash

Available transmit power settings	2.4 GHz <ul style="list-style-type: none"> • 23 dBm (200mW) • 20 dBm (100mW) • 17 dBm (50mW) • 14 dBm (25mW) • 11 dBm (12.5 mW) • 8 dBm (6.25 mW) • 5 dBm (3.13 mW) • 2 dBm (1.56 mW) • -1dBm (0.79mW) • -4dBm(0.39mW) 5 GHz <ul style="list-style-type: none"> • 26 dBm (400mW) • 23 dBm (200mW) • 20 dBm (100mW) • 17 dBm (50mW) • 14 dBm (25mW) • 11 dBm (12.5 mW) • 8 dBm (6.25 mW) • 5 dBm (3.13 mW) • 2 dBm (1.56 mW) • -1dBm (0.79mW)
Frequency band and 20-MHz operating channels	E (E regulatory domain): <ul style="list-style-type: none"> • 2.412 to 2.472 GHz; 13 channels • 5.180 to 5.320 GHz; 8 channels • 5.500 to 5.700 GHz; 8 channels (excludes 5.600 to 5.640 GHz)

Contact Us

Want to buy this series of products? please contact us:

- Mobile: +971 4 2409 998
- Whatsapp: +971503841786
- Email: sales@gntme.com

Order Now

GO to buy this product: <https://gntme.com/c9120axi-e/>