

8 Port High Speed HDMI® Video Splitter with Audio - Rack Mountable

ST128HDMI2

DE: Bedienungsanleitung - de.startech.com

FR: Guide de l'utilisateur - fr.startech.com

ES: Guía del usuario - es.startech.com


IT: Guida per l'uso - it.startech.com

NL: Gebruiksaanwijzing - nl.startech.com

PT: Guia do usuário - pt.startech.com

Packaging Contents

- 1 x HDMI® video splitter
- 2 x Rack Mounting Bracket
- 1 x Universal Power Adapter
- 1 x Package of screws
- 1 x Installation Guide



*actual product may vary from photos

System Requirements

- HDMI® enabled display device (i.e. monitor, projector, HDTV, etc)
- HDMI® enabled video source (i.e. computer, Blu-Ray player, PVR/DVR, etc)
- Available AC electrical outlet

Installation

1. Make sure all displays and the video source device are turned off before installing.
2. Connect an HDMI® cable (not included) from each of the video display devices (e.g. monitor, HDTV, etc) to the numbered output HDMI® connectors on the video splitter.

NOTE: Port 1 is the primary output so EDID information will be taken from there. The capabilities of the display on Port 1 will be applied to all other ports so be careful not to exceed the capabilities of the other displays.

3. If connecting audio separately from HDMI®, connect speakers to the corresponding 3.5mm audio outputs.
4. Connect an HDMI® cable (not included) from the video source device (e.g. computer, PVR/DVR, etc) to the 'SOURCE' input HDMI® connector on the video splitter.
5. If connecting audio separately from HDMI®, connect the audio source to the input 3.5mm audio connector.
6. Connect the included power adapter to the video splitter.
7. Turn on the display devices, followed by the video source. The video output should be displayed on all connected display devices.

Specifications

Number of Ports	8
Video Signal	High Speed HDMI® (HDMI® 1.3)
Connectors	1 x HDMI® female (input) 8 x HDMI® female (output) 1 x 3.5mm mini-jack Audio (input) 8 x 3.5mm mini-jack Audio (output) 1 x DC Power
LEDs	1 x Power/Input 8 x Output
Maximum Video Resolution	1920 x 1200 / 1080p
Maximum Cable Distance	5m
Audio Support	Yes
HDCP Support	Yes
DDC Support	Yes
Rack Mountable	Yes
Power Adapter	9 ~ 12VDC, 1500mA, center positive
Enclosure Material	Metal
Operating Temperature	0°C ~ 40°C (32°F ~ 104°F)
Storage Temperature	-10°C ~ 60°C (14°F ~ 140°F)
Humidity	0% ~ 80%
Dimensions	43.0mm x 185.0mm x 44.0mm
Weight	3500g

FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. Regardless of any direct acknowledgement elsewhere in the body of this document, StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

Technical Support

StarTech.com's lifetime technical support is an integral part of our commitment to provide industry-leading solutions. If you ever need help with your product, visit www.startech.com/support and access our comprehensive selection of online tools, documentation, and downloads.

For the latest drivers/software, please visit www.startech.com/downloads

Warranty Information

This product is backed by a three year warranty.

In addition, StarTech.com warrants its products against defects in materials and workmanship for the periods noted, following the initial date of purchase. During this period, the products may be returned for repair, or replacement with equivalent products at our discretion. The warranty covers parts and labor costs only. StarTech.com does not warrant its products from defects or damages arising from misuse, abuse, alteration, or normal wear and tear.

Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.