



Supported Platforms and Environments in Version 6.2.0

The following table lists the supported platforms for Version 6.2.0:

Table 1: Supported Platforms and Environments

Supported Platform	Supported Environment
Firepower Management Centers: MC750, MC1000, MC1500, MC2000, MC2500, MC3500, MC4000, MC4500	—
64-bit Firepower Management Center Virtual	<ul style="list-style-type: none"> • VMware vSphere/VMware ESXi 5.5 • VMware vSphere/VMware ESXi 6.0 • Amazon Web Services (AWS) VPC/EC2 • Kernel-based virtual machine (KVM)
7000 and 8000 Series devices: 7010, 7020, 7030, 7050, 7110, 7115, 7120, 7125, 8120, 8130, 8140, 8250, 8260, 8270, 8290, 8350, 8360, 8370, 8390, AMP7150, AMP8050, AMP8150, AMP8350, AMP8360, AMP8370, AMP8390	—
NGIPSv (virtual managed devices)	<ul style="list-style-type: none"> • VMware vSphere/VMware ESXi 5.5 • VMware vSphere/VMware ESXi 6.0

Supported Platform	Supported Environment
<p>Cisco ASA with FirePOWER Services: ASA 5506-X, ASA 5506H-X, ASA 5506W-X, ASA 5508-X, ASA 5512-X, ASA 5515-X, ASA 5516-X, ASA 5525-X, ASA 5545-X, ASA 5555-X, ASA 5585-X-SSP-10, ASA 5585-X-SSP-20, ASA 5585-X-SSP-40, ASA 5585-X-SSP-60</p> <p>Note You can also configure these devices as an ASA FirePOWER module managed by ASDM.</p>	<p>ASA OS, for ASA FirePOWER:</p> <ul style="list-style-type: none"> • 9.5(2), 9.5(3) except 5506 models • 9.6(x) • 9.7(x) • 9.8(x) <p>Note The ASA 5506-X does <i>not</i> support the ASA FirePOWER module when running ASA Version 9.5(x).</p> <p>ASDM Version 7.7(1) and later.</p> <p>Note The ASA 5506-X, ASA 5508-X, and ASA 5516-X require ROMMON Version 1.1.8 or later.</p>
<p>Cisco ASA with Firepower Threat Defense: ASA 5506-X, ASA 5506H-X, ASA 5506W-X, ASA 5508-X, ASA 5512-X, ASA 5515-X, ASA 5516-X, ASA 5525-X, ASA 5545-X, ASA 5555-X</p> <p>Note You can also configure these devices as Firepower Threat Defense managed by Firepower Device Manager. For more information, see the System Management topic in the Cisco Firepower Threat Defense Configuration Guide for Firepower Device Manager.</p>	<p>—</p>
<p>Firepower 9300 appliance with Firepower Threat Defense and the Firepower 4100 series with Firepower Threat Defense: Firepower 4110, Firepower 4120, Firepower 4140, Firepower 4150</p>	<p>FXOS Version 2.1(1) and later, or Version 2.2(1) and later.</p> <p>Caution Do <i>not</i> update to FXOS Version 2.3.1.56 if you are running an instance of Firepower Threat Defense that has been updated from Version 6.0.1.x of the Firepower System. Doing so may disable your Firepower Threat Defense application, which could interrupt traffic on your network. For more information, see CSCvh64138 in the Cisco Bug Search Tool.</p> <p>Note The Firepower 9300 appliance requires ROMMON Version 1.0.10 or later.</p>

Supported Platform	Supported Environment
Firepower Threat Defense Virtual	<ul style="list-style-type: none">• VMware vSphere/VMware ESXi 5.5• VMware vSphere/VMware ESXi 6.0• AWS VPC/EC2• KVM• Microsoft Azure Standard D3• Microsoft Azure Standard D3_v2

