



TS-1677XU-RP-2600-8G (Legacy)

CPU	AMD Ryzen™ 5 2600 6-core/12-thread processor, burst up to 3.9 GHz
CPU Architecture	64-bit x86
Floating Point Unit	Yes
Encryption Engine	Yes (AES-NI)
System Memory	8 GB UDIMM DDR4 (2 x 4GB)
Maximum Memory	64 GB (4 x 16 GB)
Memory Slot	4 x UDIMM DDR4
Flash Memory	5GB (Dual boot OS protection)
Drive Bay	16 x 3.5-inch SATA 6Gb/s, 3Gb/s
Drive Compatibility	3.5-inch SATA hard disk drives 2.5-inch SATA hard disk drives 2.5-inch SATA solid state drives
Hot-swappable	Yes
SSD Cache Acceleration Support	Yes
GPU pass-through	Yes
Gigabit Ethernet Port (RJ45)	2
10 Gigabit Ethernet Port	2 x 10GbE SFP+ SmartNIC port
Wake on LAN (WOL)	Yes
Jumbo Frame	Yes

PCIe Slot	4 Slot 1: PCIe Gen 3 x4 Slot 2: PCIe Gen 3 x8 or PCIe Gen 3 x4* Slot 3: PCIe Gen 3 x4 Slot 4: PCIe Gen 3 x8 or PCIe Gen 3 x4** *Slot 2 provides the width of PCIe Gen.3 x8 when Slot 1 is not in use, and provides the width of PCIe Gen.3 x4 when Slot 1 is in use. **Slot 4 provides the width of PCIe Gen.3 x8 when Slot 3 is not in use, and provides the width of PCIe Gen.3 x4 when Slot 3 is in use.
USB 3.2 Gen 1 port	4
USB 3.2 Gen 2 (10Gbps) Port	1 x Type-C USB 3.2 Gen 2 10Gbps 1 x Type-A USB 3.2 Gen 2 10Gbps
Form Factor	3U Rackmount
LED Indicators	HDD 1-16, Status, LAN, storage expansion port status
Buttons	Power, Reset
Dimensions (HxWxD)	130 × 481 × 573.5 mm Excludes ear hook and the protruding part of the Power Supply Unit.
Weight (Net)	15.26 kg
Weight (Gross)	21.38 kg
Operating Temperature	0 - 40 °C (32°F - 104°F)
Storage Temperature	-20 - 70°C (-4°F - 158°F)
Relative Humidity	5-95% RH non-condensing, wet bulb: 27°C (80.6°F)
Power Supply Unit	500W(x2), 100-240V
Power Consumption: Operating Mode, Typical	136.45 W Tested with drives fully populated.
Fan	System fan: 4 x 92mm, 12VDC
System Warning	Buzzer
Standard Warranty	3
Max. Number of Concurrent Connections (CIFS) - with Max. Memory	3500

Note: Use only QNAP memory modules to maintain system performance and stability. For NAS devices with more than one memory slot, use QNAP modules with identical specifications and refer to the hardware user manual to install compatible QNAP memory modules.

Warning: Using unsupported modules may degrade performance, cause errors, or prevent the operating system from starting. QNAP reserves the right to replace partial parts or accessories if the original is no longer available from its manufacturer/supplier. Any replacement would be fully tested and verified to meet strict compatibility and stability guidelines and will deliver identical performance to the original.

The terms HDMI, HDMI High-Definition Multimedia Interface, HDMI trade dress and the HDMI Logos are trademarks or registered

trademarks of HDMI Licensing Administrator, Inc.

Product images are for illustrative purposes only and may differ from the actual product. Due to differences in monitors, colors of products may also appear different to those shown on the site.

Designs and specifications are subject to change without notice.