

## Components and Cables for Cisco TelePresence Endpoints

CTG Technical Marketing Engineering

August 2016 / Version 8.2.1

This document is a "What's in the box?" guide for TelePresence Endpoints. Click on a link below to be taken directly to information about that product. This document is Cisco Confidential; however it may be freely distributed to partners and resellers.

PLEASE NOTE: This document does not cover SmartNet or other services; nor does it cover Shared Multiparty or other license options. They are outside the scope of this document: the focus is on hardware and feature options.

VERSION NOTE: The version number has been changed to align with CE software.

*Optimized for use with iPad*



## Collaboration Rooms and Desktop

### Immersive Endpoints

[IX5000](#)

[IX5200](#)

### Integrator Codecs and Quick Set

[SX80 with SpeakerTrack 60](#)   [SX20N with Precision 12X](#)

[SX80 with Precision 60](#)   [SX20N with Precision 40](#)

[SX80 with Precision 40](#)   [SX20 with Precision 12X](#)

[SX80 Codec](#)   [SX20 with 4X Camera](#)

[SX10N Quick Set](#)

*What are the differences between the SX20 and SX20N?* [Click here](#)

*What are the differences between the SX10 and SX10N?* [Click here](#)

### Multipurpose

[MX800 Dual](#)

[MX300 G2](#)

[MX800 Single](#)

[MX200 G2](#)

[MX700](#)

### Desktop Collaboration

[DX80](#)

[DX650](#)

[DX70](#)

[EX90](#)

### End of Sale Since Version 5.2 of This Document

Integrator Package C90 and Codec C90

AudioScience Microphone (replaced with Cisco Ceiling Microphone)

PrecisionHD 1080p 4XS (original)

SX20 with 2.5X Camera

PrecisionHD 2.5X Camera Spare

Power supply spare for Touch 8

## Peripherals

[Touch 8](#)

[Microphones](#)

[Touch 10](#)

[ISDN Link](#)

[Touch 12 \(Remanufactured\)](#) [55" LCD Monitor](#)

New cables and microphones are highlighted throughout

## Cameras and Accessories

[SpeakerTrack 60](#)

[PrecisionHD 720p \(Remanufactured\)](#)

[Precision 60 Camera](#)

[Precision 12X Camera](#)

[Precision 40 Camera \(4XS2\)](#)

## Verticals Endpoints

All Verticals Endpoint products have been transferred to Avizia. Contact [avizia.com](http://avizia.com) for sales and service.

Certain Avizia products are available on CCW  
Their PIDs begin with "AVIZ"

## Software Option for Remote Monitoring

*Effective June 2015 beginning with TC7.3.3 software*

*Applies to MX, SX, EX, C Series, and DX70/80 running CE software*

Required for the use of Web Snapshots, with functionality identical  
to software before TC7.3.0

**Top level part number: L-TP-RM**

**Option part numbers:** L-SX-SERIES-RM

L-MX-SERIES-RM

L-DX-SERIES-RM

L-EX-SERIES-RM

L-C-SERIES-RM

L-PROF-SERIES-RM

This document was prepared by Cisco CTG Technical Marketing Engineering

If you have corrections or questions please contact one of the following persons:

[bmcnine@cisco.com](mailto:bmcnine@cisco.com)

[econeder@cisco.com](mailto:econeder@cisco.com)

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-IX5000

IX5000



The IX5000 requires UCM for SIP call control. The min. version is 9.1(2). H.265 support requires min. UCM version 10.5.

## Cisco Product ID (PID)

## Description

CTS-IX5000

Cisco TelePresence IX5000

*Product Desc: IX5000 immersive telepresence one-row system, accommodates up to six people*

**Selected Main Components*****automatically included with Top Level PID***

CTS-5K-ENCODER		CTS-IX5000 Encoder / Decoder for World Wide Shipment
CTS-5K-HOSTCPU		CTS-IX5000 Host CPU for World Wide Shipment
CTS-5K-70-G1		CTS-IX5000 70" Display Qty 3
CTS-5K-6-SEAT-TBL		CTS-IX5000 6 Seat Table Option
CTS-LAPCONN-xx		TelePresence Laptop Connectivity Qty 6
CTS-CTRL-DVX-10		Touch 10 Control Device Qty 1
CAB-DV10-4M		4 meter flat grey Ethernet cable for Touch 10
CTS-5K-UI-SWITCH		Catalyst 2960C Switch 8 FE PoE, 2 x Dual Uplink, for Touch 10s, Qty 1
CTS-5K-CAM-CLSTR		CTS-IX5000 Camera Cluster
CTS-5K-CAM-TOOL		CTS-IX5000 Camera Alignment Tool Qty 2
CTS-5K-WHTBD-TOOL		CTS-IX5000 Whiteboard Alignment Tool Qty 4
CTS-5K-LED-KIT		CTS-IX5000 LED Light Fixtures Kit
CTS-5K-MIC		CTS-IX5000 Microphones, Qty 3
CTS-5K-SPKR		CTS-IX5000 Main Speakers, Qty 6
CTS-5K-SUBWOOFER		CTS-IX5000 Audio Subwoofer, Qty 1

**Table Options - choose one**

CTS-5K-TBL-H-6S	<i>standard</i>	CTS-IX5000 Front Row Hickory Table Top, 6 Seats
CTS-5K-TBL-W-6S	<i>extra cost</i>	CTS-IX5000 Front Row Walnut Table Top, 6 Seats

**Optional Components***Selectable at time of order*

Ethernet Switch Option		
CTS-5K-LC-SWITCH	<i>optional</i>	Catalyst 2960C Switch 12 FE PoE, 2 x Dual Uplink, for table connections
Content Display Option		
CTS-5K-DISP42	<i>optional</i>	<i>maximum 1</i> CTS-IX5000 42 (42" Data Display)
Additional Touch 10 Option		
CTS-CTRL-DVX-10	<i>optional</i>	<i>maximum 5 additional</i> Touch 10 Control Device - selectable option
CAB-DV10-4M		4 meter flat grey Ethernet cable (incl with Touch 10)
Seismic Bracket Option		
CTS-5K-SEISMIC	<i>optional</i>	CTS-IX5000 Seismic Bracket Kit

**55 inch Content Display***Order separately*

[CTS-MON-55-WW](#) *optional* Cisco 55 Inch Auxiliary Display - World Wide; Three max total content displays

**Postsale: to add a lower 42 inch content display, order the following:**

**42 inch Content Display - Postsale***In order to retrofit an existing IX5000 with a lower 42 inch content display*

CTS-5K-DISP42=  
CTS-5K-CBL-RUN-A= Cisco 55 Inch Auxiliary Display - World Wide; Three max total content displays  
42 Aux Display Brackets and Cable Runner

**Link to All Orderable Spares**

[IX5000 Spares](#)

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**


PWR-CORD10-AP	TelePresence 10 Power Cord - Asia Pacific
PWR-CORD10-AR	TelePresence 10 Power Cord - Argentina
PWR-CORD10-AU	TelePresence 10 Power Cord - Australia
PWR-CORD10-CE	TelePresence 10 Power Cord - Central Europe
PWR-CORD10-ITA	TelePresence 10 Power Cord - Italy
PWR-CORD10-ISR	TelePresence 10 Power Cord - Israel
PWR-CORD-JP	TelePresence NEMA 15 Power Cord - Japan
PWR-CORD-NA	TelePresence NEMA 15 Power Cord - North America
PWR-CORD10-SWI	TelePresence 10 Power Cord - Switzerland
PWR-CORD10-UK	TelePresence 10 Power Cord - United Kingdom

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-IX5200

IX5200



The IX5000 requires UCM for SIP call control. The min. version is 9.1(2). H.265 support requires min. UCM version 10.5.

Cisco Product ID (PID)	Description
<b>CTS-IX5200</b>	<b>Cisco TelePresence IX5200</b> <i>Product Desc: IX5200 immersive telepresence two-row system, accommodates up to 18 people</i>
<b>Selected Main Components</b>	<b>automatically included with Top Level PID</b>
CTS-5K-ENCODER	CTS-IX5000 Encoder / Decoder for World Wide Shipment
CTS-5K-HOSTCPU	CTS-IX5000 Host CPU for World Wide Shipment
CTS-5K-70-G1	CTS-IX5000 70 Display Qty 3
CTS-5K-18-SEAT-TBL	CTS-IX5000 18 Seat Table Option
CTS-LAPCONN-xx	TelePresence Laptop Connectivity Qty 18
CTS-CTRL-DVX-10	Touch 10 Control Device Qty 1
CAB-DV10-4M	4 meter flat grey Ethernet cable for Touch 10
CTS-5K-UI-SWITCH	Catalyst 2960C Switch 8 FE PoE, 2 x Dual Uplink, for Touch 10s
CTS-5K-CAM-CLSTR	CTS-IX5000 Camera Cluster
CTS-5K-CAM-TOOL	CTS-IX5000 Camera Alignment Tool Qty 2
CTS-5K-WHTBD-TOOL	CTS-IX5000 Whiteboard Alignment Tool Qty 4
CTS-5K-LED-KIT	CTS-IX5000 LED Light Fixtures Kit
CTS-5K-MIC	CTS-IX5000 Microphones, Qty 3
CTS-5K-MIC-TA	Turnaround microphone (for 2nd row table), Qty 6
CTS-5K-SPKR	CTS-IX5000 Main Speakers, Qty 6
CTS-5K-SUBWOOFER	CTS-IX5000 Audio Subwoofer, Qty 1
<b>Table Options - choose one</b>	
CTS-5K-TBL-H-18S <i>standard</i>	CTS-IX5000 Front Row Hickory Table Top, 6 Seats
CTS-5K-TBL-W-18S <i>extra cost</i>	CTS-IX5000 Front Row Walnut Table Top, 6 Seats

**Optional Components***Selectable at time of order*

Ethernet Switch Option  
 CTS-5K-LC-SWITCH      *optional*      Catalyst 2960C Switch 12 FE PoE, 2 x Dual Uplink, for table connections

Content Display Option  
 CTS-5K-DISP42      *optional*      *maximum 1*  
 CTS-IX5000 42 (42" Data Display)

Additional Touch 10 Option  
 CTS-CTRL-DVX-10      *optional*      *maximum 8 additional*  
 CAB-DV10-4M      Touch 10 Control Device - selectable option  
 4 meter flat grey Ethernet cable (incl with Touch 10)

Seismic Bracket Option  
 CTS-5K-SEISMIC      *optional*      CTS-IX5000 Seismic Bracket Kit

**55 inch Content Display***Order separately*

[CTS-MON-55-WW](#)      *optional*      Cisco 55 Inch Auxiliary Display - World Wide; Three max total content displays

*Postsale: to add a lower 42 inch content display, order the following:*

**42 inch Content Display - Postsale***In order to retrofit an existing IX5000 with a lower 42 inch content display*

CTS-5K-DISP42=  
 CTS-5K-CBL-RUN-A=  
 Cisco 55 Inch Auxiliary Display - World Wide; Three max total content displays  
 42 Aux Display Brackets and Cable Runner

*Postsale: to convert an IX5000 to an IX5200, order the following:*

**Upgrade Kit**

CTS-5K-18-SEAT-UPG      CTS-IX5000 6 Seat Table to 18 Seat Table Upgrade Kit

**Link to All Orderable Spares**

[IX5000 Spares](#)

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD10-AP	TelePresence 10 Power Cord - Asia Pacific
PWR-CORD10-AR	TelePresence 10 Power Cord - Argentina
PWR-CORD10-AU	TelePresence 10 Power Cord - Australia
PWR-CORD10-CE	TelePresence 10 Power Cord - Central Europe
PWR-CORD10-ITA	TelePresence 10 Power Cord - Italy
PWR-CORD10-ISR	TelePresence 10 Power Cord - Israel
PWR-CORD-JP	TelePresence NEMA 15 Power Cord - Japan
PWR-CORD-NA	TelePresence NEMA 15 Power Cord - North America
PWR-CORD10-SWI	TelePresence 10 Power Cord - Switzerland
PWR-CORD10-UK	TelePresence 10 Power Cord - United Kingdom



[Index](#)

CTS-MX800D-2CAM-K9  
 MX800 Dual with Dual Cameras  
 and Speaker Tracking

**NEW ACCESSORIES APRIL 2016**

see highlighted items



The MX800 Dual has two 70" LCD screens, with one additional output (DVI-I), and two cameras. There is no single camera option. The MX800 supports both SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description	
<b>CTS-MX800D-2CAM-K9</b>	<b>Cisco TelePresence MX800 Dual screen, dual cameras</b>	
	<i>Product Desc: Dual 70" LED/LCD, 2 Precision 60 Cameras with tracking, Touch 10 UI, 2 microphones</i>	
<b>Main Components</b>		<b>automatically included with Top Level PID</b>
CTS-MX800-MON-L-D-	<i>included</i>	Left Monitor for MX800 70" Dual Screen w/Dual Camera
CTS-MX800-MON-R-D-	<i>included</i>	Right Monitor for MX800 70" Dual Screen w/Dual Camera
CTS-MXCAM-D	<i>included</i>	Dual Camera with SpeakerTrack option for MX700/800
LIC-MX800-D-D	<i>included</i>	PRODUCT ID - MX800 Dual
CTS-MXCODEC	<i>included</i>	Codec for MX700/800 (based on SX80)
CTS-CTRL-DVX-10	<i>included</i>	Touch 10 Device
CTS-PWR-AIR-INJ5	<i>included</i>	Power Injector (802.3af)
CAB-DV10-12.5M	<i>included</i>	12.5 meter flat grey Ethernet cable for Touch 10
CAB-DV10-4M=	<i>included</i>	4 meter flat grey Ethernet cable for Touch 10
CTS-MIC-TABL60	<i>included</i>	Table Microphone 60 (Qty 2) - 9m cable, table brackets included
CAB-PRESO-2HDMI=	<i>included</i>	HDMI to HDMI cable, 8 meter, gray
CAB-DVI-VGA-PHOEN	<i>included</i>	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
n/a	<i>included</i>	Full set of Phoenix-style Euroblock connectors
<b>Software Feature Options</b>		
SW-S52010-CE8-K9	<i>included</i>	SW Image for SX80, MX700, MX800 - H.265 point to point, H.264, H.263, H.261
LIC-CE-CRYPTO-K9	<i>no-cost option</i>	License key to activate sw encryption module
LIC-Ce-NONCRYPTO	<i>no-cost option</i>	License key to activate sw without encryption module
LIC-MX800-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>	
LIC-MX800-MS	<i>optional</i>	MX800 MultiSite (5-way 720p30 Main / 1080p15 Presentation)
<b>Remote Monitoring</b>		
L-TP-RM		
L-MX-SERIES-RM	<i>order separately</i>	MX Remote Monitoring Option to enable Web Snapshots

SOFTWARE



Cisco Product ID (PID)		Description
<b>Mounting Kit Options</b> <i>(must select one)</i>		
CTS-MX800-D-FSK	<i>no-cost option</i>	Cisco MX800 Dual Screen Floor Stand Kit, freestanding or secured to the wall
CTS-MX800-D-WMK	<i>no-cost option</i>	Cisco MX800 Dual Screen Wall Mount Kit - hangs on wall (requires reinforcement) <i>Mounting Kits can be ordered as spares, in case a different mount is needed post-sale</i>
<b>Microphone Option</b>		
		<i>Up to eight microphones can be used</i>
CTS-MIC-TABL60	<i>(2) included</i>	Table Microphone 60 - 9m Euroblock cable and table bracket included
CAB-MIC-T60EXT=	<i>optional</i>	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
CAB-MIC-T60=	<i>optional</i>	Spare cable 9m for Table Microphone 60
CTS-MIC-CLNG-G2	<i>optional</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)
CAB-ETHRSHLD-10M	<i>optional</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated
<b>Presentation Cable</b>		
		<i>Must be ordered separately at this time</i>
CAB-HDMI-MULT-9M=	<i>order separately</i>	Presentation cable for HDMI, Display Port, Mini Display Port
<b>Selected Spares</b>		
CTS-MXCODEC=		Codec for MX700/MX800
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CABLES	CTS-MIC-TABL60=	Table Microphone 60 - 9m Euroblock cable and table bracket included
	CAB-MIC-T60EXT=	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
	CAB-MIC-T60=	Spare cable 9m for Table Microphone 60
	CAB-NET-EN5M=	Ethernet cable (5m)
	CAB-DVI-D181=	Cable DVI-D To DVI-D 2m
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
CAB-DVI-VGA-PHOEN=	Presentation cable w/audio, 8 meters <i>(VGA-M to DVI-M w/3.5mm male to phoenix audio)</i>	
FORM	<i>Postsale: to change from a Wall Mount Kit to Floor Stand, order the following:</i>	
	CTS-MX800-D-FSK=	Cisco MX800 Dual Screen Floor Stand Kit, freestanding or secured to the wall
	CTS-MX800-D-LGR=	Lower grille for system mounted on a stand
	<i>Postsale: to change from a Floor Stand Kit to a Wall Mount, order the following:</i>	
	CTS-MX800-D-WMK=	Cisco MX800 Dual Screen Wall Mount Kit - hangs on wall (requires reinforcement)
CTS-MX800-DWM-LGR=	Lower grille for wall mounted system	
CTS-MXCAM-D=	Dual Camera assembly with speaker tracking option for MX700/MX800	
<b>Spare Parts and Cable Schema</b>		
<a href="#">Cisco TelePresence MX800 Dual Spare Parts Overview</a>		
<a href="#">Cisco TelePresence MX800 Dual Spare Parts Replacement Guide</a>		
<a href="#">Cisco TelePresence MX800 Dual Cable Schema</a>		
<b>Post-Sale Licensing</b>		
SOFTWARE	<b>MultiSite</b>	L-MX-SERIES-PAK
	L-MX800-MS	E-delivery of MX800 MultiSite option
	<b>Remote Monitoring</b>	L-TP-RM
L-MX-SERIES-RM	MX Remote Monitoring Option to enable Web Snapshots	



**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords** *(must select one)*

PWR-CORD-ARG-D	Power Cable for Argentina
PWR-CORD-AUS-D	Power Cord AUS YP35 to YC12
PWR-CORD-BRA-D	Brazil Power Cord
PWR-CORD-CH-D	Power Cord Switzerland YP-46 to YC12
PWR-CORD-CN-D	Pwr Cord China YP03 to YC1
PWR-CORD-EUR-D	Power Cord EUR YP23 to YC12
PWR-CORD-IND-D	Power Cord for India
PWR-CORD-JPN-D	118530 Cord Pwr JPN YP12 to YC12
PWR-CORD-ROK-D	Power Cord Korea YP22K - TC12
PWR-CORD-UK-D	Power Cord UK YP-61 to YC12
PWR-CORD-US-D	Pwr Cord US YP-12 to YC12
PWR-CORD-ZAF-D	Power Cord South Africa

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.


[Index](#)

CTS-MX800S-1CAM-K9  
MX800 with Single Camera

CTS-MX800S-2CAM-K9  
MX800 with Dual Cameras  
and Speaker Tracking

**NEW ACCESSORIES APRIL 2016**

see highlighted items



The MX800 Single has one 70" LCD screen, with two additional outputs (HDMI and DVI-I). The MX800 supports both SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description
<b>CTS-MX800S-1CAM-K9</b>	<b>Cisco TelePresence MX800 Single screen, single camera option</b> <i>Product Desc: Single 70" LED/LCD, integrated Precision 60 Camera, Touch 10 UI, 2 microphones</i>
<b>Main Components Single Camera</b> <i>automatically included with Top Level PID</i>	
CTS-MX800-MON-S-S	<i>included</i> Monitor MX800 with Single Camera
CTS-MXCAM-S	<i>included</i> Single Camera option for MX700/800
LIC-MX800-S-S	<i>included</i> PRODUCT ID - MX800 Single Camera

<b>CTS-MX800S-2CAM-K9</b>	<b>Cisco TelePresence MX800 Single screen, dual camera option</b> <i>Product Desc: Single 70" LED/LCD, 2 Precision 60 Cameras with tracking, Touch 10 UI, 2 microphones</i>
<b>Main Components Dual Camera</b> <i>automatically included with Top Level PID</i>	
CTS-MX800-MON-S-D	<i>included</i> Monitor MX800 with Dual Camera
CTS-MXCAM-D	<i>included</i> Dual Camera with SpeakerTrack option for MX700/800
LIC-MX800-S-D	<i>included</i> PRODUCT ID - MX800 Dual Camera

<b>Main Components Common to both Single and Dual Camera</b>		
CTS-MXCODEC	<i>included</i>	Codec for MX700/800 (based on SX80)
CTS-CTRL-DVX-10	<i>included</i>	Touch 10 Device
CTS-PWR-AIR-INJ5	<i>included</i>	Power Injector (802.3af)
CAB-DV10-12.5M	<i>included</i>	12.5 meter flat grey Ethernet cable for Touch 10
CAB-DV10-4M=	<i>included</i>	4 meter flat grey Ethernet cable for Touch 10
CTS-MIC-TABL60	<i>included</i>	Table Microphone 60 (Qty 2) - 9m cable, table brackets included
CAB-PRESO-2HDMI=	<i>included</i>	HDMI to HDMI cable, 8 meter, gray
CAB-DVI-VGA-PHOEN	<i>included</i>	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
n/a	<i>included</i>	Full set of Phoenix-style Euroblock connectors

	Cisco Product ID (PID)	Description
<b>Software Feature Options</b>		
SOFTWARE	SW-S52010-CE8-K9	<i>included</i> SW Image for SX80, MX700, MX800 - H.265 point to point, H.264, H.263, H.261
	LIC-CE-CRYPTO-K9	<i>no-cost option</i> License key to activate sw encryption module
	LIC-CE-NONCRYPTO	<i>no-cost option</i> License key to activate sw without encryption module
	LIC-MX800-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
	LIC-MX800-MS	<i>optional</i> MX800 MultiSite (5-way 720p30 Main / 1080p15 Presentation)
<b>Remote Monitoring</b>		
	L-TP-RM	
	L-MX-SERIES-RM	<i>order separately</i> MX Remote Monitoring Option to enable Web Snapshots
<b>Mounting Kit Options (must select one)</b>		
	CTS-MX800-S-FSK	<i>no-cost option</i> Cisco MX800 Single Screen Floor Stand Kit, freestanding or secured to the wall
	CTS-MX800-S-WMK	<i>no-cost option</i> Cisco MX800 Single Screen Wall Mount Kit - hangs on wall (requires reinforcement) <i>Mounting Kits can be ordered as spares, in case a different mount is needed post-sale</i>
<b>Microphone Option</b>		
		<i>Up to eight microphones can be used</i>
	CTS-MIC-TABL60	<i>(2) included</i> Table Microphone 60 - 9m Euroblock cable and table bracket included
	CAB-MIC-T60EXT=	<i>optional</i> 9 meter extension cable for Table Microphone 60 (Euroblock connectors)
	CAB-MIC-T60=	<i>optional</i> Spare cable 9m for Table Microphone 60
	CTS-MIC-CLNG-G2	<i>optional</i> Cisco Ceiling Microphone Gen 2 (see Microphones)
	CAB-ETHRSHLD-10M	<i>optional</i> Shielded audio cable 10m, for Ceiling Microphone, not plenum rated
<b>Presentation Cable</b>		
		<i>Must be ordered separately at this time</i>
	CAB-HDMI-MULT-9M=	<i>order separately</i> Presentation cable for HDMI, Display Port, Mini Display Port
<b>Selected Spares</b>		
	CTS-MXCODEC=	Codec for MX700/MX800
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CABLES	CTS-MIC-TABL60=	Table Microphone 60 - 9m detachable cable and table bracket included
	CAB-MIC-T60EXT=	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
	CAB-MIC-T60=	Spare cable 9m for Table Microphone 60
	CAB-NET-EN5M=	Ethernet cable (5m)
	CAB-DVI-D181=	Cable DVI-D To DVI-D 2m
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
	CAB-DVI-VGA-PHOEN=	Presentation cable w/audio, 8 meters <i>(VGA-M to DVI-M w/3.5mm male to phoenix audio)</i>
FORM		<i>Postsale: to change from a Wall Mount Kit to Floor Stand, order the following:</i>
	CTS-MX800-S-FSK=	Cisco MX800 Single Screen Floor Stand Kit, freestanding or secured to the wall
	CTS-MX800-S-LGR=	Lower grille for system mounted on a stand
		<i>Postsale: to change from a Floor Stand Kit to a Wall Mount, order the following:</i>
	CTS-MX800-S-WMK=	Cisco MX800 Single Screen Wall Mount Kit - hangs on wall (requires reinforcement)
	(CTS-MX800-SWM-LGR=	Lower grille for wall mounted system
	CTS-MXCAM-S=	Single Camera assembly for MX700/800
	CTS-MXCAM-D=	Dual Camera assembly with speaker tracking option for MX700/MX800



**Link to All Orderable Spares**[Cisco TelePresence MX800 Single Spare Parts Overview](#)[Cisco TelePresence MX800 Single Spare Parts Replacement Guide](#)[Cisco TelePresence MX800 Single Cable Schema](#)**Post-Sale Licensing**

SOFTWARE

**MultiSite**

L-MX-SERIES-PAK

L-MX800-MS

E-delivery of MX800 MultiSite option

**Remote Monitoring**

L-TP-RM

L-MX-SERIES-RM

MX Remote Monitoring Option to enable Web Snapshots

**Documentation**<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>**Power Cords (must select one)**

PWR-CORD-ARG-D

Power Cable for Argentina

PWR-CORD-AUS-D

Power Cord AUS YP35 to YC12

PWR-CORD-BRA-D

Brazil Power Cord

PWR-CORD-CH-D

Power Cord Switzerland YP-46 to YC12

PWR-CORD-CN-D

Pwr Cord China YP03 to YC1

PWR-CORD-EUR-D

Power Cord EUR YP23 to YC12

PWR-CORD-IND-D

Power Cord for India

PWR-CORD-JPN-D

118530 Cord Pwr JPN YP12 to YC12

PWR-CORD-ROK-D

Power Cord Korea YP22K - TC12

PWR-CORD-UK-D

Power Cord UK YP-61 to YC12

PWR-CORD-US-D

Pwr Cord US YP-12 to YC12

PWR-CORD-ZAF-D

Power Cord South Africa

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-MX700D-1CAM-K9  
MX700 with Single Camera

CTS-MX700D-2CAM-K9  
MX700 with Dual Cameras  
and Speaker Tracking

**NEW ACCESSORIES APRIL 2016**  
see highlighted items



The MX700 has two 55" LCD screens, with an additional DVI-I output. The MX700 supports both SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description
<b>CTS-MX700D-1CAM-K9</b>	<b>Cisco TelePresence System MX700, single camera option</b> <i>Product Desc: Dual 55" LED/LCD, integrated Precision 60 Camera, Touch 10 UI, 2 microphones</i>
<b>Main Components Single Camera</b> <i>automatically included with Top Level PID</i>	
CTS-MX700-MON-L-S	<i>included</i> Left Monitor for MX700 with Single Camera
CTS-MX700-MON-R-S	<i>included</i> Right Monitor for MX700 with Single Camera
CTS-MXCAM-S	<i>included</i> Single Camera option for MX700/800
LIC-MX700-D-S	<i>included</i> PRODUCT ID - MX700 Single Camera

<b>CTS-MX700D-2CAM-K9</b>	<b>Cisco TelePresence System MX700, dual camera option</b> <i>Product Desc: Dual 55" LED/LCD, 2 Precision 60 Cams with tracking, Touch 10 UI, 2 Microphones</i>
<b>Main Components Dual Camera</b> <i>automatically included with Top Level PID</i>	
CTS-MX700-MON-L-D	<i>included</i> Left Monitor for MX700 with Dual Camera
CTS-MX700-MON-R-D	<i>included</i> Right Monitor for MX700 with Dual Camera
CTS-MXCAM-D	<i>included</i> Dual Camera with SpeakerTrack option for MX700/800
LIC-MX700-D-D	<i>included</i> PRODUCT ID - MX700 Dual Camera

<b>Main Components Common to both Single and Dual Camera</b>		
CTS-MXCODEC	<i>included</i>	Codec for MX700/800 (based on SX80)
CTS-CTRL-DVX-10	<i>included</i>	Touch 10 Device
CTS-PWR-AIR-INJ5	<i>included</i>	Power Injector (802.3af)
CAB-DV10-12.5M	<i>included</i>	12.5 meter flat grey Ethernet cable for Touch 10
CAB-DV10-4M=	<i>included</i>	4 meter flat grey Ethernet cable for Touch 10
CTS-MIC-TABL60	<i>included</i>	Table Microphone 60 (Qty 2) - 9m cable, table brackets included
CAB-PRESO-2HDMI=	<i>included</i>	HDMI to HDMI cable, 8 meter, gray
CAB-DVI-VGA-PHOEN	<i>included</i>	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
n/a	<i>included</i>	Full set of Phoenix-style Euroblock connectors

Cisco Product ID (PID)		Description
<b>Software Feature Options</b>		
SOFTWARE	SW-S52010-CE8-K9	<i>included</i> SW Image for SX80, MX700, MX800 - H.265 point to point, H.264, H.263, H.261
	LIC-CE-CRYPTO-K9	<i>no-cost option</i> License key to activate sw encryption module
	LIC-Ce-NONCRYPTO	<i>no-cost option</i> License key to activate sw without encryption module
	LIC-MX700-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
	LIC-MX700-MS	<i>optional</i> MX700 MultiSite (5-way 720p30 Main / 1080p15 Presentation)
	<b>Remote Monitoring</b>	L-TP-RM
L-MX-SERIES-RM	<i>order separately</i> MX Remote Monitoring Option to enable Web Snapshots	
<b>Mounting Kit Options (must select one)</b>		
CTS-MX700-D-FSK	<i>no-cost option</i>	Cisco MX700 Dual Screen Floor Stand Kit, freestanding or secured to the wall
CTS-MX700-D-WMK	<i>avail august</i>	Cisco MX700 Dual Screen Wall Mount Kit - hangs on wall (requires reinforcement) <i>Mounting Kits can be ordered as spares, in case a different mount is needed post-sale</i>
<b>Microphone Option</b>		
		<i>Up to eight microphones can be used</i>
CTS-MIC-TABL60	<i>(2) included</i>	Table Microphone 60 - 9m Euroblock cable and table bracket included
CAB-MIC-T60EXT=	<i>optional</i>	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
CAB-MIC-T60=	<i>optional</i>	Spare cable 9m for Table Microphone 60
CTS-MIC-CLNG-G2	<i>optional</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)
CAB-ETHRSHLD-10M	<i>optional</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated
<b>Presentation Cable</b>		
		<i>Must be ordered separately at this time</i>
CAB-HDMI-MULT-9M=	<i>order separately</i>	Presentation cable for HDMI, Display Port, Mini Display Port
<b>Selected Spares</b>		
CTS-MXCODEC=		Codec for MX700/MX800
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CABLES	CTS-MIC-TABL60=	Table Microphone 60 - 9m Euroblock cable and table bracket included
	CAB-MIC-T60EXT=	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
	CAB-MIC-T60=	Spare cable 9m for Table Microphone 60
	CAB-NET-EN5M=	Ethernet cable (5m)
	CAB-DVI-D181=	Cable DVI-D To DVI-D 2m
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
CAB-DVI-VGA-PHOEN=	Presentation cable w/audio, 8 meters <i>(VGA-M to DVI-M w/3.5mm male to phoenix audio)</i>	
FORM		<i>Postsale: to change from a Wall Mount Kit to Floor Stand, order the following:</i>
	CTS-MX700-D-FSK=	Cisco MX700 Dual Screen Floor Stand Kit, freestanding or secured to the wall
	CTS-MX700-D-LGR=	Lower grille for system mounted on a stand
		<i>Postsale: to change from a Floor Stand Kit to a Wall Mount, order the following:</i>
	CTS-MX700-D-WMK=	Cisco MX700 Dual Screen Wall Mount Kit - hangs on wall (requires reinforcement)
	CTS-MX700-DWM-LGR=	Lower grille for wall mounted system
CTS-MXCAM-S=	Single Camera assembly for MX700/800	
CTS-MXCAM-D=	Dual Camera assembly with speaker tracking option for MX700/MX800	





**Link to All Orderable Spares**[Cisco TelePresence MX700 Spare Parts Overview](#)[Cisco TelePresence MX700 Spare Parts Replacement Guide](#)[Cisco TelePresence MX700 Cable Schema](#)**Post-Sale Licensing**

SOFTWARE

**MultiSite**

L-MX-SERIES-PAK

L-MX700-MS

E-delivery of MX700 MultiSite option

**Remote Monitoring**

L-TP-RM

L-MX-SERIES-RM

MX Remote Monitoring Option to enable Web Snapshots

**Documentation**<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>**Power Cords** *(must select one)*

PWR-CORD-ARG-D

Power Cable for Argentina

PWR-CORD-AUS-D

Power Cord AUS YP35 to YC12

PWR-CORD-BRA-D

Brazil Power Cord

PWR-CORD-CH-D

Power Cord Switzerland YP-46 to YC12

PWR-CORD-CN-D

Pwr Cord China YP03 to YC1

PWR-CORD-EUR-D

Power Cord EUR YP23 to YC12

PWR-CORD-IND-D

Power Cord for India

PWR-CORD-JPN-D

118530 Cord Pwr JPN YP12 to YC12

PWR-CORD-ROK-D

Power Cord Korea YP22K - TC12

PWR-CORD-UK-D

Power Cord UK YP-61 to YC12

PWR-CORD-US-D

Pwr Cord US YP-12 to YC12

PWR-CORD-ZAF-D

Power Cord South Africa

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-MX300-K9

MX300 G2

**NEW ACCESSORIES APRIL 2016**

see highlighted items



The MX300 G2 has a 55" LCD screen, with (3) presentation inputs and an HDMI output for an additional screen. The MX300 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description	
<b>CTS-MX300-K9</b>	<b>Cisco TelePresence MX300 G2</b>	
	<i>Product Desc: 55" LED/LCD, integrated PHD1080p4xCam, Touch 10 UI, 2 microphones</i>	
	<i>The 4X cam has 4X optical and 2X digital zoom; total zoom 8X</i>	
<b>Main Components</b>	<b>automatically included with Top Level PID</b>	
CTS-MX300-UNIT	<i>included</i>	MX300 G2 integrated codec, LCD screen, speakers, bezel mic
CTS-CTRL-DVX-10	<i>included</i>	Touch 10 Device
CAB-DV10-8M=	<i>included</i>	8 meter flat grey Ethernet cable for Touch 10
CTS-MIC-TABL20	<i>included</i>	Table Microphone 20 (Qty 2) - 7.5m cable attached
LIC-MX300	<i>included</i>	PRODUCT ID - MX300 G2
CAB-NET-EN5M=	<i>included</i>	Ethernet cable (5m)
CAB-PRESO-2HDMI	<i>included</i>	HDMI presentation cable 8 meters
<b>Software Feature Options</b>		
SW-S52010-CE8-K9	<i>included</i>	SW Image for SX20 and MX200/300 G2 endpoints
LIC-CE-CRYPTO-K9	<i>no-cost option</i>	License key to activate sw encryption module
LIC-CE-NONCRYPTO	<i>no-cost option</i>	License key to activate sw without encryption module
LIC-MX300-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>	
LIC-MX300-MS	<i>optional</i>	MX300 G2 MultiSite (w576p30 Main / 1080p30 Presentation)
<b>Remote Monitoring</b>	L-TP-RM	<b>must be ordered separately</b>
L-MX-SERIES-RM	<i>order separately</i>	MX Remote Monitoring Option to enable Web Snapshots
<b>Mounting Kit Options (select one)</b>	<b>Mounting Kits can be ordered as spares, in case a different mount is needed post-sale</b>	
CTS-MX300-FSK	<i>no-cost option</i>	Cisco TelePresence MX300 G2 Floor Stand Kit
CTS-MX300-WMK	<i>no-cost option</i>	Cisco TelePresence MX300 G2 Wall Mount Kit
CTS-MX300-WBK	<i>no-cost option</i>	Cisco TelePresence MX300 G2 Wheelbase

SOFTWARE

Cisco Product ID (PID)	Description
------------------------	-------------

### Presentation Cable Options

CAB-HDMI-MULT-9M

CAB-DVI-VGA-8M

Presentation cable for HDMI, Display Port, Mini Display Port  
VGA presentation cable with 3.5mm audio, 8 meters



### Microphone Option

CAB-MIC20-EXT=

CTS-MIC-CLNG-G2=

CAB-ETHRSHLD-10M=

*order separately*

*order separately*

Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M  
Cisco Ceiling Microphone Gen 2 (see Microphones)  
Shielded audio cable 10m, for Ceiling Microphone, not plenum rated

### Selected Spares

TOUCH

CTS-CTRL-DV10=

CTS-PWR-AIR-INJ5=

CAB-DV10-12.5=

CAB-DV10-8M=

CAB-DV10-4M=

Touch 10 Device  
Power Injector (802.3af) (requires power cable)  
12.5 meter flat grey Ethernet cable for Touch 10  
8 meter flat grey Ethernet cable for Touch 10  
4 meter flat grey Ethernet cable for Touch 10

CTS-MIC-TABL20=

Table Microphone 20 - *7.5m cable attached*

CABLES

CAB-MIC20-EXT=

CAB-NET-EN5M=

CAB-PRESO-2HDMI=

CAB-HDMI-MULT-9M=

CAB-DVI-VGA-8M=

CAB-DVI-VGA-3.5mm=

Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M  
Ethernet cable (5m)  
HDMI to HDMI cable, 8 meter, gray  
Presentation cable for HDMI, Display Port, Mini Display Port  
VGA presentation cable with 3.5mm audio, 8 meters  
Presentation cable w/audio, 6 meters  
*(VGA-M to DVI-M w/3.5mm audio)*

FORM

CTS-MX300-FSK=

CTS-MX300-WMK=

CTS-MX300-WBK=

CTS-MX300-FB=

Cisco TelePresence MX300 G2 Floor Stand Kit  
Cisco TelePresence MX300 G2 Wall Mount Kit  
Cisco TelePresence MX300 G2 Wheelbase  
Front Bezel spare for MX300

### Post-Sale Licensing

SOFTWARE

#### MultiSite / PR

L-MX-SERIES-PAK

L-MX300-MS

L-MX300-PR

*zero dollar*

E-delivery of MX300 G2 MultiSite option  
E-delivery of MX300 G2 Premium Resolution option

#### Remote Monitoring

L-TP-RM

L-MX-SERIES-RM

MX Remote Monitoring Option to enable Web Snapshots

### Documentation

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

### Power Cords *(must select one)*

PWR-CORD-ARG-E

PWR-CORD-AUS-E

PWR-CORD-BZ-E

PWR-CORD-CH-E

PWR-CORD-CN-E

PWR-CORD-EUR-E

PWR-CORD-JP-E

PWR-CORD-ROK-E

PWR-CORD-UK-E

PWR-CORD-US-E

PWR-CORD-IND-E

PWR-CORD-ZAF-E

MX - Pwr cable Argentina 5m  
MX - Pwr cable Australia 5m  
Brazil Power Cord EL223, EL702, 250V, 10A, 5M, RT Angle  
MX - Pwr cable Switzerland 5m  
MX - Pwr cable CN (China) 5m  
MX - Pwr cable Euro 5m  
MX - Pwr cable Japan 5m  
MX - Pwr cable Korea 5m  
MX - Pwr cable UK 5m  
MX - Pwr cable US 4.5m  
MX - Power cable for India  
MX - Power cable for South Africa

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-MX200-K9

MX200 G2

**NEW ACCESSORIES APRIL 2016**

see highlighted items



The MX200 G2 has a 42" LCD screen, with (3) presentation inputs and an HDMI output for an additional screen. The MX200 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description	
<b>CTS-MX200-K9</b>	<b>Cisco TelePresence MX200 G2</b>	
	<i>Product Desc: 42" LED/LCD, integrated PHD1080p2.5xCam, Touch UI, 1 microphone</i>	
	<b>The 2.5X cam has 2.5X optical and 2X digital zoom; total zoom 5X</b>	
<b>Main Components</b>	<b>automatically included with Top Level PID</b>	
CTS-MX200-UNIT	<i>included</i>	MX200 G2 integrated codec, LCD screen, speakers, bezel mic
CTS-CTRL-DVX-10	<i>included</i>	Touch 10 Device
CAB-DV10-8M=	<i>included</i>	8 meter flat grey Ethernet cable for Touch 10
CTS-MIC-TABL20	<i>included</i>	Table Microphone 20 (Qty 1) - 7.5m cable attached
LIC-MX200	<i>included</i>	PRODUCT ID - MX200 G2
CAB-NET-EN5M=	<i>included</i>	Ethernet cable (5m)
CAB-PRESO-2HDMI	<i>included</i>	HDMI presentation cable 8 meters
<b>Software Feature Options</b>		
SW-S52010-CE8-K9	<i>included</i>	SW Image for SX20 and MX200/300 G2 endpoints
LIC-CE-CRYPTO-K9	<i>no-cost option</i>	License key to activate sw encryption module
LIC-CE-NONCRYPTO	<i>no-cost option</i>	License key to activate sw without encryption module
LIC-MX200-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>	
LIC-MX200-MS	<i>optional</i>	MX200 G2 MultiSite (w576p30 Main / 1080p30 Presentation)
<b>Remote Monitoring</b>	L-TP-RM	
L-MX-SERIES-RM	<i>order separately</i>	MX Remote Monitoring Option to enable Web Snapshots
<b>Mounting Kit Options (select one)</b>	<b>Mounting Kits can be ordered as spares, in case a different mount is needed post-sale</b>	
CTS-MX200-FSK	<i>no-cost option</i>	Cisco TelePresence MX200 G2 Floor Stand Kit
CTS-MX200-TSK	<i>no-cost option</i>	Cisco TelePresence MX200 G2 Table Stand Kit
CTS-MX200-WBK	<i>no-cost option</i>	Cisco TelePresence MX200 G2 Wheelbase
CTS-MX200-WMK	<i>no-cost option</i>	Cisco TelePresence MX200 G2 Wallmount Kit

SOFTWARE

Cisco Product ID (PID)	Description
------------------------	-------------

**Presentation Cable Options**

- CAB-HDMI-MULT-9M
- CAB-DVI-VGA-8M

Presentation cable for HDMI, Display Port, Mini Display Port  
VGA presentation cable with 3.5mm audio, 8 meters



**Microphone Option**

- CTS-MIC-TABL20
- CAB-MIC20-EXT=
- CTS-MIC-CLNG-G2=
- CAB-ETHRSHLD-10M=

*order separately*  
*order separately*

Table Mic 20 (2nd mic) - 7.5m cable attached  
Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M  
Cisco Ceiling Microphone Gen 2 (see Microphones)  
Shielded audio cable 10m, for Ceiling Microphone, not plenum rated

**Selected Spares**

TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10

	CTS-QSC20-MIC=	Table Microphone 20 - 7.5m cable attached
--	----------------	---

CABLES	CAB-MIC20-EXT=	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M
	CAB-NET-EN5M=	Ethernet cable (5m)
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
	CAB-DVI-VGA-3.5mm=	Presentation cable w/audio, 6 meters <i>(VGA-M to DVI-M w/3.5mm audio)</i>

FORM	CTS-MX200-FSK=	Cisco TelePresence MX200 G2 Floor Stand Kit
	CTS-MX200-TSK=	Cisco TelePresence MX200 G2 Table Stand Kit
	CTS-MX200-WBK=	Cisco TelePresence MX200 G2 Wheelbase
	CTS-MX200-WMK=	Cisco TelePresence MX200 G2 Wallmount Kit

**Post-Sale Licensing**

SOFTWARE	<b>MultiSite</b>	L-MX-SERIES-PAK
	L-MX200-MS	E-delivery of MX200 G2 MultiSite option
	<b>Remote Monitoring</b>	L-TP-RM
	L-MX-SERIES-RM	MX Remote Monitoring Option to enable Web Snapshots

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords** *(must select one)*

PWR-CORD-ARG-E	MX - Pwr cable Argentina 5m
PWR-CORD-AUS-E	MX - Pwr cable Australia 5m
PWR-CORD-BZ-E	Brazil Power Cord EL223, EL702, 250V, 10A, 5M, RT Angle
PWR-CORD-CH-E	MX - Pwr cable Switzerland 5m
PWR-CORD-CN-E	MX - Pwr cable CN (China) 5m
PWR-CORD-EUR-E	MX - Pwr cable Euro 5m
PWR-CORD-JP-E	MX - Pwr cable Japan 5m
PWR-CORD-ROK-E	MX - Pwr cable Korea 5m
PWR-CORD-UK-E	MX - Pwr cable UK 5m
PWR-CORD-US-E	MX - Pwr cable US 4.5m
PWR-CORD-IND-E	MX - Power cable for India
PWR-CORD-ZAF-E	MX - Power cable for South Africa

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CP-DX80-K9=  
CP-DX80-NR-K9=

DX80

**Important:** Choice of CE software or Android

CE software is consistent with room-based collaboration systems

Android allows for customization, but no further Cisco development

For now, DX80s may arrive with Android software or CE8 software. It is

possible to change between them: [Convert Between CE and Android](#)



The DX80 has a 23" 1080p touchscreen, and one HDMI input for desktop display or Presentation.  
The DX80 running CE8 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.  
The DX80 running Android supports SIP only. It requires CUCM for call control.

## Cisco Product ID (PID)

## Description

CP-DX80-K9=

**Cisco DX80**

*Product Desc: 23" multi-touch LCD with Android OS, integrated camera, speaker, 2 microphones*

CP-DX80-NR-K9=

**Cisco DX80 No-Radio Version**

*Product Desc: DX80 without Bluetooth or Wi-Fi hardware*

**Main Components**

**automatically included with Top Level PID**

CAB-COMBO-2M	<i>included</i>	USB and HDMI cable set, 2 meters
CAB-GREY-2.9M	<i>included</i>	Ethernet cable, grey, 2.9 meters
CP-PWR-CUBE-5	<i>included</i>	Power supply for DX70 and DX80 12VDC 5A

**Options**

**order separately**

CP-DX80-VESA=		VESA Compatible Wall Mount Kit for DX80
SPVAC-H450-W-US=		Jabra Handset 450 for Cisco - US - White
SPVAC-H450-W-TW=		Jabra Handset 450 for Cisco - Taiwan - White
SPVAC-H450-W-JP=		Jabra Handset 450 for Cisco - Japan - White
SPVAC-H450-W-EU=		Jabra Handset 450 for Cisco - EU, Australia, and NZ - White

**Remote Monitoring**

L-TP-RM

**CE8 software only**

L-DX-SERIES-RM

*order separately*

DX Remote Monitoring Option to enable Web Snapshots (CE8 Software)

**Selected Spares**

CAB-COMBO-2M=	USB and HDMI cable set, 2 meters
CAB-GREY-2.9M=	Ethernet cable, grey, 2.9 meters
CP-DX80-FS=	Replacement foot stand
CP-PWR-CUBE-5=	Power supply for DX70 and DX80 12VDC 5A

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

CP-PWR-CORD-AP	Power cord for Asia Pacific regions such as Hong Kong and Malaysia
CP-PWR-CORD-AR	Power cord for Argentina
CP-PWR-CORD-AU	Power cord for Australia and New Zealand
CP-PWR-CORD-BZ	Power cord for Brazil
CP-PWR-CORD-CE	Power cord for Europe and regions that use the same plugs
CP-PWR-CORD-CN	Power cord for China
CP-PWR-CORD-JP	Power cord for Japan
CP-PWR-CORD-NA	Power cord for North America and regions that use the same plugs
CP-PWR-CORD-SW	Power cord for Switzerland
CP-PWR-CORD-UK	Power cord for United Kingdom and regions that use the same plugs

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.



[Index](#)

CP-DX70-W-K9=  
CP-DX70-W-NR-K9=

DX70

**Important:** Choice of CE software or Android

CE software is consistent with room-based collaboration systems

Android allows for customization, but no further Cisco development

For now, DX70s may arrive with Android software or CE8 software. It is

possible to change between them: [Convert Between CE and Android](#)



The DX70 has a 14" 1080p touchscreen, one HDMI input for computer desktop, and one HDMI output for mirroring (Android only).

The DX70 running CE8 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

The DX70 running Android supports SIP only. It requires CUCM for call control.

Cisco Product ID (PID)	Description	
CP-DX70-W-K9=	<b>Cisco DX70</b>	
	<i>Product Desc:</i> 14" multi-touch LCD with Android OS, integrated camera, speaker, 1 microphone	
CP-DX70-W-NR-K9=	<b>Cisco DX70 No-Radio Version</b>	
	<i>Product Desc:</i> DX70 without Bluetooth or Wi-Fi hardware	
<b>Main Components</b>		
CAB-GREY-2.9M	<i>included</i>	<b>automatically included with Top Level PID</b> Ethernet cable, grey, 2.9 meters
CP-PWR-CUBE-5	<i>included</i>	Power supply for DX70 and DX80 12VDC 5A
<b>Options</b>		
CAB-DX-2HDMI-3M	<i>optional</i>	3M HDMI to HDMI cable for connecting source to DX70
CP-DX70-VESA=	<i>order separately</i>	VESA Compatible Wall Mount Kit for DX70
SPVAC-H450-W-US=	<i>order separately</i>	Jabra Handset 450 for Cisco - US - White
SPVAC-H450-W-TW=	<i>order separately</i>	Jabra Handset 450 for Cisco - Taiwan - White
SPVAC-H450-W-JP=	<i>order separately</i>	Jabra Handset 450 for Cisco - Japan - White
SPVAC-H450-W-EU=	<i>order separately</i>	Jabra Handset 450 for Cisco - EU, Australia, and NZ - White
<b>Remote Monitoring</b>		
L-DX-SERIES-RM	<i>order separately</i>	L-TP-RM <b>CE8 software only</b> DX Remote Monitoring Option to enable Web Snapshots (CE8 Software)
<b>Selected Spares</b>		
CAB-GREY-2.9M=		Ethernet cable, grey, 2.9 meters
CP-DX70-FS=		Replacement foot stand
CP-PWR-CUBE-5=		Power supply for DX70 and DX80 12VDC 5A
<b>Documentation</b>		
<a href="http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323">http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323</a>		

**Power Cords**

CP-PWR-CORD-AP	Power cord for Asia Pacific regions such as Hong Kong and Malaysia
CP-PWR-CORD-AR	Power cord for Argentina
CP-PWR-CORD-AU	Power cord for Australia and New Zealand
CP-PWR-CORD-BZ	Power cord for Brazil
CP-PWR-CORD-CE	Power cord for Europe and regions that use the same plugs
CP-PWR-CORD-CN	Power cord for China
CP-PWR-CORD-JP	Power cord for Japan
CP-PWR-CORD-NA	Power cord for North America and regions that use the same plugs
CP-PWR-CORD-SW	Power cord for Switzerland
CP-PWR-CORD-UK	Power cord for United Kingdom and regions that use the same plugs

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CP-DX650-K9=  
CP-DX650-W-K9=

DX650



The DX650 has a 7" touchscreen with 1024x600 resolution, and one high definition HDMI output for extending the desktop. Power over Ethernet (IEEE 802.3af minimum) is supported. The DX650 requires CUCM for SIP call control.

**Cisco Product ID (PID)****Description**

**CP-DX650-K9=**

**Cisco DX650 Smoke**

*Product Desc: 7" multi-touch LCD with Android OS, integrated camera, speaker, microphone*

**CP-DX650-W-K9=**

**Cisco DX650 White**

*Product Desc: 7" multi-touch LCD with Android OS, integrated camera, speaker, microphone*

**Selected Items**

CP-DX-HS=

**order separately**

Spare Handset Grey

CP-DX-W-HS=

Spare Handset White

CP-DX-CORD=

Spare Coil Cord Grey

CP-DX-W-CORD=

Spare Coil Cord White

CP-DX650-ADA-WMK=

ADA Locking Wall Mount Kit for DX650

CP-PWR-CUBE-4=

Power Cube 4 adapter for Cisco Unified 8800/9900 and DX600 Series

*To be used when PoE is not available*

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords****order separately when Power Cube is used**

CP-PWR-CORD-AP=

Power cord for Asia Pacific regions such as Hong Kong and Malaysia

CP-PWR-CORD-AR=

Power cord for Argentina

CP-PWR-CORD-AU=

Power cord for Australia and New Zealand

CP-PWR-CORD-BZ=

Power cord for Brazil

CP-PWR-CORD-CE=

Power cord for Europe and regions that use the same plugs

CP-PWR-CORD-CN=

Power cord for China

CP-PWR-CORD-JP=

Power cord for Japan

CP-PWR-CORD-NA=

Power cord for North America and regions that use the same plugs

CP-PWR-CORD-SW=

Power cord for Switzerland

CP-PWR-CORD-UK=

Power cord for United Kingdom and regions that use the same plugs

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-EX90-K9

EX90



The EX90 has a WUXGA screen; DVI and HDMI inputs for desktop display or Presentation. The EX90 supports SIP and H.323. It registers to CUCM, VCS, and third party devices.

Cisco Product ID (PID)	Description	
<b>CTS-EX90-K9</b>	<b>Cisco TelePresence EX90</b>	
	<i>Product Desc: 24" LCD screen, integrated camera, speakers, microphone</i>	
<b>Main Components</b>	<b>automatically included with Top Level PID</b>	
CTS-CTRL-DV8	<i>included</i>	8" Touch Control for EX with cradle and handset - 1.5m cable
LIC-EX90	<i>included</i>	PRODUCT ID - EX90
CAB-ETH-5M=	<i>included</i>	Ethernet cable (5m)
CAB-DVI-A-VGA125	<i>included</i>	DVI-A to VGA Presentation cable 2m
CAB-DVI-D181	<i>included</i>	DVI-D to DVI-D Presentation cable 2m
CAB-STEREO35MM	<i>included</i>	3.5mm stereo audio cable 2m
PSU-EX90=	<i>included</i>	Power Supply for EX90/150watts
<b>SOFTWARE</b>	<b>Software Feature Options</b>	
LIC-S52000-TCX.XK9	<i>no-cost option</i>	License Key Encrypted SW - 10Mb total / 6Mb per call - <i>includes 720p30</i>
SW-S52000-TC7-K9	<i>no-cost option</i>	SW Image Encrypted for C/EX/Profile/MX(1st gen) series endpoints
LIC-S52001-TCX.X	<i>no-cost option</i>	License Key Non-Encrypted SW - 10Mb total / 6Mb per call - <i>includes 720p30</i>
SW-S52001-TC7	<i>no-cost option</i>	SW Image Non-encrypted for C/EX/Profile/MX(1st gen) series endpoints
LIC-ECXX-NPP	<i>included</i>	EX Series NPP option
<i>Please remember to specify the no-cost Premium Resolution and Dual Display options when ordering</i>		
LIC-EX90-DD	<i>no-cost option</i>	EX90 Dual Display - <i>enables HDMI output</i>
LIC-EX90-PR	<i>no-cost option</i>	EX90 - Premium Resolution (720p60 / 1080p30 / UXGA)
LIC-EX90-MS	<i>optional</i>	EX90 MultiSite (720p30 Main / WXGAp30 Presentation)
<b>Remote Monitoring</b>	<b>L-TP-RM</b>	
L-EX-SERIES-RM	<i>order separately</i>	EX Remote Monitoring Option to enable Web Snapshots

**Selected Spares**

CTS-CTRL-DV8=	Touch Device for EX with cradle and handset - 1.5m cable
CTS-CTRL-DV8CRDL=	Spare Cradle w/Handset - <i>EX Series ONLY/Touch NOT included</i>

*The EX90 supports the use of one Table Mic 20*

CTS-MIC-TABL20	Table Mic 20 - integrated 7.5m cable (new version)
CTS-QSC20-MIC=	Table Mic 20 - integrated 7.5m cable

**CABLES**

CAB-MIC20-EXT=	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M
CAB-NET-EN5M=	Ethernet cable (5m)
CAB-DVI-D181=	DVI-D to DVI-D Presentation cable 2m
CAB-STEREO35MM=	3.5mm stereo audio cable 2m
CAB-DVI-A-VGA125=	Presentation cable w/audio (VGA-M to DVI-M w/3.5mm audio)
CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
CAB-2HDMI-5M=	HDMI cable 5 meter

PSU-EX90=	Power Supply for EX90/150watts
-----------	--------------------------------

**Post-Sale Licensing****SOFTWARE**

<b>MultiSite / PR / DD</b>	L-EX-PAK	
L-EX90-MS		Order L-EX-PAK for E delivery of EX90 MS Option
L-EX90-PR	zero dollar	Order L-EX-PAK for E-delivery of EX90 PR Option
L-EX90-DD	zero dollar	Order L-EX-PAK for E-delivery of EX90 DD Option

<b>Remote Monitoring</b>	L-TP-RM	
L-EX-SERIES-RM		EX Remote Monitoring Option to enable Web Snapshots

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-JP-A	Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-UK-A	Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	Pwr Cord US 1.8m Black YP-12 To YC-12

[Index](#)

CTS-SX80-IPST60-K9

SX80 Integrator Package SpeakerTrack 60



The SX80 supports three high-definition monitors. Transmit / receive resolutions up to 1080p60 are supported. The SX80 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description
------------------------	-------------

CTS-SX80-IPST60-K9

Cisco SX80 Integrator Package SpeakerTrack 60

*Product Desc: SX80 codec with SpeakerTrack 60 and Touch 10 User Interface*

*The SpeakerTrack 60 has 10X optical and 2X digital zoom; total zoom 20X*

**Main Components**

CTS-SX80CODEC	<i>included</i>	Cisco SX80 Codec
CTS-SPKER-TRACK60	<i>included</i>	SpeakerTrack 60, complete, includes (2) P60 cameras
PWR-12VDC-84W	<i>included</i>	Power supply 12VDC 84W for SpeakerTrack 60
CTS-CTRL-DVX-10	<i>included</i>	Touch 10 Device
CTS-PWR-AIR-INJ5	<i>included</i>	Power Injector (802.3af)
CAB-DV10-12.5M	<i>included</i>	12.5 meter flat grey Ethernet cable for Touch 10
CAB-DV10-4M=	<i>included</i>	4 meter flat grey Ethernet cable for Touch 10
CAB-DVI-VGA-PHOEN	<i>included</i>	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
CTS-SX80-RACKEARS	<i>included</i>	SX80 Rackmount ears for 19" rack
n/a	<i>included</i>	Full set of Phoenix-style Euroblock connectors
LIC-SX80	<i>included</i>	PRODUCT ID - SX80 Codec

**Hardware Options**

CTS-CAM-P60	<i>optional</i>	Precision 60 Camera - additional Qty 1 can be ordered
CTS-CAM60-BRKT	<i>optional</i>	Wall and ceiling bracket for Precision 60 Camera
CTS-MIC-TABL60	<i>optional</i>	Table Microphone 60 - 9m Euroblock cable and table bracket included
CTS-MIC-CLNG-G2=	<i>optional</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)
CAB-ETHRSHLD-10M=	<i>optional</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated

*Note: no microphones are included unless chosen as options*

**Presentation Cable**

CAB-HDMI-MULT-9M=	<i>order separately</i>	Presentation cable for HDMI, Display Port, Mini Display Port
CAB-PRESO-2HDMI=	<i>order separately</i>	HDMI to HDMI cable, 8 meter, gray

*Must be ordered separately*



	Cisco Product ID (PID)	Description
<b>Software Feature Options</b>		
SOFTWARE	SW-S52010-CE8-K9	<i>included</i> SW Image for SX80, MX700, MX800 - H.265 point to point, H.264, H.263, H.261
	LIC-CE-CRYPTO-K9	<i>no-cost option</i> License key to activate sw encryption module
	LIC-CE-NONCRYPTO	<i>no-cost option</i> License key to activate sw without encryption module
	LIC-SX80-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
	LIC-SX80-MS	<i>optional</i> SX80 MultiSite (5-way 720p30 Main / 1080p15 Presentation)
	<b>Remote Monitoring</b>	L-TP-RM
	L-SX-SERIES-RM	<i>order separately</i> SX Remote Monitoring Option to enable Web Snapshots
<b>Selected Spares</b>		
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CABLES	CTS-MIC-TABL60=	Table Microphone 60 - 9m Euroblock cable and table bracket included
	CAB-MIC-T60EXT=	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
	CAB-MIC-T60=	Spare cable 9m for Table Microphone 60
	CAB-XLR-EUROBLOCK=	Euroblock (Phoenix) to female XLR adapter, 20 cm
	CAB-VC2-5M	Visca Control Cable 5m - DB9 to RJ45 - <i>requires PSU-12VDC-40W2=</i>
	CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-DVI-VGA-PHOEN	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
	CAB-2HDMI-6M=	HDMI cable 6 meter
CAB-NET-EN5M=	Ethernet cable 5 meter	
CAMERAS	CTS-CAM-P60=	Precision 60 Camera
	CTS-CAM-P40=	Precision 40 Camera (4XS2) (Old PID: CTS-PHD1080P4XS2=)
	PSU-12VDC-40W2=	Power Supply for Camera - 12VDC 40W
	CTS-CAM60-BRKT=	Wall and ceiling bracket for Precision 60 Camera
	BRKT-PHD4X-MONITR=	Bracket for mounting 4XS2 PHDCam to monitor
	CTS-SX80CODEC=	SX80 Codec Spare - for cold standby use
	CTS-SX80-RACKEARS=	1RU mounting ears for 19" rack
<b>All SpeakerTrack Orderable Spares</b>		
SPEAKER TRACK	CTS-SPKER-TRACK60=	SpeakerTrack 60, complete
	CTS-CAM-P60=	Precision 60 Camera Qty 2
	CTS-ST-ARRAY60=	Speaker Track 60 Microphone Array
	CTS-ST-ARR60-WMK=	Wall Mount Kit for Speaker Track 60 Microphone Array
	CAB-ETH-ST-SHORT=	Qty (2) Ethernet cables (0.35m&0.2m) for SpeakerTrack 60
	CAB-PWR-ST-SHORT=	Qty (2) 12V power cables (0.45m&0.2m) for SpeakerTrack 60
	CTS-ST-INT-PLATE=	Interface plate CAM-P60 to Speaker Track 60
	PWR-12VDC-84W=	Power supply 12VDC 84W for SpeakerTrack 60
<b>Post-Sale Licensing</b>		
SOFTWARE	<b>MultiSite</b>	L-SX-SERIES-PAK
	L-SX80-MS	Order L-SX-Series-PAK for e-delivery of MultiSite sw option
	<b>Remote Monitoring</b>	L-TP-RM
	L-SX-SERIES-RM	SX Remote Monitoring Option to enable Web Snapshots



**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-IND-A	Power cable India 1.8m
PWR-CORD-JP-A	Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	Pwr Cord US 1.8m Black YP-12 To YC-12
PWR-CORD-ZAF-A	Power cable South Africa 1.8 m

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-SX80-IP60-K9

SX80 Integrator Package 60



The SX80 supports three high-definition monitors. Transmit / receive resolutions up to 1080p60 are supported. The SX80 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description
------------------------	-------------

CTS-SX80-IP60-K9

Cisco SX80 Integrator Package 60

*Product Desc: SX80 codec with Precision 60 Camera and Touch 10 User Interface*

*The Precision60 has 10X optical and 2X digital zoom; total zoom 20X*

**Main Components**

CTS-SX80CODEC	<i>included</i>	Cisco SX80 Codec
CTS-CAM-P60	<i>included</i>	Precision 60 Camera
PSU-12VDC-40W2	<i>included</i>	Power Supply 12VDC 40W (for camera)
CTS-CTRL-DVX-10	<i>included</i>	Touch 10 Device
CTS-PWR-AIR-INJ5	<i>included</i>	Power Injector (802.3af)
CAB-DV10-12.5M	<i>included</i>	12.5 meter flat grey Ethernet cable for Touch 10
CAB-DV10-4M=	<i>included</i>	4 meter flat grey Ethernet cable for Touch 10
CAB-DVI-VGA-PHOEN	<i>included</i>	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
CTS-SX80-RACKEARS	<i>included</i>	SX80 Rackmount ears for 19" rack
n/a	<i>included</i>	Full set of Phoenix-style Euroblock connectors
LIC-SX80	<i>included</i>	PRODUCT ID - SX80 Codec

**Hardware Options**

CTS-CAM-P60	<i>optional</i>	Precision 60 Camera - additional Qty 2 can be ordered
CTS-CAM60-BRKT	<i>optional</i>	Wall and ceiling bracket for Precision 60 Camera
CTS-MIC-TABL60	<i>optional</i>	Table Microphone 60 - 9m Euroblock cable and table bracket included
CTS-MIC-CLNG-G2	<i>optional</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)
CAB-ETHRSHLD-10M	<i>optional</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated

*Note: no microphones are included unless chosen as options*

**Presentation Cable**

CAB-HDMI-MULT-9M=	<i>order separately</i>	Presentation cable for HDMI, Display Port, Mini Display Port
CAB-PRESO-2HDMI=	<i>order separately</i>	HDMI to HDMI cable, 8 meter, gray



Cisco Product ID (PID)		Description
<b>Software Feature Options</b>		
SOFTWARE	SW-S52010-CE8-K9	<i>included</i> SW Image for SX80, MX700, MX800 - H.265 point to point, H.264, H.263, H.261
	LIC-CE-CRYPTO-K9	<i>no-cost option</i> License key to activate sw encryption module
	LIC-CE-NONCRYPTO	<i>no-cost option</i> License key to activate sw without encryption module
	LIC-SX80-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
	LIC-SX80-MS	<i>optional</i> SX80 MultiSite (5-way 720p30 Main / 1080p15 Presentation)
	<b>Remote Monitoring</b>	L-TP-RM
L-SX-SERIES-RM	<i>order separately</i> SX Remote Monitoring Option to enable Web Snapshots	
<b>Selected Spares</b>		
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CABLES	CTS-MIC-TABL60=	Table Microphone 60 - 9m Euroblock cable and table bracket included
	CAB-MIC-T60EXT=	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
	CAB-MIC-T60=	Spare cable 9m for Table Microphone 60
	CAB-XLR-EUROBLOCK=	Euroblock (Phoenix) to female XLR adapter, 20 cm
	CAB-VC2-5M	Visca Control Cable 5m - DB9 to RJ45 - <i>requires PSU-12VDC-40W2=</i>
	CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-DVI-VGA-PHOEN	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
	CAB-2HDMI-6M=	HDMI cable 6 meter
	CAB-NET-EN5M=	Ethernet cable 5 meter
CAMERAS	CTS-CAM-P60=	Precision 60 Camera
	CTS-PHD1080P4XS2=	PrecisionHD 4X Camera with unity connector
	PSU-12VDC-40W2=	Power Supply for Camera - 12VDC 40W
	CTS-CAM60-BRKT=	Wall and ceiling bracket for Precision 60 Camera
	BRKT-PHD4X-MONITR=	Bracket for mounting 4XS2 PHDCam to monitor
CTS-SX80CODEC=	SX80 Codec Spare - for cold standby use	
CTS-SX80-RACKEARS=	1RU mounting ears for 19" rack	
<b>Post-Sale Licensing</b>		
SOFTWARE	<b>MultiSite</b>	L-SX-SERIES-PAK
	L-SX80-MS	Order L-SX-Series-PAK for e-delivery of MultiSite sw option
	<b>Remote Monitoring</b>	L-TP-RM
L-SX-SERIES-RM	SX Remote Monitoring Option to enable Web Snapshots	

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-IND-A	Power cable India 1.8m
PWR-CORD-JP-A	Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	Pwr Cord US 1.8m Black YP-12 To YC-12
PWR-CORD-ZAF-A	Power cable South Africa 1.8 m

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-SX80-IP40-K9

SX80 Integrator Package 40



The SX80 supports three high-definition monitors. Transmit / receive resolutions up to 1080p60 are supported. The SX80 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description
------------------------	-------------

CTS-SX80-IP40-K9

Cisco SX80 Integrator Package 40

*Product Desc:* SX80 codec with PrecisionHD 4X Camera and Touch 10 User Interface  
*The 4XS2 camera has 4X optical and 2X digital zoom; total zoom 8X*

**Main Components**

CTS-SX80CODEC	<i>included</i>	Cisco SX80 Codec
CTS-PHD1080P4XS2	<i>included</i>	PrecisionHD 4X Camera with unity connector
PSU-12VDC-40W2	<i>included</i>	Power Supply 12VDC 40W (for camera)
CAB-PHD4XS2-SPLIT	<i>included</i>	Camera Break Out Cable - unity connector to RJ45-F and HDMI-F
CAB-VC2-5M	<i>included</i>	Visca Control Cable 5m - DB9 to RJ45
CTS-CTRL-DVX-10	<i>included</i>	Touch 10 Device
CTS-PWR-AIR-INJ5	<i>included</i>	Power Injector (802.3af)
CAB-DV10-12.5M	<i>included</i>	12.5 meter flat grey Ethernet cable for Touch 10
CAB-DV10-4M=	<i>included</i>	4 meter flat grey Ethernet cable for Touch 10
CAB-DVI-VGA-PHOEN	<i>included</i>	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
CTS-SX80-RACKEARS	<i>included</i>	SX80 Rackmount ears for 19" rack
n/a	<i>included</i>	Full set of Phoenix-style Euroblock connectors
LIC-SX80	<i>included</i>	PRODUCT ID - SX80 Codec

**Hardware Options**

CTS-CAM-P60	<i>optional</i>	Precision 60 Camera - additional Qty 2 can be ordered
CTS-CAM60-BRKT	<i>optional</i>	Wall and ceiling bracket for Precision 60 Camera
CTS-MIC-TABL60	<i>optional</i>	Table Microphone 60 - 9m Euroblock cable and table bracket included
CTS-MIC-CLNG-G2	<i>optional</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)
CAB-ETHRSHLD-10M	<i>optional</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated

**Presentation Cable**

CAB-HDMI-MULT-9M=	<i>order separately</i>	Presentation cable for HDMI, Display Port, Mini Display Port
CAB-PRESO-2HDMI=	<i>order separately</i>	HDMI to HDMI cable, 8 meter, gray



Cisco Product ID (PID)		Description
<b>Software Feature Options</b>		
SOFTWARE	SW-S52010-CE8-K9	<i>included</i> SW Image for SX80, MX700, MX800 - H.265 point to point, H.264, H.263, H.261
	LIC-CE-CRYPTO-K9	<i>no-cost option</i> License key to activate sw encryption module
	LIC-CE-NONCRYPTO	<i>no-cost option</i> License key to activate sw without encryption module
	LIC-SX80-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
	LIC-SX80-MS	<i>optional</i> SX80 MultiSite (5-way 720p30 Main / 1080p15 Presentation)
	<b>Remote Monitoring</b>	L-TP-RM
L-SX-SERIES-RM	<i>order separately</i> SX Remote Monitoring Option to enable Web Snapshots	
<b>Selected Spares</b>		
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CABLES	CTS-MIC-TABL60=	Table Microphone 60 - 9m Euroblock cable and table bracket included
	CAB-MIC-T60EXT=	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
	CAB-MIC-T60=	Spare cable 9m for Table Microphone 60
	CAB-XLR-EUROBLOCK=	Euroblock (Phoenix) to female XLR adapter, 20 cm
	CAB-VC2-5M	Visca Control Cable 5m - DB9 to RJ45 - <i>requires PSU-12VDC-40W2=</i>
	CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-DVI-VGA-PHOEN	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
	CAB-2HDMI-6M=	HDMI cable 6 meter
	CAB-NET-EN5M=	Ethernet cable 5 meter
CAMERAS	CTS-CAM-P60=	Precision 60 Camera
	CTS-PHD1080P4XS2=	PrecisionHD 4X Camera with unity connector
	PSU-12VDC-40W2=	Power Supply for Camera - 12VDC 40W
	CTS-CAM60-BRKT=	Wall and ceiling bracket for Precision 60 Camera
	BRKT-PHD4X-MONITR=	Bracket for mounting 4XS2 PHDCam to monitor
	CTS-SX80CODEC=	SX80 Codec Spare - for cold standby use
CTS-SX80-RACKEARS=	1RU mounting ears for 19" rack	
<b>Post-Sale Licensing</b>		
SOFTWARE	<b>MultiSite</b>	L-SX-SERIES-PAK
	L-SX80-MS	Order L-SX-Series-PAK for e-delivery of MultiSite sw option
	<b>Remote Monitoring</b>	L-TP-RM
L-SX-SERIES-RM	SX Remote Monitoring Option to enable Web Snapshots	

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-IND-A	Power cable India 1.8m
PWR-CORD-JP-A	Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	Pwr Cord US 1.8m Black YP-12 To YC-12
PWR-CORD-ZAF-A	Power cable South Africa 1.8 m

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.



[Index](#)

CTS-SX80-K9

SX80 Codec



The SX80 supports three high-definition monitors. Transmit / receive resolutions up to 1080p60 are supported. The SX80 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description
------------------------	-------------

<b>CTS-SX80-K9</b>	<b>Cisco SX80 Codec</b> <i>Product Desc: SX80 codec with power cable</i>
--------------------	---

**Main Components**

CTS-SX80CODEC	<i>included</i>	Cisco SX80 Codec
CTS-SX80-RACKEARS	<i>included</i>	SX80 Rackmount ears for 19" rack
n/a	<i>included</i>	Full set of Phoenix-style Euroblock connectors
LIC-SX80	<i>included</i>	PRODUCT ID - SX80 Codec

**Suggested Optional Equipment**

*Note: no microphones are included unless ordered as spares*

CTS-MIC-TABL60=	<i>order separately</i>	Table Microphone 60 - 9m Euroblock cable and table bracket included
CAB-MIC-T60EXT=	<i>order separately</i>	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
CAB-MIC-T60=	<i>order separately</i>	Spare cable 9m for Table Microphone 60
CTS-MIC-CLNG-G2=	<i>order separately</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)
CAB-ETHRSHLD-10M=	<i>order separately</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated

**Presentation Cable**

*Must be ordered separately*

CAB-HDMI-MULT-9M=	<i>order separately</i>	Presentation cable for HDMI, Display Port, Mini Display Port
CAB-PRESO-2HDMI=	<i>order separately</i>	HDMI to HDMI cable, 8 meter, gray



**Software Feature Options**

<b>SOFTWARE</b>	SW-S52010-CE8-K9	<i>included</i>	SW Image for SX80, MX700, MX800 - H.265 point to point, H.264, H.263, H.261
	LIC-CE-CRYPTO-K9	<i>no-cost option</i>	License key to activate sw encryption module
	LIC-CE-NONCRYPTO	<i>no-cost option</i>	License key to activate sw without encryption module
	LIC-SX80-PR	<i>As of CE8.2, this option is included in base software, and is not listed separately</i>	
	LIC-SX80-MS	<i>optional</i>	SX80 MultiSite (5-way 720p30 Main / 1080p15 Presentation)
<b>Remote Monitoring</b>		L-TP-RM	
	L-SX-SERIES-RM	<i>order separately</i>	SX Remote Monitoring Option to enable Web Snapshots

Cisco Product ID (PID)		Description
<b>Selected Spares</b>		
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CTS-MIC-TABL60= Table Microphone 60 - 9m Euroblock cable and table bracket included		
CABLES	CAB-MIC-T60EXT=	9 meter extension cable for Table Microphone 60 (Euroblock connectors)
	CAB-MIC-T60=	Spare cable 9m for Table Microphone 60
	CAB-XLR-EUROBLOCK=	Euroblock (Phoenix) to female XLR adapter, 20 cm
	CAB-VC2-5M	Visca Control Cable 5m - DB9 to RJ45 - <i>requires PSU-12VDC-40W2=</i>
	CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-DVI-VGA-PHOEN	Presentation cable w/audio, 8 meters (VGA-M to DVI-M w/3.5mm male to phoenix audio)
	CAB-2HDMI-6M=	HDMI cable 6 meter
CAB-NET-EN5M=	Ethernet cable 5 meter	
CAMERAS	CTS-CAM-P60=	Precision 60 Camera
	CTS-PHD1080P4XS2=	PrecisionHD 4X Camera with unity connector
	PSU-12VDC-40W2=	Power Supply for Camera - 12VDC 40W
	CTS-CAM60-BRKT=	Wall and ceiling bracket for Precision 60 Camera
	BRKT-PHD4X-MONITR=	Bracket for mounting 4XS2 PHDCam to monitor
CTS-SX80CODEC=	SX80 Codec Spare - for cold standby use	
CTS-SX80-RACKEARS=	1RU mounting ears for 19" rack	
<b>Post-Sale Licensing</b>		
SOFTWARE	<b>MultiSite</b>	L-SX-SERIES-PAK
	L-SX80-MS	Order L-SX-Series-PAK for e-delivery of MultiSite sw option
	<b>Remote Monitoring</b>	L-TP-RM
L-SX-SERIES-RM	SX Remote Monitoring Option to enable Web Snapshots	
<b>Documentation</b>		
<a href="http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323">http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323</a>		
<b>Power Cords</b>		
PWR-CORD-ARG-A	Power cable ARG 1.8m black	
PWR-CORD-AUS-A	Pwr Cord AUS 1.8m Black YP-35 To YC-12	
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M	
PWR-CORD-CH-A	Pwr Cord CH 1.8m Black YP-46 To YC-12	
PWR-CORD-CN-A	Pw Cord CN (China) 1.8m Black w. ground	
PWR-CORD-EUR-A	Pwr Cord Euro 1.8m Black YP-23 To YC-12	
PWR-CORD-IND-A	Power cable India 1.8m	
PWR-CORD-JP-A	Pwr Cord Japan 1.8m With Label YP12/YC12	
PWR-CORD-ROK-A	Pwr Cord ROK 1.8m BlackYP-22K To YC-12	
PWR-CORD-UK-A	Pwr Cord UK 1.8m Black YP-61 To YC-12	
PWR-CORD-US-A	Pwr Cord US 1.8m Black YP-12 To YC-12	
PWR-CORD-ZAF-A	Power cable South Africa 1.8 m	
All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.		

[Index](#)

CTS-SX20N-12X-K9

SX20N Quick Set with 12X

*Ships with CE8 software and TRC6 remote control*

*What are the differences between the SX20 and SX20N?*

[Click here](#)



Dual Display and Premium Resolution are now included at no cost.

The SX20 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)

Description

CTS-SX20N-12X-K9

SX20N Quick Set with Precision 12x Camera

*Product Desc: SX20 codec, Dual Display, Prem Res, 12x PHDCam, 1 microphone, TRC6 remote control*

**Main Components**

CTS-SX20N-CODEC	<i>included</i>	SX20N Codec
CTS-PHD1080P12XS2	<i>included</i>	Precision 12X Camera Gen 2
CAB-HDMI-PHD12XS	<i>included</i>	Custom SX camera cable; HDMI, Ctrl and Power (3m)
CAB-2HDMI-3M	<i>included</i>	HDMI to HDMI cable for monitor, 3m
CTS-MIC-TABL20	<i>included</i>	Table Microphone 20 (Qty 1) - 7.5 meter cable attached
CTS-RMT-TRC6	<i>included</i>	Remote Control TRC 6
CAB-ETH-5M	<i>included</i>	Ethernet cable (5m) - <i>in SX 20 accessories kit</i>
LIC-SX20	<i>included</i>	PRODUCT ID - Quick Set SX20
PWR-60W-SX-AC	<i>included</i>	Power Supply for SX20

**Encryption Options (must select one)**

LIC-S5210-CE-K9	<i>no cost</i>	License key to activate sw with encryption module
SW-S52010-CE8-K9	<i>no cost</i>	SW Image: 6Mb total / 6Mb per call - includes 1080p60
LIC-S5211-CE	<i>no cost</i>	License key to activate sw without encryption module
SW-S52011-CE8	<i>no cost</i>	SW Image: 6Mb total / 6Mb per call - includes 1080p60

**Software Feature Options**

LIC-SX20-MS	<i>optional</i>	MultiSite Option for SX20 (w576p30 / 720p30 or 1080p30 Presentation)
LIC-SX20-NPP		<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
LIC-SX20-HD		<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
LIC-SX20-DD		<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
LIC-SX20-PR		<i>As of CE8.2, this option is included in base software, and is not listed separately</i>

SOFTWARE

**Remote Monitoring**

L-SX-SERIES-RM	<i>order separately</i>	L-TP-RM SX Remote Monitoring Option to enable Web Snapshots
----------------	-------------------------	--

Cisco Product ID (PID)		Description
<b>Optional Components</b>		<i>Selectable at time of order</i>
CTS-CTRL-DVX-10	<i>optional</i>	Touch 10" with cables
CAB-DV10-8M-		8 meter flat grey Ethernet cable (incl with Touch 10)
CTS-SX20-QS-WMK	<i>optional</i>	Wall Mount Kit for SX20
BRKT-12X-MONITR	<i>optional</i>	Bracket for mounting 12X PHD Cam to monitor
CTS-POE-INJ	<i>optional</i>	Power Injector (802.3af) <i>For a spare please order CTS-PWR-AIR-INJ5=</i>
CAB-DV10-4M		4 meter flat grey Touch 10 Ethernet cable (incl with CTS-POE-INJ)
CTS-MIC-TABL20	<i>optional</i>	Table Microphone 20 (2nd mic) - 7.5m cable attached
CAB-MIC20-EXT	<i>optional</i>	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M
CAB-DVI-HDMI-8M	<i>optional</i>	Presentation DVI-HDMI cable 8m with 3.5mm mini-jack audio
CAB-DVI-VGA-8M	<i>optional</i>	Presentation DVI-VGA cable 8m with 3.5mm mini-jack audio
CTS-MIC-CLNG-G2	<i>optional</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)
CAB-ETHRSHLD-10M=	<i>order separately</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated
<b>Selected Spares</b>		
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CABLES	CTS-RMT-TRC5=	Remote Control TRC 5
	CTS-RMT-TRC6=	Remote Control TRC 6
	CTS-SX20-QS-WMK=	Wall Mount Kit for SX20
	CTS-MIC-TABL20=	Table Microphone 20 - 7.5m cable attached
CABLES	CAB-MIC20-EXT=	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M
	CAB-PHD4XS2-SPLIT=	Camera Break Out Cable - unity connector to RJ45-F and HDMI-F
	CAB-HDMI-PHD12XS=	Custom 12X camera cable; HDMI, Ctrl and Power (3m)
	CAB-DVI-HDMI-8M=	Presentation DVI-HDMI cable 8m with 3.5mm mini-jack audio
	CAB-DVI-VGA-8M=	Presentation DVI-VGA cable 8m with 3.5mm mini-jack audio
	CAB-2HDMI-5M=	HDMI to HDMI Cable 5m
	CAB-ETH-USB=	USB to Ethernet Cable for Touch 10
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-2HDMI-3M=	HDMI to HDMI Cable 3m
	CAB-NET-EN5M=	Ethernet cable 5 meter
CAM	CTS-PHD1080P12XS2=	Precision 12X Camera Gen 2
	BRKT-12X-MONITR=	Bracket for mounting 12X PHD Cam to monitor
	PSU-12VDC-40W2=	Power Supply for camera - 12VDC 40W
CAM	CTS-SX20N-CODEC=	SPARE SX20 Codec
	PWR-60W-SX-AC=	Power Supply for SX20
<b>Post-Sale Licensing</b>		
SOFTWARE	<b>MultiSite</b>	L-SX-SERIES-PAK
	L-SX20-MS	Order L-SX-Series-PAK for e-delivery of MultiSite sw option
	<b>Remote Monitoring</b>	L-TP-RM
	L-SX-SERIES-RM	SX Remote Monitoring Option to enable Web Snapshots

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	112983 Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	112984 Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	113351 Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	112982 Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-JP-A	115127 Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	115060 Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	112985 Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	112981 Pwr Cord US 1.8m Black YP-12 To YC-12

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-SX20N-P40-K9

SX20N Quick Set with Precision 40  
(New name: 4XS2 camera to "Precision 40")

**Ships with CE8 software and TRC6 remote control**

**What are the differences between the SX20 and SX20N?**

[Click here](#)



Dual Display and Premium Resolution are now included at no cost.

The SX20 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)

Description

CTS-SX20N-P40-K9

**SX20N Quick Set with Precision 40 (4XS2) Camera**

*Product Desc:* SX20 codec, Dual Display, Prem Res, 4x PHDCam, 1 microphone, TRC6 remote control  
**The Precision 40 has 4X optical and 2X digital zoom; total zoom 8X**

**Main Components**

CTS-SX20N-CODEC	<i>included</i>	SX20N Codec
CTS-CAM-P40	<i>included</i>	Precision 40 Camera (4XS2) (Old PID CTS-PHD1080P4XS2)
CAB-HDMI-PHD4XS2	<i>included</i>	Custom 4xcamera cable; HDMI, Ctrl and Power (3m)
CAB-2HDMI-3M	<i>included</i>	HDMI to HDMI cable for monitor, 3m
CTS-MIC-TABL20	<i>included</i>	Table Microphone 20 (Qty 1) - 7.5 meter cable attached
CTS-RMT-TRC6	<i>included</i>	Remote Control TRC 6
CAB-ETH-5M	<i>included</i>	Ethernet cable (5m) - <i>in SX 20 accessories kit</i>
LIC-SX20	<i>included</i>	PRODUCT ID - Quick Set SX20
PWR-60W-SX-AC	<i>included</i>	Power Supply for SX20

**Encryption Options (must select one)**

LIC-S5210-CE-K9	<i>no cost</i>	License key to activate sw with encryption module
SW-S52010-CE8-K9	<i>no cost</i>	SW Image: 6Mb total / 6Mb per call - includes 1080p60
LIC-S5211-CE	<i>no cost</i>	License key to activate sw without encryption module
SW-S52011-CE8	<i>no cost</i>	SW Image: 6Mb total / 6Mb per call - includes 1080p60

**Software Feature Options**

LIC-SX20-MS	<i>optional</i>	MultiSite Option for SX20 (w576p30 / 720p30 or 1080p30 Presentation)
LIC-SX20-NPP		<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
LIC-SX20-HD		<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
LIC-SX20-DD		<i>As of CE8.2, this option is included in base software, and is not listed separately</i>
LIC-SX20-PR		<i>As of CE8.2, this option is included in base software, and is not listed separately</i>

SOFTWARE

**Remote Monitoring**

L-TP-RM		
L-SX-SERIES-RM	<i>order separately</i>	SX Remote Monitoring Option to enable Web Snapshots

Cisco Product ID (PID)		Description
<b>Optional Components</b>		<i>Selectable at time of order</i>
CTS-CTRL-DVX-10	<i>optional</i>	Touch 10" with cables
CAB-DV10-8M-		8 meter flat grey Ethernet cable (incl with Touch 10)
CTS-SX20-QS-WMK	<i>optional</i>	Wall Mount Kit for SX20
BRKT-P40-MONITR	<i>optional</i>	Bracket for mounting P40 Cam to monitor
CAB-PHD4XS2-SPLIT=	<i>optional</i>	Camera Break Out Cable - unity connector to RJ45-F and HDMI-F
CTS-POE-INJ	<i>optional</i>	Power Injector (802.3af) <i>For a spare please order CTS-PWR-AIR-INJ5=</i>
CAB-DV10-4M		4 meter flat grey Touch 10 Ethernet cable (incl with CTS-POE-INJ)
CTS-MIC-TABL20	<i>optional</i>	Table Microphone 20 (2nd mic) - 7.5m cable attached
CAB-MIC20-EXT	<i>optional</i>	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M
CAB-DVI-HDMI-8M	<i>optional</i>	Presentation DVI-HDMI cable 8m with 3.5mm mini-jack audio
CAB-DVI-VGA-8M	<i>optional</i>	Presentation DVI-VGA cable 8m with 3.5mm mini-jack audio
CTS-MIC-CLNG-G2	<i>optional</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)
CAB-ETHSHLD-10M	<i>order separately</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated
<b>Selected Spares</b>		
TOUCH	CTS-CTRL-DV10=	Touch 10 Device
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
CABLES	CTS-RMT-TRC5=	Remote Control TRC 5
	CTS-RMT-TRC6=	Remote Control TRC 6
	CTS-SX20-QS-WMK=	Wall Mount Kit for SX20
	CTS-MIC-TABL20=	Table Microphone 20 - 7.5m cable attached
CABLES	CAB-MIC20-EXT=	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M
	CAB-PHD4XS2-SPLIT=	Camera Break Out Cable - unity connector to RJ45-F and HDMI-F
	CAB-HDMI-PHD12XS=	Custom 12X camera cable; HDMI, Ctrl and Power (3m)
	CAB-DVI-HDMI-8M=	Presentation DVI-HDMI cable 8m with 3.5mm mini-jack audio
	CAB-DVI-VGA-8M=	Presentation DVI-VGA cable 8m with 3.5mm mini-jack audio
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
	CAB-2HDMI-5M=	HDMI to HDMI Cable 5m
	CAB-ETH-USB=	USB to Ethernet Cable for Touch 10
	CAB-2HDMI-3M=	HDMI to HDMI Cable 3m
	CAB-NET-EN5M=	Ethernet cable 5 meter
CAM	CTS-CAM-P40=	Precision 40 Camera (4XS2) (Old PID: CTS-PHD1080P4XS2=)
	BRKT-P40-MONITR	Bracket for mounting P40 Cam to monitor
	PSU-12VDC-40W2=	Power Supply for camera - 12VDC 40W
	CTS-SX20N-CODEC=	SPARE SX20 Codec
	PWR-60W-SX-AC=	Power Supply for SX20
<b>Post-Sale Licensing</b>		
SOFTWARE	<b>MultiSite</b>	L-SX-SERIES-PAK
	L-SX20-MS	Order L-SX-Series-PAK for e-delivery of MultiSite sw option
	<b>Remote Monitoring</b>	L-TP-RM
	L-SX-SERIES-RM	SX Remote Monitoring Option to enable Web Snapshots



**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	112983 Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	112984 Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	113351 Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	112982 Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-JP-A	115127 Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	115060 Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	112985 Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	112981 Pwr Cord US 1.8m Black YP-12 To YC-12

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.



[Index](#)

CTS-SX20-PHD12X-K9

SX20 Quick Set (original) with 12X

*Ships with TC7 software and TRC5 remote control*

*What are the differences between the SX20 and SX20N?*

[Click here](#)

Shown with optional Wall Mount Kit



Dual Display and Premium Resolution are now included at no cost.

The SX20 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description	
<b>CTS-SX20-PHD12X-K9</b>	<b>SX20 Quick Set with Precision 12x Camera</b>	
	<i>Product Desc: SX20 codec, Dual Display, Prem Res, 12x PHDCam, 1 microphone, TRC5 remote control</i>	
<b>Codec</b>		
CTS-SX20CODEC-K9		SX20 Codec - encrypted
CTS-SX20CODEC		SX20 Codec - non-encrypted
<b>Main Components</b>		
CTS-PHD1080P12XS2=	<i>included</i>	Precision 12X Camera Gen 2
CAB-HDMI-PHD12XS	<i>included</i>	Custom SX camera cable; HDMI, Ctrl and Power (3m)
BRKT-PHD-MONITOR	<i>included</i>	Bracket for mounting PHD Cam to monitor
CAB-2HDMI-3M	<i>included</i>	HDMI to HDMI cable
CTS-QSC20-MIC	<i>included</i>	Table Microphone 20 (Qty 1) - 7.5 meter cable attached
CTS-RMT-TRC5	<i>included</i>	Remote Control TRC 5
CAB-ETH-5M=	<i>included</i>	Ethernet cable (5m) - <i>in SX 20 accessories kit</i>
CAB-DVI-VGA-3.5MM=	<i>included</i>	Presentation cable w/audio, 6 meters (VGA-M to DVI-M w/3.5mm audio)
LIC-SX20	<i>included</i>	PRODUCT ID - Quick Set SX20
PWR-60W-SX-AC	<i>included</i>	Power Supply for SX20
<b>Software Feature Options</b>		
LIC-S52010-TC-K9	<i>no-cost option</i>	License Key Encrypted SW - 6Mb total / 6Mb per call
SW-S52010-TC7-K9	<i>no-cost option</i>	Software Image for SX20 Encrypted - SIP / H.323
LIC-S52011-TC	<i>no-cost option</i>	License Key Non-Encrypted SW - 6Mb total / 6Mb per call
SW-S52011-TC7	<i>no-cost option</i>	Software Image for SX20 Non-Encrypted - SIP / H.323
LIC-SX20-MS	<i>optional</i>	MultiSite Option for SX20 (w576p30 / 720p30 or 1080p30 Presentation)
LIC-SX20-NPP	<i>included</i>	SX20 Natural Presenter Package (NPP)
LIC-SX20-HD	<i>included</i>	SX20 License Key for HD
LIC-SX20-DD	<i>included</i>	Dual Display Option for SX20
LIC-SX20-PR	<i>included</i>	SX20 Premium Resolution Software Option - <i>includes 1080p60</i>

SOFTWARE

Cisco Product ID (PID)		Description	
<b>Remote Monitoring</b>			
L-SX-SERIES-RM	L-TP-RM <i>order separately</i>	SX Remote Monitoring Option to enable Web Snapshots	
<b>Optional Components</b>			
		<i>Selectable at time of order</i>	
CTS-CTRL-DVX-10	<i>optional</i>	Touch 10" with cable	
CAB-DV10-8M-		8 meter flat grey Ethernet cable (incl with Touch 10)	
CTS-SX20-QS-WMK	<i>optional</i>	Wall Mount Kit for SX20	
CTS-QSC20-MIC	<i>optional</i>	Table Mic 20 (2nd mic) - 7.5m cable attached	
CAB-MIC20-EXT	<i>optional</i>	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M	
CTS-POE-INJ	<i>optional</i>	Power Injector (802.3af) <i>For a spare please order CTS-PWR-AIR-INJ5=</i>	
CAB-DV10-4M		4 meter flat grey Touch 10 Ethernet cable (incl with CTS-POE-INJ)	
CTS-MIC-CLNG-G2	<i>order separately</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)	
CAB-ETHRSHLD-10M	<i>order separately</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated	
<b>Selected Spares</b>			
TOUCH	CTS-CTRL-DV10=	Touch 10 Device	
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)	
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10	
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10	
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10	
CABLES	CTS-RMT-TRC5=	Remote Control TRC 5	
	CTS-RMT-TRC6=	Remote Control TRC 6	
	CTS-SX20-QS-WMK=	Wall Mount Kit for SX20	
	CTS-QSC20-MIC=	Table Mic 20 - 7.5m cable attached	
	CAB-MIC20-EXT=	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M	
	CAB-PHD4XS2-SPLIT=	Camera Break Out Cable - unity connector to RJ45-F and HDMI-F	
	CAB-HDMI-PHD12XS=	Custom 12X camera cable; HDMI, Ctrl and Power (3m)	
	CAB-DVI-VGA-3.5MM=	Presentation cable w/audio, 6 meters (VGA-M to DVI-M w/3.5mm audio)	
	CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray	
	CAB-2HDMI-5M=	HDMI to HDMI Cable 5m	
CAB-2HDMI-3M=	HDMI to HDMI Cable 3m		
CAB-NET-EN5M=	Ethernet cable 5 meter		
CAM	CTS-PHD1080P12XS2=	Precision 12X Camera Gen 2	
	BRKT-PHD-MONITOR=	Bracket for mounting PHD Cam to monitor	
	PSU-12VDC-40W2=	Power Supply for camera - 12VDC 40W	
	CTS-SX20CODEC-K9=	SPARE SX20 Codec encrypted	
	CTS-SX20CODEC=	SPARE SX20 Codec - no encryption	
	PWR-60W-SX-AC=	Power Supply for SX20	
<b>Post-Sale Licensing</b>			
SOFTWARE	<b>MultiSite / PR / DD</b>	L-SX-SERIES-PAK	
	L-SX20-MS		Order L-SX-Series-PAK for e-delivery of MultiSite sw option
	L-SX20-PR	<i>zero dollar</i>	Order L-SX-Series-PAK for e-delivery of Premium Resolution
	L-SX20-DD	<i>zero dollar</i>	Order L-SX-Series-PAK for e-delivery of Dual Display option
	<b>Remote Monitoring</b>	L-TP-RM	
L-SX-SERIES-RM		SX Remote Monitoring Option to enable Web Snapshots	

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	112983 Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	112984 Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	113351 Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	112982 Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-JP-A	115127 Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	115060 Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	112985 Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	112981 Pwr Cord US 1.8m Black YP-12 To YC-12

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-SX20-PHD4X-K9

SX20 Quick Set (original) with 4X

*Ships with TC7 software and TRC5 remote control*

*What are the differences between the SX20 and SX20N?*

[Click here](#)



Dual Display and Premium Resolution are now included at no cost.

The SX20 supports SIP and H.323. It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)	Description
------------------------	-------------

CTS-SX20-PHD4X-K9

**SX20 Quick Set with Precision 40 (4XS2) Camera**

*Product Desc: SX20 codec, Dual Display, Prem Res, 4x PHDCam, 1 microphone, TRC5 remote control  
The 4X cam has 4X optical and 2X digital zoom; total zoom 8X*

**Codec**

CTS-SX20CODEC-K9	SX20 Codec - encrypted
CTS-SX20CODEC	SX20 Codec - non-encrypted

**Main Components**

CTS-PHD1080P4XS2	<i>included</i>	PrecisionHD 4X Camera with unity connector
CAB-HDMI-PHD4XS2	<i>included</i>	Custom 4xcamera cable; HDMI, Ctrl and Power (3m)
BRKT-PHD4X-MONITR	<i>included</i>	Bracket for mounting 4xS2 PHDCam to monitor
CAB-2HDMI-3M	<i>included</i>	HDMI to HDMI cable (Qty 2)
CTS-QSC20-MIC	<i>included</i>	Table Microphone 20 (Qty 1) - 7.5 meter cable attached
CTS-RMT-TRC5	<i>included</i>	Remote Control TRC 5
CAB-ETH-5M=	<i>included</i>	Ethernet cable (5m) - <i>in SX 20 accessories kit</i>
CAB-DVI-VGA-3.5MM=	<i>included</i>	Presentation cable w/audio, 6 meters (VGA-M to DVI-M w/3.5mm audio)
LIC-SX20	<i>included</i>	PRODUCT ID - Quick Set SX20
PWR-60W-SX-AC	<i>included</i>	Power Supply for SX20

**Software Feature Options**

SOFTWARE	LIC-S52010-TC-K9	<i>no-cost option</i>	License Key Encrypted SW - 6Mb total / 6Mb per call - <i>includes 720p30</i>
	SW-S52010-TC7-K9	<i>no-cost option</i>	Software Image for SX20 Encrypted - SIP / H.323
	LIC-S52011-TC	<i>no-cost option</i>	License Key Non-Encrypted SW - 6Mb total / 6Mb per call - <i>includes 720p30</i>
	SW-S52011-TC7	<i>no-cost option</i>	Software Image for SX20 Non-Encrypted - SIP / H.323
	LIC-SX20-MS	<i>optional</i>	MultiSite Option for SX20 (w576p30 / 720p30 or 1080p30 Presentation)
	LIC-SX20-NPP	<i>included</i>	SX20 Natural Presenter Package (NPP)
	LIC-SX20-HD	<i>included</i>	SX20 License Key for HD
	LIC-SX20-DD	<i>included</i>	Dual Display Option for SX20
LIC-SX20-PR	<i>included</i>	SX20 Premium Resolution Software Option	

Cisco Product ID (PID)		Description	
<b>Remote Monitoring</b>			
L-SX-SERIES-RM	L-TP-RM <i>order separately</i>	SX Remote Monitoring Option to enable Web Snapshots	
<b>Optional Components</b>			
		<i>Selectable at time of order</i>	
CTS-CTRL-DVX-10	<i>optional</i>	Touch 10" with cable	
CAB-DV10-8M-		8 meter flat grey Ethernet cable (incl with Touch 10)	
CTS-SX20-QS-WMK	<i>optional</i>	Wall Mount Kit for SX20	
CTS-QSC20-MIC	<i>optional</i>	Table Mic 20 (2nd mic) - 7.5m cable attached	
CAB-MIC20-EXT	<i>optional</i>	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M	
CTS-POE-INJ	<i>optional</i>	Power Injector (802.3af) <i>For a spare please order CTS-PWR-AIR-INJ5=</i>	
CAB-DV10-4M		4 meter flat grey Touch 10 Ethernet cable (incl with CTS-POE-INJ)	
CTS-MIC-CLNG-G2	<i>order separately</i>	Cisco Ceiling Microphone Gen 2 (see Microphones)	
CAB-ETHRSHLD-10M	<i>order separately</i>	Shielded audio cable 10m, for Ceiling Microphone, not plenum rated	
<b>Selected Spares</b>			
TOUCH	CTS-CTRL-DV10=	Touch 10 Device	
	CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)	
	CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10	
	CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10	
	CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10	
CABLES	CTS-RMT-TRC5=	Remote Control TRC 5	
	CTS-RMT-TRC6=	Remote Control TRC 6	
	CTS-SX20-QS-WMK=	Wall Mount Kit for SX20	
	CTS-QSC20-MIC=	Table Mic 20 - 7.5m cable attached	
	CAB-MIC20-EXT=	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M	
CAB-PHD4XS2-SPLIT=	Camera Break Out Cable - unity connector to RJ45-F and HDMI-F		
CAB-HDMI-PHD4XS2=	Custom 4x camera cable; HDMI, Ctrl and Power (3m)		
CAB-DVI-VGA-3.5MM=	Presentation cable w/audio, 6 meters <i>(VGA-M to DVI-M w/3.5mm audio)</i>		
CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray		
CAB-2HDMI-5M=	HDMI to HDMI Cable 5m		
CAB-2HDMI-3M=	HDMI to HDMI Cable 3m		
CAB-NET-EN5M=	Ethernet cable 5 meter		
CAM	CTS-PHD1080P4XS2=	Precision 40 Camera Gen 2 with unity connector	
	BRKT-PHD4X-MONITR=	Bracket for mounting 4xS2 PHDCam to monitor	
	PSU-12VDC-40W2=	Power Supply for camera - 12VDC 40W	
CTS-SX20CODEC-K9=	SPARE SX20 Codec encrypted		
CTS-SX20CODEC=	SPARE SX20 Codec - no encryption		
PWR-60W-SX-AC=	Power Supply for SX20		
<b>Post-Sale Licensing</b>			
SOFTWARE	<b>MultiSite / PR / DD</b>	L-SX-SERIES-PAK	
	L-SX20-MS		Order L-SX-Series-PAK for e-delivery of MultiSite sw option
	L-SX20-PR	<i>zero dollar</i>	Order L-SX-Series-PAK for e-delivery of Premium Resolution
	L-SX20-DD	<i>zero dollar</i>	Order L-SX-Series-PAK for e-delivery of Dual Display option
	<b>Remote Monitoring</b>	L-TP-RM	
L-SX-SERIES-RM		SX Remote Monitoring Option to enable Web Snapshots	

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>


**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	112983 Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	112984 Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	113351 Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	112982 Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-JP-A	115127 Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	115060 Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	112985 Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	112981 Pwr Cord US 1.8m Black YP-12 To YC-12

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

What are the differences between SX20 and SX20N?



**FAQ - SX20 / SX20N**

**The SX20 and SX20N are nearly identical.** There are differences in the following: software version shipped, accessories, and user interface

**SUMMARY:**

- \* Order SX20N if you know your customer will run CE8 software
- \* Order SX20 if you know your customer will run TC7 or TC6 software
- \* If you don't know which software version will be used, then order SX20N, but also order a spare TRC5 remote control (CTS-RMT-TRC5=)
- \* The Touch 10 will work with both new and old (TC7) software, so if you are ordering a Touch 10, order the SX20N

**Components**

CODEC		The codec is identical between SX20 and SX20N. Any software version from TC5.1 to CE8 can be used
CAMERAS		The 12X camera is identical between SX20 and SX20N The Precision 40 Camera is identical to the 4XS2 camera <i>(name change only)</i>
SOFTWARE		The SX20N ships with CE8 software - can be downgraded to TC7 or T6 The SX20 ships with TC7 software - can be upgraded to CE8
TOUCH 10		The Touch 10 can be used with either SX20 or SX20N
REMOTE CONTROL	<i>IMPORTANT see picture</i>	<b>The Touch 8 cannot be used with CE8 software</b> The SX20 ships with a TRC5 remote - will not work correctly with CE8 The SX20N ships with a TRC6 - will not work correctly with TC7 or TC6
ACCESSORIES		There is a new part number for the microphone, and presentation cable options are different
USER INTERFACE	<i>FYI</i>	If a Touch 10 is being used, then the TRC5/6 is not needed

**Part Numbers**

<a href="#">CTS-SX20N-12X-K9</a>	<i>new</i>	SX20N Quick Set with 12X
<a href="#">CTS-SX20N-P40-K9</a>	<i>new</i>	SX20N Quick Set with Precision 40
<a href="#">CTS-SX20-PHD12X-K9</a>	<i>original</i>	SX20 Quick Set with 12X
<a href="#">CTS-SX20-PHD4X-K9</a>	<i>original</i>	SX20 Quick Set with 4X

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-SX10N-K9  
 CTS-SX10-K9

SX10 Quick Set



What are the differences between the SX10 and SX10N?

[Click here](#)

The SX10(N) supports a single 1080p screen, and has (2) presentation inputs. It supports PoE. The SX10(N) supports SIP and H.323 (as of CE8.2). It registers to CUCM, VCS, Spark Services, and third party devices.

Cisco Product ID (PID)		Description
<b>CTS-SX10N-K9</b>		<b>SX10 Quick Set (N)</b>
<i>Product Desc:</i> SX10 codec/2.5X camera, integrated microphone, wall mount kit, TRC6 remote control <b>The 2.5X cam has 2.5X optical and 2X digital zoom; total zoom 5X</b>		
<b>Main Components</b>		
BRKT-SX10-WMK	<i>included</i>	Wall Mount Kit for SX10
CTS-RMT-TRC6	<i>included</i>	Remote Control TRC 6
CAB-2HDMI-2M	<i>included</i>	HDMI cable 2 meter
CAB-ETH-5M	<i>included</i>	Ethernet cable 5 meter
PWR-SX10-AC	<i>included</i>	Power supply 12VDC for SX10
LIC-SX10	<i>included</i>	PRODUCT ID - Quick Set SX10
<b>Software Feature Options</b>		
<b>SOFTWARE</b>	SW-S52030-CE8-K9	<i>included</i> Software image for SX10
	LIC-CE-CRYPTO-K9	<i>no-cost option</i> License key to activate sw encryption module
	LIC-CE-NONCRYPTO	<i>no-cost option</i> License key to activate sw without encryption module
	<b>Remote Monitoring</b>	L-TP-RM
L-SX-SERIES-RM	<i>order separately</i> SX Remote Monitoring Option to enable Web Snapshots	
<b>Optional Components</b>		
		<i>Selectable at time of order</i>
CTS-CTRL-DVX-10	<i>optional</i>	Touch 10" with cable
CAB-DV10-4M-		4 meter flat grey Ethernet cable (incl with Touch 10)
BRKT-SX10-SMK	<i>optional</i>	Screen Mount Kit for SX10
CAB-PRESO-2HDMI	<i>optional</i>	HDMI cable 8 meter (for presentation)
CAB-VGA-8M	<i>optional</i>	VGA-VGA cable 8 meter (for presentation)
CTS-MIC-TABL20	<i>optional</i>	Table Microphone 20 - 7.5m cable attached
CAB-HDMI-MULT-9M	<i>optional</i>	Presentation cable for HDMI, Display Port, Mini Display Port
CTS-POE-INJ	<i>optional</i>	Touch 10 PoE power injector





## CTS-SX10-K9

## SX10 Quick Set (original)

*Product Desc:* SX10 codec/2.5X camera, integrated microphone, wall mount kit, TRC6 remote control  
**The 2.5X cam has 2.5X optical and 2X digital zoom; total zoom 5X**

**Main Components**

BRKT-SX10-WMK	<i>included</i>	Wall Mount Kit for SX10
CTS-RMT-TRC6	<i>included</i>	Remote Control TRC 6
CAB-2HDMI-2M	<i>included</i>	HDMI cable 2 meter
CAB-ETH-5M	<i>included</i>	Ethernet cable 5 meter
LIC-SX10	<i>included</i>	PRODUCT ID - Quick Set SX10

**Software Feature Options**

SW-S52030-CE8-K9	<i>included</i>	Software image for SX10
LIC-TC-CRYPTO-K9	<i>no-cost option</i>	License key to activate sw encryption module
LIC-TC-NONCRYPTO	<i>no-cost option</i>	License key to activate sw without encryption module

## SOFTWARE

**Remote Monitoring**

L-TP-RM

L-SX-SERIES-RM	<i>order separately</i>	SX Remote Monitoring Option to enable Web Snapshots
----------------	-------------------------	---

**Optional Components***Selectable at time of order*

CTS-CTRL-DVX-10	<i>optional</i>	Touch 10" with cable
CAB-DV10-4M-		4 meter flat grey Ethernet cable (incl with Touch 10)
BRKT-SX10-SMK	<i>optional</i>	Screen Mount Kit for SX10
CAB-2HDMI-6M	<i>optional</i>	HDMI cable 6 meter (for presentation)
CAB-2VGA-6M	<i>optional</i>	VGA cable 6 meter (for presentation)
CTS-QSC20-MIC	<i>optional</i>	Table Mic 20 - 7.5m cable attached
PWR-SX10-AC	<i>optional</i>	Power supply 12VDC for SX10

## Other PIDs for both SX10 and SX10N

**Selected Spares**

## TOUCH

CTS-CTRL-DV10=	Touch 10 Device
CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10

## CABLES

CTS-RMT-TRC6=	Remote Control TRC 6
CTS-MIC-TABL20=	Table Microphone 20
CAB-MIC20-EXT=	Extension Cable 10m, for CTS-QSC20-MIC, 3.5mm F to 3.5mm M
CAB-2HDMI-2M=	HDMI cable 2 meter
CAB-PRESO-2HDMI=	HDMI to HDMI cable, 8 meter, gray
CAB-HDMI-MULT-9M=	Presentation cable for HDMI, Display Port, Mini Display Port
CAB-VGA-8M=	Presentation cable, VGA to VGA, 8 meter
CAB-NET-EN5M=	Ethernet cable 5 meter

## FORM

CTS-SX10CODEC=	SX10N codec + camera spare
BRKT-SX10-WMK=	Wall Mount Kit for SX10
BRKT-SX10-SMK=	Screen Mount Kit for SX10
PWR-SX10-AC=	Power supply 12VDC for SX10

**Post-Sale Licensing**

SW

**Remote Monitoring**

L-TP-RM

L-SX-SERIES-RM

SX Remote Monitoring Option to enable Web Snapshots

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-IND-A	Power cable India 1.8m
PWR-CORD-JP-A	Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	Pwr Cord US 1.8m Black YP-12 To YC-12
PWR-CORD-ZAF-A	Power cable South Africa 1.8 m

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

What are the differences between SX10 and SX10N?



**FAQ SX10 / SX10N**

**The SX10 and SX10N are nearly identical.** There are differences in the following:  
 The SX10N has an ultrasonic speaker, with a grill on the front, used only for Intelligent Proximity and Spark pairing  
 SX10N includes a power adapter, and has different presentation cables

**SUMMARY:**

\* Specify SX10N for all new orders. It has better hardware functionality

**Components**

CODEC	The SX10 codec has a high frequency loudspeaker on the front which is used for Intelligent Proximity and Spark pairing
SOFTWARE	Both SX10N and SX10 can run exactly the same software SX10N can register to Cisco Spark Services (CE8.1 and later) SX10 can register to Cisco Spark Services (CE8.2 and later)
TOUCH 10	The optional Touch 10 can be used with either SX10 or SX10N
REMOTE CONTROL	Both SX10 and SX10N ship with a TRC6 remote control
ACCESSORIES	SX10N - There is a new part number for the microphone SX10N includes an AC adapter Presentation cable options are different between the two SKUs

**Part Numbers**

<a href="#">CTS-SX10N-K9</a>	<i>new</i>	SX10N
<a href="#">CTS-SX10-K9</a>	<i>original</i>	SX10

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-MON-55-WW

Cisco TelePresence 55 Inch Auxiliary  
Display - World Wide

The 55 inch LCD monitor, with LED lighting, has multiple inputs including HDMI. Speakers are not included. Standard VESA mount pattern. No stand is provided. Customer needs to furnish an appropriate VESA mount or stand.

## Cisco Product ID (PID)

## Description

CTS-MON-55-WW

Cisco TelePresence 55 Inch Auxiliary Display - World Wide

*Product Desc: 55 inch LCD display with LED lighting, remote control, DVI-F to HDMI-M adapter  
Can be used as Aux display with IX5000 and IX5200.*

**Suggested Items**

CAB-2HDMI-6M=

HDMI cable 6 meter

CAB-PRESO-2HDMI=

HDMI to HDMI cable, 8 meter, gray

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

*Standard YC-12 computer power cord is required, and should be ordered separately*

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-SPKER-TRACK60

SpeakerTrack 60



Requires two HDMI and one Ethernet cable.

SpeakerTrack 60 must be wall-mounted. Recommended lens height is 48-72 inches AFF. Field of view is 80 degrees horizontal.

## Cisco Product ID (PID)

## Description

CTS-SPKER-TRACK60

Cisco TelePresence SpeakerTrack 60

*Incl wall-mount bracket, electronics base, mic array, two cameras, power supply**Can be used with C40, C60, C90, and SX80**MX700/800 with Dual Cameras have speaker tracking built in***Components**

CTS-CAM-P60	<i>included</i>	Precision 60 Camera Qty 2
CTS-ST-ARRAY60	<i>included</i>	Speaker Track 60 Microphone Array
CTS-ST-ARR60-WMK	<i>included</i>	Wall Mount Kit for Speaker Track 60 Microphone Array
CAB-ETH-ST-SHORT	<i>included</i>	Qty (2) Ethernet cables (0.35m&0.2m) for SpeakerTrack 60
CAB-PWR-ST-SHORT	<i>included</i>	Qty (2) 12V power cables (0.45m&0.2m) for SpeakerTrack 60
CTS-ST-INT-PLATE	<i>included</i>	Interface plate CAM-P60 to Speaker Track 60
PWR-12VDC-84W	<i>included</i>	Power supply 12VDC 84W for SpeakerTrack 60

**Suggested Items**

CAB-2HDMI-6M=	HDMI cable 6 meter
CAB-NET-EN5M=	Ethernet cable 5 meter

**Orderable Spares**

CTS-CAM-P60=	Precision 60 Camera Qty 2
CTS-ST-ARRAY60=	Speaker Track 60 Microphone Array
CTS-ST-ARR60-WMK=	Wall Mount Kit for Speaker Track 60 Microphone Array
CAB-ETH-ST-SHORT=	Qty (2) Ethernet cables (0.35m&0.2m) for SpeakerTrack 60
CAB-PWR-ST-SHORT=	Qty (2) 12V power cables (0.45m&0.2m) for SpeakerTrack 60
CTS-ST-INT-PLATE=	Interface plate CAM-P60 to Speaker Track 60
PWR-12VDC-84W=	Power supply 12VDC 84W for SpeakerTrack 60

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-IND-A	Power cable India 1.8m
PWR-CORD-JP-A	Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	Pwr Cord US 1.8m Black YP-12 To YC-12
PWR-CORD-ZAF-A	Power cable South Africa 1.8 m

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-CAM-P60=

Precision 60 Camera



The Precision 60 uses Ethernet for camera control. This camera can be mounted upside down. When used as main camera, recommended lens height is 48-72 inches AFF. Field of view is 80 degrees horizontal.

Cisco Product ID (PID)	Description
CTS-CAM-P60=	<p><b>Precision 60 Camera Spare</b></p> <p><i>Supported on SX80, MX700, MX800. 10X optical, 2X digital, total zoom 20X</i></p> <p><i>This spare does not include power supply or cables</i></p>
<p><b>Suggested Items</b></p> <p>PSU-12VDC-40W2=</p> <p>CTS-CAM60-BRKT=</p> <p>CAB-2HDMI-6M=</p> <p>CAB-NET-EN5M=</p>	<p>Power Supply for Camera - 12VDC 40W</p> <p>Wall and ceiling bracket for Precision 60 Camera</p> <p>HDMI cable 6 meter</p> <p>Ethernet cable 5 meter</p>
<p><b>Documentation</b></p> <p><a href="http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323">http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323</a></p>	
<p>All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.</p>	

[Index](#)

CTS-PHD1080P12XS2=  
Precision 12X Camera

...for C Series, SX80,  
and SX20



When using multiple cameras, the 1080p 12X can be anywhere in the control chain. It can be mounted upside down.  
When used as main camera, recommended lens height is 48-72 inches AFF. Field of view is 72 degrees horizontal.

Cisco Product ID (PID)	Description
CTS-PHD1080P12XS2=	Precision 12X Camera Gen 2, with 12X optical zoom <i>Ships with SX20. Can be used with any C Series, and with SX80</i> <i>This spare does not include power supply or cables</i>

Selected Spares	
CAB-VC2-5M=	Visca Control Cable 5m - DB9 to RJ45
CAB-HDMI-PHD12XS=	Custom SX20 camera cable, from SX20 to 12X; HDMI, Ctrl and Power (3m)
BRKT-PHD-MONITOR=	Bracket for mounting PHD Cam to monitor
PSU-12VDC-40W2=	Power Supply for camera - 12VDC 40W
<b>Documentation</b>	
<a href="http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323">http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323</a>	
All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.	



[Index](#)

CTS-PHD-S-RF

PrecisionHD 720p Camera Remanufactured



The PrecisionHD 720p camera is used with Edge MXP, 3000 MXP, and 6000 MXP, as well as Profiles based on those codecs.

Cisco Product ID (PID)

Description

CTS-PHD-S-RF

PrecisionHD 720p Camera Remanufactured with 7X Optical Zoom

*This spare does not include power supply or cables***Documentation**<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-CAM-P40=  
 CTS-PHD1080P4XS2=

*These PIDs are identical*

Precision 40 Camera / 4XS2



When using multiple cameras, the Precision 40 must be the last in the control chain. It can be mounted upside down.  
 When used as main camera, recommended lens height is 48-72 inches AFF. Field of view is 70 degrees horizontal.

## Cisco Product ID (PID)

## Description

CTS-CAM-P40=

**Precision 40 Camera**

*Ships with SX20 and SX80. 4X optical zoom, plus 2X digital. Total zoom 8X*

*This camera is supported on SX20, SX80, and MX700/800*

*This spare does not include power supply or cables*

CTS-PHD1080P4XS2=

**PrecisionHD 1080p4X Gen 2**

*This is exactly the same camera as CTS-CAM-P40=. The name has changed*

*This camera is supported on SX20, SX80, and MX700/800*

*This spare does not include power supply or cables*

## Selected Spares

BRKT-PHD4X-MONITR=

Bracket for mounting 4xS2 PHDCam to monitor

CAB-HDMI-PHD12XS=

Custom SX20 camera cable, from SX20 to 12X; HDMI, Ctrl and Power (3m)

CAB-HDMI-PHD4XS2=

Custom SX20 camera cable, from SX20 to 4XS2; HDMI, Ctrl and Power (3m)

CAB-PHD4XS2-SPLIT=

Camera Break Out Cable - unity connector to RJ45-F and HDMI-F

PSU-12VDC-40W2=

Power Supply for camera - 12VDC 40W

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-MIC-CLNG-G2=	Cisco Ceiling Microphone G2
CTS-MIC-TABL60=	Table Microphone 60
CTS-MIC-TABL20=	Table Microphone 20 (new PID)
CTS-QSC20-MIC=	Table Microphone 20 (old PID)
CTS-MIC-OMNIDIR-RF	AT841UG Condenser Microphone Refurbished
CTS-TX9K-MIC-RF	TX9x00 Microphone Refurbished

## Cisco Product ID (PID)

## Description

## CTS-MIC-CLNG-G2=

## Cisco Ceiling Microphone G2

*Product Desc:* Boundary Layer Microphone mounted on an acrylic assembly. Replaces AudioScience CAT 5e or 6 cable is used to carry the audio signal. Shielded cable is recommended  
*Can be used with all SX and MX. Adapters are included*

**Main Components**


CTS-MIC-CLNG-PLT	<i>included</i>	Ceiling Microphone parts - Top and Back plates
CTS-MIC-CLNG-ELM	<i>included</i>	Microphone element for Ceiling Microphone
CTS-MIC-CLNG-DNG	<i>included</i>	Ceiling Mic. dongles, RJ45-Euroblock and RJ45-MiniJack
CTS-MIC-CLNG-WRK	<i>included</i>	Ceiling Microphone parts - Ceiling mounting wire kit

**Optional Components**

CAB-ETHRSHLD-10M	<i>optional</i>	<i>Selectable at time of order</i> Shielded Ethernet/microphone cable (10 m) - (Not plenum rated)
------------------	-----------------	--

**Spares**

CTS-MIC-CLNG-PLT=	Ceiling Microphone parts - Top and Back plates
CTS-MIC-CLNG-ELM=	Microphone element for Ceiling Microphone
CTS-MIC-CLNG-DNG=	Ceiling Mic. dongles, RJ45-Euroblock and RJ45-MiniJack
CTS-MIC-CLNG-WRK=	Ceiling Microphone parts - Ceiling mounting wire kit
CAB-ETHRSHLD-10M=	Shielded Ethernet/microphone cable (10 m) - (Not plenum rated)

**CTS-MIC-TABL60=****Table Microphone 60 - 9m detachable cable and table bracket included***Product Desc: Omnidirectional boundary layer tabletop mic, with mute button**Cable includes phoenix-style Euroblock connectors for SX80 platform**Used with SX80, MX700, and MX800***CTS-MIC-TABL20=****Cisco Table 20 Microphone****CTS-QSC20-MIC=***Product Desc: Omnidirectional boundary layer tabletop mic, with mute button**Integrated 7.5m cable, terminating in 3.5mm male 4 conductor**Used with C20, EX90, SX10, SX20, MX200, MX300***CTS-MIC-OMNIDIR-RF****AT841UG Condenser Microphone***Product Desc: Omnidirectional boundary layer tabletop mic, phantom powered REMANUFACTURED**Connector is mini-XLR 3 pin. Includes 7.5m cable to XLR male**Used with various C Series codecs and Profiles*

CTS-TX9K-MIC-RF

TX9000 Microphone

*Product Desc: Cardioid condenser microphone for TX9X00 REMANUFACTURED***Microphone Cables**

CAB-ETHRSHLD-10M=

Shielded Ethernet/microphone cable (10 m) for ceiling mic - (Not plenum rated)

CAB-MIC-T60EXT=

9 meter extension cable for Table Microphone 60 (Euroblock connectors)

CAB-MIC-T60=

Spare cable 9m for Table Microphone 60

CAB-MIC20-EXT=

Extension Cable 10m, for CTS-MIC-TABL20, 3.5mm F to 3.5mm M

CAB-XLR-EUROBLOCK=

Euroblock (Phoenix) to female XLR adapter, 20 cm


**Documentation**<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-ISDNLINK-K9

Cisco TelePresence ISDN Link



ISDN Link is supported on EX / C Series / MX / SX20 / SX80. It is not supported on SX10 or DX70/80. In most countries, an NT-1 is required.

Cisco Product ID (PID)	Description
------------------------	-------------

<b>CTS-ISDNLINK-K9</b>	<b>Cisco TelePresence ISDN Link Encrypted</b> <i>Product Desc: Support for 4 BRI, or 1 PRI, or external networks (V.35, RS530, RS449, and RS366)</i>
------------------------	---

**Software Feature Options**

SW-S51500-K9	Software Image for ISDN Link Encrypted
--------------	--

**Included Components**

Power cable	<i>included</i>	External power adapter with 12V / 1.25A DC output; 100/240AC
-------------	-----------------	--

**Note:** *In most countries, a third party NT-1 is required*

**Spares**

PSU-12VDC-15W=	ISDN Link Power Supply spare
----------------	------------------------------

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.

[Index](#)

CTS-CTRL-DVC8-RF  
 CTS-CTRL-DV8=



The handset is available only with Touch 8" for EX

Cisco Product ID (PID)	Description
CTS-CTRL-DVC8-RF	Cisco TelePresence Touch 8" for C Series/Profile - no handset, 7.5m cable, PSU Remanufactured

**Included Components**

PSU-DVC-POE13V	<i>included</i>	Power Supply For Touch Device - C Series/Profiles
72-100158-01	<i>included</i>	Shielded Ethernet cable - 5m

**Power Cords**

PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	112983 Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-CH-A	112984 Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	113351 Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	112982 Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-JP-A	115127 Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	115060 Pwr Cord ROK 1.8m BlackYP-22K To YC-12
PWR-CORD-UK-A	112985 Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	112981 Pwr Cord US 1.8m Black YP-12 To YC-12

CTS-CTRL-DV8=	Cisco TelePresence Touch 8" for EX with cradle and handset - 1.5m cable
CTS-CTRL-DV8-RF	Cisco TelePresence Touch 8" for EX with cradle and handset - Remanufactured
Power Cord not required	

CTS-CTRL-DVP8-RF	Cisco TelePresence Touch 8" for MX200/300 Gen 1, with 7.5m cable - Remanufactured
Power Cord not required	

**Selected Spares**

CTS-CTRL-DV8CRDL= Spare Cradle w/Handset - EX Series ONLY/Touch NOT included

**Documentation**

<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.



[Index](#)

CTS-CTRL-DV10  
CTS-CTRL-DV10=

Touch 10



The Touch 10 is used with latest-generation endpoints. When included with a system, the PID is CTS-CTRL-DVX-10.

Cisco Product ID (PID)	Description
<b>CTS-CTRL-DV10</b>	<b>Touch 10 with Power Injector and 4 Meter Cable</b>
CAB-DV10-4M=	<i>included</i> 4 meter flat grey Ethernet cable for Touch 10
CTS-PWR-AIR-INJ5=	<i>included</i> Power Injector (802.3af) (requires power cable)
<b>CTS-CTRL-DV10=</b>	<b>Touch 10 Spare Only - no cables or power injector</b>
<b>Selected Spares</b>	
CTS-PWR-AIR-INJ5=	Power Injector (802.3af) (requires power cable)
CAB-DV10-12.5=	12.5 meter flat grey Ethernet cable for Touch 10
CAB-DV10-8M=	8 meter flat grey Ethernet cable for Touch 10
CAB-DV10-4M=	4 meter flat grey Ethernet cable for Touch 10
<b>Power Cords</b>	
PWR-CORD-ARG-A	Power cable ARG 1.8m black
PWR-CORD-AUS-A	112983 Pwr Cord AUS 1.8m Black YP-35 To YC-12
PWR-CORD-BZ-A	Brazil Power Cord EL223, EL701B, 250V, 10A, 2M
PWR-CORD-CH-A	112984 Pwr Cord CH 1.8m Black YP-46 To YC-12
PWR-CORD-CN-A	113351 Pw Cord CN (China) 1.8m Black w. ground
PWR-CORD-EUR-A	112982 Pwr Cord Euro 1.8m Black YP-23 To YC-12
PWR-CORD-JP-A	115127 Pwr Cord Japan 1.8m With Label YP12/YC12
PWR-CORD-ROK-A	115060 Pwr Cord ROK 1.8m Black YP-22K To YC-12
PWR-CORD-UK-A	112985 Pwr Cord UK 1.8m Black YP-61 To YC-12
PWR-CORD-US-A	112981 Pwr Cord US 1.8m Black YP-12 To YC-12
<b>Documentation</b>	
<a href="http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323">http://www.cisco.com/cisco/web/psa/default.html?mode=prod&amp;level0=280789323</a>	
All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.	

[Index](#)

CTS-CTRL-DV12-A-RF=

Touch 12 for CTS500-32, 1300-47,  
TX13XX, remanufactured

## Cisco Product ID (PID)

CTS-CTRL-DV12-A-RF=

## Description

Cisco Touch 12 inch Device, remanufactured

**Selected Spares**

CTS-PWR-AIR-INJ5=

Power Injector (802.3af) (requires power cable)

**Documentation**<http://www.cisco.com/cisco/web/psa/default.html?mode=prod&level0=280789323>

All contents are Copyright © 1992–2016 Cisco Systems, Inc. All rights reserved. This document is Cisco Confidential.



Americas Headquarters  
Cisco Systems, Inc.  
San Jose, CA

Asia Pacific Headquarters  
Cisco Systems (USA) Pte. Ltd.  
Singapore

Europe Headquarters  
Cisco Systems International BV Amsterdam,  
The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)