

9PXM battery backup times (in minutes)

Battery modules (part number 9PXMBAT).

You must order two battery modules to occupy one slot.

Load													
kVA	kW	2	4	6	8	10	12	14	16	18	20	22	24
4 kVA	3.6 kW	6	17	28	39	52	65	78	92	107	121	136	152
8 kVA	7.2 kW		6	11	17	22	28	33	39	45	52	58	65
12 kVA	10.8 kW			6	9	13	17	20	24	28	31	35	39
16 kVA	14.4 kW				6	8	11	14	17	19	22	25	28
20 kVA	18.0 kW					6	8	10	12	14	17	19	21
kVA	kW	26	28	30	32	34	36	38	40	42	44	46	48
4 kVA	3.6 kW	167	183	200	216	233	250	267	284	302	320	338	356
8 kVA	7.2 kW	71	78	85	92	99	107	114	121	129	136	144	152
12 kVA	10.8 kW	43	48	52	56	60	65	69	74	78	83	87	92
16 kVA	14.4 kW	30	33	36	39	42	45	49	52	55	58	61	65
20 kVA	18.0 kW	23	25	28	30	32	35	37	39	42	44	47	49
kVA	kW	50	52	54	56	58	60	62	64	66	68	70	72
4 kVA	3.6 kW	374	393	411	430	449	468	487					
8 kVA	7.2 kW	160	167	175	183.4	192	200	208	216	224	233	241	250
12 kVA	10.8 kW	97	102	107	111	116	121	126	131	136	141	147	152
16 kVA	14.4 kW	68	71	75	78	82	85	89	92	96	99	103	107
20 kVA	18.0 kW	52	54	57	59	62	65	67	70	73	75	78	81
kVA	kW	74	76	78	80	82	84	86	88	90	92	94	96
4 kVA	3.6 kW												
8 kVA	7.2 kW	258	267	276	284	293	302	311	320	329	338	347	356
12 kVA	10.8 kW	157	162	16	173	178	183	189	194	200	205	211	216
16 kVA	14.4 kW	110	114	118	121	125	129	133	136	140	144	148	152
20 kVA	18.0 kW	84	87	89	92	95	98	101	104	107	109	112	115
kVA	kW	98	100	102	104	106	108	110	112	114	116		
4 kVA	3.6 kW												
8 kVA	7.2 kW	365	374	383	393	402	411	421	430	440	449		
12 kVA	10.8 kW	222	227	233	238	244	250	256	261				
16 kVA	14.4 kW	156	160	163	167	171	175	179					
20 kVA	18.0 kW	118	121	124	127	130	133						

Battery runtimes are approximate and may vary with equipment, configuration, battery age, temperature, etc.

Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
Eaton.com

© 2021 Eaton
All Rights Reserved
Printed in USA
Publication No. BR153085EN / GG
February 2021

To learn more, visit [Eaton.com/9PXM](https://www.eaton.com/9PXM)

Follow us on social media to get the latest product and support information.

