

Redundant 200W Media Converter Chassis Power Supply Module for ETCHS2U

StarTech ID: *ETCHS2UPSU*



The ETCHS2UPSU Redundant / Replacement 200W Chassis Power Module for ETCHS2U lets you add a redundant power supply, or keep a replacement power supply on hand for your [ETCHS2U](#) media converter chassis.

A hot-swappable, modular design allows a second media converter redundant power supply to be removed or installed while the chassis is still operating, avoiding unnecessary downtime. The power supply is installed using thumbscrews for a quick and easy installation that doesn't require additional tools.

Backed by a StarTech.com 2-year warranty and free lifetime technical support.

Applications

- Install into the ETCHS2U media converter chassis to provide redundancy
- Store a replacement power supply to have it on hand in the event of a failure

Features

- Redundant / replacement power supply for ETCHS2U
- 200W Output
- Hot-swappable, simple installation
- Active Power Factor Correction (PFC)

Technical Specifications

Warranty	2 Years
Efficiency Rating	90% (Typical Load)
MTBF	65,000 Hours (25°C)
Output Power	200W
Power Factor Correction	Active
Enclosure Type	Steel
Product Height	1.7 in [42 mm]
Product Length	6.3 in [160 mm]
Product Weight	2.8 lb [1.3 kg]
Product Width	6.3 in [159 mm]
Input Current	2.2A @ 115VAC / 1.2A @ 230VAC
Input Voltage	110 ~ 240 AC
Output Current	16.6A
Output Voltage	12 DC
Humidity	5~90% RH Non-condensing
Operating Temperature	0°C to 60°C (32°F to 140°F)
Storage Temperature	-10°C to 70°C (14°F to 158°F)
Shipping (Package) Weight	3.3 lb [1.5 kg]
Included in Package	1 - Replacement 200W Power Module for ETCHS2U

Certifications, Reports and Compatibility

