Datasheet

# HP Color LaserJet Managed Flow MFP

Businesses that stay ahead don't slow down. It's why HP built the next generation of HP Color LaserJet MFPs—to power productivity with a streamlined design that delivers premium color value, maximum uptime, and the strongest security.<sup>1</sup>

Print Speed: Letter: Up to 30 ppm black; Up to 30 ppm color; First Page Out: As fast as 9.7 sec black; As fast as 11.4 sec color

**Print Resolution:** Black (best): Up to 1200 x 1200 dpi reduced speed; Color (best): Up to 1200 x 1200 dpi reduced speed

Standard Connectivity: 2 Hi-Speed USB 2.0 Host; 1 Hi-Speed USB 2.0 Device; 1 Gigabit Ethernet 10/100/1000T network; 1 Hardware Integration Pocket; 1 Fax modem port Standard Memory: Standard: 7 GB; Maximum: 7 GB

Mobile Printing Capability: SNMPv3, SSL/TLS, WPA2-Enterprise, 802.1X authentication (EAP- PEAP, EAP-TLS), IPP over TLS, IPsec/Firewall with Certificate, Pre-Shared Kev Authentication, and Kerberos Authentication

Paper Handling: 100-sheet multi-purpose tray, 2 x 520-sheet input tray, 520-sheet input tray, 250 sheet ADF; 500 sheet face-down output bin

**Display:** 8.0-in (20.3 cm) touchscreen, SVGA Color Graphic Display (CGD)















#### Big color. Small cost.

- Print premium, professional-quality documents with vivid color images and graphics for a low cost.
- Get consistent, professional quality and performance you count on with Original HP toner cartridges and drums.
- Choose from a range of modular accessories designed to adapt to the needs of workgroups of all sizes.

#### Minimal interruptions. Maximum uptime.

- Avoid interruptions with an HP LaserJet Managed MFP designed to be streamlined for maximum productivity.
- Tailor this MFP to the needs of your business with a wide range of paper-handling accessories.
- Scan files directly to Microsoft<sup>®</sup> Office 365 and SharePoint, plus email, USB, and network folders.<sup>2</sup>
- Grab pages and go, without waiting. This HP Laser Jet wakes up quickly and prints fast—up to 30 ppm.<sup>3</sup>

#### The world's most secure printing<sup>1</sup>

- With HP Sure Start, each printer regularly checks its operating code and repairs itself from attempted hacks.
- Help protect information on the MFP and in transit over the network. Store data on the encrypted hard disk.4
- Continually monitor to detect and stop attacks, then automatically reboot with run-time intrusion detection.
- Whitelisting checks firmware during startup to help ensure it's authentic, good code—digitally signed by HP.

#### Give workgroups the speed they need

- Help workgroups capture every page easily and detect potential errors or missed pages—every time.
- Enter data more quickly and accurately using the pull-out keyboard.
- Help ensure every scanned document is properly oriented, cropped to size, and grayscale-optimized.
- Load up to 250 pages into the automatic document feeder for fast, unattended scanning.

<sup>1</sup> Based on HP review of 2016 published security features of competitive in-class printers. Only HP offers a combination of security features that can monitor to detect and automatically stop an attack then self-validate software integrity in a reboot. For a list of printers, visit http://www.hp.com/go/printersThatProtect. For more information: http://www.hp.com/go/printersecurityclaims<sup>2</sup> Requires an Internet connection to the printers. Services may require registration. App availability varies by country, language, and agreements. For details, see http://www.hp.com/go/printersecurityclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.<sup>4</sup> Some features require additional purchase. A FutureSmart service pack update may be required to activate security features. Learn more at http://www.hp.com/go/printerscurity.<sup>5</sup> Scan speed measured from ADF at default 300 dpi (lack-and-white, grayscale, and color). Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.

### HP Color LaserJet Managed Flow MFP E77830z - Speed 30 ppm Specifications Table

| nd; Tray 2, 3: 16 to 58 lb bond  |  |   |
|--|--|---|
| Tray 1: Letter, Letter R, Legal, Executive, Statement, Oficio, 11 x 17, 4 x 6, 5 x 7, 5 x 8, 10 x 15, 8k,<br>envelope #9, Envelope #10, Envelope Monarch, Tray 2: Letter, Letter R, Legal, Executive, Statement,<br>Oficio, 4 x 6, 5 x 7, 5 x 8, 16k; Tray 3: Letter, Letter R, Legal, Executive, Statement, Oficio, 11 x 17,<br>16k   |  |   |
|  |  |   |
| 11.69 x 17 in; Tray 2: 5.48 x 8.27 to 11.69 x 14.33 in; Tray 3: 5.48 x 8.27 to 11  |  |   |
| bose tray, 2 x 520-sheet input tray, 520-sheet input tray, 250 sheet ADF; 500  |  |   |
| sheet face-down output bin; Duplex Options: Automatic (standard); Auto Document Feeder Capaci<br>Standard, 250 sheets; Envelope Feeder. No; Standard Paper Trays: 3; Input Capacities: Up to 520<br>cheatr. Up that Capacities: Up to 520<br>cheatr. Up that Capacities: Up to 520   |  |   |
| sheets; Output Capacities: Up to 500 sheets; Up to 40 envelopes<br>X3A83A Engine; TCU; Drums; Assy-Color WG Nameplate and Label; Power Cords; Assembly-CD W<br>Hardware install and setup documentation; Support flyers (DOES NOT INCLUDE TONER) <sup>1</sup><br>HP Black Managed LJ Toner Cartridge (ISO Yield 34,000) W9040MC, HP Cyan Managed LJ Toner<br>Cartridge (ISO Yield 32,000) W9041MC, HP Vellow Managed LJ Toner Cartridge (ISO Yield 32,000)<br>W9042MC, HP Magenta Managed LJ Toner Cartridge (ISO Yield 32,000) W9043MC <sup>8</sup>   |  |   |
|  |  | x 36.5 in; <b>Maximum</b> : 50.2 x 30.9 x 46.8 in   |
|  |  |   |
| 90 day parts only. Extended Warranty and support options vary by product, country and local lega<br>requirements. Go to http://www.hp.com/support to learn about HP award winning service and sup<br>options in your region.   |  |   |
| RGY STAR® qualified; EPEAT® Silver; CECP   |  |   |
| 8.0-in (20.3 cm) Color Graphics Display (CGD) with touchscreen; rotating (adjustable angle) display;<br>illuminated Home button (for quick return to the Home menu); USB High-speed 2.0 port; Hardware   |  |   |
| illuminated Home button (for quick return to the Home menu); USB High-speed 2.0 port; Hardw<br>Integration Pocket; Pull-out Keyboard   |  |   |
| 8.0-in (20.3 cm) touchscreen, SVGA Color Graphic Display (CGD)<br>HP Connected, HP Device Experience (DXP), HP PCL 6 Printer Driver, HP Software Installer/Uninstal<br>Mac OS Welcome Screen (Directs users to 123.HP.com or OS App Source for printer software), Onli<br>user manuals   |  |   |
|  |  | fonts   |
| 5.0), Linux Debian (7.0, 7.1, 7.2, 7.3, 7.4, 7.5, 7.6, 7.7, 7.8, 7.9, 8.0, 8.1, 8.2, 8.3   |  |   |
| 8.4, 8.5, 8.6), Linux Fedora (22, 23, 24), Linux Mint (17, 17.1, 17.2, 17.3, 18), Linux Red Hat Enterpris<br>(60, 7.0), Linux SUSE (13.2, 42.1), Linux Uburtu (12.04, 14.04, 15.10, 15.04, 16.10), OS mac05 10.1<br>Sierra, 05 X 10.10 Vosemite (05 X 10.11 E Lapitan, UNIX, Windows 10 all 32-8 64-bit editions<br>(excluding RT OS for Tablets), Windows 7 all 32-8 64-bit editions, Windows 8(8.1 all 32-8 64-bit editions<br>(editions (excluding RT OS for Tablets), Windows Vistail all 25th editions (Hondows 8(8.1 all 32-8 64-bit editions))  |  |   |
|  | indows XP SP3 32-bit editions (XP Home, XP Pro, etc.)  |   |
| Citrix MetaFrame Presentation Server 3.0. Citrix MetaFrame XP Presentation Server (Feature Releases 2, and 3). Citrix on Windows Server 2003/2008R2. Citrix on Windows Server 2008/2008R2 2008 R2 Strix Oral Server 4.0/4.5, Citrix XenApp 5.0.[6] Feature Pack 2 & 3) for Windows Server 2008 Terminal Services 32- and 64-bit, Citrix XenApp 5.0.[6] [for Windows Server 2008 R2 SPT - Citrix Server 2008 Terminal Services, 32- and 64-bit), Citrix XenApp 5.0.[6] [for Windows Server 2008 R2 SPT - Terminal Services, 32- and 64-bit), Citrix XenApp 5.0.[6] Server 2012 and 2012 R2 Terminal Services, 32- and 64-bit), Citrix XenApp 5.0.[6] Server 2012 and 2012 R2 Terminal Services, 32- and 64-bit), Citrix XenApp 5.0.[6] Server 2012 and 2012 R2 Terminal Services, 32- and 64-bit), Citrix XenApet 5.0[6] Server 2012 and 2012 R2 Terminal Services, 64-bit), Citrix XenDesktop 5.6[70 // 5] for Windows Server 2008 R2 SPT - Terminal Services, 52- and 64-bit), Citrix XenDesktop 5.6[70 // 5] Terminal Services, 32- and 64-bit), Citrix XenDesktop 5.6[70 // 7] Server 2001 R2 SPT - Terminal Services, 32- and 64-bit), Citrix XenDesktop 5.6[70 // 7] Server 2001 R2 SPT - Terminal Services, 54-bit), Citrix XenDesktop 5.6[70 // 7] Server 2012 and 2012 R2 Terminal Services, 54-bit), Citrix XenDesktop 5.6[70 // 7] Server 2001 R2 SPT - Terminal Services, 54-bit), Novell Den Enterprise Server 11/SP1, Novell Cient Server 2012 R2 For Linux, No Servers Xww.novell.com/print, Nirdows Server 2003 R2 SP (54-bit), Server Sover 2003 R2 SP (54-bit), Server Sover 2012 R2 SP1 SP1) |  |   |
|  | Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2003/2003 R2 32-<br>(SP1/SP2); Standard/Enterprise (- Cluster & Terminal Services), Windows Server 2008 32-(64-bit (S)<br>Standard/Enterprise (+ Cluster & Terminal Services), Windows Server 2008 R2 64-bit (SP1)<br>Standard/Enterprise (+ Cluster & Terminal Services), Windows Server 2008/2008 R2 32-(64-bit<br>(SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2008/2008 R2 32-(64-bit<br>(SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2008/2008 R2 32-(64-bit<br>(SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2008/2008 R2 32-(64-bit |   |
|  | oundation/Essentials/Datacenter (+ Cluster & Terminal Services), Windows Serv<br>d/ Essential/Datacenter (+ Cluster & Terminal Services)   |   |
|  | rd disk space; OS hardware requirements see microsoft.com; MAC: 1.3 GB availa  |   |
| hard drive space; Internet; OS hardware requirements see Apple.com for more info<br><b>Power Supply Type</b> : Internal (Built-in) power supply; <b>Power Requirements</b> : input voltage: 110 to 12<br>(+ / 10%, 220 to 240/sc / (- / 10%), 50/50 Hz (+ / - 3%); <b>Power Consumption</b> : 804 waits (printing),<br>watts (ready), 12 waits (sleep), 0.5 waits (auto-off), 0.1 waits (off) <sup>6</sup>   |  |   |
|  |  | slons: 6.7 B(A), printing color simplex A4 at 30 ppm; Acoustic Pressure Emission<br>or simplex A4 at 30 ppm |
| re Range: 59 to 86°F; Recommended Operating Temperature: 59 to 86°F; Stora   |  |   |
| 14 to 104°F; Non-Operating Humidity Range: 10 to 80% RH; Operating Humidit<br>; Recommended Humidity Operating Range: 20 to 80% RH   |  |   |
| : SNMPv3, SSL/TLS, WPA2-Enterprise, 802.1X authentication (EAP- PEAP,  |  |   |
| EAP-TLS), IPP over TLS, IPsec/Firewall with Certificate, Pre-Shared Key Authentication, and Kerbero<br>Authentication; Support for WJA-10 IPsec Configuration using IPsec Plug-in  |  |   |
| Cabinet Workgroup Y1G17A, Dual Cassette Feeder (2x520) Workgroup Y1F97A, 2000 Sheet HCI WG<br>Y1F99A, Inner Finisher Y1G00A, Inner Finisher Hole Punch 2/3 Y1G02A, Inner Finisher Hole Punch 2/<br>Y1G03A, Inner Finisher Hole Punch Sweidsh Y1G0A, Stapler/Stacker Finisher Y1G18A, Boddet Finis<br>Y1G07A, Stapler/Stacker Finisher Staples Y1G14A, Inner Finisher & Booklet Maker Staples Y1G13A,<br>Separator WG Y1G15A, Tray Heater Y1G22A, 2nd exit Y1G23A, Spacer Y1G24A, Hole Punch 2/3<br>Y1G10A, Hole Punch 2/4 Y1G11A, Hole Punch Sweidsh Y1G12A, D0D CC Card Reader C534B, SIPI<br>- Classified Card Reader F8830A, FiH USB Foreign Interface Harness BSL31A, Two Internal USB port<br>solutions BSL28A, HOL PH Secure High Performance Hard Disk Drive BSL29A, HPAC Card Reader<br>HIP1 C220BA, HBAC Card Reader - HIP1 X3D03A, HPAC Card Reader - HIP2 X3D03A, Analog Fax<br>Accessory C4847A  |  |   |
|  | Parline De Carles (D.C. Barris H. B. C. B. C.  |   |
|  | dt Business Day Service wDefective Media Retention for Color Laserlet T778xx<br>E + HP 3 yn Rvst Business Day Service wDefective Media Retention for Color<br>Managed; U9LP5E - HP 4 yn Next Business Day Service wDefective Media<br>service T778xx MPP Managed; U9LP6E - HP 5 yn Next Business Day Service<br>tention for Color Laserlet E778xx MPP Managed; U9LP7E - HP 3 yr 4 hour 9x5<br>Hedia Retention for Color Laserlet E778xx MPP Managed; U9LP8E - HP 4 yr 4 h<br>ve Media Retention for Color Laserlet E778xx MPP Managed;   |   |
| Dr.C   |  |   |

## Learn more at hp.com

<sup>1</sup> No, please purchase USB cable separately (EMEA, Americas; AP) (Service Technician must install units) <sup>2</sup> Based on standard ITU-T test image #1 at standard resolution and MMR encoding, the HP fax device can transmit at 3 sec/page for V.37 and 6 sec/page for V.17 <sup>3</sup>Measured using ISO/IEC 17629. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>4</sup> Optional Wireless <sup>1</sup>Declared yield value in accordance with ISO/IEC 19752. Actual yields vary considerably based on images printed and other factors. For more information, visit http://www.hp.com/go/learnaboutsupplies <sup>6</sup> Power requirements are based on the country/region where the printer is sold. D on to convert operating voltages. This will damage the printer and void the product warranty. <sup>7</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/learnaboutsupplies <sup>9</sup> Scan speeds measured from ADF. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies. <sup>9</sup> Scan speeds measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software. <sup>10</sup> Power requirements are based on the country/region where the printer is sold. D on to convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies. <sup>9</sup> Scan speeds measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software. <sup>10</sup> Power requirements are based on the country/region where the printer is sold. D on to convert operating voltages. This will damage the printer and void the product waranty. Energy Star value typically based on measurement

© Copyright 2017-2018 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Windows is a registered trademark of Microsoft Corporation. AirPrint, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.