





**EN** - For pricing and availability in your local country please visit one of the below links:

**DE** - Informationen zu Preisen und Verfügbarkeit in Ihrem Land erhalten Sie über die unten aufgeführten Links:

FR - Pour connaître les tarifs et la disponibilité dans votre pays, cliquez sur l'un des liens suivants:

S1100

#### ΕN

This Datasheet is presented by the manufacturer

#### DE

Dieses Datenblatt wird vom Hersteller bereitgestellt

#### FR

Cette fiche technique est présentée par le fabricant

# **Document Scanners**

ScanSnap S1100



shaping tomorrow with you



#### S ON BOTH WINDOWS AND MAC OS OPERATING SYSTEMS • OPERATES ON BO

## Compact, easy to use "one touch" scanning!

Easily digitises your documents!

Perfect for home or office use!

A must have for the paperless era!

Make your paper documents more mobile!

#### One of the smallest mobile A4 scanners in the world

The ScanSnap S1100 document scanner pushes the limits of size for extreme portability while delivering smooth A4 size document scanning<sup>1</sup>. All you need is your laptop and one USB cable to scan and share your documents anywhere, anytime.



The S1100 delivers a snappy 7.5 seconds/page (approximately 8 ppm) scanning speed for color A4 documents at resolutions up to 300 dpi.<sup>2</sup>

- <sup>1</sup> When using an optional carrier sheet it is possible to scan even A3 size documents and stitch the front and back side of the folded document together.
- $^{\rm 2}$  The time for scanning was measured from the time a page first enters to the time it fully exits the scanner.

#### Scans plastic cards and other various document types\*

In addition to standard paper types, the S1100 can scan plastic cards like the ones used for membership IDs.

\*Card type ISO 7810, ID-1 format = 86 x 54 mm (supports embossed cards)



#### **Continuous Document Feeding (CDF Function)**

Even though the S1100 is one of the world's smallest document-feed scanners, you can smoothly scan multiple page documents with remarkable speed. The Continuous Document Feeding function allows you to insert pages one after another without any extra button pressing by detecting when a sheet enters and exits the S1100.

#### Scanning a two-sided document using the CDF Function



1 Insert the page face up and press the Scan button. 2 The S1100 proceeds to scan the front side. 3 The page exits facing front side down. 4 Reinsert the page without pressing the Scan button. 5 The page is scanned. Press the Scan button to end the scanning process and create the PDF image file.

#### **Seamless linking to Cloud services**

The ScanSnap series scanners come with a standard array of functions for near effortless scanning to Evernote, Google Docs, Salesforce, SugarSync and Dropbox.

#### ScanSnap Folder (Windows OS only)\*

You can now easily scan into your preferred application or cloud service even when no scan interface is available, through the import capability. Browse to the new ScanSnap Folder and hit the blue scan button. The documents are now imported into your application and automatically deleted from the ScanSnap Folder on your local computer!

#### ScanSnap welcomes Dropbox\*

Dropbox is a free service that lets you bring all your photos, docs and videos anywhere. This means that any file you save to your Dropbox will automatically save to all your computers, phones and even the Dropbox website.

With more cloud services to choose from, ScanSnap customers are sure to find the right application for their documents.

\*Current ScanSnap S1100 users can add any newly enhanced software functions free of charge, please visit http://emea.fujitsu.com/ScanSnapSupport for a variety of options

#### Two selectable paper paths

Switch the S1100's paper output guide to either the folded position for the straight path or the open position for the U-turn path to best suit the document you want to scan.

Straight path



U-turn path



#### OPERATES ON BOTH WINDOWS AND MAC OS OPERATING SYSTEMS . OPERATES ON BOTH WINDOWS AND MAC OS OPERATING

#### **Document received** » Document scanned » Now make your paper productive ➤ Scan to PowerPoint® (Windows Only) Scan to Folder Scan to Email Scan to Word Scan to Print Scan to Excel Scan to Picture Folder (Windows Only) Scan and extract business Scan to iPhoto card data (MAC Only) Scan to ScanSnap Organizer Scan to Evernote (Windows Only) Scan to iPhone®/ Google Docs iPad®, Android<sup>™</sup> and Kindle<sup>™</sup> Scan to SugarSync Scan to Salesforce Chatter Scan to SharePoint Scan to DropBox (Windows Only)

#### Generates Microsoft Word®, Excel® and PowerPoint Files\*

 Scan editable image data directly to Microsoft® Word, Excel and PowerPoint® files\*\*

\*For Mac OS, Scanning to Microsoft® Word and Excel are available.
\*\*Generated images and text may vary from the original.

Top-class OCR Engine

Bundled ABBYY FineReader for ScanSnap™ 4.1

## Fast and flexible application of scanned data with Quick Menu

After scanning is complete, the Quick Menu appears. Navigate through the Quick Menu's easy to use interface to smoothly send your digitized document to an application of your choice.

• Quick Menu for Windows® OS Users




Quick Menu for Mac OS Users



For PC Users: ScanSnap Manager V5.1 for Windows
For Mac Users: ScanSnap Manager V3.2 for MAC

#### Efficiently organises data from scanned business card

- Scan your collection of business cards into easy to navigate digital business card holders
- Import the data from your scanned business cards into Excel, Outlook, Address Book, SalesForce and other database programs for fast referencing and application



Business card scanning software

For PC Users: CardMinder™ V4.1

For Mac Users: Cardiris™ 4.0 for ScanSnap

#### ScanSnap S1100 Deluxe comes with Rack2-Filer V5.0

- Directly file and organize your digitized documents in virtual binders
- Realistic page flip interface with useful editing functions
- A powerful tool for uniformly managing image data produced by the S1100 and other devices



#### Scans to a greater range of mobile devices



Like all scanners of the ScanSnap series, the S1100 supports wireless scanning to iPad® and iPhone® devices for convenient mobile viewing via the ScanSnap Connect Application\*, which now comes in a version for Android™ smartphones and tablets and also for Kindle™ devices.

\* ScanSnap Connect Application is available as a free download from the official application distribution service of the device (Google Play, Apple App Store and Amazon App Store). The Wi-Fi of the ScanSnap installed computer must be turned on to use this feature.

### **ScanSnap S1100 Specifications**



| Product name Scanner type               |   | ScanSnap S1100 CDF (Continuous Document Feeding), simplex sheetfed two way paper pass (Straight path, U turned path)   |                  |  |
|---|---|--|------------------|--|
| Scanning modes                          |   | Colour, grayscale, monochrome, automatic (colour / grayscale / monochrome detection)   |                  |  |
| Image sensor                            |   | CIS (Contact Image Sensor) x 1   |                  |  |
| Light source                            |   | 3 Colour LED (Red/Green/Blue)  |                  |  |
| Optical resolution                      |   | 600 dpi  |                  |  |
| Scanning speed*1<br>(A4 portrait)       | USB bus powered   | 7.5 seconds per page (Auto mode (default)'², Normal mode (150 dpi), Better mode (200 dpi), Best mode (300 dpi))<br>35 seconds per page Excellent mode (600 dpi)  | Sca<br>bu<br>fro |  |
| Document size                           | Normal mode   | A4, A5, A6, B5, B6, Business card, Post card, Letter, Legal and Custom sizes<br>(Max : 216 x 360 mm , Min : 25.4 x 25.4 mm) / Automatically recognises document size   | Ch<br>12 Do      |  |
|   | Normal mode with Carrier sheet  Long paper scanning <sup>43</sup> | Use of a carrier sheet permits the scanning of A3, B4, double letter and photographs as well as the document sizes that are listed above  Max: 216 x 863 mm (300 dpi or less)  | 148<br>"B        |  |
| Paper weight (Thickness)                |   | 52 to 209 g/m², or 14 to 56 lb (Straight path) / 52 to 80 g/m², or 14 to 20 lb (U turned path)  Card can be used. (portrait/landscape), Non-Embossed : 0.76 mm or Less, Embossed : 0.76 + 0.48 mm (ISO7810 conforming) |                  |  |
| Paper setting                           |   | Front side up  |                  |  |
| Interface*4                             |   | USB 2.0 (USB 1.1 compatible)   |                  |  |
| Power requirement                       |   | 5V / 0.5A ( x 1 port)  | gua<br>"5 Wh     |  |
| Power consumption                       |   | During operation : 2.5W or less, During sleep mode : 1W or less, During power off: Less than 0.5W  | fol              |  |
| Operation environment                   |   | Temperature: 5 to 35°C (41 to 95°F) / Relative humidity: 20 to 80% (Non-condensing)  |                  |  |
| Dimensions (W x D x H)*5, Device weight |   | 273 x 47.5 x 34 mm, 350g   | *6 PFI<br>de     |  |
| Environmental compliance                |   | ENERGY STAR® compliant / RoHS™   |                  |  |
| Driver                                  |   | ScanSnap specific driver, Windows: Does not support TWAIN / ISIS™, Mac OS : Does not support TWAIN   |                  |  |
|   |   |  |                  |  |

| System requirements for Windows |                                    | Windows® 8 (32bit / 64bit)  | Windows® 7 (32bit / 64bit)                             | Windows Vista™ (32bit / 64bit)             | Windows® XP (32bit) |  |
|---------------------------------|------------------------------------|---|--|--|---------------------|--|
| Driver / Applications*1,*2      | ScanSnap Manager V5.1              | Supported   | Supported  | Supported*3                                | Supported*4         |  |
|                                 | ScanSnap Organizer V4.1*5          | Supported   | Supported  | Supported*3                                | Supported*4         |  |
|                                 | CardMinder™ V4.1                   | Supported   | Supported  | Supported*3                                | Supported*4         |  |
|                                 | ABBYY FineReader for ScanSnap™ 4.1 | Supported   | Supported  | Supported*3                                | Supported*4         |  |
|                                 | Evernote for Windows 4.4           | Supported   | Supported  | Supported*3                                | Supported*4         |  |
|                                 | Scan to Microsoft® SharePoint 3.4  | Supported   | Supported  | Supported*3                                | Supported*4         |  |
| Hardware requirements           | CPU*6                              | Intel® Pentium® 4 1.8 GHz or higher (recommended: Intel® Core™ 2 Duo 2.2 GHz or higher)                                     |  |  |                     |  |
|                                 | Memory capacity*6                  | 64bit: 2 GB or more<br>32bit: 1 GB or more  |  | 512 MB or more (recommended: 1 GB or more) |                     |  |
|                                 | Display                            | 1024 x 768 pixels or more   | 800 x 600 pixels or more, High colour (16-bit) or more |  |                     |  |
|                                 | Disk capacity*7                    | 2,220 MB or more of free hard disk space, (2,470 MB or more of free hard disk space is required for using with Rack2-Filer) |  |  |                     |  |
|                                 | DVD-ROM drive                      | Required for Installation   |  |  |                     |  |
|                                 | USB port*6                         | USB 2.0 / USB 1.1   |  |  |                     |  |

| System requirements for Mac OS |                                    | Mac OS X v10.8  | Mac 0S X v10.7 | Mac OS X v10.6*1  | Mac OS X v10.5*2  | Mac OS X v10.4*3     |
|--------------------------------|------------------------------------|---|----------------|---|---|----------------------|
| Driver / Applications*4,*5     | ScanSnap Manager V3.2              | Supported   | Supported      | Supported   | Supported   | Supported            |
|                                | Cardiris™ 4.0 for ScanSnap         | Supported   | Supported      | Supported   | Supported   | Supported            |
|                                | ABBYY FineReader for ScanSnap™ 4.1 | Supported   | Supported      | Supported*5   | Supported   | Supported            |
|                                | Evernote for Mac 3.3               | Supported   | Supported      | Supported   | Not Supported   | Not Supported        |
| <b>Hardware requirements</b>   | CPU* <sup>7</sup>                  | Intel® Core™ 2 Duo Processor<br>(recommended: Intel® Core™ 2 Duo 2.4 GHz or higher) |                | Intel® Core™ Duo 1.83 GHz or<br>higher (recommended: Intel®<br>Core™ 2 Duo 2.4 GHz or higher) | Intel® Core™ Duo 1.83 GHz or higher<br>(recommended: Intel® Core™ 2 Duo 2.4 GHz<br>or higher) Power PC G5 1.6 GHz or higher |                      |
|                                | Memory capacity*7                  | 2 GB or more  |                | 1 GB or more  | 512 MB or more (recommo   | ended: 1 GB or more) |
|                                | Display                            | 1024 x 768 pixels or more   |                |   |   |                      |
|                                | Disk capacity                      | 1,555 MB free hard disc space for installation                                      |                |   |   |                      |
|                                | DVD-ROM drive                      | Required for installation   |                |   |   |                      |
|                                | USB port*7                         | USB 2.0 / USB 1.1   |                |   |   |                      |

| Consumables and Options | Part number   | Remarks  |  |  |
|-------------------------|---------------|--|--|--|
| ScanSnap S1100 Case     | PA03610-0001  | Specially designed for ScanSnap S1100 and included items |  |  |
| ScanSnap Carrier Sheet  | PA03360-0013A | 5 Carrier Sheets for ScanSnap models                     |  |  |
| ScanSnap Cleaning Wipes | SC-CLE-SS     | 24 x Cleaning Fluid Impregnated Cleaning Wipes           |  |  |

| Included items Getting started, Set-up DVD-ROM, USB cable (2.0m), Rack2-Filer (Exclusive to S1100 with Rack2-Filer) |  |
|---|--|
|---|--|

All names, manufacturer names, brand and product designations are subject to special trademark rights and are manufacturer's trademarks and/or registered brands of their respective owners. All indications are non-binding. Technical data is subject to change without prior notification. Apple iPad, iPhone, iPod touch and iTunes are trademarks of Apple Inc., registered in the U.S. and other countries. App Store is a service mark of Apple Inc.

canning speeds may vary due to the system nvironment used. Scanning Speed means the me from "Start feeding document" to "Finish utput document"after pre-pick and pushing can button. In case of "From pushing Scan utton", Warm-up time is added. Warm-up time: rom Ready status: Less than 2 seconds From hute Cover Closed Status: Less than 3 seconds.

ocuments measuring approximately 48 mm in length or less are scanned in Best mode", while other documents are canned in "Better mode".

ne S1100 is capable of scanning documents hat exceed A4 size in length. This function is vailable for all modes except Excellent mode

C with USB 3.0 works as USB 2.0 It is uaranteed only attached USB cable.

hen the paper output guide is in the

FU LIMITED, a Fujitsu company, has etermined that this product meets RoHS equirements (2002/95/EC).

\*1 These products only support Microsoft Windows® \*2 For the latest support information, visit the ScanSnap homepage.

\*3 Service Pack 1 or later required.

\*4 Service Pack 3 or later required.

\*5 Adobe® Acrobat® 7.0 or later (not included) is required in order to use the Adobe® Acrobat® search feature. Please check the Adobe homepage to find out which version of Acrobat is supported by the OS you are using.

memory capacity and USB 1.1 requirements are not met.

Microsoft .NET Framework 3.5 SP1 will be installed (requires 500 MB of disk space) together with either ScanSnap Manager or ScanSnap Organizer for systems that do not have .NET Framework 3.5 SP1 installed.

\*1 Mac OS X v10.6.6 or later recommended.

Mac OS X v10.4.11 recommended.

\*4 These products only support Mac OS. 15 For the latest support information, visit the ScanSnap homepage

\*6 Mac OS X v10.5.8 only.

Scanning speeds may drop if recommended CPU, memory capacity and USB1.1 requirements







**PFU Imaging Solutions Europe Limited** 

Hayes Park Central Hayes End Road, Hayes Middlesex UB4 8FE England

(+44-(0)20) 8573 4444 Fax: (+44-(0)20) 8573 2643

www.ScanSnapit.com

PFU Imaging Solutions GmbH PFU Imaging Solutions S.p.A.

Frankfurter Ring 211 80807 Munich

(+49-(0)89) 32378-0 Tel: (+49-(0)89) 32378-100 Via Nazario Sauro, 38

20099 Sesto San Giovanni (MI)

(+39) 0226294.1 Tel: (+39) 0226294.201









**EN** - For pricing and availability in your local country please visit one of the below links:

**DE** - Informationen zu Preisen und Verfügbarkeit in Ihrem Land erhalten Sie über die unten aufgeführten Links:

FR - Pour connaître les tarifs et la disponibilité dans votre pays, cliquez sur l'un des liens suivants:

S1100

#### ΕN

This Datasheet is presented by the manufacturer

#### DE

Dieses Datenblatt wird vom Hersteller bereitgestellt

#### FR

Cette fiche technique est présentée par le fabricant