



# HP LaserJet Pro MFP M521dn

Finish jobs faster, produce high-quality documents, and make scanning and sharing simple. Get set up and connected quickly.<sup>3,7</sup> Send quick commands from an intuitive color touchscreen. Easily conserve resources and recycle used cartridges.<sup>11</sup>



**Print speed** Up to 42 ppm black (letter), Up to 40 ppm black (A4)

**First page out (black)** As fast as 13.4 sec.

**Scan speed (letter)** Up to 21 ppm (b&w), up to 15 ppm (color)

**Copy resolution** Up to 600 x 600 dpi graphics and text, Up to 600 x 600 dpi color graphics and text.

**Fax speed** Up to 33.6 kbps; 3 sec per page.

**Paper handling** 00-sheet multipurpose tray, 500-sheet input tray 2, 50-sheet automatic document feeder, 250-sheet output bin, 100-sheet rear output bin

**Standard connectivity** HP Jetdirect ew2500 802.11b/g Wireless Print Server J8021A; HP

Jetdirect 2700w USB Wireless Print Server J8026A.

**Duty cycle (monthly)** Up to 75,000 pages

## Quickly create, capture, and deliver documents

- Finish faster—with less standing around—using single-pass, dual-head scanning.
- Stay on schedule—print up to 42 pages per minute.<sup>4</sup> Handle high-volume printing without worries.
- Scan documents and send digital files in one easy step—to email, the cloud, network folders, or a USB drive.
- Efficiently handle large jobs, with an input capacity up to 1,100 sheets and automatic two-sided printing.

## Increase efficiency with an easy-to-manage MFP

- Work smarter—access, store, and print business content quickly from the 3.5-inch color touchscreen.<sup>5</sup>
- Go from zero to done, right at the MFP—print, copy, scan, and fax with ease.
- Save time with an easy-to-install Original HP cartridge. Save more, using a high-capacity cartridge.<sup>6</sup>
- Efficiently manage this MFP, using HP Web Jetadmin to remotely monitor office printing and device status.<sup>12</sup>

## Set up fast and stay connected

- HP ePrint—now print from your smartphone and tablet from virtually anywhere.<sup>8</sup>
- Use resources more efficiently with 100/1000 Base-TX Ethernet networking—easily print and share.
- Pull print jobs from your pocket—walk up and print right from a memory device via the USB port.

## Improve your energy costs and save resources

- Help save energy with HP Auto-On/Auto-Off Technology, Instant-on Copy, and Instant-on Technology.<sup>10</sup>
- Conserve resources and save paper—use automatic two-sided printing.
- Get centralized, easy access to custom energy-saving options and printer settings with HP EcoSMART Console.
- Reduce your impact—easily recycle Original HP LaserJet toner cartridges through HP Planet Partners.<sup>11</sup>



Easy access USB

2-sided printing



<sup>4</sup> Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. For more information, see [hp.com/go/printerclaims](http://hp.com/go/printerclaims). Exact speed varies depending on the system configuration, software application, driver, and document complexity. First page out exact speed varies depending on the system configuration, software program, document complexity, network, media width, media weight, environment, and job size.<sup>5</sup> Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see [hpconnected.com](http://hpconnected.com).<sup>6</sup> HP LaserJet 255X Black Toner Cartridge not included; please purchase separately.<sup>8</sup> Local printing requires mobile device and printer to be on the same network or have a direct wireless connection to the printer. Wireless performance is dependent on physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz operations only. Remote printing requires an Internet connection to an HP web-connected printer. App or software and HP ePrint account registration may also be required. Wireless broadband use requires separately purchased service contract for mobile devices. Check with service provider for coverage and availability in your area. See [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting) for more details.<sup>10</sup> HP Auto-On and Auto-Off Technology are subject to printer and settings. Instant-on Technology claim based on comparison with products that use traditional fusing. Instant-on Copy claim based on comparison with fluorescent tubes.<sup>11</sup> Program availability varies. Original HP cartridge return and recycling is currently available in more than 50 countries, territories and regions in Asia, Europe, and North and South America through the HP Planet Partners program. For more information, visit: [hp.com/recycle](http://hp.com/recycle) <sup>12</sup> HP Web Jetadmin is free and can be downloaded at [hp.com/go/webjetadmin](http://hp.com/go/webjetadmin)

# HP LaserJet Pro MFP M521dn Specifications Table

<b>Functions / Multitasking Supported</b>	Print, copy, scan, fax / Yes
<b>Print Speed</b>	<b>Letter:</b> Up to 42 ppm black; <sup>5</sup> <b>First Page Out:</b> As fast as 8.0 sec black; <sup>6</sup>
<b>Print Resolution</b>	<b>Black (best):</b> Up to 1200 x 1200 dpi
<b>Print Technology</b>	Laser
<b>Print Resolution Technologies</b>	HP FastRes 1200 (600 x 600 dpi), HP ProRes 1200 (1200 x 1200 dpi), 600 x 600 dpi
<b>Print Cartridges Number</b>	1 (black)
<b>Standard Print Languages</b>	HP PCL 6, HP PCL 5, HP postscript level 3 emulation, PCLm
<b>Printer Smart Software Features</b>	HP ePrint, Apple AirPrint™, Mopria-certified, HP Auto-On/Auto-Off technology
<b>Printer Management</b>	Windows: HP Device Toolbox, Status Alerts (default install), SNP Alerts (minimum network install), HP Web Jetadmin (download); Mac: HP Utility
<b>Scan Type / Technology</b>	Flatbed, ADF / Contact Image Sensor (CIS)
<b>Scan Resolution</b>	<b>Hardware:</b> Up to 300 x 300 dpi (color, grayscale and mono, ADF); Up to 1200 x 1200 dpi (color, grayscale and mono, flatbed); <b>Optical:</b> Up to 300, 600, 1200 dpi
<b>Scan Input Modes</b>	From PC: Solution Center Lite (Windows Vista, Windows XP) or Device Stage (Windows 7, 8); TWAIN-compliant or WIA-compliant software
<b>Scan Size</b>	<b>ADF:</b> 8.5 x 14 in Maximum; 5 x 7 in Minimum; <b>Flatbed:</b> 8.5 x 11.7 in
<b>Scan Speed</b>	Up to 19 ppm (black & white), up to 15 ppm (color) <sup>7</sup> <b>Duplex:</b> Up to 36 ipm (black & white), up to 14 ipm (color)
<b>Scanner Advanced Features</b>	Duplex scanning from ADF; Scan to USB flash drive; Scan to network folder; Scan to email; Scan to cloud; Optimize text/picture; Selectable scan resolution 75 to 300 dpi
<b>Native Scan File Format</b>	PDF, JPG <sup>8</sup>
<b>Software Scan File Format</b>	Windows: JPG, RAW(BMP), PDF, TIFF, PNG, RTF; Mac: JPG, JPEG-2000, TIFF, PNG, PDF, Searchable PDF, RTF, TXTHP Scan software included in the box - file formats supported through software running on a PC <sup>9</sup>
<b>Bit depth / Grayscale levels</b>	24 bit (8 bit for grayscale duplex jobs) / 256
<b>Copy Speed</b>	<b>Black (letter):</b> Up to 42 ppm
<b>Copy Resolution</b>	<b>Black (text and graphics):</b> Up to 600 x 600 dpi; Up to 600 x 600 dpi; <b>Color (text and graphics):</b> Up to 600 x 600 dpi
<b>Maximum Number Of Copies</b>	Up to 99 copies
<b>Copier Resize</b>	25 to 400%
<b>Copier Settings</b>	Number of copies; Reduce/Enlarge; Lighter/Darker; Optimize; Paper; Multi-page copy; Collation; Tray select; Two-sided; Draft mode; Image adjustment; Set as new defaults; Restore defaults
<b>Fax Speed</b>	<b>Up to:</b> 33.6 kbps; <b>Letter:</b> 3 sec per page <sup>4</sup>
<b>Fax Resolution</b>	<b>Black (best):</b> Up to 300 x 300 dpi; <b>Black (standard):</b> 203 x 98 dpi
<b>Fax Smart Software Features</b>	Permanent fax memory backup; Fax forwarding; Fax address book; TAM interface, Speed-dial; Group dial; Auto redial; Block junk faxes; Polling; Send a fax with confirmation; Private fax receive
<b>Fax Features</b>	<b>Fax Memory:</b> Up to 250 pages; <b>Auto Fax Reduction Supported:</b> Yes; <b>Auto-Redialing:</b> Yes; <b>Fax Delayed Sending:</b> Yes; <b>Distinctive Ring Detection Supported:</b> Yes; <b>Fax Forwarding Supported:</b> Yes; <b>Fax Phone TAM Interface Supported:</b> Yes; <b>Fax Polling Supported:</b> Yes; <b>Fax Telephone Mode Supported:</b> Yes; <b>Junk Barrier Supported:</b> Yes, requires Caller ID; <b>Maximum Speed Dialing Numbers:</b> Up to 100 numbers (each can contain 100 numbers); <b>PC Interface Supported:</b> Yes, software not included; <b>Remote Retrieval Capability Supported:</b> No; <b>Telephone Handset Supported:</b> No
<b>Standard Connectivity</b>	1 Hi-Speed USB 2.0 Device; 1 Hi-Speed USB 2.0 Host; 1 Gigabit Ethernet 100/100/1000Base-TX; 1 Telecom; 1 Phone
<b>Network Capabilities</b>	Via built-in 100/1000Base-TX networking
<b>Network Ready</b>	Standard (built-in Gigabit Ethernet)
<b>Mobile Printing Capability</b>	HP ePrint, Apple AirPrint™, Mopria-certified, Mobile Apps
<b>Memory</b>	<b>Standard:</b> 256 MB; <b>Maximum:</b> 256 MB
<b>Processor Speed</b>	800 MHz / <b>Hard disk:</b> None
<b>Duty Cycle</b>	<b>Monthly, letter:</b> 75000
<b>Recommended Monthly Page Volume</b>	2000 to 6000
<b>Media Types Supported</b>	Paper (bond, color, letterhead, plain, preprinted, prepunched, recycled, rough); envelopes, labels, cardstock, transparencies, user-defined
<b>Media Weight Supported</b>	Tray 1: 14 to 53 lb; Tray 2, 3: 14 to 32 lb
<b>Media Sizes Supported</b>	Letter, Legal, Statement, 3 x 5 in, 4 x 6 in, 5 x 7 in, 5 x 8 in, Executive, 8.5 x 13 in, Envelope (#9, #10, Monarch, C5, DL, B5, C6), Discrete Custom Sizes: Minimum size 3 x 5 in, Maximum size 8.5 x 14 in
<b>Media Sizes Custom</b>	Tray 1: 3 x 5 to 8.5 x 14 in; tray 2, optional 500-sheet tray (3): 4.1 x 5.8 to 8.5 x 14 in
<b>Paper Handling</b>	100-sheet multipurpose tray, 500-sheet input tray 2, 50-sheet Automatic Document Feeder (ADF); 250-sheet output bin, 100-sheet rear output bin; <b>Duplex Options:</b> Automatic (standard); <b>Auto Document Feeder Capacity:</b> Standard, 50 sheets; <b>Envelope Feeder:</b> No; <b>Standard Paper Trays:</b> 2; <b>Input Capacities:</b> Up to 600 sheets; <b>Output Capacities:</b> Up to 250 sheets; Up to 10 envelopes; Up to 75 sheets
<b>What's in the box</b>	<b>A8P79A</b> HP LaserJet Pro MFP M521dn; HP LaserJet Black cartridge (~6000 pages); Printer documentation and software on CDs (Windows/Mac OS installation CD); Installation guide; Support flyer; warranty card; Power cord; Fax Cable <sup>1</sup>
<b>Replacement Cartridges</b>	HP LaserJet Black Cartridge CE255A (~6000 pages based on ISO/IEC 19752); HP LaserJet Black Cartridge CE255X (~12,500 pages based on ISO/IEC 19752) <sup>3</sup>

<b>Product Dimensions</b>	<b>W x D x H:</b> 18.3 x 18.3 x 20 in; <b>Maximum:</b> 18.3 x 35.4 x 29.5 in
<b>Product Weight</b>	52.7 lb
<b>Warranty Features</b>	One-year limited hardware warranty; For more info please visit us at <a href="http://support.hp.com">http://support.hp.com</a>
<b>Energy Efficiency Compliance</b>	ENERGY STAR® qualified; EPEAT® Silver
<b>Control Panel</b>	3.5-in intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error)
<b>Display Description</b>	3.5" (8.89 cm) touchscreen, LCD (color graphics)
<b>Software Included</b>	Windows: HP Installer/Uninstaller, HP PCL 6 print driver, HP WIA Scan Driver, HP TWAIN Scan Driver, HP Scan, HP Fax Setup Wizard, HP Send Fax, HP Fax Print Driver, Status Alerts, HP Update, DXP; Mac: HP Installer/Uninstaller, HP Postscript driver, HP Scan, HP Setup Assistant, HP Fax Print Driver, HP Utility, HP Alerts, HP Firmware Updater
<b>Fonts and Typefaces</b>	84 scalable TrueType fonts. Additional Font Solutions available at <a href="http://hp.com/go/laserjetfonts">hp.com/go/laserjetfonts</a> .
<b>Compatible Operating Systems</b>	Full software installs supported on: Windows 10 32-bit and 64-bit, Windows 8 32-bit and 64-bit, Windows 7 32-bit and 64-bit, Windows Vista 32-bit and 64-bit, Windows XP 32-bit (SP2 or higher); Driver only installs supported on: Windows 2012; Windows Server 2008 32-bit and 64-bit, Windows Server 2003 32-bit (SP3 or higher); Mac OS X v 10.6.8 and later; Linux: Linux (9.4, 9.5), Red Hat Enterprise Linux 5.0 (supported with a pre-built package); SUSE Linux (10.3, 11.0, 11.1, 11.2), Fedora (9.0, 10.0, 10.1, 11.0, 11.2, 12.0), Ubuntu (8.04, 8.04.1, 8.04.2, 8.10, 9.04, 9.10, 10.04), Debian (5.0, 5.0.1, 5.0.2, 5.0.3) (supported by the automatic installer); HPLUX 11 and Solaris 8/9
<b>Minimum System Requirements</b>	<b>PC:</b> Windows 10 (32-bit/64-bit), Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit): 1 GHz 32-bit (x86) or 64-bit (x64) processor; 1 GB RAM (32-bit) or 2 GB RAM (64-bit); 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor; 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port; <b>MAC:</b> Mac OS X v 10.6; PowerPC G4, G5, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port
<b>Power</b>	<b>Power Supply Type:</b> Built-in power supply; <b>Power Requirements:</b> Input voltage: 110 to 127 VAC (+/-10%), 50/60Hz (+/- 3 Hz) and 220V-240 VAC (+/- 10%), 50/60Hz (+/- 3 Hz); <b>Power Consumption:</b> 760 watts (Printing), 520 watts (Copying from ADF), 18.2 watts (Ready), 4.3 watts (Sleep), 0.3 watts (Off) <sup>2</sup>
<b>Acoustics</b>	<b>Acoustic Power Emissions:</b> 6.7 B(A); <b>Acoustic Pressure Emissions:</b> 54 dB(A)
<b>Operating Environment</b>	<b>Operating Temperature Range:</b> 50 to 90.5°F; <b>Recommended Operating Temperature:</b> 59 to 90.5°F; <b>Storage Temperature Range:</b> -4 to 104°F; <b>Non-Operating Humidity Range:</b> 10 to 90% RH; <b>Operating Humidity Range:</b> 10 to 80% RH; <b>Recommended Humidity Operating Range:</b> 30 to 70% RH
<b>Security Management</b>	Embedded Web Server: password-protection, secure browsing via SSL/TLS; Network: enable/disable network ports and features, SNMPv1 community password change, SNMPv3, 802.1x, Firewall, Access Control List; HP ePrint: HTTPS with certificate validation, HTTP Basic Access authentication, SASL authentication
<b>Accessories</b>	HP LaserJet 500-sheet Feeder/Tray CE530A, HP LaserJet MFP M525 Cabinet CF338A
<b>HP Service and Support Options</b>	HP 3 year 4h 9x5 LaserJet Pro M521MFP HW Support, U6Z61E; HP 3 year 4h 13X5 LaserJet Pro M521MFP HW Support, U6Z62E; HP 3 year Next Business Day + DMR LaserJet Pro M521MFP Support, U6Z65E; HP 1 year Post Warranty Next Business Day + DMR LaserJet Pro M521MFP Support, U6Z67PE; HP 1 year Post Warranty 4h 9x5 LaserJet Pro M521MFP Support, U6Z68PE; HP 1 year Post Warranty 4h 13x5 LaserJet Pro M521MFP Support, U6Z69PE; HP Network Install Inkjet/Personal LaserJet Service, H3110E

Learn more at [hp.com](http://hp.com)

<sup>1</sup> One CE255A cartridge included and its declared yield is 6000 pages based on ISO/IEC 19752. Actual yield varies considerably based on images printed and other factors. For details please see [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies). Pages may vary based on customer printing conditions and usage. And users can also purchase CE255X cartridge for this printer, which declared yield is 12500 pages based on ISO/IEC 19752. <sup>2</sup> Values subject to change. Power numbers are the highest values measured using all standard voltages. See [hp.com/support](http://hp.com/support) for current information. Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. <sup>3</sup> Approximate average yield based on ISO/IEC 19752. Actual yield varies considerably based on printer platform, content of printed pages and other factors. For details see [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies). <sup>4</sup> Based on standard ITU-T test image #1 at standard resolution. More complicated pages or higher resolution will take longer and use more memory. <sup>5</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see [hp.com/go/printerclaims](http://hp.com/go/printerclaims). Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>6</sup> Exact speed varies depending on the system configuration, software application, driver and document complexity. <sup>7</sup> Scan speeds of up to 21 ppm measured at 200 dpi (b&w) and up to 15 ppm at 200 dpi (color) from automatic document feeder when scanning to digital file. Actual speeds may vary depending on scan resolution, network conditions, computer performance and application software. <sup>8</sup> HP Scan software included in the box - file formats supported through software running on a PC



# HP LaserJet Enterprise MFP

## M527 series



**Finish tasks faster<sup>1</sup> and help protect against threats with multi-level device security.<sup>10</sup>**

Finish tasks faster with an MFP that starts right away and helps conserve energy.<sup>1</sup> Multi-level device security helps protect from threats.<sup>10</sup> Original HP Toner cartridges with JetIntelligence and this printer produce more high-quality pages.<sup>2</sup>



**HP LaserJet Enterprise MFP M527dn**

### Accelerate your work and use less energy

- Don't wait for documents. Print your first page in as few as 8.7 seconds from energy-efficient sleep mode.
- Speed through jobs. Print and scan both sides of the page at once.
- This MFP leads its class in low energy use—thanks to its innovative design and toner technology.<sup>3</sup>
- Now 24% smaller—this MFP fits in tight places to boost performance in any workspace.<sup>9</sup>

### Unparalleled fleet security and management

- Embedded features detect security threats and heal your MFP, protecting it from boot up to shutdown<sup>10</sup>.
- Protect sensitive data on the MFP and in transit, using embedded security features and 256-bit encryption.<sup>10</sup>
- Protect sensitive business data with embedded and optional HP JetAdvantage Security Solutions.<sup>11</sup>
- Centralize control of your printing environment with HP Web Jetadmin<sup>12</sup>—and help build business efficiency.

### More. Pages, Performance, and Protection.

- Produce sharp text, bold blacks, and crisp graphics with precision black toner.
- Get more. Original HP Toner with JetIntelligence delivers more pages per cartridge than predecessors.<sup>2</sup>
- Help ensure the Original HP quality you paid for with anti-fraud and cartridge authentication technology.
- Print right away with a preinstalled toner cartridge. Replace it with an optional high-yield cartridge.<sup>13</sup>



**HP LaserJet Enterprise MFP M527f**

### Stay connected with secure mobile printing options

- Enable 128-bit encrypted wireless direct printing from mobile devices—without accessing the network.<sup>4</sup>
- Print with just a touch of your NFC-enabled mobile device to this printer—no network needed.<sup>6</sup>
- Easily print from a variety of smartphones and tablets—generally no setup or apps required.<sup>7</sup>
- Easily access, print, and share resources with Ethernet and optional wireless networking.<sup>5</sup>



**HP LaserJet Enterprise Flow MFP M527c**



**HP LaserJet Enterprise Flow MFP M527z**

<sup>1</sup> Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print and copy speed completed 8/2015. Subject to device settings. Actual results may vary. For details, see [hp.com/go/Ljclaims](http://hp.com/go/Ljclaims) <sup>2</sup> More pages versus predecessor cartridges claim based on page-yield comparison of HP 55X High Yield Black Original LaserJet Toner Cartridges with HP 87X High Yield Black Original LaserJet Toner Cartridges. For more information, see [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies) <sup>3</sup> Based on HP testing using the ENERGY STAR<sup>®</sup> program's Typical Electricity Consumption (TEC) method or as reported in [energystar.gov](http://energystar.gov) versus the top three leading competitors as of 8/2015. Actual results may vary. For details see [hp.com/go/Ljclaims](http://hp.com/go/Ljclaims) <sup>4</sup> Wireless direct printing is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device needs to be connected directly to the WiFi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Wireless performance is dependent on physical environment and distance from the access point in the MFP or printer. For details, see [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting) <sup>5</sup> Wireless networking requires purchase of the HP Jetdirect 2900nw Print Server. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections. <sup>6</sup> Touch-to-print capability is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device must support Near Field Communication (NFC)-enabled printing. For more information, see [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting) <sup>7</sup> Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting) <sup>8</sup> Purchase of optional paper trays required to reach maximum input capacity. <sup>9</sup> Compared with the HP LaserJet Enterprise MFP M525. <sup>10</sup> Only HP offers a combination of security features for integrity checking down to the BIOS with self-healing capabilities. Some features require additional purchase. A FutureSmart service pack update may be required to activate security features. Learn more at [hp.com/go/printersthatprotect](http://hp.com/go/printersthatprotect) <sup>11</sup> Some solutions require download or additional purchase. Learn more at [hp.com/go/printingsolutions](http://hp.com/go/printingsolutions) <sup>12</sup> Universal device plug-in is offered with HP Web Jetadmin 10.3 SR4 and higher. HP Web Jetadmin is free and available for download at [hp.com/go/webjetadmin](http://hp.com/go/webjetadmin) <sup>13</sup> HP 87X High Yield Black Original LaserJet Toner Cartridges not included; please purchase separately.

## Product walkaround

1. 100-sheet automatic document feeder (ADF) with single-pass, two-sided scanning and HP EveryPage
2. Hardware Integration Pocket (HIP) for connecting accessory and third-party devices
3. Built-in wireless direct<sup>3</sup> and NFC touch-to-print<sup>4</sup>
4. Easy-access USB port to save and print files directly<sup>2</sup>
5. 250-sheet output tray
6. Top cover (access to Original HP Toner cartridges with JetIntelligence)
7. 100-sheet multipurpose tray
8. 550-sheet tray 2
9. Intuitive 8-inch (20.3 cm) touchscreen control panel
10. Pull-out keyboard for easy, accurate data entry
11. Convenience stapler
12. Convenient front on/off button
13. Built-in automatic duplexer
14. 800 MHz processor, 1.5 GB RAM<sup>5</sup>
15. HP High-Performance Secure Hard Disk
16. Slot for optional cable-type security lock
17. Fax port
18. HP Jetdirect Gigabit Ethernet print server
19. Hi-Speed USB 2.0 printing port
20. Hi-Speed USB 2.0 port (for connecting third party devices)
21. Rear door (access to the print path)



## Series at a glance



Model	HP LaserJet Enterprise MFP M527dn	HP LaserJet Enterprise MFP M527f	HP LaserJet Enterprise Flow MFP M527c	HP LaserJet Enterprise Flow MFP M527z
<b>Product number</b>	F2A76A	F2A77A	F2A81A	F2A78A
<b>Fax</b>	Optional	✓	✓	✓
<b>HP High-Performance Secure Hard Disk</b>	Optional	✓	✓	✓
<b>100-page ADF with single-pass, two sided scanning</b>	✓	✓	✓ (Plus HP EveryPage)	✓ (Plus HP EveryPage)
<b>Advanced workflow capabilities including pull-out keyboard</b>	Not available	Not available	✓	✓
<b>Wireless direct<sup>3</sup> and NFC touch to print<sup>4</sup></b>	Optional	Optional	Optional	✓
<b>ENERGY STAR<sup>®</sup> and Blue Angel certified</b>	✓	✓	✓	✓

<sup>1</sup>Solutions deployed through the Hardware Integration Pocket may require additional purchase. <sup>2</sup>An administrator must enable the easy-access USB port before use. <sup>3</sup>Wireless direct printing is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device needs to be connected directly to the Wi-Fi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Wireless performance is dependent on physical environment and distance from the access point in the MFP or printer. For details, see [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting). <sup>4</sup>Touch-to-print capability is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device must support Near Field Communication (NFC)-enabled printing. For more information, see [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting). <sup>5</sup>Maximum memory can be expanded to 2 GB (System memory) by replacing standard memory module. 2 GB Memory DIMM Kit (B3G84-67909) can be purchased separately. Please visit [hp.com/buy/parts](http://hp.com/buy/parts) for purchase options.

## HP Services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs. HP Care Pack Services provide a comprehensive suite of protection services designed to keep HP hardware and software up and running so employees can stay productive.

### Next Business Day with Defective Media Retention:

Customers can retain their hard disk drive and keep control of sensitive data.

### Same Day – 4 hour 9x5 and 13x5:

Sends an HP technician to customers' site the same business day for repair, within 4 hours, if the issue cannot be resolved through remote support. Various support window times are available, for different requirements.

For carepack availability visit: [hp.com/go/cpc](http://hp.com/go/cpc)



## Top features

Work quickly with the fastest first page out from sleep mode—on the most energy-efficient MFP in its class.<sup>13</sup> Launch two-sided printing, scan, and fax right from the touchscreen. Reload paper less often with a 2300-sheet maximum capacity.<sup>8</sup>

Trust your MFP is secure from power-up to power-down. Get strong protection for devices, data, and documents with embedded and optional security features while centrally managing your entire fleet.<sup>10</sup>

Bring out the best in your MFP. Print more high-quality pages than ever before,<sup>2</sup> using specially designed Original HP Toner cartridges with JetIntelligence. Count on the authentic HP quality you paid for—something the competition can't match.

Enable secure wireless printing in the office—with or without network access<sup>4</sup>—and keep users connected with Ethernet and optional wireless networking. Print with just a touch from mobile devices.<sup>5</sup>

---

### Accessories

F2A72A - HP LaserJet 500-sheet Paper Tray  
 F2A73A - HP LaserJet Printer Cabinet  
 E5K48A - HP 1GB DDR3x32 144-pin 800MHz SODIMM  
 B5L29A - HP Secure High Performance Disk Drive<sup>11</sup>  
 B5L53A - HP LaserJet MFP Analog Fax Accessory 600<sup>11</sup>  
 F2A87A - HP Internal USB Ports for M506/M527  
 J8031A - HP JetDirect 2900nw Print Server  
 J8030A HP JetDirect 3000w NFC/Wireless Accessory<sup>12</sup>  
 F5S62A - HP Trusted Platform Module Accessory  
 CZ208A - HP Common Card Reader  
 B5L31A - HP Foreign Interface Harness  
 A7W12A - HP LaserJet Keyboard Overlay Kit for Simplified Chinese & Traditional Chinese<sup>13</sup>  
 A7W14A - HP LaserJet Keyboard Overlay Kit Swedish<sup>13</sup>

---

### Supplies

CF287A - HP 87A LaserJet Toner Cartridge, black  
 CF287X - HP 87X LaserJet Toner Cartridge, black  
 Q7732A - HP Staple Cartridge Refill  
 B5L52A - HP 200 ADF Roller Replacement Kit

---

### Services

#### HP LaserJet Enterprise Flow MFP M527 series

U8TT5E - HP 3 year Next Business Day + DMR LaserJet M527 MultiFunction Hardware Support  
 U8TT6E - HP 4 year Next Business Day + DMR LaserJet M527 MultiFunction Hardware Support  
 U8TT7E - HP 5 year Next Business Day + DMR LaserJet M527 MultiFunction Hardware Support  
 U8TT8E - HP 3 year 4 hour 9X5 + DMR LaserJet M527 MultiFunction Hardware Support  
 U2010E - HP Network Installation mid-range LaserJet Multifunction printer Service

---

<sup>1</sup> Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print and copy speed completed 8/2015. Subject to device settings. Actual results may vary. For details, see [hp.com/go/ljclaims](http://hp.com/go/ljclaims) <sup>2</sup> More pages versus predecessor cartridges claim based on page-yield comparison of HP 55X High Yield Black Original LaserJet Toner Cartridges with HP 87X High Yield Black Original LaserJet Toner Cartridges. For more information, see [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies) <sup>3</sup> Based on HP testing using the ENERGY STAR® program's Typical Electricity Consumption (TEC) method or as reported in [energystar.gov](http://energystar.gov) versus the top three leading competitors as of 8/2015. Actual results may vary. For details see [hp.com/go/ljclaims](http://hp.com/go/ljclaims) <sup>4</sup> Wireless direct printing is standard on the HP LaserJet Enterprise Flow MFP M527z only. Requires purchase of optional HP Jetdirect 3000w NFC/Wireless Direct Accessory for the HP LaserJet Enterprise MFP M527dn/f/c. Mobile device needs to be connected directly to the WiFi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Wireless performance is dependent on physical environment and distance from the access point in the MFP or printer. For details, see [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting) <sup>5</sup> Wireless networking requires purchase of the HP Jetdirect 2900nw Print Server. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections. <sup>8</sup> Purchase of optional paper trays required to reach maximum input capacity. <sup>10</sup> Some features require additional purchase. Learn more at [hp.com/go/printsecurity](http://hp.com/go/printsecurity) <sup>11</sup> M527dn bundle only. <sup>12</sup> M527z bundle only. <sup>13</sup> M527c and M527z bundles only

# HP LaserJet Enterprise MFP M527 series

Technical Specifications	HP LaserJet Enterprise MFP M527dn(F2A76A)	HP LaserJet Enterprise MFP M527(F2A77A)	HP LaserJet Enterprise Flow MFP M527(F2A81A)	HP LaserJet Enterprise Flow MFP M527z(F2A78A)
<b>AIO functions</b>	Print, copy, scan; <b>AIO multitasking supported:</b> Yes		Print, copy, scan, fax; <b>AIO multitasking supported:</b> Yes	
<b>Print speed</b>	<b>Letter:</b> Up to 45 ppm black; <sup>15</sup> ; <b>First Page Out Black:</b> As fast as 5.7 sec.; As fast as 11.2 sec (100 V); <sup>17</sup>		<b>Letter:</b> Up to 45 ppm black; <sup>15</sup> ; <b>First Page Out Black:</b> As fast as 5.9 sec.; As fast as 11.3 sec (100 V); <sup>17</sup>	
<b>Print resolution</b>	<b>Black (best):</b> Up to 1200 x 1200 dpi			
<b>Print Technology</b>	Laser; <b>Print Resolution Technologies:</b> 300 dpi, 600 dpi, HP FastRes 1200, HP ProRes 1200			
<b>Standard Print Languages</b>	HP PCL 6, HP PCL 5 (HP PCL 5 driver available from the Web only), HP postscript level 3 emulation, native PDF printing (v 1.7)			
<b>Printer Smart Software Features</b>	Print preview, duplex printing, print multiple pages per sheet (2, 4, 6, 9, 16), collation, watermarks, store print jobs, easy-access USB			
<b>Printer Management</b>	UPD Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP Web JetAdmin Software; HP Proxy Agent Software; HP JetAdvantage Security Manager			
<b>Scan Type / Technology</b>	<b>Type:</b> Flatbed, ADF (two-sided, single-pass); <b>Technology:</b> CIS (Contact Image Sensor)			
<b>Scan Resolution</b>	<b>Hardware:</b> Up to 600 x 600 dpi; <b>Optical:</b> Up to 600 dpi			
<b>Scan File Format</b>	<b>M527c &amp; M527fz:</b> Digital Send: PDF, JPEG, TIFF, MTIFF, XPS, PDF/A, TEXT (OCR), Unicode TEXT (OCR), RTF (OCR), Searchable PDF (OCR), Searchable PDF/A (OCR), HTML (OCR), CSV (OCR); Scan to easy access USB: PDF, JPEG, TIFF, MTIFF, XPS, PDF/A, TEXT (OCR), Unicode TEXT (OCR), RTF (OCR), Searchable PDF (OCR), Searchable PDF/A (OCR), HTML (OCR), CSV (OCR); Print from easy access USB: PDF, PS, Print Ready files (.prn, .pcl, .cht)			
<b>Scan Input Modes</b>	Front panel applications: Copy, E-mail, Save to Network Folder, Save to USB, Save to Device Memory, Open Extensibility Platform (OXF) applications			
<b>Scan Size</b>	<b>ADF:</b> 8.5 x 14 in Maximum; 4 x 6 in Minimum; <b>Flatbed:</b> 8.5 x 14 in			
<b>Scan Speed</b>	Up to 45 ppm/45 ipm (b&w), up to 40 ppm/40 ipm (color) <sup>15</sup> ; <b>Duplex:</b> Up to 45 ipm (color)		Up to 48 ppm/68 ipm (b&w), up to 48 ppm/60 ipm (color) <sup>15</sup> ; <b>Duplex:</b> Up to 68 ipm (b&w), up to 60 ipm (color)	
<b>Scanner Advanced Features</b>	Optimize text/picture; Image adjustments; Job build; Output quality setting; Selectable scan resolution 75 to 600 dpi; Auto detect color; Edge Erase; Job notification; Blank page suppression; HP Quick Sets		Optimize text/picture; Image adjustments; Job build; Output quality setting; Selectable scan resolution 75 to 600 dpi; Auto detect color; Edge Erase; Job notification; Blank page suppression; HP Quick Sets; HP EveryPage; Auto orientation; Embedded Optical Character Recognition (OCR), Auto crop to page; Auto-tone	
<b>Bit depth / Grayscale levels</b>	24-bit / 256			
<b>Digital Sending Standard Features</b>	Scan to E-mail; Save-to-Network Folder; Save-to-USB drive; Send to Sharepoint (M527c & M527z only); Send to FTP (M527c & M527z only); Send to LAN Fax (M527f, M527c & M527z only); Send to Internet Fax (M527f, M527c & M527z only); OCR (M527c & M527z only); Local Address Book; SMTP over SSL; Blank Page Removal; Edge Erase; Auto Color Sense; Auto Crop To Content; Compact PDF; Auto Tonescale (M527c & M527z only); Auto Orientation (M527c & M527z only); Multi-Pick Detect (M527c & M527z only); Auto Straighten (M527c & M527z only); Auto Crop To Page (M527c & M527z only);			
<b>Copy Speed</b>	<b>Black (letter):</b> Up to 45 cpm; <sup>18</sup>			
<b>Copy Resolution</b>	<b>Black (text and Graphics):</b> Up to 600 x 600 dpi (flatbed), 600 x 450 dpi (ADF); <b>Color (text and Graphics):</b> Up to 600 x 600 dpi (flatbed), 300 x 600 dpi (ADF)			
<b>Copier Settings</b>	Two-sided copying; scalability; image adjustments (darkness, contrast, background cleanup, sharpness); N-up; N or Z-ordering; content orientation; collation; booklet; job build; edge-to-edge job storage; ID Copy; Book Copy; A-to-B Copy (different media sizes)			
<b>Fax Speed</b>	<b>Up to:</b> 33.6 kbps; <b>Letter:</b> 3 sec per page <sup>14</sup>			
<b>Fax Resolution</b>	<b>Black (best):</b> Up to 300 x 300 dpi (400 x 400 dpi for received faxes only); <b>Black (standard):</b> 203 x 98 dpi			
<b>Fax Smart Software Features</b>	Stored faxes; Fax archiving; Fax forwarding; Scale to fit; Fax address book; LAN/Internet fax; Fax number confirmation; Holiday fax schedule			
<b>Fax Features</b>	<b>Fax Memory:</b> Up to 500 pages; <b>Auto Fax Reduction Supported:</b> Yes; <b>Auto-Redialing:</b> Yes; <b>Fax Delayed Sending:</b> No; <b>Fax Forwarding Supported:</b> Yes; <b>Fax Telephone Mode Supported:</b> No; <b>Junk Barrier Supported:</b> Yes; <b>PC Interface Supported:</b> Yes; <b>Telephone Handset Supported:</b> No			
<b>Standard Connectivity</b>	2 Hi-Speed USB 2.0 Host; 1 Hi-Speed USB 2.0 Device; 1 Gigabit Ethernet 10/100/1000T network; 1 Fax (M527f, M527c & M527z only), Wireless Direct 802.11 b/g/n (M527z only), NFC (M527z only).			
<b>Network Capabilities</b>	IPv4/IPv6; Apple Bonjour Compatible (Mac OS v10.2.4 or higher), SNMPv1/v2c/v3, HTTP, HTTPS, FTP, TFTP, Port 9100, LPD, WS Discovery, IPP, Secure-IPP, XMPR, IPsec/Firewall; IPv6: DHCPv6, MLDv1, ICMPv6; IPv4: Auto-IP, SLIP, Telnet, IGMPv2, BOOTP/DHCP, WINS, IP Direct Mode, WS Print			
<b>Network Ready</b>	Standard (built-in Gigabit Ethernet)			
<b>Wireless Capability</b>	Optional, enabled with purchase of HW accessories.	No	Yes, integrated NFC/HP Wireless Direct	
<b>Mobile Printing Capability</b>	HP ePrint; Apple AirPrint™; Mopria-certified <sup>12</sup> ; Wireless Direct Printing (M527z only); NFC touch-to-print <sup>13</sup> (M527z only)			
<b>Memory</b>	<b>Standard:</b> 1.25 GB (Printer), 500 MB (Scanner); <b>Maximum:</b> 2.0 GB (Printer), 500 MB (Scanner)			
<b>Processor Speed</b>	1.2 GHz	1.2 GHz Z; <b>Hard disk:</b> Standard, embedded HP High-Performance Secure Hard Disk, minimum 320 GB; AES 128 hardware encryption or greater; Secure erase capabilities (Secure Erase-Temporary Job Files, Secure Erase-Job Data, Secure ATA Erase-Disk); U.S. Government: Standard, FIPS 140-2 validated hard disk, minimum 500 GB		
<b>Duty Cycle</b>	<b>Monthly, letter:</b> Up to 150,000 pages <sup>9</sup> ; <b>Recommended Monthly Page Volume:</b> 2000 to 7500			
<b>Paper Handling</b>	<b>Input Capacities:</b> 1 x 550-sheet input tray; 1 x 100-sheet multipurpose tray; 3 x optional additional 550-sheet input trays; Up to 650 sheets standard; Up to 10 envelopes labels legal; <b>Output Capacities:</b> 250-sheet output bin; Up to 250 sheets standard labels legal; <b>Duplex Options:</b> Automatic (standard) <b>Auto Document Feeder Capacity:</b> Standard, 100 sheets; <b>Envelope Feeder:</b> No; <b>Standard Paper Trays:</b> 2; <b>Media Types Supported:</b> Paper (bond, color, letterhead, plain, preprinted, prepunched, recycled, rough); envelopes; labels; cardstock; transparencies; user-defined; <b>Media Weight Supported:</b> Tray 1: 16 to 53 lb; Tray 2+: 16 to 32 lb; <b>Media Sizes Supported:</b> Tray 1: Letter, legal, executive, 4 x 6, 5 x 8, 8.5 x 13, envelopes (No. 10, Monarch); Tray 2: letter, legal, executive, 8.5 x 13; Optional trays 3+: letter, legal, executive, 8.5 x 13; Optional Automatic Duplexer: letter; <b>Media Sizes Custom:</b> Tray 1: 3 x 5 to 8.5 x 14 in; 550-sheet input Tray 2: 4.1 x 5.8 to 8.5 x 14 in; optional 550-sheet input Tray 3+: 4.1 x 5.8 to 8.5 x 14 in			
<b>Product Dimensions</b>	<b>W x D x H:</b> 18.98 x 19.52 x 19.55 in; <b>Maximum:</b> 19.96 x 24.83 x 19.55 in			
<b>Product Weight</b>	48.2 lb <sup>1</sup>	48.5 lb <sup>1</sup>	48.6 lb <sup>1</sup>	49.1 lb <sup>1</sup>
<b>What's in the box</b>	HP LaserJet M527 Printer; HP 87A Black Original LaserJet Toner (~ 9000 pages); CDs containing software and electronic documentation; User Guide; Support Flyers; Warranty Cards; Required Erratas			
<b>Warranty Features</b>	One-year, next-business day, onsite warranty. Warranty and support options vary by product, country and local legal requirements.			
<b>Energy Efficiency Compliance</b>	ENERGY STAR® certified; Blue Angel; CECP; EPEAT®			
<b>Control Panel</b>	8.0-in (20.3 cm) color LCD with touchscreen; rotating (adjustable angle) display; illuminated Home button (for quick return to the Home menu)		8.0-in (20.3 cm) color LCD with touchscreen; rotating (adjustable angle) display; illuminated Home button (for quick return to the Home menu); Integrated Keyboard	
<b>Display Description</b>	8.0" (20.3 cm) touchscreen, SVGA LCD (color graphics), smooth gesture enabled touchscreen			
<b>Software Included</b>	For Windows OS: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Send Fax, HP Update, Product Registration Assist, HP Web Services Assist (HP Connected), Online user manuals; For Mac OS: Welcome Screen. (Directs users to HP.com or OS App Store for LaserJet Software)			
<b>Fonts and Typefaces</b>	105 internal TrueType fonts scalable in HP PCL, 92 internal scalable fonts in HP postscript Level 3 emulation (Euro symbol built-in); 1 internal Unicode Fonts (Andale Mono World Type); 2 Internal Windows Vista 8 Fonts (Calibri, Cambria); additional font solutions available via third-party flash memory cards; HP LaserJet Fonts and IPDS Emulation available at <a href="http://www.hp.com/go/laserjetfonts">http://www.hp.com/go/laserjetfonts</a>			
<b>Compatible Operating Systems</b>	Go to <a href="http://hp.com/search">hp.com/search</a> for Hp LaserJet Enterprise MFP M527 Printer for all operating systems			
<b>Compatible Network Operating Systems</b>	Go to <a href="http://hp.com/search">hp.com/search</a> for Hp LaserJet Enterprise MFP M527 Printer for all operating systems			
<b>Minimum System Requirements</b>	<b>PC:</b> Windows XP SP3 all 32-bit editions (XP Home, XP Pro, etc.); Windows Vista all 32-bit editions (Home Basic, Premium, Professional, etc.); Windows 7 all 32- & 64-bit editions; Windows 8/8.1 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows 10 all 32- & 64-bit editions (excluding RT OS for Tablets); CD-ROM or DVD drive, or Internet connection; Dedicated USB or network connection or Wireless connection; 200 MB available hard disk space; OS compatible hardware (For OS hardware requirements see <a href="http://www.microsoft.com">http://www.microsoft.com</a> ); <b>MAC:</b> Mac OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite; Internet; USB; 1 GB HD; OS compatible hardware (For OS hardware requirements see <a href="http://www.apple.com">http://www.apple.com</a> )			
<b>Power</b>	<b>Power Supply Type:</b> Internal (Built-in) power supply; <b>Power Requirements:</b> Input Voltage: 100 to 127 VAC, 50/60 Hz, 7.5 A (+/- 10%); Input Voltage: 220 to 240 VAC, 50/60 Hz, 4.0 A (+/- 10%) (Not dual voltage, input voltage requirement and supplied power cord varies by part number and option code identifier); <b>Power Consumption:</b> 671 watts (Printing), 27.8 watts (Ready), 3.2 watts (Sleep), 0.71 watts (Auto-Off/Auto-On), LAN connection: 0.06 watts (Auto-Off), 0.06 watts (Off) <sup>7</sup>			
<b>Acoustics</b>	<b>Acoustic Power Emissions:</b> 6.8 B(A); <b>Acoustic Pressure Emissions:</b> 54 dB(A) <sup>7</sup>			
<b>Operating Environment</b>	<b>Operating Temperature Range:</b> 59 to 90.5°F; <b>Recommended Operating Temperature:</b> 63.5 to 77°F; <b>Storage Temperature Range:</b> -4 to 140°F; <b>Non-Operating Humidity Range:</b> 10 to 90% RH; <b>Operating Humidity Range:</b> 10 to 80% RH; <b>Recommended Humidity Operating Range:</b> 30 to 70% RH			
<b>Security Management</b>	Management security: SNMPv3, SSL/TLS, WPA2-Enterprise, 802.1X authentication (EAP-PEAP, EAP-TLS), IPP over TLS, IPsec/Firewall with Certificate, Pre-Shared Key Authentication, and Kerberos Authentication; Support for WJA-10 IPsec Configuration using IPsec Plug-in			

<sup>1</sup> Includes size A toner cartridge. <sup>2</sup> AirPrint™ and iOS 4.2 or later devices require an 802.11 wireless network connection to the printer. Wireless performance is dependent upon physical environment and distance from the access point. AirPrint and the AirPrint Logo are trademarks of Apple® Inc. Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting) <sup>3</sup>Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115 V device. <sup>4</sup> Based on the BA TEC method with the following possible exceptions: 1 minute or less sleep delay setting, Wi-Fi disabled. <sup>5</sup> Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies) <sup>6</sup> HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. Only available with Original HP supplies; Internet access required. To learn more, visit [hp.com/go/SureSupply](http://hp.com/go/SureSupply) <sup>7</sup> Acoustic values are subject to change. For current information see [hp.com/support](http://hp.com/support) <sup>8</sup> Maximum memory is with 1 GB DIMM installed. The maximum the FW can use is 2GB so 250 MB is unused in this configuration. <sup>9</sup> Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPS to satisfy the demands of connected individuals or groups. <sup>10</sup> HP recommends that the number of scanned pages per month be within the stated range for optimum device performance. <sup>11</sup> Not all "Compatible Operating Systems" are supported with inbox software; Full solution software available only for Windows 7 and newer; Legacy Windows Operating Systems (XP, Vista, and equivalent servers) get print and Scan drivers only; Windows RT OS for Tablets (32- & 64-bit) uses a simplified HP printer driver built into the RT OS; UNIX modelscripts are available on HP.com (Modelscripts are printer drivers for UNIX operating systems); Linux systems use in-OS HPLIP software. <sup>12</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see [hp.com/go/printerclaims](http://hp.com/go/printerclaims). Exact speed varies depending on the system configuration, software application, driver, and document complexity.

## Learn more at [hp.com](http://hp.com)

© Copyright 2015 - 2016 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Windows is a registered trademark of Microsoft Corporation. AirPrint, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.

