

# Xerox® VersaLink® B400 Printer

VersaLink B400 Printers are built on Xerox® ConnectKey® Technology.  
For more information, go to [www.ConnectKey.com](http://www.ConnectKey.com).



SYSTEM SPECIFICATIONS	VERSALINK B400/DN
<b>One-sided Speed<sup>1</sup></b> A4 / 210 x 297 mm 216 x 356 mm	Up to 45 ppm black and white Up to 38 ppm black and white
<b>Two-sided Speed<sup>1</sup></b> A4 / 210 x 297 mm 216 x 356 mm	Up to 28 ppm black and white Up to 25 ppm black and white
<b>Monthly Duty Cycle<sup>2</sup></b>	Up to 150,000 pages / month
<b>Recommended Average Monthly Print Volume<sup>3</sup></b>	Up to 15,000 pages
<b>Processor</b>	1.05 GHz Dual Core
<b>Memory</b>	2 GB
<b>Connectivity</b>	Ethernet 10/100/1000 Base-T, High-speed USB 3.0, Wi-Fi 802.11n and Wi-Fi Direct with optional Wi-Fi Kit (concurrent wired and wireless connections supported), NFC Tap-to-Pair
<b>Controller Features</b>	Configuration Cloning, Xerox Extensible Interface Platform®, Xerox App Gallery, Xerox® Standard Accounting Tool, Network Accounting Enabled, Role Based Permissions, Convenience Authentication Enabled, Online Support (accessed from the user interface and print driver)
<b>User Interface Languages</b>	English, French, Italian, German, Spanish, Brazilian Portuguese, Russian, Dutch, Swedish, Danish, Finnish, Norwegian, Greek, Turkish, Polish, Czech, Hungarian, Romanian, Catalan, Ukrainian, Croatian

# Xerox® VersaLink® B400 Printer

DEVICE SPECIFICATIONS				
<b>ELECTRICAL REQUIREMENTS</b>				
North America	Voltage: 110-127 VAC Frequency: 50/60 Hz 11 A			
Europe and Other Geographies	Voltage: 220-240 VAC Frequency: 50/60 Hz 6 A			
<b>POWER CONSUMPTION</b>				
Continuous Printing <sup>4</sup>	565 watts or less			
Ready (Standby) <sup>4</sup>	46 watts or less			
Energy Saver (Sleep Mode) <sup>4</sup>	4 watts or less			
<b>OPERATING ENVIRONMENT</b>				
Required Temperature Range (Storage)	0 to 35° C			
Required Temperature Range (Operating)	10 to 32° C			
Required Relative Humidity	10% to 85%			
Sound Power Levels Operating Standby	7.5 B(A) or less 5.3 B(A) or less			
Sound Pressure Levels Operating Standby	56 dB(a) or less 30 dB(a) or less			
Boot Time (from Off to UI Ready)	As fast as 60 seconds			
Warm-Up Time (from Sleep to UI Ready)	As fast as 5 seconds			
<b>DIMENSIONS AND WEIGHT (UNPACKAGED)</b>	<b>WIDTH</b>	<b>DEPTH</b>	<b>HEIGHT</b>	<b>WEIGHT</b>
VersaLink B400/DN	459 mm	426 mm	339 mm	14 kg
550-sheet Paper Tray	393 mm	393 mm	94 mm	3.2 kg
<b>DIMENSIONS AND WEIGHT (PACKAGED)</b>	<b>WIDTH</b>	<b>DEPTH</b>	<b>HEIGHT</b>	<b>WEIGHT</b>
VersaLink B400/DN	540 mm	588 mm	480 mm	17.35 kg
550-sheet Paper Tray	498 mm	504 mm	234 mm	4.4 kg
<b>SYSTEM CERTIFICATION/REGULATORY COMPLIANCE</b>				
Certifications	To view the latest list of certifications, go to <a href="http://www.xerox.com/OfficeCertifications">www.xerox.com/OfficeCertifications</a> .			
<b>PRINT</b>				
First-print-out Time	As fast as 8 seconds			
Print Resolution	Up to 1200 x 1200 dpi (enhanced)			
Page Description Languages	PCL® 5e, 6 PDF XPS	TIFF JPEG	HP-GL Adobe® PostScript® 3™	
Maximum Print Area	4 mm from edge of paper			

# Xerox® VersaLink® B400 Printer

<b>Print Features</b>	<ul style="list-style-type: none"> <li>Application Defaults</li> <li>Banner Pages Enable / Disable</li> <li>Bi-directional Real-time Status</li> <li>Booklet Layout</li> <li>Draft Mode</li> <li>Fit to new paper size</li> <li>Job Identification (Print ID or Banner, Print ID in margins on first page only or all pages)</li> <li>Job Monitoring (Client or Local User Interface)</li> <li>N-up Page Layout (up to 16 pages per sheet)</li> <li>Paper Selection by Attribute</li> <li>Personal Print</li> <li>Print Around Enable / Disable</li> <li>Print from USB</li> <li>Sample Set</li> <li>Saved Job</li> <li>Scaling</li> <li>Secure Print</li> <li>Skip Blank Pages</li> <li>Special Pages (exception page programming: covers, inserts, exceptions pages)</li> <li>Store and Recall Driver Settings</li> <li>Stored Jobs Deletion</li> <li>Two-sided Printing (as default – DN configuration)</li> <li>Watermark (predefined and custom)</li> <li>Earth Smart Driver Settings</li> </ul>
<b>Print from USB</b>	<ul style="list-style-type: none"> <li>Allows walk-up printing from Type A USB port</li> <li>Supports direct printing from computer via Type B USB port</li> <li>Supported file formats: PDF, JPEG, TIFF, XPS, PDF/A</li> </ul>
<b>Operating Systems</b>	<ul style="list-style-type: none"> <li>Windows® 7, 8, 8.1, 10</li> <li>Windows Server 2008 SP2, Server 2008 R2 SP1, Server 2012, Server 2012 R2, Server 2016</li> <li>macOS® 10.11, 10.12, 10.13</li> <li>Citrix®</li> <li>Redhat® Enterprise Linux®</li> <li>Fedora Core</li> <li>IBM® AIX®</li> <li>HP-UX®</li> <li>Oracle® Solaris</li> <li>SUSE®</li> <li>SAP®</li> </ul> <p>Note: For information about supported versions for the above operating systems, please visit our Drivers &amp; Downloads page and specify your device at <a href="http://www.support.xerox.com">www.support.xerox.com</a></p>
<b>Fonts</b>	<ul style="list-style-type: none"> <li>PostScript fonts: 136</li> <li>PCL fonts: 83</li> </ul>
<b>Xerox® Global Print Driver®</b>	<p>A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management.</p>
<b>Xerox® Pull Print Driver</b>	<p>Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others.</p>

# Xerox® VersaLink® B400 Printer

SOFTWARE SOLUTIONS	
<b>Xerox® ConnectKey Apps (Found at the Xerox App Gallery)</b>	Increase user productivity by simplifying and shortening everyday tasks. Unlike traditional software, ConnectKey Apps do not require a dedicated server, PC or IT resource. Instead, simply download these lightweight, serverless ConnectKey Apps to the ConnectKey-enabled device.
MOBILE SOLUTIONS AND MOBILE DEVICE APPS	
<b>Apple® AirPrint®</b>	Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.
<b>Google Cloud Print™</b>	Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.
<b>Mopria® Certified</b>	ConnectKey Technology-enabled MFPs are Mopria® certified. Mopria® certification ensures you can print wirelessly from your Mopria® supported (Android) smart phone, tablet and other mobile devices instantly and easily.
<b>Xerox® @printbyXerox App</b>	@printbyXerox App is a free service that allows secure printing from any email-enabled device (computer, phone, tablet, iOS, Android™, Google® Chromebook™ and more) to a Xerox® printer or MFP using a single email address with no IT intervention. No training is needed. End-users simply send attachments to the email address, and release them at the MFP panel.
<b>Xerox® Print Service Plug-in for Android™ (Free at Google Play™ Store)</b>	The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to multifunction printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.
<b>Xerox® Workplace Suite and Xerox® Workplace Cloud</b>	Xerox® Workplace Suite is a modular set of workflows designed to save customers time and money by providing effective control over their print fleet, while enabling worker productivity and mobility through a set of robust workflows. Xerox enables ultimate customer flexibility by offering these capabilities in both an on-premises server version (Workplace Suite) and with a cloud-based version (Workplace Cloud) of this solution.
SECURITY	
<b>Security Features</b>	<ul style="list-style-type: none"> <li>Access Controls</li> <li>AES 256-bit Encryption</li> <li>Audit Log</li> <li>Certificate Path Validation</li> <li>Certificate Revocation List (CRL)/Status Protocol (OCSP)</li> <li>Detection of external program falsification (XCP Plug-in)</li> <li>Cisco® Identity Services Engine (ISE) Integration</li> <li>Domain Filtering</li> <li>FIPS 140-2</li> <li>Firmware Verification</li> <li>IP Address Filtering</li> <li>IPsec</li> <li>Network Authentication</li> <li>Port Filtering</li> <li>Pre-installed Self-Signed Certificates</li> <li>Role Based Permissions</li> <li>Secure Print</li> <li>Security Certificate Management</li> <li>Smart Card Enablement (CAC/PIV/.NET)</li> <li>SNMPv3</li> <li>Status Protocol (OCSP)</li> <li>TLS/SSL</li> <li>Trusted Platform Module (TPM)</li> </ul>

ACCOUNTING			
<b>XEROX® STANDARD ACCOUNTING TOOL / NETWORK ACCOUNTING (STANDARD)</b>			
<b>Tracking</b>	Print usage		
<b>Accounting</b>	Xerox® Standard Accounting Tool Up to 1,000 User Accounts without SSD Up to 9,999 User Accounts with SSD Up to 500 General accounts  Network Accounting (Job Based Accounting) Up to 1,000 User IDs; Up to 1,000 Account IDs without SSD Up to 60,000 User IDs; Up to 60,000 Account IDs with SSD Up to 14,000 accounting records (transactions)		
<b>Features</b>	Administrator can manage the feature via the Embedded Web Server.		
<b>ACCOUNTING OPTIONS – NETWORK ACCOUNTING (ALLOWS CENTRAL SERVER TO MANAGE ALL ACCOUNTING)</b>			
	<ul style="list-style-type: none"> <li>Enhanced network accounting with up to the minute data on how the system is being used</li> <li>Comprehensive management and enterprise scale tracking and reporting of print usage</li> <li>Numerous solutions are available through Xerox Alliance Partners. For details visit <a href="http://www.xerox.com">www.xerox.com</a></li> <li>Security enhancements include simultaneous support for HTTP/HTTPS protocols</li> <li>Device requests account authentication from third party server enabling larger databases of users and accounts</li> <li>Accept Authentication Login at control panel and pass to third party Networking Account</li> <li>Interface with third party accounting terminal for accounting user interface</li> </ul>		
PAPER HANDLING			
<b>BYPASS TRAY</b>			
<b>Capacity<sup>5</sup></b>	150 sheets		
<b>Sizes</b>	Custom sizes: 76.2 x 127 mm to 216 x 356 mm		
<b>Weights</b> One sided: Two-sided:	60 to 220 gsm 60 to 163 gsm		
<b>Media Types</b>	Bond Plain Paper Cardstock Custom	Envelopes Hole Punched Labels Letterhead	Lightweight Cardstock Pre-Printed Recycled
<b>TRAY 1</b>			
<b>Capacity<sup>5</sup></b>	550 sheets		
<b>Sizes</b>	Custom Sizes: 76.2 x 127 mm to 216 x 356 mm		
<b>Weights</b> One sided: Two-sided:	60 to 220 gsm 60 to 163 gsm		
<b>Media Types</b>	Bond Plain Paper Cardstock Custom	Hole Punched Labels Letterhead	Lightweight Cardstock Pre-Printed Recycled
<b>OPTIONAL TRAY 2</b>			
<b>Capacity<sup>5</sup></b>	550 sheets		
<b>Sizes</b>	Custom sizes: 139.7 x 210 mm to 216 x 356 mm		
<b>Weights</b> One sided: Two-sided:	60 to 220 gsm 60 to 163 gsm		

# Xerox® VersaLink® B400 Printer

<b>Media Types</b>	Bond Plain Paper Cardstock Custom	Hole Punched Labels Letterhead	Lightweight Cardstock Pre-Printed Recycled
<b>TOTAL CAPACITY<sup>5</sup></b>			
<b>Device Standard Capacity<sup>5</sup></b>	700 sheets		
<b>Device Total Capacity<sup>5</sup></b>	2,350 sheets		
<b>PAPER OUTPUT</b>			
<b>Output Capacity<sup>5</sup></b>	250 sheets		
<b>Automatic Two-sided Printing</b>	Standard		
<b>DEVICE MANAGEMENT</b>			
<b>Network Protocols</b>	TCP/IP: HTTP/HTTPS, Internet Printing Protocol, LPR/LPD, Raw Socket Printing/Port 9100, IPv4/IPv6, WSD LDAP Bonjour® / AirPrint® Most protocols not in use can be disabled		
<b>Administrative Protocols</b>	DHCP, SNMP, WINS, HTTP, HTTPS, TLS, SNTP, MDNS		
<b>REMOTE CONTROL PANEL</b>			
	<ul style="list-style-type: none"> <li>• Enables faster, more convenient technical support and user training</li> <li>• IT administrators and other authorized users can control the device remotely from a web page</li> <li>• Remote user experience is identical to performing tasks directly at the device</li> </ul>		
<b>XEROX® CENTREWARE® WEB</b>			
	<ul style="list-style-type: none"> <li>• A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system</li> <li>• Works with any SNMP-managed printer from any manufacturer</li> <li>• Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management</li> </ul>		
<b>EMBEDDED WEB SERVER – INTEGRATED DEVICE WEB PAGE</b>			
<b>Device Status</b>	<ul style="list-style-type: none"> <li>• Tray status/contents</li> <li>• Consumables status</li> <li>• Billing / Usage</li> <li>• Quick Links</li> <li>• Online Support</li> </ul>		
<b>Print Queue Viewing</b>	Job print queue management—view and delete		
<b>Job Submission</b>	Print-ready files (PS, PCL, PDF, XPS, JPEG)		
<b>Device Administration</b>	Allows simple, remote installation setting of configuration options and management of the device		
<b>Browsers</b>	Microsoft® Internet Explorer® Microsoft Edge™ Mozilla™ Firefox® Apple® Safari® Google Chrome™		

# Xerox® VersaLink® B400 Printer

REMOTE SERVICES		
<b>Automated Meter Reading (AMR)</b>	Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time.	
<b>Automated Supplies Replenishment (ASR)</b>	Automatically orders supplies for Xerox® output devices based on actual usage, eliminating the need to manually manage supplies inventory.	
WHAT COMES IN THE BOX		
	VersaLink B400 Printer Standard Capacity Toner Cartridge: 5,900 print capacity <sup>6</sup> Software and Documentation CD (Safety, Regulatory, Recycling and Disposal Guides, Print Drivers, and Warranty Statement) Installation Guide Quick Use Guides Power cord	
SUPPLIES AND ACCESSORIES	QUANTITY	PART NUMBER
SUPPLIES		
<b>Standard Capacity Toner Cartridges</b>	5,900 standard pages <sup>6</sup>	106R03580
<b>High Capacity Toner Cartridges</b>	13,900 standard pages <sup>6</sup>	106R03582
<b>Extra-High Capacity Toner Cartridges</b>	24,600 standard pages <sup>6</sup>	106R03584
<b>Drum Cartridge</b>	65,000 standard pages <sup>7</sup>	101R00554
ACCESSORIES / OPTIONS		
<b>550-sheet Paper Tray</b>		497K13620
<b>Productivity Kit with 16 GB Solid State Drive</b>		097S04913
<b>Stand</b>		497K13660
<b>Wireless Network Adapter Kit</b>		497K16750

<sup>1</sup> Declared print speed in accordance with ISO/IEC 24734.

<sup>2</sup> Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

<sup>3</sup> Recommended average throughput is not a minimum, but is intended to cover a range of volumes for different environments.

<sup>4</sup> Power states defined per ENERGY STAR® Program requirements for Imaging Equipment.

<sup>5</sup> Paper capacities are based on 20 lb. / 75 gsm stock; capacities will vary with different weight stocks.

<sup>6</sup> Average standard pages. Declared Yield in accordance with ISO/IEC19752. Yield will vary based on image, area coverage and print mode.

<sup>7</sup> Approximate pages. Declared yield will vary depending on job run length, media size/orientation and machine speed. For more information visit: <http://www.office.xerox.com/latest/SUPGL-01.pdf>.

For more information, visit us at [www.xerox.com/Office](http://www.xerox.com/Office)

Configurations vary by geography.