

DC Power Adapter - 5V, 2A

Product ID: SVA5H2NEUA



This replacement power adapter can provide a power source for any electronic device that has an H type barrel jack and requires 5 volts and up to 2 amps of power.

Replace your failed or lost power adapter

The adapter is a perfect replacement for the lost or damaged power adapter you've used to power your existing electronics.

Keep a spare power adapter on hand

When downtime isn't an option, keeping spare power adapters on hand ensures that you won't be left waiting for a replacement to arrive or have to replace your devices just for the sake of a compatible power source.

This power adapter is a direct replacement for the power adapters included with the following StarTech.com products:

[Dual-Bay 2.5in Hard Drive Enclosure \(S252BU33R\)](#)

[3-Port Portable USB 3.0 Hub plus Gigabit Ethernet \(ST3300GU3B\)](#)

[4 Port Compact Black USB 2.0 Hub \(ST4202USB\)](#)

[4 Port Black USB 2.0 Hub \(ST4202USBGB\)](#)

[7 Port Compact Black USB 2.0 Hub \(ST7202USB\)](#)

[7 Port Black USB 2.0 Hub \(ST7202USBGB\)](#)

[15m USB 2.0 Active Cable with 4 Port Hub \(USB2EXT4P15M\)](#)

[10m USB 3.0 Active Extension Cable \(USB3AAEXT10M\)](#)

[3m USB 3.0 Active Extension Cable \(USB3AAEXT3M\)](#)

[5m USB 3.0 Active Extension Cable \(USB3AAEXT5M\)](#)

[4K HDMI 4-Port Video Splitter \(ST124HD4K\)](#)

[Wireless Display Adapter with HDMI \(WIFI2HDMCGE\)](#)

[4-Port HDMI Automatic Video Switch \(VS421HD4K\)](#)

The SVA12DN4NEUA is backed by a StarTech.com 2-year warranty and free lifetime technical support.

Certifications, Reports and Compatibility



Applications

- Replace a lost or broken power adapter
- Keep an extra power adapter on hand for your mission-critical devices
- Use a single power adapter as you travel between multiple regions

Features

- Supports a range of devices that require 5 volt and 2 amps (or less) of power and an H-type barrel connector
- Reduces downtime in the event of a failure, by keeping a spare power adapter on-hand

Power	Warranty	2 Years
	Center Tip Polarity	Positive
	Input Current	0.4 A
	Input Voltage	110V-240V AC
	Output Current	2 A
	Output Voltage	5 DC
	Plug Type	H
	Power Consumption (In Watts)	10
	Power Source	AC Adapter Included
Physical Characteristics	Product Height	64.6 mm [2.5 in]
	Product Length	1314.6 mm [51.8 in]
	Product Weight	100 g [3.5 oz]
	Product Width	39 mm [1.5 in]
Packaging Information	Shipping (Package) Weight	178 g [6.3 oz]
What's in the Box	Included in Package	1 - universal power adapter (NA/JP, EU, UK, AU)

Product appearance and specifications are subject to change without notice.