HP LaserJet Enterprise MFP M631dn



This HP LaserJet MFP with JetIntelligence combines performance, energy efficiency, and security.

This HP LaserJet MFP with JetIntelligence combines exceptional performance and energy efficiency with professional-quality documents right when you need them—all while protecting your network from attacks with the industry's deepest security.





The world's most secure printing

- With HP Sure Start, each printer regularly checks its operating code and repairs itself from attempted hacks.
- Help prevent potential attacks and take immediate action with instant notification of security issues.
- Centralize control of your printing environment with HP Web Jetadmin—and help build business efficiency.³
- Paper handling options include a wheeled stand and 550-sheet input feeder for paper sizes A6 to legal .



High-speed performance meets energy efficiency

- Speed through tasks and save paper. Print two-sided documents nearly as fast as single-sided.
- This printer wakes up fast and prints your first page faster—in as quickly as 7.8 seconds.²
- This MFP uses exceptionally low amounts of energy thanks to its innovative design and toner technology.⁶
- Paper handling options include a wheeled stand and 550-sheet input feeder for paper sizes A6 to legal.



More. Pages, Performance, and Protection.

- Produce sharp text, bold blacks, and crisp graphics with precision black toner.
- Original HP Toner cartridges with JetIntelligence deliver more pages per cartridge than predecessors.5
- Help retain the Original HP quality you paid for with anti-fraud and cartridge authentication technology.
- Spend less time replacing toner, and more on business. Choose high-yield toner cartridges.

Technical specifications

Functions	Print, Copy, Scan		
Print			
Ouplex print options	Automatic (standard)		
rint speed ⁶	Black (A4, normal) Up to 52 ppm; Black (letter, normal) Up to 55 ppm; Black (A5, landscape) Up to 80 ppm; Black (A4, duplex) Up to 43 ppm; Black (letter, duplex) Up to 45 ppm		
0	Black (A4, ready) As fast as 5.4 sec; Black (A4, sleep) As fast as 7.9 sec		
irst page out ⁸			
Print resolution Print technology	Black (best) Up to 1200 x 1200 dpi; Black (normal) FastRes1200 Laser		
Print resolution technology	FastRes 1200; 1200 x 1200 dpi		
Print cartridges number	1 (black)		
itandard print languages	HP PCL 6, HP PCL 5 (HP PCL 5 driver available from the Web only), HP postscript level 3 emulation, native PDF printing (v 1.7), Apple AirPrint™		
Printer management	HP JetAdvantage Security Manager; HP SNMP Proxy Agent; HP Web JetAdmin Software; HP WS Pro Proxy Agent; Printer Administrator Resource Kit for HP Unive Print Driver		
Scan			
ican technology	Type Flatbed, ADF; Technology Charge Coupled Device (CCD)		
ican speed ¹¹	Normal (A4) Up to 69 ppm (b&w), up to 69 ppm (color)		
Scan resolution	Enhanced 600 dpi; Hardware 600 x 600 dpi; Optical up to 600 dpi		
can size	ADF 215.9 x 863.6 mm Flatbed 220 x 365 mm		
can input modes	Front panel applications: Copy; E-mail; Save to Network Folder; Save to USB; Save to Device Memory; Save to SharePoint; Open Extensibility Platform (OXP) applications; HP Scan or user application via TWAIN		
ican file format	PDF, JPG, TIF, MTIF ¹²		
ору			
opy speed	Black (A4, normal) Up to 52 cpm; Black (letter, normal) Up to 55 cpm; Black Duplex (A4) Up to 43 cpm; Black (letter, duplex) Up to 45 cpm		
irst copy out	Black (A4) As fast as 4.9 sec Black (A4, sleep) As fast as 10.4 sec		
opy resolution	Black (text and graphics) Up to 600 x 600 dpi (flatbed); Up to 600 x 450 dpi (ADF);		
Max. number of copies	Up to 9999 copies		
opier resize	25 to 400%		
Copier settings	Two-sided copying, scalability, image adjustments (darkness, contrast, background cleanup, sharpness), N-up, N or Z-ordering, content orientation, collation,		
Connectivity	booklet, job build, edge-to-edge, job storage, ID Copy, Book Copy, A-to-B Copy (different media sizes)		
tandard connectivity	1 Hi-Speed Device USB 2.0; 2 Host USB (1 walk-up and 1 external accessible); 1 Gigabit Ethernet 10/100/1000T network; 1 Hardware Integration Pocket		
Mobile printing capability	HP ePrint; Apple AirPrint™; Mopria™-certified; Google Cloud Print 2.0		
Network ready	Standard (built-in Gigabit Ethernet)		
Vireless capability	Optional, enabled with purchase of HP Jetdirect 2900nw Print Server J8031A or HP Jetdirect 3000w NFC/Wireless Accessory J8030A		
letwork Capabilities	Yes, via HP Jetdirect Ethernet embedded print server (standard) which supports: 10Base-T, 100Base-Tx, 100Base-T; 802.3az (EEE) support on Fast Ethernet and		
etwork capabilities	Gig Links; IPsec (standard); 802.11a/b/g/n wireless networking (optional).		
IP ePrint capability	Yes		
lemory	Standard 1.5 GB (printer); 512 MB (scanner); Maximum 2 GB Total		
Processor speed	1.2GHz		
Outy cycle (monthly)	Up to 300,000 pages; Recommended monthly page volume: 5,000 to 30,000		
Paper handling			
nput	100-sheet multipurpose feeder, 550-sheet input feeder, 150-sheet automatic document feeder; Optional 1 x 550-sheet paper feeder, 1 x 550-sheet feeder with cabinet, 2000-sheet feeder high capacity input with 1 x 550-sheet paper feeder, optional 3 x 550-sheet feeder, optional envelope feeder		
Output	500-sheet ouput feeder, two-sided printing		
Media type	Paper (plain, light, bond, recycled, heavy, extra heavy, cardstock, pre-printed, pre-punched, colored, rough, heavy rough), mono transparency, labels, letterhead, envelope, heavy envelope		
Media weight	Feeder 1: 60 to 200 g/m²; feeder 2: 60 to 120 g/m²		
Media sizes custom	feeder 1: 76 x 127 to 216 x 356 mm; feeder 2: 99 x 148 to 216 x 297 mm		
Dimensions (W x D x H)	512 x 558 x 640 mm		
Veight	33.2 kg		
What's in the box 1	HP LaserJet Multifunction Printer; HP Black Original LaserJet Toner Cartridge (~11K yield); CD with software drivers and documentation; Documentation (Hardware		
	Install Guide); Power cord		
Warranty features	1 Year Limited Warranty (Next Business Day On-Site)		
Systems Compatible operating systems	Android, Linux Boss (5.0), Linux Debian (7.0, 7.1, 7.2, 7.3, 7.4, 7.5, 7.6, 7.7, 7.8, 7.9, 8.0, 8.1, 8.2, 8.3, 8.4, 8.5, 8.6), Linux Fedora (22, 23, 24), Linux Mint (17, 17.1, 17.2, 17.3, 18), Linux Red Hat Enterprise (6.0, 7.0), Linux SUSE (13.2, 42.1), Linux Ubuntu (12.04, 14.04, 15.10, 16.04, 16.10), OS macOS 10.12 Sierra, OS X 10.10		
	Yosemite, OS X 10.11 El Capitan, UNIX, Windows 10 all 32- & 64-bit editions (excluding RT OS for Tablets), Windows 7 all 32- & 64-bit editions, windows 8/8.1 all 32- & 64-bit editions (excluding RT OS for Tablets), Windows Vista all 32bit editions (Home Basic, Premium, Professional, etc.), Windows XP SP3 32-bit editions (XHome, XP Pro, etc.)		
Ainimum system requirements	PC 2GB available hard disk space; OS hardware requirements see microsoft.com		
um system requirements	Mac 1.3 GB available hard drive space; Internet; OS hardware requirements see Apple.com for more info		
Fonts and Typefaces	105 internal TrueType fonts scalable in HP PCL, 92 internal scalable fonts in HP postscript level 3 emulation (Euro symbol built-in); 1 internal Unicode Fonts (Anda Mono World Type); 2 Internal Windows Vista 8 Fonts (Calibri, Cambria); Additional font solutions available via third-party flash memory cards; HP LaserJet Fonts are		
	IPDS Emulation available at http://www.hp.com/go/laserjetfonts		
Control panel	8.0-in (20.3 cm) Color Graphics Display (CGD) with touchscreen; rotating (adjustable angle) display; illuminated Home button (for quick return to the Home menu) 8.0-in (20.3 cm) Color Graphics Display (CGD) with touchscreen; rotating (adjustable angle) display; illuminated Home button (for quick return to the Home menu)		
Display	8.0-in (20.3 cm) Color Graphics Display (LGD) with touchscreen; rotating (adjustable angle) display; illuminated Home button (for quick return to the Home menu) Power supply type Built in 115V or 220V Power Supply; Power supply required Input voltage: 100V to 127V nominal (+/-10%), 50 - 60Hz nominal (+/-3Hz), 12		
ower	Input voltage: 220V to 240V nominal, (+/-10%) 50 - 60Hz nominal (+/- 3Hz), 6 A; Power consumption ² : 740 watts (printing/copying), 29.0 watts (ready), 3.3 wat		
oftware included	(sleep), < 0.1 watts (Auto Off/Manual On), < 0.1 watts (Manual Off); Typical electricity consumption (TEC) number⁹: ES: 2.348 kWh/week; BA: 2.219 kWh/week HP Connected, HP Device Experience (DXP), HP PCL 6 Printer Driver, HP Software Installer/Uninstaller, Mac OS Welcome Screen (Directs users to 123.HP.com or OS		
Acoustics	App Source for printer software), Online user manuals Acoustic power emissions: 6.9 Bel; Acoustic power emissions (ready) inaudible; Acoustic pressure emissions bystander (active, printing) 55 dB(A); Acoustic		
	pressure emissions bystander (ready) inaudible Operating townparature 15 to 225°C Recommended operating townparature 15 to 27°C Non-operating hymidity range 10 to 2004 PM: Operating		
invironmental ranges	Operating temperature range 15 to 32.5°C; Recommended operating temperature 15 to 27°C; Non-operating humidity range 10 to 80% RH; Operating humidity range 30 to 70% RH		
ecurity management	Identity management: Kerberos authentication; LDAP authentication; 1000 user PIN codes; optional HP and 3rd party advanced authentication solutions (e.g., be readers); Network: IPsec/firewall with Certificate; Pre-Shared Key; and Kerberos authentication; Supports WIA-10 IPsec configuration Plug-in; 802.1X authentical (EAP-PEAF_EAP-TLS; SNMPS); AITPS; Certificates; Access Control List; Data Stroage Encryption; Encrypted PC & Email (uses FIPS 140 wildladed cryptoplapilibraries from Microsoft); Secure Erase; SSL/TLS (HTTPS); Encrypted Credentials; Device: Security lock slot; USB port disablement; hardware integration pocket fo security solutions; Intrusion Detection with Red Ballon) Security Technology - Constant in -device monitoring for attacks; SureStart Secure Bort - Bol's Integrity Checking with self-healing capability; Whitelisting - loads only known good code (DLLs, EKS., J.; Security management: Compatible with HP JetAdvantage Secur		
Safety approvals and requirements	Manager, Device Security Syslog Messages processed and accessable in Arcsight and Splunk SIEMS IEC 60950-1:2005 +A1:2009 +A2:2013 (International); EN60950-1:2006 +A1:2010 +A1:2010 +A1:2010 +A1:2011 +A2:2013 (EU/EN 60825-1:2007 / IEC 60825-1		
Supported network protocols	Deviations pursuant to Laser notice No. 50, Useted June 24, 2007; Other Sately approvals as required by individual countries. Wis built-in returnering solution: TCPIR [PN4, IPC6, Pint: TCPI-P prot 1900 Direct Mode, IPO (raw queue support only), Meb Services Printing, IPP 2.0, Apple AirPrint*, IPP ePnint, FTP Print, Google Cloud Print; DISCOVERY* SLR Bonjour, Web Services Discovery, IP CONFIG: IPv4 (BootP DHCP, AutoIP, Manual, TFTP Config, ARP-Ping), IPP-6 (Stateless Link-Local and via Route; Statefull via DHCPv6); Management: SNMPv2/N3, HTTP/HTTPs, Telnet, TFTP Config, FTP FW Download, Syslog; Security: SNMPv3, SSL Cert Management, Firewall, ACL, 802.1x.		

















Ordering Information

Description

HP LaserJet Enterprise MFP M631dn J8J63A

Supplies and Maintenance Kits

Number	Description
CF237A	HP 37A Black Original LaserJet Toner Cartridge
CEDDAY	(11,000 pages)
CF237X	HP 37X High Yield Black Original LaserJet Toner Cartridge (25,000 pages)
CF237Y	HP 37Y Extra High Yield Black Original LaserJet
	Toner Cartridge (41,000 pages)
J8J87A	HP LaserJet 110V Maintenance Kit (Up to
	225,000 pages)
J8J88A	HP LaserJet 220V Maintenance Kit (Up to
	225,000 pages)
J8J95A	HP 300 ADF Roller Replacement Kit (Up to
	150,000 pages)

Accessories

Number	Description
B5L28A	HP Internal USB Ports
B5L29A	HP High-Performance Secure Hard Disk
B5L31A	HP Foreign Interface Harness
CC487A	HP LaserJet MFP Analog Fax Accessory 500
E5K48A	HP 1 GB x32 144-pin (800 MHz)DDR3 SODIMM
F5S62A	HP Trusted Platform Module Accessory
J8030A	HP Jetdirect 3000w NFC/Wireless Accessory
J8031A	HP Jetdirect 2900nw Print Server
J8J89A	HP LaserJet 550-sheet Feeder Tray
J8J90A	HP LaserJet Envelope Feeder
J8J91A	HP LaserJet 1x550 Paper Feeder and Cabinet
J8J92A	HP LaserJet High Capacity Paper Feeder and
	Stand
J8J93A	HP LaserJet 3x550-sheet Paper Feeder with
	Cabinet
J8J96A	HP Staple Cartridge Refill

HP Care Packs

Number Description

Number	Description
U9NK0E	HP 3 year Next Business Day HW Support
	w/Defective Media Retention for LaserJet
	Enterprise MFP M63x
U9NK1E	HP 4 year Next Business Day HW Support
	w/Defective Media Retention for LaserJet
	Enterprise MFP M63x
U9NK2E	HP 5 year Next Business Day HW Support
	w/Defective Media Retention for LaserJet
	Enterprise MFP M63x
U9NK3E	HP 3 year 4 hour 9x5 Hardware Support
	w/Defective Media Retention for LaserJet
	Enterprise MFP M63x
U9NK4E	HP 4 year 4 hour 9x5 Hardware Support
	w/Defective Media Retention for LaserJet
	Enterprise MFP M63x
U9NK5E	HP 5 year 4 hour 9x5 Hardware Support
	w/Defective Media Retention for LaserJet
	Enterprise MFP M63x
U9NL8PE	HP 1 year Post Warranty 4 hour 13x5 Hardware
	Support w/DMR for LaserJet Enterprise MFP M63x
U9NL9PE	HP 2 year Post Warranty 4 hour 13x5 Hardware
	Support w/DMR for LaserJet Enterprise MFP M63x
U9NM0PE	HP 1 year Post Wty NBD CTR HW Support
	w/Defective Media Retention for LaserJet
	Enterprise MFP M63x
U9NM1PE	HP 2 year Post Wty NBD CTR HW Support
	w/Defective Media Retention for LaserJet

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to hp.com/go/cpc

Enterprise MFP M63x

HP Inc. offices

Australia	(613) 8833 5000	hp.com.au
China	(010) 6564 3888	hp.com.cn
Hong Kong	(852) 3077 2688	hp.com.hk
India	(80) 2612 9000	hp.com/in
Indonesia	(62-21) 5799 1088	hp.com/id
Korea	(02) 2199 0114	hp.co.kr
Malaysia	(603) 2332 3333	hp.com.my
New Zealand	(09) 918 9555	hp.co.nz
Philippines	(632) 888 5900	hp.com/ph
Singapore	(65) 6275 3888	hp.com.sg
Taiwan	(02) 3789 9900	hp.com.tw
Thailand	(662) 353 9500	hp.com/th
Vietnam	(848) 3823 4151	hp.com/vn

For the following countries, please fax your queries to(65) 6275 6707 Bangladesh, Bhutan, Brunei, Cambodia, Maldives, Nepal, Pakistan, Sri Lanka

Supported paper

Contact HP via phone: Asia: 65 6253 8500

Solutions

For more solutions information, please visit

hp.com/go/gsc

Paper-handling accessories



550-sheet paper feeder (J8J89A)



1x550-sheet paper feeder with stand and cabinet (J8J91A)



3x550-sheet paper feeder and stand (J8J93A)



1x550 and 2,000sheet HCI feeder with stand (J8J92A)



Envelope feeder (J8J90A)



3-hin stapler/stacker

Footnotes

¹ Based on HP review of 2016 published security features of competitive in-class printers. Only HP offers a combination of security features that can monitor to detect and automatically stop an attack then

- self-validate software integrity in a reboot. For a list of printers, visit http://www.hp.com/go/PrintersThatProtect. For more information: http://www.hp.com/go/printersecurityclaims ² Measured after 15 min in sleep. Exact speed varies depending on the system configuration, software application, driver, document complexity and time in sleep.
- ³ HP Web Jetadmin is available for download at no additional charge at http://www.hp.com/go/webjetadmin ⁴ Measured using ISO/IEC 24734, excludes first set of test documents. For more information, see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- 6 More pages versus predecessor cartridges claim based on page-vield comparison of HP 37X High Yield Black Original LaserJet Toner Cartridges with HP 87X High Yield Black Original LaserJet Toner Cartridges. For
- based on HP testing using the ENERGY STAR® program's Typical Electricity Consumption (TEC) method or as reported in energystar.gov versus the top three leading competitors as of 8/2015. Actual results may vary. For details see http://www.hp.com/go/Ljclaims
- ⁷ HP 37X High Yield Black Original LaserJet Toner Cartridges not included; please purchase separately.
- 8 Scan speed measured from ADF at default 300 dpi (black-and-white, grayscale, and color). Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and

Technical specifications disclaimers

- ¹ Cartridges included; yields 11,000 black pages based on ISO/IEC 19798 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/qo/learnaboutsupplies
- ² Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typicallty based on measurement of 115 v device.
- ³ Average color composite (C/M/Y) and black declared yields based on ISO/IEC 19798 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see
- http://www.hp.com/go/learnaboutsupplies

 Declared yield value in accordance with ISO/IEC 19752. Actual yields vary considerably based on images printed and other factors. For more information, visit http://www.hp.com/go/learnaboutsupplies
- 5 Based on standard ITU-T test image #1 at standard resolution and MMR encoding, the HP fax device can transmit at 3 sec/page for V.34 and 6 sec/page for V.17 Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software
- application, driver, and document complexity.

 Measured using ISO 24734 Feature Test, A5 Landscape Feed. Speed may vary based on content, PC, media orientation, and media type.
- ^a Measured using ISO/IEC 17629. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. 9 Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on
- Based on the BA TEC method with the following possible exceptions: 1 minute or less sleep delay setting, Wi-Fi disabled.
 Scan speeds measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.
- 12 Scan software not included in box, HP Scan and TWAIN driver available for download at http://hp.com/support

To learn more, visit hp.com





