## HyperX FURY DDR3 Memory

HYPERXGAMING.COM

# Auto-overclocking up to 1866MHz to get you in the game faster.

HyperX® FURY DDR3 memory automatically overclocks up to 1866MHz¹ for hassle-free, plug-and-play functionality that gets you in the game faster and instant top-level performance that helps you win it. With voltages as low as 1.35V, it draws less power and generates less heat, while supporting Intel's new 100 Series chipset. Its asymmetric, aggressive design lets you stand out from the crowd of "squared" designs and features quality aluminum and a diamond-cut finish. It's available in black, blue, white and red with a black PCB to match the latest color schemes of motherboards, cases and other components.

- > Automatic overclocking up to 1866MHz1
- > Voltages start as low as 1.35V
- > Asymmetric, aggressive heat spreader design
- > Available in multiple colors with a black PCB



Features/specs on reverse >>



### **HyperX FURY DDR3 Memory**

#### **FEATURES/BENEFITS**

- > **Automatic overclocking** Get in the game faster with automatic overclocking up to the highest frequency published.
- > Low voltage options HyperX FURY DDR3 offers low 1.35V options to draw less power and generate less heat while increasing reliability. This low power offering is compatible with Intel's 100 Series chipset.
- > Aggressive look, asymmetrical design Its innovative design makes HyperX FURY DDR3 memory stand out from the crowd. Its asymmetrical heat spreader and black PCB complement the look of many systems.
- > In multiple colors to match your system HyperX FURY DDR3 comes in multiple colors, so there's sure to be one that goes with your system or that custom case mod you've been working on.
- > Reliable 100-percent factory tested
- > **Guaranteed** lifetime warranty, free technical support

#### **SPECIFICATIONS**

- > Capacities 4GB, 8GB (single) and 8GB, 16GB (kits)
- > Frequency (speed) 1333MHz, 1600MHz, 1866MHz
- > Dual Channel
- > Latency CL9-11
- > Voltage 1.35V, 1.5V
- > Operating Temperature 0°C to 85°C
- > Storage Temperature -55°C to 100°C
- > **Dimensions** 133.35mm x 32.8mm
- > **Compatible** with Intel 6, 7, 8, 9 and 100<sup>2</sup> series chipsets, as well as A75, A87, A88, A89, A78 and E35 AMD chipsets



#### **HYPERX PART NUMBERS**

۱ ۸	/  _	: 1	
1/1	/ r ·	ווו	$\omega$

 HX313C9FW/4
 HX316C10FW/4
 HX318C10FW/4

 HX313C9FW/8
 HX316C10FW/8
 HX318C10FW/8

 HX313C9FWK2/8
 HX316C10FWK2/8
 HX318C10FWK2/8

 HX313C9FWK2/16
 HX316C10FWK2/16
 HX318C10FWK2/16

#### Black

HX313C9FB/4 HX316C10FB/4 HX318C10FB/4 HX313C9FB/8 HX316C10FB/8 HX318C10FB/8 HX313C9FBK2/8 HX316C10FBK2/8 HX318C10FBK2/8 HX313C9FBK2/16 HX316C10FBK2/16 HX318C10FBK2/16

#### Black Low Voltage

 HX316LC10FB/4
 HX318LC11FB/4

 HX316LC10FBK2/8
 HX318LC11FBK2/8

 HX316LC10FB/8
 HX318LC11FB/8

 HX316LC10FBK2/16
 HX318LC11FBK2/16

#### Red

HX313C9FR/4 HX316C10FR/4 HX318C10FR/4 HX313C9FR/8 HX316C10FR/8 HX318C10FR/8 HX313C9FRK2/8 HX313C9FRK2/16 HX316C10FRK2/16 HX318C10FRK2/16 HX318C10FRK2/16 HX318C10FRK2/16

#### Blue

HX313C9F/4 HX316C10F/4 HX318C10F/4 HX313C9F/8 HX316C10F/8 HX318C10F/8 HX313C9FK2/8 HX316C10FK2/8 HX318C10FK2/8 HX313C9FK2/16 HX316C10FK2/16 HX318C10FK2/16





<sup>1</sup> HyperX PnP memory will run in most DDR3 systems up to the speed allowed by the manufacturer's system BlOS. PnP cannot increase the system memory speed faster than is allowed by the manufacturer's BlOS.

<sup>2 100</sup> Series chipset supports Fury DDR3 Low Voltage 1.35V parts only