HP Laser MFP 131a

Laser performance at an affordable price

Get productive MFP performance at an affordable price. Print, scan and copy and with high-quality results.





Legendary quality, surprisingly affordable price

- This surprisingly small laser delivers exceptional quality, page after page.
- Produce sharp text, bold blacks and crisp graphics.
- Rely on a high-performance laser MFP at an affordable price.



Designed to fit your space

- You can fit this MFP almost anywhere it's that small and compact.
- Get print speeds up to 20 ppm (A4).1
- Get quick and easy printing directly at the control panel.

 $^{^{1}\,\}text{Measured using ISO/IEC\,24734}, excludes \,first\,\text{set}\,\text{of}\,\text{test}\,\text{documents}.\,\text{For}\,\text{more}\,\text{information}, \text{see}\,\underline{\text{hp.com/go/printerclaims}}.$

Technical specifications

Number of user	1–5 Users
Functions	Print, copy and scan
Print	This, copy and scan
Technology	Laser
Duplex print options	Manual (driver support provided)
Speed ¹	Black (normal, A4): Up to 20 ppm
First page out ²	Black (A4, ready): As fast as 8.3 seconds; Black (A4, sleep): As fast as 18 seconds (15 min)
Resolution	Black (best): Up to 1200 x 1200 dpi; Black (normal): Up to 600 x 600 dpi
Cartridges number	1 (black)
Standard print languages	SPL
Scan	
Туре	Flatbed
Technology	Contact Image Sensor (CIS)
Resolution	Hardware: Up to 4800 x 4800 dpi; Optical: Up to 600 x 600 dpi; Enhanced: Up to 4800 x 4800 dpi
Max scanning size	Flatbed: 216 x 297 mm
Grayscale levels	256
Bit depth	8-bit (mono); 16-bit (colour)
File format	Windows Scan SW supports file format: PDF, JPG, TIFF, PNG, BMP
Input modes	Front-panel copy, HP MFP scan software, user application via TWAIN or WIA
Scanner advanced features	Scan to WSD (network support only);Book Scanning; Poster Stitching for multiple scan; Text Converting; Scan to E-Book; Existing File to E-Book
Twain version	Version 1.9
Сору	
Speed ³	Black (normal, A4): Up to 20 cpm
First copy out	Black (A4): As fast as 8.9 seconds; Black (A4, sleep): As fast as 17 seconds (15 min)
Max copies	Up to 99 copies
Copier reduce/enlarge	25 to 400%
Copier setting	Copies; Original Size; Reduce/Enlarge; Darkness; Original Type; Collation; 2-Up; 4-Up; ID Copy; Adjust Background Auto Fit Copy
Copier smart software	Automatic adjusting background; Extended layout (2-up, 4-up, ID copy); expanded contrast adjustments (11
features	different settings);Scale from one paper size to another (Letter>A4, AutoFit);
Display	2-Line LCD (16 characters per line)
Control panel	2-Line LCD; 12 Buttons (Power, Cancel, Start, Navigation (Menu, OK, Back, Left, Right), ID Copy, Contrast, Scale, Info); LED indicator lights (Power, Status)
Duty cycle⁴	Up to 10,000 pages
Recommended monthly	100 to 2,000 pages
page volume ⁵	Lii Coord LICD 2 O port
Connectivity (standard) Media	Hi-Speed USB 2.0 port
Paper handling	Input: 150-sheet input tray; Output: 100-sheet output bin
Туре	Plain, Thick, Thin, Cotton, Colour, Preprinted, Recycled, Labels, CardStock, Bond, Archive, Envelope
Weight (Supported)	60 to 163 q/m ²
Sizes (Supported)	A4; A5; A5 (LEF); B5 (JIS); Oficio; Envelope (DL,C5)
Processor speed	600 MHz
Memory	Standard/Maximum: 128 MB
Compatible operating systems	Windows®: 7 (32/64 bit), 2008 Server R2, 8 (32/64 bit), 8.1 (32/64 bit), 10 (32/64 bit), 2012 Server, 2016 Server
Minimum system requirements	PC: Windows 7 or newer, Intel [®] Pentium [®] IV 1 GHz 32-bit or 64-bit processor or higher, 1 GB RAM, 16 GB HDD
Environmental	
Acoustic	Acoustic power emissions (active, printing): 6.5 B(A) (printing at 20 ppm); Acoustic power emissions (active scan): 6.25 B(A) (only 20 ipm ADF)
Operating environment	Operating temperature range: 10 to 30° C; Recommended operating temperature: 15 to 27° C; Operating humidity range: 10 to 80% RH (non-condensing); Recommended operating humidity range: 20 to 70% RH (non-condensing); Storage temperature range: -20 to 40° C
Energy savings feature technology	HP Auto-Off Technology; Power save
Power specifications	Power supply type: Internal (Built-in) power supply; Power supply required: 110-volt input voltage: 110 to 127 VAC, 50/60Hz and 220-volt input voltage: 220 to 240 VAC, 50/60Hz; Power consumption: Active Printing: 300 watts, Ready: 38 watts, Sleep: 1.9 watts, Manual off: 0.2 watts, Auto off/Manual on: 0.2 watts; Typical electricity consumption (TEC): 0.876 kWh/Week (BA), 0.924 kWh/Week (ES)
Warranty features	One-year limited hardware warranty; For more info please visit us at support.hp.com
Dimension ⁸	406 x 359.6 x 253 mm
Weight ⁹	7.46 kg
What's in the box ¹⁰	HP Laser MFP 131a, Preinstalled introductory HP Laser Jet Black print cartridges (~0.7K pages, Bidding); Setup Guide; Reference Guide; Regulatory Statements Flyer; Power cord; USB cable
	setup duide, Reference duide, Regulatory Staternerits Flyer, Power Cord, 056 Cable

Ordering information

Number	Description
4ZB92A	HP Laser MFP 131a

Replacement cartridges11

Number	Description
W1003AC	HP Black Contractual Original Laser Toner
	Cartridge (~1,500 pages) - China Only
W1004AC	HP Black Contractual Original Laser Toner
	Cartridge (~1 500 pages) - India Only

HP Care Packs

Number	Description
UB4V5E	HP 3-year Onsite Exchange Laser 13x MFP SV
	HP 3-year Next Business Day Exchange Laser
UB4V8E	13x MFP SVC

UB4W1E HP 3-year Standard Exchange Laser 13x MFP

SVC

UB4W4E HP 3-year Return to Depot Laser 13x MFP SVC

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to <u>hp.com/go/cpc</u>

Recommended Papers¹¹

Number	Description
CG964A	HP Professional Laser Paper, Glossy, A4,
	250 sheets, 120 gsm
CG965A	HP Professional Laser Paper, Glossy, A4,
	150 sheets, 150 gsm
CG966A	HP Professional Laser Photo Paper, Glossy, A4
	100 sheets, 200 gsm
Q6550A	HP Professional Laser Photo Paper, Matte, A4,
	100 sheets
Please visit <u>hp.c</u>	om/apac/paper for more details.

HP Inc offices

China	(010) 6564 3888	hp.com.cn
India	(80) 2612 9000	hp.com/in

For more information, please visit us at <u>hp.com/apac/homeandoffice</u>

HP Order-a-Cartridge¹²

Call HP's Order-a-Cartridge¹² service and have them conveniently delivered to your doorstep.

China 800 820 0851/400 820 0851

India 1800 3003 3003





© 2019 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.



Neasured using ISO/IEC 24734, excludes first set of test documents. For more information see https://excludes.nc.nig/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. Measured using ISO/IEC 29183, excludes first set of test documents. For more information see https://excludes.nc.nig/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups. Pherecommends that the number of printed pages per month be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period. Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115V device. Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115V device and 230V for Blue Angel. Dimensions vary as per configuration to the product warranty. Energy Star value typically based on measurement of 115V device and 230V for Blue Angel. Dimensions vary as per configuration? Weight varies as per configuration to the product warranty. Energy Star value typically based on measurement of 115V device and 230V for Blue Angel. Dimensions vary as per configuration? Weight varies consi