

Xerox® Phaser® 3610 Black and White Printer



Phaser 3610DN

| Phaser 3610DN | |
|-----------------------------|---|
| Output Speed | Up to 45 ppm A4 / 210 x 297 mm |
| Automatic Two-sided | Up to 28 ppm A4 / 210 x 297 mm |
| Paper Handling – Input | |
| Multipurpose Tray | |
| Capacity¹ | 150 sheets |
| Sizes | Custom sizes: 76 x 127 mm to 216 x 356 mm |
| Weights | 60 to 216 gsm |
| Media Types | Plain Plain thick Other Card stock Lightweight Heavyweight Rough surface Labels Envelopes Letterhead Hole punched |
| Tray 1 | |
| Capacity¹ | 550 sheets |
| Sizes | Custom sizes: 148 x 210 mm to 216 x 356 mm |
| Weights | 60 to 216 gsm |
| Media Types | Plain Plain thick Other Card stock Lightweight Heavyweight Rough surface Labels Letterhead Hole punched |

Xerox® Phaser® 3610

| Up to 3 Additional Trays (Optional) | |
|--|---|
| Capacity¹ | 550 sheets each |
| Sizes | Custom sizes: 148 x 210 mm to 216 x 356 mm |
| Weights | 60 to 216 gsm |
| Media Types | Plain Plain thick Other Card stock Lightweight Heavyweight Rough surface Labels Letterhead Hole punched |
| Paper Input Capacity | |
| Standard Paper Capacity¹ | 700 sheets |
| Maximum Paper Capacity¹ | 2,350 sheets |
| Paper Output | |
| Automatic Two-sided Output | 250 sheets |
| Print | |
| First-page-out Time | As fast as 6.5 seconds |
| Print Resolution | Up to 1200 x 1200 dpi |
| Maximum Print Area | 4 mm from all edges or 207.7 mm x 347.4 mm (default), 215.9 mm x 255.6 mm with edge-to-edge mode |
| Memory (std / max) | 512 MB / 1 GB with optional memory |
| Processor | 400 MHz |
| Page Description Languages | PCL® 5e and 6 emulations PostScript® 3™ emulation PDF emulation |
| Connectivity | 10/100/1000Base-T Ethernet Optional Wi-Fi (with Xerox® Wireless Connectivity Kit) |
| Print Features | Booklet printing Scaling Fit to page Watermarks Custom-size pages N-up Toner save mode Secure print Collation |
| Supported Operating Systems | Microsoft® Windows® XP SP1, Vista, 7, 2008 Server, 2003 Server Mac OS® 10.5 and later Various Linux® and UNIX® distributions, including: <ul style="list-style-type: none"> • IBM® AIX® 5 • HP-UX® 11i v2 • openSUSE® 11 • Red Hat® Fedora® Core 11-14 • Ubuntu® |

| | |
|--|---|
| Print Drivers | Microsoft Windows XP and above 2003 Server and above Mac OS 10.5 and above Red Hat Enterprise 4, 5 Fedora Core 14-16 openSUSE 11, 12 IBM AIX-5 HP-UX 11, 11i Solaris® 9, 10 Ubuntu Xerox® Global Print Driver® Xerox® Mobile Express Driver® |
| Font Capability | 87 PostScript® Fonts; 96 PCL® Fonts |
| Xerox® Mobile Express Driver® (X-MED) | Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox devices in every new location. Plug into a new network, and X-MED automatically discovers available printers and provides status and capability information. Save a list of "favourite" printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT. <ul style="list-style-type: none"> • Printers are automatically discovered • Printer list can be managed based on location • Gives Bidirectional feedback device status, supplies, queue management |
| Xerox® Global Print Driver® (X-GPD) | A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management. <ul style="list-style-type: none"> • Printers are automatically discovered • Printer list can be managed based on location • Gives Bidirectional feedback device status, supplies, queue management |

Security

| | |
|--------------------------|---|
| Security Features | Secure HTTPS (SSL, Secure LDAP) IPsec 802.1X Authentication Network Authentication IPv6 SNMPv3 IP Filtering Secure Print |
|--------------------------|---|

Wi-Fi Security

| Authentication Method | Encryption | Productivity Kit |
|--|---|------------------|
| Open WPA PSK WPA PSK / WPA2 PSK | WEP 64 / 128 ASCII / HEX TKIP AES | No |
| WPA Enterprise WPA Enterprise / WPA 2™ Enterprise WPA Enterprise Authentication Method options: <ul style="list-style-type: none"> • PEAPVO MS-CHAPV2 • EAP-TLS • EAP-TTLS PAP • EAP-TTLS CHAP | TKIP AES | Yes |

| Device Management | |
|--|--|
| Xerox® CentreWare® Web | |
| | <ul style="list-style-type: none"> • A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system • Works with any SNMP-managed printer from any manufacturer • Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management |
| Xerox® CentreWare® Internet Services – Integrated Device Web Page | |
| Device Status | Web server embedded <ul style="list-style-type: none"> • Tray status / contents • Consumables status |
| Print Queue Viewing | Complete job print queue management – hold, release, promote and delete |
| Job Submission | Print-ready files (PS, PCL®, TIFF, PDF) Output feature selection |
| Device Administration | Allows simple, remote installation setting of configuration options and management of the device |
| Browsers | Microsoft® Internet Explorer® 7 Firefox® version 4 and above |
| Xerox® Mobile Solutions | |
| Xerox® PrintBack | PrintBack takes the capabilities of the printer you already use, and extends them beyond your computer and out to your Apple® iOS- or Android™-based mobile device. When you're working off-site or away from your desk and receive an important document via your mobile device, simply use PrintBack to print it with your default printer back at your office or desk. Plus, it supports the most common office file types (Microsoft® Office documents, PDF, etc.) with uncompromised print quality. |
| Xerox® Mobile Express Driver® | The Xerox® Mobile Express Driver is a single, universal printer driver that can be downloaded to a PC and used to print to virtually any PostScript device on the network, including printers made by other manufacturers. Instead of downloading individual printer drivers for each product in each office, users can download the single, simple, Mobile Express Driver. |
| Apple® AirPrint™ | Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network. |
| Device Specifications | |
| Duty Cycle | |
| | Up to 110,000 pages per month ² |
| Recommended Monthly Print Volume | |
| | Up to 14,000 pages per month ³ |
| Power Consumption | |
| 220 to 240 VAC, 50 / 60 Hz, 6A | |
| Continuous Printing | 686 W |
| Ready (Standby) Mode | 52 W |
| Energy Saver Mode (Sleep) | 2 W |
| Environment | |
| Warm-up Time | UI ready: <20 seconds First page printed: <20 seconds |
| Temperature Range | 15° to 28° C |
| Humidity | 20 to 70 % |
| Sound Pressure Levels | |
| Printing / Copying | 56 dB(A) |
| Standby | 30 dB(A) |
| Energy Save Mode | 0 dB(A) |
| Sound Power Levels | |
| Printing / Copying | 7.48 B(A) |
| Standby | 5.3 B(A) |

Xerox® Phaser® 3610

| Dimensions and Weights (Unpackaged) | | | | |
|-------------------------------------|---|--------------|--------|---------|
| | Width | Depth | Height | Weight |
| Phaser 3610DN | 393 mm | 426 mm | 315 mm | 13 kg |
| 550-sheet Tray | 393 mm | 393 mm | 94 mm | 3.2 kg |
| Stand | 442 mm | 470 mm | 390 mm | 13.3 kg |
| Dimensions and Weights (Packaged) | | | | |
| Phaser 3610DN | 534 mm | 540 mm | 470 mm | 15.9 kg |
| 550-sheet Tray | 498 mm | 504 mm | 234 mm | 4.4 kg |
| Stand | 515 mm | 510 mm | 230 mm | 15.4 kg |
| Certifications | | | | |
| | UL 60950-1:2007 / CSA 60950-1-07+A1:2011, FDA / CDRH – Class 1 Laser Product, FCC Part 15, Class A, Canada ICES-003, Class A, CE marked, Low Voltage Directive 2006 / 95 / EC, EN 60950-1, 1st Edition, EN 60825-1 – Class 1 Laser Product, EMC Directive 2004 / 108 / EC, EN 55022, Class B, RoHS Directive 2011 / 65 / EU, WEEE Directive 2002 / 96 / EC, ENERGY STAR® qualified, Citrix Ready®, Blue Angel | | | |
| | To view the latest list of certifications, go to www.xerox.com/OfficeCertifications | | | |
| What Comes in the Box | | | | |
| | Phaser 3610 Printer Toner cartridge (5,900 page capacity ⁴) Drum cartridge Quick Installation Guide, Quick Use Guide, Driver CD, Documentation CD (User Manual, System Administration, Guide) Power cable | | | |
| Supplies and Options | Description | Order Number | | |
| Standard Capacity Toner Cartridge | 5,900 impressions ⁴ | 106R02720 | | |
| High-Capacity Toner Cartridge | 14,100 impressions ⁴ | 106R02722 | | |
| Extra-high Capacity Toner Cartridge | 25,300 impressions ⁴ | 106R02731 | | |
| Drum Cartridge | 85,000 impressions | 113R00773 | | |
| Options | Description | Order Number | | |
| 550-sheet Tray | Adjustable up to A4 | 497K13620 | | |
| Memory | Includes 512 MB RAM memory, expanded Secure Print, expanded Job Collation | 497K13640 | | |
| Productivity Kit | Includes 4 GB device memory, expanded Secure Print, Saved Print, expanded Job Collation, Security Certificates Storage, Font / Form / Macro Storage | 497K13650 | | |
| Stand | Adds storage capacity for supplies, device stability, mobility and 394 mm of height | 497K13660 | | |
| Wireless Connectivity Kit | Expand workflow options for your Xerox® equipment | 097S04409 | | |

¹ Paper capacities are based on 75 gsm stock. Capacities will vary with different weight stocks.

² Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

³ Range reflects the number of pages per month the product can regularly print while maintaining optimal performance (considering factors including supplies replenishment and reliability over the expected product life).

⁴ Average standard pages. Declared Yield in accordance with ISO/IEC 19752. Yield will vary based on image, area coverage and print mode.

