■ General Specifications			
Product name			ScanSnap S1300i
Scanner type	е		ADF (Automatic Document Feeder), duplex scanning
Scanning modes			Color, grayscale, monochrome, automatic (color / grayscale / monochrome detection)
Image senso	r		CIS (Contact Image Sensor) x 2
Light source			3 Color LED (Red / Green / Blue)
Optical reso	lution		600 dpi
		Auto mode *2	Simplex / Duplex: 6 ppm
		Normal mode	Color / Grayscale: 150 dpi, Monochrome: 300 dpi, Simplex / Duplex: 12 ppm
	AC adapter	Better mode	Color / Grayscale: 200 dpi, Monochrome: 400 dpi, Simplex / Duplex: 9 ppm
	auapto.	Best mode	Color / Grayscale: 300 dpi, Monochrome: 600 dpi, Simplex / Duplex: 6 ppm
Scanning speed		Excellent mode	Color / Grayscale: 600 dpi, Monochrome: 1,200 dpi, Simplex / Duplex: 1 ppm
(A4 portrait)*1		Auto mode *2	Simplex / Duplex: 2 ppm
(Tr portrary		Normal mode	Color / Grayscale: 150 dpi, Monochrome: 300 dpi, Simplex / Duplex: 4 ppm
	USB bus powered∗₃	Better mode	Color / Grayscale: 200 dpi, Monochrome: 400 dpi, Simplex / Duplex: 3ppm
		Best mode	Color / Grayscale: 300 dpi, Monochrome: 600 dpi, Simplex / Duplex: 2ppm
		Excellent mode	Color / Grayscale: 600 dpi, Monochrome: 1,200 dpi, Simplex / Duplex: 1 ppm
Document size Normal mode		node	A4, A5, A6, B5, B6, Business card, Post card, Letter, Legal and Custom sizes (Max: 216 x 360 mm (8.5 x 14.17 in.), Min: 50.8 x 50.8 mm (2 x 2 in.)) / Automatically recognizes document size
	Long paper scanning*4		863 mm (34 in.)
Paper weight (Thickness)		ess)	64 to 104.7 g/m ² (17.1 to 28.0 lb)
Paper chute	capacity	k 5	Maximum 10 sheets (A4, 80 g/m ² or 20 lb)
Interface			USB 2.0 (USB 1.1 Compatible)
Power	AC adapter		AC 100 to 240 V, 50 / 60 Hz
requirement	USB bus power		5 V / 1 A (0.5 A x 2 port)
Power	Power cable connection		During operation: 9 W or less, During sleep mode: 2.6 W or less, During off mode: 0.5 W or less
consumption	USB bus power cable connection		During operation: 5 W or less, During sleep mode: 2 W or less, During off mode: 0.5 W or less
Operation environment			Temperature: 5 to 35 °C (41 to 95 °F) Relative humidity: 20 to 80 % (Non-condensing)
Dimensions (WxDxH)*6			284 x 99 x 77 mm (11.18 x 3.90 x 3.03 in.)
Device weight			1.4 kg (3.08 lb)
Environmental compliance			ENERGY STAR® / RoHS
Multifeed detection			Length check
Driver			Specific driver ■ Windows®: Does not support TWAIN / ISIS™ ■ macOS: Does not support TWAIN

■ Software

Windows®	macOS	
ScanSnap Home*1		
ABBYY FineReader for ScanSnap™		

*1 ScanSnap Home installation requires a computer and Internet. Activation is also necessary for software use. Please visit the company website for download information. https://scansnap.fujitsu.com/g-support/en

■ Ontions

= Options			
Description	Part number	Remarks	
ScanSnap S300 Soft Case *1	PA03541-0004	Intended for ScanSnap S1300i, S1300, S300, S300M and included items	

^{*1} This product has been especially designed for storing and carrying ScanSnap S1300i / S1300 / S300 / S300M. Please note that this product is not guaranteed to withstand damage by excessive shock or external pressure.

■ ScanSnap S1300i System Requirements

Windows®

Recommended op	erating systems	Windows® 10 (32-bit / 64-bit) *1 Windows® 8.1 (32-bit / 64-bit) *1 Windows® 7 (32-bit / 64-bit)
	CPU *3	Intel® Core™ i5 2.5 GHz or higher
Hardware	Memory capacity *3	4 GB or more
requirements *2	Display resolution	1,024 x 768 pixels or higher
	Disk capacity *4	3.8 GB or more of free hard disk space

*1 Operate Windows in desktop mode. *2 The ScanSnap device may not work if the connected computer does not meet these requirements. *3 Scanning speeds may drop if the recommended CPU, memory capacity and USB 1.1 requirements are not met. *4 Microsoft NET Framework 4.7 or later must be installed. If it is not installed, it is installed with ScanSnap Home. Up to 4.5 GB of disk space is required for the installation. *Please refer to the ScanSnap website for the lates support information of the driver and applications. Compatibility may differ depending on the software's version. *The system requirements may change depending on the duration of support and the support policy of the companies that

Recommended operating systems		macOS v.10.12.4 or later
	CPU *2	Intel® Core™ i5 2.5 GHz or higher
	Memory capacity *2	8 GB or more
requirements *1	Display resolution	1,024 x 768 pixels or higher
	Disk capacity	2.0 GB or more of free hard disk space

■ Included items

AC cable
 USB bus power cable
 Safety Precautions
 AC adapter
 USB cable

■ Consumables

Description	Part number	Remarks
Pick Roller *1	PA03541-0001	Life cycle: Every 100,000 sheets or one year.
Pad Assy *1	PA03541-0002	Life cycle: Every 10,000 sheets or one year.
Cleaner F1	PA03950-0352	100 ml bottle: For use on the Pick Roller and Pad Assy
Cleaning Wipe	PA03950-0419	1 pack (24 packets): For use on the Pick Roller and Pad Assy

*1 These recommended lifetimes are for 80 g/m² (20 lb) A4 sized documents. Therefore, appropriate replacement lifetimes may vary for other document types.

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

*ABBYY and FineReader are trademarks of ABBYY Software, Ltd. which may be registered in some jurisdictions. ABBYY™ FineReader™ Engine
ØABBYY. OCR by ABBYY *Evernote is a registered trademark or trademark of Evernote Corporation. *#Google, Google Drive, Android and Google Play
are registered trademarks or trademarks of Google Inc. **Intel, Pentium, and Intel Core are registered trademarks or trademarks of Intel Corporation in the
United States and other countries. *#ISIS™ is a registered trademark of EMC Corporation in the United States. **Mac. macOS, and the Mac logo are
trademarks of Apple Inc. **ScanSnap, Home are registered trademarks of EMC United Inc. **Intel, Pentium Inc. **Intel® Pentium Inc. **Int. **Int.



For more ScanSnap related information, visit our website at: www.fujitsu.com/id/scanners

▲ Safety Precautions	precautions prior to using this product	Do not place this device in wet, moist, steamy, dusty or oily areas. Using this product under such conditions may result in electrical shock, fire or damage to this product.

©2019 PFU Limited Printed in some country 2017.12 U-100 SZX-50K7



shaping tomorrow with you