

ScanSnap S300 Technical Specifications



| Scanner Type | ADF (Automatic Docur | ADF (Automatic Document Feeder). Duplex color scanning | | |
|--|--|--|--|--|
| Scanning Modes | Color / B&W / Automa | Color / B&W / Automatic Color & B&W detection | | |
| Image Sensor | CIS (Color Image Sens | CIS (Color Image Sensor) X 2 | | |
| Light Source | 3 color LED (Red / Gre | 3 color LED (Red / Green / Blue) | | |
| Optical Resolution | 600 dpi x 600 dpi | 600 dpi x 600 dpi | | |
| Scanning Speed 1 | Normal Mode | Color 150 dpi, B&W 300 dpi: 8 pages per minute / 16 images per minute | | |
| | Better Mode | Color 200 dpi, B&W 400 dpi: 6 pages per minute / 12 images per minute | | |
| (A4 portrait / AC adapter) | Best Mode | Color 300 dpi, B&W 600 dpi: 4 pages per minute / 8 images per minute | | |
| | Excellent Mode | Color 600 dpi, B&W 1,200 dpi: 0.5 pages per minute / 1 image per minute | | |
| | Normal Mode | Color 150 dpi, B&W 300 dpi: 4 pages per minute / 8 images per minute | | |
| Scanning Speed 1 | Better Mode | Color 200 dpi, B&W 400 dpi: 3 pages per minute / 6 images per minute | | |
| (A4 portrait / USB bus power) ² | Best Mode | Color 300 dpi, B&W 600 dpi: 2 pages per minute / 4 images per minute | | |
| | Excellent Mode | Color 600 dpi, B&W 1,200 dpi: 0.5 pages per minute / 1 image per minute | | |
| Scanning Range | | A4, A5, A6, B5, B6, Business card, Letter, Legal and Custom sizes. Max: 8.5 X 14.17 in. (216 X 360mm), Min: 2 X 2 in. (50.8 X 50.8mm), Automatically recognizes document type by paper length. | | |
| Paper Weight (Thickness) | 17 to 28 lb. (64 to 10 | 17 to 28 lb. (64 to 104.7 g/m ²) | | |
| Paper Chute Capacity | Maximum 10 sheets (| Maximum 10 sheets (A4 size at 20 lb. or 80 g/m ²) | | |
| Interface | USB2.0 (USB1.1 Com | USB2.0 (USB1.1 Compatible) | | |
| Driver ³ | ScanSnap specific driv | ScanSnap specific driver (TWAIN / ISIS™ not supported) ³ | | |
| Applications | ScanSnap Manager V | ScanSnap Manager V4.2, ScanSnap Organizer V3.2, CardMinder™ V3.2 | | |
| Included items | USB cable, USB bus p | USB cable, USB bus power cable, AC adapter, AC cable, Getting started guide and Setup CD-ROM | | |
| Power Poquirement | AC Adapter | AC 100V to 240V, 50 / 60 Hz | | |
| Power Requirement | USB Bus Power | 5V / 1A (0.5A X 2 Port) | | |
| Power Consumption | | Operating: 9W or less Sleep mode: Less than 5W | | |
| Operation Environment | Temperature: 41°F to 95°F (5°C to 35°C) | | | |
| | Relative humidity: 20% to 80% (Non-condensing) | | | |
| Dimensions (W X D X H) ⁴ | 11.18 in. X 3.74 in. X | 11.18 in. X 3.74 in. X 3.03 in. (284mm X 95mm X 77mm) | | |
| Device Weight | 3.08 lb. (1.4kg) witho | 3.08 lb. (1.4kg) without power adapter | | |
| Environmental Compliance | ENERGY STAR® comp | ENERGY STAR® compliant / RoHS | | |
| Limited Warranty | 1 year Limited Warran | 1 year Limited Warranty. For full details, visit www.fcpa.fujitsu.com/warranties or call (800) 626-4686 | | |
| Service Options | , , , , | In-warranty Upgrade: Advance Exchange. Post-Warranty: Advance Exchange Plus, Depot Plus, ScanAid Kit, Cleaning and Consumable Kit. For full details on all service programs, visit www.ImagingService.com | | |
| Part Number | PA03541-B005 | | | |

¹ Scanning speeds may vary due to the system environment used. ² Requires simultaneous connection to two active powered USB ports on computer. ³ TWAIN or ISIS® applications cannot be used directly. ⁴ When hopper is closed.

| System Requirements | | Windows® 2000 Professional Windows® XP | | Windows® Vista™ | | |
|---------------------------------------|------------------------------|--|-------------|--|--|--|
| Compatible Operating Systems | ScanSnap Manager V4.2 | Supported | Supported 1 | Supported | | |
| | ScanSnap Organizer V3.2 | Supported | Supported 1 | Supported ² | | |
| | CardMinder™ V3.2 | Supported | Supported 1 | Supported | | |
| | CPU | Intel® Pentium® III processor 1.2GHz or higher (Intel® Celeron® M 430 1.73GHz or higher is recommended) | | Intel® Pentium® 4 1.8GHz or higher (Intel® Celeron® M 430 1.73GHz or higher is recommended) | | |
| Hardware Requirements ⁴ | Memory Capacity ³ | 512MB or higher (1GB or higher is recommended) | | 1GB or higher (1GB or higher is recommended) | | |
| | Disk Capacity | Spare capacity of a least 920MB is necessary to install the software that is included in this table. | | | | |
| | CD-ROM Drive | Required for installation | nstallation | | | |
| | USB Port | USB 2.0 / USB 1.1 | | | | |

¹ Compatible with Windows[®] 2000 Professional and Windows[®] XP Professional / Home Edition (Service Pack 1 or higher). ² Operates most effectively with Windows Vista[™] compatible versions of Adobe Acrobat. Use with non-Windows Vista[™] compatible versions of Adobe Acrobat might result in the generation of PDF files that cannot be searched. ³ Memory capacity of 1GB or higher is recommended when scanning in "Excellent mode". ⁴ Scanning speeds may drop if recommended CPU, memory capacity and USB 2.0 requirements are not met.

Consumables

| Description | Model Number | Remarks | Description | Model Number | Remarks |
|-----------------------|--------------|--|---------------|--------------|--|
| Pad ASSY ¹ | PA03541-0002 | Lifetime: Every 10,000 sheets or one year. | Pick Roller 1 | PA03541-0001 | Lifetime: Every 100,000 sheets or one year. |
| Cleaner F1 | PA03950-0352 | 100ml bottle. Used to clean Pad ASSY ASSY and Pick roller | Cleaning Wipe | PA03950-0419 | 1 pack (24sheets) Used to clean Pad and Pick roller |

¹ These recommended lifetimes are for 17 lb. (64g/m2) A4 sized documents. Therefore, appropriate replacement lifetimes may vary for other document types.

| Options | | |
|------------------------|--------------|---|
| Description | Model Number | Remarks |
| ScanSnap carrying Case | PA03541-0004 | Intended for ScanSnap S300 and included items |



Introducing the ScanSnap S300. The truly portable, full-featured scanner.

530



THE POSSIBILITIES ARE INFINITE

Easy to use "one button" scanning!

Just press the "SCAN" button and the ScanSnap S300 quickly captures both sides of documents, presenting images as they are meant to be seen. The Fujitsu ScanSnap S300 provides a host of automatic image correction features to ensure great scanning results. Simply load a stack of documents into the hopper and press the "SCAN" button. The S300 automatically recognizes the size of each document, detects and corrects for skew, and shows images in their proper orientation with blank pages removed.

Instantly creates scans that can be searched by their content. The ScanSnap S300 automatically converts scanned data into searchable PDF files that let you quickly and easily locate your images and find information contained within your documents using keyword searches.



It's the world's smallest duplex ADF scanner designed to provide best-in-class performance inside or outside of the home or office.

Compact mobile scanning solutions. At half the size of other ScanSnap scanners, the S300 is designed to be the smallest Fujitsu ADF scanner. As a mobile alternative, the ScanSnap S300 is compact enough to carry around and you will never have to worry about finding a spot to put it.

Double sided multi-sheet feeding. The ScanSnap S300 holds up to 10 letter sheets of paper in the Automatic Document Feeder and scans both sides simultaneously at an incredible speed of up to 8 pages per minute.

Operates on USB bus power. For added mobile convenience, the Fujitsu ScanSnap S300 can be powered though the PC's USB port* when an AC power source is not available. *When using the USB bus power cable, the PC must have two USB ports; one for power feeding and the other for USB cable connection.

Scans anything from thick business cards and postcards to legal size documents. In addition to automatically recognizing document size, the ScanSnap S300 de-skews images, removes blank pages and shows them in their proper orientation. The ScanSnap S300 is also able to scan business cards and postcards that are thicker than normal (Up to 56 lb.)

© 2008 Fujitsu Computer Products of America, Inc. All rights reserved. Fujitsu and the Fujitsu logo are registered trademarks and The Possibilities are Infinite is a trademark of Fujitsu Limited. Adobe and Acrobat are either registered trademarks or trademarks of Adobe Systems Incorporated in the United States and/or other countries. As an ENERGY STAR® Partner, Fujitsu Ltd. has determined that this product meets the ENERGY STAR® guidelines for energy efficiency. ENERGY STAR® is a U.S. registered trademark. Microsoft, ISIS and ABBYY and all other trademarks are the property of their respective owners. All statements

herein are valid only in the U.S. for U.S. residents, are based on normal operating conditions, are provided for informational purposes only, and are not intended to create any implied warranty of merchantability or fitness for a particular purpose. Fujitsu Computer Products of America, Inc. reserves the right to modify at any time without prior notice these statements, our products, their performance specifications, availability, price and warranty, post-warranty and service programs. Printed in the U.S.A. Qty. 10M P/N DS37800408




THE PARTY OF THE P

CityCourier

The easy way to organize and view PDF files.

- View PDF and JPEG files with the thumbnail viewer
- Arrange files with simple drag and drop actions
- Easily insert and delete images
- Change thumbnail display sizes
- Automatically creates searchable PDF files
- Quick drag and drop to e-mail or to a printer



Efficiently manage business cards and contact information. Quickly scan business cards for fast and easy reference. Capture both sides of a business card in a single pass. Information on the business card is captured and can be exported to Outlook, CSV (Excel), and others.



http://scansnap.fujitsu.com

THE POSSIBILITIES ARE INFINITE



POWERED BY ABBY FineReader



